

# Backup Exec 2012 Hardware Compatibility List (HCL)

Created on August 29, 2014

# Introduction

This Hardware Compatibility List (HCL) document contains information for all editions of Backup Exec 2012. All hardware must be present on this HCL for support, unless a section clearly states that the devices listed are not the only devices supported. If your tape drive, tape library, or virtual tape library is not properly detected, please update your system using the latest Service Pack or Device Driver Installer (DDI) before calling Support. Updating the drivers frequently resolves device related issues. This update can be found on our support site. [http://entsupport.symantec.com/menu\\_ddProduct\\_BEWNT.htm](http://entsupport.symantec.com/menu_ddProduct_BEWNT.htm)

Backup Exec support policy is that all of the vendors involved (both hardware and software) must support all the pieces involved. For example, the Host Bus Adapter must be supported by the hardware vendor and the operating system vendor in order for Symantec to provide support. Always consult the hardware manufacturer's support list and the operating system vendor's support list when troubleshooting or planning a data protection installation. All entries were believed to be fully supported by all parties involved when they were added to this Symantec list, but if a vendor drops their support after this list was published, Symantec support will be on a reasonable-effort basis.

Hardware is selected and prioritized for certification based on market research and input from the field, including customer feedback. If a customer would like to have their hardware considered for inclusion on this HCL, simply submit the request via an email [Backup\\_Exec\\_HCL@symantec.com](mailto:Backup_Exec_HCL@symantec.com). Requests will be reviewed by the appropriate Symantec Product Management team members for possible certification, with final decisions based on the overall fit with the product, target market, and frequency of request.

**Alternative Configurations:** Our Licensed Software is designed to interoperate with many types of systems, applications, and hardware. Sometimes a customer may choose to use our Licensed Software in an "**Alternative Configuration**", namely, an environment that has not been validated, approved or verified to operate with our Licensed Software or which does not support such Licensed Software or only supports limited functionality. In most cases, we do not support Alternative Configurations, and we have no obligation to provide Support Services to Licensed Software in an Alternative Configuration. Symantec makes no warranty with respect to use of Licensed Software in an Alternative Configuration and any such use is at your own risk. A "**Supported Configuration**" might be converted into an Alternative Configuration where a vendor modifies one of its components that is part of the original Supported Configuration. As a consequence, your Licensed Software would then be operating in an Alternative Configuration. If you experience a problem with the Licensed Software in an Alternative Configuration or if your issue deals with script that was not developed by Symantec or an authorized consulting partner, then we may ask you to reproduce the problem in a Supported Configuration environment. Please note we have no obligation to attempt to resolve problems that cannot be replicated in a Supported Configuration. However, if the problem can be replicated in a Supported Configuration, we will investigate the problem in that Supported Configuration and attempt to resolve it. If the problem cannot be replicated in a Supported Configuration, then we may elect not to work on that problem.

Configuring a tape device with a virtual machine is considered an "Alternative Configuration". For more details on the configuration of virtual machines with tape devices, see the following related articles, <http://www.symantec.com/docs/TECH130609>, <http://www.symantec.com/docs/TECH146293>, and <http://www.symantec.com/docs/TECH70246>.

## Contents

<u>Newly-Supported Devices</u>	<u>Select hardware by BE option or agent</u>	<u>Backup Exec Appliance (BE 3600 R2)</u>
<u>Cloud Storage</u>	<u>Disk Targets</u>	<u>Virtual Tape Libraries with Drives</u>
<u>Tape Drives</u>	<u>Tape Libraries with Drives</u>	<u>NDMP Platforms</u>
<u>NAS Sources</u>	<u>SAN Infrastructure components</u>	<u>Support End-of-Life</u>
<u>Retiring Soon</u>		

# Newly-Supported Devices

The following new devices have been added to this HCL **since the last time it was created**. The creation date is listed on the first page of this document. See the device in its respective section, via bookmarks, for more details.

LiveUpdate will obtain the latest updates for your BE version. Hotfix 215122 (aka BE 2012 SP4) contains the latest driver patches available for BE 2012, build 1798.  
<<http://www.symantec.com/docs/TECH215122>>

Device Driver releases used to be packaged in a Hotfix called a DDI. These device driver patches are now being released as part of the regular Service Pack process.

Your device may require that you download and install a Service Pack or DDI, but it is RECOMMENDED that the latest patches are always used. If a new Service Pack or DDI is utilized, it is required that Simplified Disaster Recovery (SDR) users regenerate the SDR boot media.

## **New Backup-to-Disk | Basic:**

1. Data Domain DD2200 - CIFS

## **New Backup-to-Disk | OpenStorage appliances:**

1. Data Domain 3.0 plugin
2. Data Domain DD2200

## **New NDMP Option components:**

1. NetApp FAS Series with OnTap 8.2.1

# Select hardware by BE option or agent

The listed options and agents have hardware requirements. They are included here for the purpose of helping choose the appropriate hardware for the selected agent/option.

## Advanced Disk-based Backup Option

The Advanced Disk-based Backup Option (ADBO, included with the Enterprise Server Option), as it relates to hardware devices in this HCL, can be seen in the [VSS Providers for Offhost backup](#) section.

## Deduplication Option

The Deduplication Option support information is included with the Disk Targets sections. There are two basic options to choose from:

1. Backup Exec Deduplication Option Storage. To find tested devices, search by storage device vendor in the [Disk Targets | Disk Storage section](#) , then model, then look for a check [✓] in the "dedup" column for tested disk devices.
2. Deduplication Appliance - sometimes referred to as OpenStorage, including Symantec PureDisk and devices from our hardware/software partners. See the [Deduplication Appliances / OpenStorage section](#) .

## Simplified Disaster Recovery Option

The Simplified Disaster Recovery (SDR) Option is supported on tape libraries, tape drives, virtual tape libraries, and disk devices (present at system start time) unless otherwise mentioned in a footnote, or section header paragraph.

For compatibility information on physical tape libraries with SDR, please refer to the [Tape Libraries with Drives Section](#) of this document.

For compatibility information on virtual tape libraries (VTLs) with SDR, please refer to the [Virtual Tape Libraries with Drives Section](#) of this document.

For compatibility information on tape drives with SDR, please refer to the [Tape Drives Section](#) of this document.

## NDMP Option

The storage devices supported by the NDMP option are included with the Tape Library / Virtual Tape Library sections. Please refer to the NDMP-specific notes in the "NDMP Platforms" section. These notes can be found as footnotes, per NDMP vendor / device combination. These notes apply to the "Virtual Tape Libraries with Drives" and "Tape Libraries with Drives Section" sections. Search by storage device vendor, then model, then look for a check [✓] in the NDMP column for support. Please note that the presence of a check means that Symantec will support the storage device and NDMP combination IF and ONLY IF the NDMP vendor also supports the library / drive combination. Please refer to the NDMP vendors' documentation for storage device support.

For compatibility information on NDMP platforms supported, please refer to the [NDMP Platforms Section](#) of this document.

For compatibility information on physical tape libraries with NDMP, please refer to the [Tape Libraries with Drives Section](#) of this document.

For compatibility information on virtual tape libraries (VTLs) with NDMP, please refer to the [Virtual Tape Libraries with Drives Section](#) of this document.

# Remote Media Agent for Linux

The Remote Media Agent for Linux (RMAL) support information is included with the Tape Library / Virtual Tape Library / Tape Drives sections. Search by storage device vendor, then model, then look for a check [✓] in the RMAL column for support.

For compatibility information on physical tape libraries with RMAL, please refer to the [Tape Libraries with Drives Section](#) of this document.

For compatibility information on virtual tape libraries (VTLs) with RMAL, please refer to the [Virtual Tape Libraries with Drives Section](#) of this document.

For compatibility information on tape drives with RMAL, please refer to the [Tape Drives Section](#) of this document.

## Enterprise Server Option for use with SAN shared storage

The SAN Shared Storage Option is now available as part of the Enterprise Server Option in Backup Exec 2012. All references to SSO on the HCL are now replaced with ESO due to the change. If you used the SAN Shared Storage Option in a previous version of Backup Exec, the SAN primary server will be upgraded to a Central Administration Server. SAN secondary servers will be upgraded to Managed Backup Exec Servers and will have the Managed Backup Exec Server option installed and the Unrestricted access to catalogs and backup sets for restore option selected.

The Enterprise Server Option (ESO) hardware support information is included with the Tape Library / Virtual Tape Library sections. Search by storage device vendor, then model, then look for a check [✓] in the ESO column for support.

For compatibility information on physical tape libraries with ESO, please refer to the [Tape Libraries with Drives Section](#) of this document.

For compatibility information on virtual tape libraries (VTLs) with ESO, please refer to the [Virtual Tape Libraries with Drives Section](#) of this document.

For compatibility information on storage area network (SAN) components with ESO, including fibre-channel and iSCSI components, please refer to the [SAN Infrastructure components Section](#) of this document.

## Storage Provisioning Option

The Storage Provisioning Option (SPO) supported hardware configurations, including hardware and VDS provider, can be seen in the [VDS Providers for Storage Provisioning Option](#) section.

## Library Expansion Option

The Library Expansion Option (LEO) supported hardware configurations, including tape library and tape drive combinations, can be seen in the [Tape Libraries with Drives](#) section.

## Virtual Tape Library Unlimited Drive Option

The Virtual Tape Library Unlimited Drive Option (VUDO) supported hardware configurations, including virtual tape library and virtual tape drive combinations, can be seen in the [Virtual Tape Libraries with Drives](#) section.

Often, a single VTL can be configured with a variable number of tape drives and tape libraries. VUDO allows for the variance in drives per physical VTL, not logical VTL. In other words, creating more than one logical VTL will require the need for multiple VUDO licenses.

# Backup Exec Appliance (BE 3600 R2)

Backup Exec Appliances are Symantec-branded devices offering a Backup Exec media server with built-in deduplication in an appliance form factor.

For more information, see the Backup Exec 3600 R2 Appliance page: <http://www.symantec.com/business/backup-exec-3600-appliance>

## Backup Exec 3600 R2 Appliance

Support Type	Notes
Internal Disk Storage	Configured as Backup Exec Media Server Deduplication appliance. The C drive contains operating system and Backup Exec program Files. The D drive contains the deduplication store.
External Disk Storage Support	Any Disk Target (B2D) device seen in the <a href="#">Disk Storage</a> or <a href="#">Disk Cartridge</a> sections with "Connectivity" of <b>USB</b> or <b>CIFS</b> are supported for use with the appliance.
External Tape Storage Support	Any tape device seen in the <a href="#">Tape Drives</a> or <a href="#">Tape Libraries with Drives</a> sections identified with a "Drive Interface" of <b>SAS</b> are supported for use with the appliance. Multi-drive SAS libraries can be supported with a multi-lane/fan-out SAS cable (sold separately from the hardware manufacturer).
OpenStorage Storage Servers (OST)	The Symantec NetBackup 5000/5020 appliance may be used as a target for backups, and optimized duplication. Optimized Duplication is best used in a LAN environment. Optimized Duplication over a WAN can have performance implications due to the current need to rehydrate the data across the WAN during a Verify. See the <a href="#">Symantec NBU appliance</a> section for more details.
NDMP Support	Any NDMP platform seen in the <a href="#">NDMP Platforms</a> section are supported for use with the appliance.

## Backup Exec 3600 R2 Appliance - Supported Versions

Appliance version	Function	Backup Exec version
3.0.419.0, BE3600 R2	"Drop in" Backup Exec Media Server with on-board disk	Based on Backup Exec 2012

# Cloud Storage

## OST

Backup Exec OpenStorage (OST) Cloud Storage plug-ins enable Symantec data protection applications to access Cloud Storage Solutions. Either the storage vendor or Symantec provides a software plug-in, which is installed on each Backup Exec server that is connected to the cloud solution. If you do not see OST support for your desired Cloud Storage Solution provider / Backup Exec Server OS platform, please contact that Storage Server appliance vendor to request OST support for that platform. Please see the Backup Exec System Administrator's Guide for more information on how to use OST.

### Quantum

Cloud Storage Solution	Cloud API Version	Plug-in	Windows Server 2003	Windows Server 2008
Q-Cloud <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	Galaxy OS 2.2.1	2.6.0	✓	✓

1. For information on how to setup Q-Cloud with Backup Exec, goto <http://www.quantum.com/serviceandsupport/softwareanddocumentationdownloads/index.aspx> select the appropriate DXi product, select the "Documentation" tab, in the best practices section select "DXi-Series and Best Practices Guide for Backup Exec from Symantec". Once you enter the appropriate serial number, search for Appendix A.
2. DXi server model DXi8500 (3TB) or DXi6802 is required to support Data-at-Rest encryption.
3. See the [Quantum OST appliance](#) section also

## Disk Targets

The disk target software versions listed in this section are the minimum software levels that are supported. Where more than one software level is listed, this implies a newer version has been tested. The earlier software version is the minimum version required.

Cloud storage providers will be individually certified for use with Backup Exec, therefore, additional Cloud providers will be added as they are certified.



# Riverbed

Family	Family Members	Software Tested	Supported Cloud Providers	Connectivity	Basic B2D	GRT Tested
SteelStore Appliance [1] [2] [3]	WWA730, WWA2030, WWA3030	SteelStore OS 3.0.2	Amazon S3	CIFS	✓	✓
SteelStore Virtual Appliance [1] [2] [3]	SteelStore Virtual 110, SteelStore Virtual 210, SteelStore Virtual 410, SteelStore Virtual 810, SteelStore Virtual 1610	SteelStore OS 3.1.1a	Amazon S3	CIFS	✓	✓
Whitewater Appliance [1] [2] [3]	WWA510, WWA710, WWA2010, WWA3010	SteelStore OS 3.0.2	Amazon S3	CIFS	✓	✓

1. Backup Exec Simplified Disaster Recovery (SDR) is not supported. Refer to the SteelStore docs for recovery instructions.
2. SteelStore Solution Guide: <<http://media-cms.riverbed.com/documents/Solution+Guide+-+SteelStore+with+Backup+Exec+3.1.1.pdf>>
3. See the [Riverbed Disk Targets](#) section also

# Disk Targets

For this basic support, any device recognized and supported by the Windows platform should work with Backup Exec. Mapped network drives are not supported. UNC paths are supported. The disk devices listed in these two sections have been tested with Backup Exec as a result of a formal joint business agreement and OEM relationship, **but are not intended to be a complete list of compatible devices.**

For "basic" disk storage capabilities, Backup Exec does not exclude or block recognition for disk devices. Basic disk storage devices can be seen in the [Disk Storage](#) and [Disk Cartridge](#) sections. This information is organized by vendor and provides information on the storage devices tested, the Inquiry Strings (if applicable), the type of interface, media type, and any special notes on a per device basis.

If the desired device is not already listed in this section, customers are encouraged to run the B2D test tool to verify their desired device's level of functionality. If Backup Exec is not already installed, the B2D test tool can be downloaded from [<http://www.symantec.com/docs/TECH69107.>](http://www.symantec.com/docs/TECH69107) Instructions for use are in that same technote. Backup Exec Technical Support will be unable to offer assistance if the device experiences failures during the B2Dtest and the customer should contact the hardware vendor for advice and assistance.

Devices running the Windows Unified Data Storage Server OS which provides iSCSI target functionality are supported per the Software Compatibility List. See [<http://entsupport.symantec.com/umi/V-269-1>](http://entsupport.symantec.com/umi/V-269-1) for supported operating system details.

For more advanced disk capabilities, refer to the [Deduplication Appliances / OpenStorage section](#) , [VSS Providers for Offhost backup](#) , and [VDS Providers for Storage Provisioning Option](#) sections. The presence of the disk device in these advanced sections is required for support.

## Granular Restore Technology (GRT) support, per deduplication type

Deduplication type	GRT support method
Backup Exec Deduplication Disk Storage and BE 3600 appliance	Non-GRT and GRT backups are supported and no staging is needed for GRT restores.
Hardware based deduplication OpenStorage appliances	1. Non-GRT and GRT backup are supported but staging is needed at time of GRT restores. Backups will be faster and restores slower (due to staging). 2. Alternately if the device supports it then one can create B2D using CIFS share and then run backups. Backups will be slower but GRT restores will be faster.
NBU5000/NBU5020 appliance	Non-GRT and GRT backups are supported and no staging is needed for GRT restores.
Pure Disk appliance, also known as Classic Pure Disk	Non-GRT and GRT backups are supported and no staging is needed for GRT restores.

# Disk Storage

## Disk Device Legend

Value	Meaning
Connectivity	The method by which the device communicates with the Backup Exec server.
✓	Character used to denote successful completion of acceptance testing for the item listed in the column.
Basic B2D	Basic functionality of a device as it relates to being used as a Backup-to-Disk device (Disk Storage) in Backup Exec. Backup Exec's Granular Restore Technology (GRT) is not included in Basic B2D.
GRT Tested	Granular Restore Technology (GRT) has been validated specifically for this device. The presence of a checkmark ✓ in this column indicates that no staging is needed for GRT restores. The presence of an "S" in this column indicates that staging may be needed at time of GRT restores. This is typically exhibited with CIFS connectivity.
BEDedup	Backup Exec Deduplication is the native method for deduplication - enabled via an additional "Backup Exec Deduplication Option", and referred to as "Backup Exec Deduplication Disk Storage". Only Local disks may be used for deduplication storage. Removable interfaces like USB and FireWire are also not supported due to the perceived temporary connection method and issues that can arise from a device that is unsafely removed or appears on a different path. For Devices with a supported interface the absence of a check here does not signify that the device will not be supported, merely that deduplication tests have not been run in combination with this device. See comments above regarding, "not intended to be a complete list of compatible devices". The Backup Exec Deduplication Option is recommended for use on a dedicated / non-removable volume as the location to store the deduplication disk storage. For this reason, there are no dedup checkboxes in the Disk Cartridge device section. While possible, the usage of the "Backup Exec Deduplication Option" with USB, FireWire, and remote disks implies the customer is doing so at their own risk and without official Symantec support.

## Contents

<a href="#"><u>BlueArc</u></a>	<a href="#"><u>Buffalo</u></a>	<a href="#"><u>Data Domain</u></a>
<a href="#"><u>Dell</u></a>	<a href="#"><u>Drobo (formerly Data Robotics)</u></a>	<a href="#"><u>EMC</u></a>
<a href="#"><u>Exablox</u></a>	<a href="#"><u>ExaGrid</u></a>	<a href="#"><u>Hitachi</u></a>
<a href="#"><u>HP</u></a>	<a href="#"><u>IBM</u></a>	<a href="#"><u>Imation</u></a>
<a href="#"><u>Infortrend</u></a>	<a href="#"><u>LaCie</u></a>	<a href="#"><u>NEC</u></a>
<a href="#"><u>NETGEAR</u></a>	<a href="#"><u>Nexsan</u></a>	<a href="#"><u>Oracle</u></a>
<a href="#"><u>Overland Storage</u></a>	<a href="#"><u>QNAP</u></a>	<a href="#"><u>Quantum</u></a>
<a href="#"><u>Riverbed</u></a>	<a href="#"><u>Synology</u></a>	<a href="#"><u>Tandberg</u></a>

## BlueArc

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Mercury series <a href="#">[1]</a>	CIFS	✓	✓	Mercury 50, Mercury 100	

1. Supported with the BE 3600 R2 appliance.

## Buffalo

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
LinkStation 400 Series <a href="#">[1]</a>	CIFS	✓	S	LinkStation 410, LinkStation 420, LinkStation 420s, LinkStation 421, LinkStation 441	
LinkStation Pro/DUO Series <a href="#">[1]</a>	CIFS	✓	S	LinkStation Pro DUO Enclosure, LS-WVL, LS-WXL	
Quad - HD-QLSU2R5	eSATA	✓	✓	Quad - HD-QLSU2R5	✓
TeraStation 3000 <a href="#">[1]</a>	CIFS	✓	S	TeraStation 3400, TeraStation 3400r Rackmount	
TeraStation 3000	iSCSI	✓	✓	TeraStation 3400, TeraStation 3400r Rackmount	✓
TeraStation 5000 <a href="#">[1]</a>	CIFS	✓	S	TeraStation 5200, TeraStation 5400, TeraStation 5400r Rackmount, TeraStation 5600, TeraStation 5800	
TeraStation 5000	iSCSI	✓	✓	TeraStation 5200, TeraStation 5400, TeraStation 5400r Rackmount, TeraStation 5600, TeraStation 5800	✓
TeraStation 7000 <a href="#">[1]</a>	CIFS	✓	S	TeraStation 7120r, TeraStation 7120r Enterprise	
TeraStation 7000	iSCSI	✓	✓	TeraStation 7120r, TeraStation 7120r Enterprise	✓
TeraStation III <a href="#">[1]</a>	CIFS	✓	S	TS-RXL/R5, TS-XL/R5	
TeraStation III iSCSI	iSCSI	✓	✓	TS-IXL/R5, TS-RIXL/R5	✓
TeraStation Pro <a href="#">[1]</a>	CIFS	✓	S	TeraStation Pro	

1. Supported with the BE 3600 R2 appliance.

## Data Domain

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Appliance series [1]	CIFS	✓	S	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	

1. Supported with the BE 3600 R2 appliance.

## Dell

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Compellent FS8600 [1]	CIFS	✓	S	Compellent FS8600	
Compellent Storage Center 5	Fibre Channel	✓	✓	Compellent Storage Center 5.2, Compellent Storage Center 5.3, Compellent Storage Center 5.4	✓
Compellent Storage Center 5	iSCSI	✓	✓	Compellent Storage Center 5.2, Compellent Storage Center 5.3, Compellent Storage Center 5.4	✓
DR Series [1]	CIFS	✓	S	DR4000, DR4100, DR6000	
EqualLogic FS7500 [1]	CIFS	✓	S	EqualLogic FS7500	
EqualLogic FS7600 [1]	CIFS	✓	S	EqualLogic FS7600	
EqualLogic FS7610 [1]	CIFS	✓	S	EqualLogic FS7610	
EqualLogic PS3000 series	iSCSI	✓	✓	EqualLogic PS3000E, EqualLogic PS3000X, EqualLogic PS3000XV	✓
EqualLogic PS4000 series	iSCSI	✓	✓	EqualLogic PS4000E, EqualLogic PS4000X, EqualLogic PS4000XV, EqualLogic PS4100E, EqualLogic PS4100X, EqualLogic PS4100XV, EqualLogic PS4100XV3.5"	✓
EqualLogic PS5000 series	iSCSI	✓	✓	EqualLogic PS5000E, EqualLogic PS5000X, EqualLogic PS5000XV, EqualLogic PS5500E	✓

# Dell

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
EqualLogic PS6000 series	iSCSI	✓	✓	EqualLogic PS6000E, EqualLogic PS6000S, EqualLogic PS6000X, EqualLogic PS6000XV, EqualLogic PS6000XVS, EqualLogic PS6010E, EqualLogic PS6010S, EqualLogic PS6010X, EqualLogic PS6010XV, EqualLogic PS6010XVS, EqualLogic PS6100E, EqualLogic PS6100X, EqualLogic PS6100XV, EqualLogic PS6100XV3.5", EqualLogic PS6500E, EqualLogic PS6500X, EqualLogic PS6500XV, EqualLogic PS6510E, EqualLogic PS6510X, EqualLogic PX6100S, EqualLogic PX6100XS	✓
PowerVault DL2000	SAS	✓	✓	PowerVault DL2000	✓
PowerVault DL2100	SAS	✓	✓	PowerVault DL2100	✓
PowerVault DL2200	SAS	✓	✓	PowerVault DL2200	✓
PowerVault MD1000	SAS	✓	✓	PowerVault MD1000	✓
PowerVault MD1200	SAS	✓	✓	PowerVault MD1200	✓
PowerVault MD3000	SAS	✓	✓	PowerVault MD3000	✓
PowerVault MD3000i	iSCSI	✓	✓	PowerVault MD3000i	✓
PowerVault NX3500 [1]	CIFS	✓	S	PowerVault NX3500	
PowerVault NX3600 [1]	CIFS	✓	S	PowerVault NX3600	
PowerVault NX3610 [1]	CIFS	✓	S	PowerVault NX3610	

1. Supported with the BE 3600 R2 appliance.

## Drobo (formerly Data Robotics)

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
B800i	iSCSI	✓	✓	B800i	✓
B1200i	iSCSI	✓	✓	B1200i	✓
Drobo <a href="#">[1]</a>	USB	✓	✓	Drobo	
DroboElite	iSCSI	✓	✓	DroboElite	✓
DroboElite <a href="#">[1]</a>	USB	✓	✓	DroboElite	
DroboPro	iSCSI	✓	✓	DroboPro	✓
DroboPro <a href="#">[1]</a>	USB	✓	✓	DroboPro	

1. Supported with the BE 3600 R2 appliance.

## EMC

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
DL3D series <a href="#">[1]</a>	CIFS	✓	S	DL1500, DL3000	
lomega StorCenter ix series network storage <a href="#">[1]</a>	CIFS	✓	✓	lomega StorCenter ix2-200, lomega StorCenter ix4-200d, lomega StorCenter ix12-300r, lomega StorCenter Pro ix4-200r	
lomega StorCenter px series network storage	iSCSI	✓	✓	lomega StorCenter px4-300d, lomega StorCenter px4-300r, lomega StorCenter px6-300d, lomega StorCenter px12-350r	✓

1. Supported with the BE 3600 R2 appliance.

## Exablox

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
OneBlox <a href="#">[1]</a>	CIFS	✓	✓	OneBlox	

1. Supported with the BE 3600 R2 appliance.

## ExaGrid

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
EX series <a href="#">[1]</a>	CIFS	✓	S	EX1000, EX2000, EX3000, EX4000, EX5000, EX7000, EX10000E, EX13000E, EX21000E	

1. Supported with the BE 3600 R2 appliance.

## Hitachi

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Capacity Optimization (HCO) <a href="#">[1]</a> <a href="#">[2]</a>	CIFS	✓	S	HCO 210, HCO 230	
Data Ingestor (HDI) <a href="#">[2]</a>	CIFS	✓	S	Data Ingestor (HDI)	
NAS Platform, 4000 and 3000 Series <a href="#">[2]</a>	CIFS	✓	✓	HNAS 3080 (M1), HNAS 3090 (M2), HNAS 4040, HNAS 4060, HNAS 4080, HNAS 4100	
NAS Platform F1000 (HNAS F1000) <a href="#">[2]</a>	CIFS	✓	S	HNAS F1140	
SMS/AMS2000 series	Fibre Channel	✓	✓	AMS2100, AMS2300, AMS2500, SMS100	✓
Virtual File Platform (VFP) <a href="#">[2]</a>	CIFS	✓	S	VFP 50, VFP 70, VFP 80, VFP 100N, VFP 110, VFP 200N, VFP 300N, VFP 500N, VFP 600N, VFP 2010, VFP 2100, VFP 2300	

1. GRT is not recommended when the microcode version of HCO is 2.1

2. Supported with the BE 3600 R2 appliance.



## HP

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
D2D4xxx iSCSI series	iSCSI	✓	✓	D2D4106i Backup System	✓
D2D4xxx series [1]	CIFS	✓	✓	D2D4004fc Backup System, D2D4104fc Backup System, D2D4106fc Backup System, D2D4112 Backup System, D2D4312 Backup System, D2D4324 Backup System	✓
D2D25xx series [1]	CIFS	✓	S	D2D2502i Backup System, D2D2503i Backup System, D2D2504i Backup System	
D2D4100 G2 Backup System [1]	CIFS	✓	S	D2D4106fc G2 Backup System, D2D4106i G2 Backup System, D2D4112 G2 Backup System	
EVA4400/6400/8400	Fibre Channel	✓	✓	EVA4400, EVA6400, EVA8400	✓
P2000 G3 MSA series	Fibre Channel	✓	✓	P2000 G3 FC, P2000 G3 FC/iSCSI, P2000 G3 iSCSI, P2000 G3 SAS	✓
P2000 G3 MSA series	iSCSI	✓	✓	P2000 G3 FC, P2000 G3 FC/iSCSI, P2000 G3 iSCSI, P2000 G3 SAS	✓
P2000 G3 MSA series	SAS	✓	✓	P2000 G3 FC, P2000 G3 FC/iSCSI, P2000 G3 iSCSI, P2000 G3 SAS	✓
StoreOnce 6000 Backup System [1]	CIFS	✓	S	StoreOnce 6500 Backup System, StoreOnce B6200 Backup System	
StoreOnce VSA [1] [2]	CIFS	✓	S	StoreOnce VSA	

1. Supported with the BE 3600 R2 appliance.

2. StoreOnce VSA is a virtual appliance supported on ESX v5.x. For device details & platform support refer to: <http://bizsupport1.austin.hp.com/bc/docs/support/SupportManual/c03822673/c03822673.pdf>

## IBM

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
System Storage TS7600 series with ProtecTIER [1]	CIFS	✓	S	System Storage TS7620, System Storage TS7650AP1, System Storage TS7650G	

1. Supported with the BE 3600 R2 appliance.

## Imation

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
DataGuard Appliances <a href="#">[1]</a>	CIFS	✓	S	R4, T5R	
DataGuard Appliances	iSCSI	✓	✓	R4, T5R	✓
Nexsan E-Series Systems	Fibre Channel	✓	✓	Nexsan E18, Nexsan E48, Nexsan E60	✓
Nexsan E-Series Systems	iSCSI	✓	✓	Nexsan E18, Nexsan E48, Nexsan E60	✓
Nexsan E-Series V Systems	Fibre Channel	✓	✓	Nexsan E18V System, Nexsan E32V System, Nexsan E48V System, Nexsan E60V System	✓
Nexsan E-Series V Systems	iSCSI	✓	✓	Nexsan E18V System, Nexsan E32V System, Nexsan E48V System, Nexsan E60V System	✓
Nexsan NST5000 series <a href="#">[1]</a>	CIFS	✓	S	Nexsan NST5100, Nexsan NST5300, Nexsan NST5500	
Nexsan NST5000 series	iSCSI	✓	✓	Nexsan NST5100, Nexsan NST5300, Nexsan NST5500	✓

1. Supported with the BE 3600 R2 appliance.

## Infotrend

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
EonNAS 3000 series <a href="#">[1]</a>	CIFS	✓	S	EonNAS 3000 series	
EonStor DS FC series	Fibre Channel	✓	✓	EonStor DS FC series	✓
EonStor DS iSCSI series	iSCSI	✓	✓	EonStor DS iSCSI series	✓

1. Supported with the BE 3600 R2 appliance.

## LaCie

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
5big Storage Server	iSCSI	✓	✓	5big Storage Server	✓
12big Rack Network	iSCSI	✓	✓	12big Rack Network	✓
12big Rack Network [1]	USB	✓	✓	12big Rack Network	

1. Supported with the BE 3600 R2 appliance.

## NEC

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
HYDRAsTOR HS8 and HS3 series, iStorage HS8 and HS3 series [1]	CIFS	✓	S	HYDRAsTOR HS3-210, HYDRAsTOR HS3-310, HYDRAsTOR HS3-410-8, HYDRAsTOR HS3-410-16, HYDRAsTOR HS3-410-24, HYDRAsTOR HS8-2002S, HYDRAsTOR HS8-2004R, HYDRAsTOR HS8-2004S, HYDRAsTOR HS8-2010R, HYDRAsTOR HS8-2020R, HYDRAsTOR HS8-2110R, HYDRAsTOR HS8-3002S, HYDRAsTOR HS8-3004R, HYDRAsTOR HS8-3004S, HYDRAsTOR HS8-3010R, HYDRAsTOR HS8-3020R, HYDRAsTOR HS8-3110R, HYDRAsTOR HS8-4001S-(12-48), HYDRAsTOR HS8-4001S-96, HYDRAsTOR HS8-4002S-96, HYDRAsTOR HS8-4002S-192, HYDRAsTOR HS8-4006R-720, HYDRAsTOR HS8-4165-7920, iStorage HS3-20T, iStorage HS3-30T, iStorage HS3-30T2, iStorage HS3-40, iStorage HS8-20R, iStorage HS8-20S, iStorage HS8-30R, iStorage HS8-30S, iStorage HS8-40	

1. Supported with the BE 3600 R2 appliance.

## NETGEAR

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
NV+ [1]	CIFS	✓	✓	NV+	
ReadyNAS 1100 [1]	CIFS	✓	S	ReadyNAS 1100	
ReadyNAS 2100 [1]	CIFS	✓	S	ReadyNAS 2100	
ReadyNAS 2100	iSCSI	✓	✓	ReadyNAS 2100	✓

# NETGEAR

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
ReadyNAS 3100 [1]	CIFS	✓	S	ReadyNAS 3100	
ReadyNAS 3100	iSCSI	✓	✓	ReadyNAS 3100	✓
ReadyNAS 3200 [1]	CIFS	✓	S	ReadyNAS 3200	
ReadyNAS 3200	iSCSI	✓	✓	ReadyNAS 3200	✓
ReadyNAS 4200 [1]	CIFS	✓	S	ReadyNAS 4200	
ReadyNAS 4200	iSCSI	✓	✓	ReadyNAS 4200	✓
ReadyNAS NVX [1]	CIFS	✓	S	ReadyNAS NVX	
ReadyNAS NVX	iSCSI	✓	✓	ReadyNAS NVX	✓
ReadyNAS Pro [1]	CIFS	✓	S	ReadyNAS Pro	
ReadyNAS Pro	iSCSI	✓	✓	ReadyNAS Pro	✓

1. Supported with the BE 3600 R2 appliance.

# Nexsan

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Beast Systems	Fibre Channel	✓	✓	SASBeast, SATABeast, SATABeast2	✓
Beast Systems	iSCSI	✓	✓	SASBeast, SATABeast, SATABeast2	✓
Boy Systems	Fibre Channel	✓	✓	SASBoy, SATABoy2	✓
Boy Systems	iSCSI	✓	✓	SASBoy, SATABoy2	✓
SATABoy	Fibre Channel	✓	✓	SATABoy	✓
SATABoy	iSCSI	✓	✓	SATABoy	✓

## Oracle

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
ZFS Storage Appliance series <a href="#">[1]</a>	CIFS	✓	S	Oracle ZFS Storage 7110, Oracle ZFS Storage 7120, Oracle ZFS Storage 7210, Oracle ZFS Storage 7310, Oracle ZFS Storage 7320, Oracle ZFS Storage 7410, Oracle ZFS Storage 7420, ZFS Storage ZS3-2, ZFS Storage ZS3-4	

1. Supported with the BE 3600 R2 appliance.

## Overland Storage

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
SnapServer DX <a href="#">[1]</a>	CIFS	✓	S	SnapServer DX1, SnapServer DX2	
SnapServer DX	iSCSI	✓	✓	SnapServer DX1, SnapServer DX2	✓

1. Supported with the BE 3600 R2 appliance.

## QNAP

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Business NAS series <a href="#">[1]</a>	CIFS	✓	S	TS-809 series, TS-x39 series, TS-x59 series, TS-x69 series, TS-x79 series	
Business NAS series	iSCSI	✓	✓	TS-809 series, TS-x39 series, TS-x59 series, TS-x69 series, TS-x79 series	✓

1. Supported with the BE 3600 R2 appliance.

## Quantum

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
DXi2500-D [1]	CIFS	✓	S	DXi2500-D	
DXi3500 [1]	CIFS	✓	S	DXi3500	
DXi4000 Family [1]	CIFS	✓	S	DXi4510, DXi4520, DXi4601	
DXi4700 Family [1]	CIFS	✓	S	DXi4701	
DXi5500 [1]	CIFS	✓	S	DXi5500	
DXi6000 Family [1]	CIFS	✓	S	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	
DXi6700 Family [1]	CIFS	✓	S	DXi6700, DXi6701, DXi6702	
DXi6800 Family [1]	CIFS	✓	S	DXi6802	
DXi6900 Family [1]	CIFS	✓	S	DXi6902	
DXi7500 Family [1]	CIFS	✓	S	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	
DXi8500 Family [1]	CIFS	✓	S	DXi8500, DXi8500 2TB, DXi8500 3TB	
DXi V Family [1] [2]	CIFS	✓	S	DXi V1000, DXi V4000	

1. Supported with the BE 3600 R2 appliance.

2. This device is a virtual appliance. Representative VMware-supported ESX4, ESXi4, or ESXi5 servers/storage were tested. Refer to [http://downloads.quantum.com/dxiv1000/6-67611-01\\_DXi\\_V1000\\_QuickStartGuide\\_RevA.pdf](http://downloads.quantum.com/dxiv1000/6-67611-01_DXi_V1000_QuickStartGuide_RevA.pdf)

## Riverbed

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
SteelStore Series [1] [2] [3] [4]	CIFS	✓	✓	SteelStore 730, SteelStore 2030, SteelStore 3030	
SteelStore Virtual Appliance [1] [2] [3] [4]	CIFS	✓	✓	SteelStore Virtual 110, SteelStore Virtual 210, SteelStore Virtual 410, SteelStore Virtual 810, SteelStore Virtual 1610	
WhiteWater Series [1] [2] [3] [4]	CIFS	✓	✓	WhiteWater 510, WhiteWater 710, WhiteWater 2010, WhiteWater 3010	

1. Backup Exec Simplified Disaster Recovery (SDR) is not supported. Refer to the SteelStore docs for recovery instructions.

2. SteelStore Solution Guide: <http://media-cms.riverbed.com/documents/Solution+Guide++SteelStore+with+Backup+Exec+3.1.1.pdf>

3. This device includes Cloud features. Please see the Riverbed Cloud Storage section for specifics.
4. Supported with the BE 3600 R2 appliance.

## Synology

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
Large Scale Business [1]	CIFS	✓	S	DS3612xs, RS3412RPxs, RS3412xs, RS3413xs+, RS10613xs+	
Small and Medium Business [1]	CIFS	✓	S	DS112+, DS213+, DS412+, DS713+, DS1513+, DS1813+, DS2413+, RS812+, RS812RP+, RS814+, RS814RP+, RS2414+, RS2414RP+	

1. Supported with the BE 3600 R2 appliance.

## Tandberg

Family	Connectivity	Basic B2D	GRT Tested	Devices	BEDedup
BizNAS D400/R400 [1]	CIFS	✓	S	BizNAS D400, BizNAS D408, BizNAS R400, BizNAS R408	
BizNAS D400/R400	iSCSI	✓	✓	BizNAS D400, BizNAS D408, BizNAS R400, BizNAS R408	✓
DPS2000 Series NAS [1]	CIFS	✓	S	DPS2040, DPS2140, DPS2142	

1. Supported with the BE 3600 R2 appliance.

## Disk Cartridge

**Note:** Granular Restore Technology (GRT) is not supported on disk cartridge devices if the backup spans media.

**Note:** USB 3.0 devices are supported (when available from the vendor).

## Disk Device Legend

Value	Meaning
^	Character used to denote a space in the INQUIRY STRING.
✓	Character used to denote support for the item listed in the column.
WinBES	The listed device is supported directly attached to a Windows Backup Exec Server platform. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Windows Server Operating System platforms.

### actidata

Device	Inquiry String	Drive Interface	Media	WinBES
actiDisk RDX	IMATION^RDX	SATA	disk	✓
actiDisk RDX [1]	IMATION^RDX	USB	disk	✓

1. Tested with the BE 3600 R2 appliance.

### Dell

Device	Inquiry String	Drive Interface	Media	WinBES
RD1000 [1]	Dell^^^RD1000	SATA	disk	✓
RD1000 [1] [2]	Dell^^^RD1000	USB	disk	✓

1. See TechNote <<http://www.symantec.com/docs/TECH61089>> for limitations.

2. Tested with the BE 3600 R2 appliance.



## HP

Device	Inquiry String	Drive Interface	Media	WinBES
RDX [1] [2] [3]	HP~~~~~RDX	USB	disk	✓

1. Requires the use of the HP RDX utility from <http://www.hp.com/support/rdx> for proper eject functionality.
2. See TechNote <http://www.symantec.com/docs/TECH61089> for limitations.
3. Tested with the BE 3600 R2 appliance.

## IBM

Device	Inquiry String	Drive Interface	Media	WinBES
GoVault [1]	IBM~~~~~GoVault	SATA	disk	✓
RDX [2]	IBM~~~~~RDX	USB	disk	✓

1. See the referenced document for more details. ( <http://www.symantec.com/docs/TECH47473> )
2. Tested with the BE 3600 R2 appliance.

## Imation

Device	Inquiry String	Drive Interface	Media	WinBES
LR1100 RDX 1U Storage Enclosure [1]	IMATION^RDX-USB3	USB	disk	✓
RDX Removable HDD System	IMATION^RDX	SATA	disk	✓
RDX Removable HDD System [1]	IMATION^RDX	USB	disk	✓
RDX USB 3.0 [1]	IMATION^RDX-USB3	USB	disk	✓

1. Tested with the BE 3600 R2 appliance.

## Lenovo

Device	Inquiry String	Drive Interface	Media	WinBES
Internal USB RDX [1]	LENOVO^RDX	USB	disk	✓

1. Tested with the BE 3600 R2 appliance.

## ProStor

Device	Inquiry String	Drive Interface	Media	WinBES
RDX	ProStor^RDX	SATA	disk	✓

## Quantum

Device	Inquiry String	Drive Interface	Media	WinBES
GoVault	QUANTUM^GoVault	SATA	disk	✓
GoVault [1]	QUANTUM^GoVault	USB	disk	✓
QR1201 [1]	QUANTUM^GoVault	USB	disk	✓
RDX [1]	QUANTUM^RDX	USB	disk	✓
RDX USB 3.0 [1]	QUANTUM^RDX-USB3	USB	disk	✓

1. Tested with the BE 3600 R2 appliance.

# Tandberg

Device	Inquiry String	Drive Interface	Media	WinBES
RDX [1]	TANDBERGRDX	SATA	disk	✓
RDX [1] [2]	TANDBERGRDX	USB	disk	✓

1. See TechNote <<http://www.symantec.com/docs/TECH61089>> for limitations.

2. Tested with the BE 3600 R2 appliance.

## Deduplication Appliances / OpenStorage

### OST-Appliance

OpenStorage Servers are intelligent storage devices that interface to Backup Exec Servers and Remote Agents for Windows (with Direct Access) via the Symantec OpenStorage (OST) API. The vendor supplying the Storage Server appliance provides a software Plug-in, which is installed on each Backup Exec Server and Remote Agent for Windows (with Direct Access) that is attached to the OpenStorage Server.

OST functionality is available on supported Windows BE 2012 Backup Exec Server and Remote Agent for Windows platforms.

Please see the Backup Exec System Administrator's Guide for more information on how to use OST.

**Attention: OpenStorage (OST) appliance users:** The 2012 release of Backup Exec may require a new OST plug-in from your appliance vendor. Please contact your vendor for access to this new plug-in. If needed, the required 2012 plug-in details will be listed as a footnote in the "Storage Server Family" column, per vendor.

In the tables below, "Basic Duplication" refers to server-side or client-side deduplication.

Where support is shown for Windows Server 2003 or Windows Server 2008 please reference the Software Compatibility List ( <<http://entsupport.symantec.com/umi/V-269-1>> ) for supported operating system versions.

## Data Domain

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
Appliance series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Appliance series <a href="#">[1]</a> <a href="#">[2]</a>	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Appliance series <a href="#">[1]</a> <a href="#">[2]</a>	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Appliance series <a href="#">[1]</a> <a href="#">[2]</a>	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.6	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Appliance series <a href="#">[1]</a> <a href="#">[2]</a>	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	3.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DDX Array series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DDX	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Gateway series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DD560g, DD580g, DD690g, DD880g	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Global Deduplication Array series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	GDA	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. Plug-in 2.3.1.0 or newer is required for usage with BE 2012.

2. See the Backup Exec sections in the DataDomain OST Admin guide for installation and configuration details. (Data Domain Support account and access to the 2.x plug-in release required)

3. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## Dell

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DR Series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DR4000, DR4100, DR6000	1.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DR Series <a href="#">[1]</a> <a href="#">[2]</a>	DR4000, DR4100, DR6000	2.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DR Series <a href="#">[1]</a>	DR4000, DR4100, DR6000	3.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. 64 bit Operating Systems are required as only the 64 bit Dell plugin is supported.
2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
3. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## ExaGrid

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
EX series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	EX1000, EX2000, EX3000, EX4000, EX5000, EX7000, EX10000E, EX13000E, EX21000E	V10.3.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
EX series <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	EX1000, EX2000, EX3000, EX4000, EX5000, EX7000, EX10000E, EX13000E, EX21000E	V11.4.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. Browse to the Help->Online Library in the ExaGrid administrative interface and view/download Using Symantec Backup Exec™ with an ExaGrid System.
2. ExaGrid OS version 4.6.4 P12 (or higher) is required when using Backup Exec 2012 SP3 (or higher).
3. For more information, see here: [http://www.exagrid.com/backup\\_applications/Symantec\\_VERITAS\\_Backup\\_Exec.asp](http://www.exagrid.com/backup_applications/Symantec_VERITAS_Backup_Exec.asp)

## FalconStor

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
FDS series [1] [2] [3]	FDS 100, FDS 300, FDS 600	2.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. FDS Server version 2.10 (or newer) is required for usage with BE 2012.

2. Please contact FalconStor for procedure and requirements for large chunk size (block size) support. The block size used for the FDS must match the selected "data stream chunk size" in the Advanced Property section for the OST storage device.

3. The OpenStorage plug-in can be obtained through Falconstor Professional Services.

## Fujitsu

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
ETERNUS CS800 S3 [1]	ETERNUS CS800 S3	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
ETERNUS CS800 S3 [1]	ETERNUS CS800 S3	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
ETERNUS CS800 S4 [1]	ETERNUS CS800 S4	2.6	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
ETERNUS CS800 S4 [1]	ETERNUS CS800 S4	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. For more information, see <http://support.ts.fujitsu.com/Download/> Then, fill in the following values in the "Driver and Downloads" section: select "Storage solutions", then select "ETERNUS CS/CentricStor", then select "ETERNUS CS800"

## GreenBytes

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
GB-X series [1] [2] [3] [4] [5] [6]	GB-1000, GB-2000, GB-4000	1.3.42	Ethernet	✓	✓	Basic Deduplication

1. Backup Exec Remote Agents are not supported by GreenBytes. This must be used with a Backup Exec Server.

2. Limited to one Backup Exec Server per GreenBytes LSU (Logical Storage Unit).

3. Please contact GreenBytes for the required plug-in and configuration instructions.

4. Sharing a GreenBytes LSU between Backup Exec Servers in a Enterprise Server Option (ESO) environment is not supported.

5. The Microsoft iSCSI initiator is required for communication to the GreenBytes server.
6. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## HP

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2008	Supported OpenStorage Functionality
StoreOnce 2000 Backup System [1]	StoreOnce 2620 Backup System, StoreOnce 2700 Backup System	2.0	Ethernet	✓	Basic Deduplication, Optimized Duplication
StoreOnce 4000 Backup System [1]	StoreOnce 4210fc Backup System, StoreOnce 4210i Backup System, StoreOnce 4220 Backup System, StoreOnce 4420 Backup System, StoreOnce 4430 Backup System, StoreOnce 4500 Backup System, StoreOnce 4700 Backup System, StoreOnce 4900 Backup System	2.0	Ethernet	✓	Basic Deduplication, Optimized Duplication
StoreOnce 6000 Backup System [1]	StoreOnce 6500 Backup System, StoreOnce B6200 Backup System	2.0	Ethernet	✓	Basic Deduplication, Optimized Duplication
StoreOnce VSA [2]	StoreOnce VSA	2.0	Ethernet	✓	Basic Deduplication, Optimized Duplication

1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>

2. StoreOnce VSA is a virtual appliance supported on ESX v5.x. For device details & platform support refer to: <http://bizsupport1.austin.hp.com/bc/docs/support/SupportManual/c03822673/c03822673.pdf>

## Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi2500-D [1] [2] [3]	DXi2500-D	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D [1] [2]	DXi2500-D	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D [1] [2]	DXi2500-D	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D [1] [2]	DXi2500-D	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family [1] [2] [3]	DXi4510, DXi4520, DXi4601	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

# Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi4000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4510, DXi4520, DXi4601	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4510, DXi4520, DXi4601	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4510, DXi4520, DXi4601	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4510, DXi4520, DXi4601	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4701	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi4701	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DXi6700, DXi6701, DXi6702	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6700, DXi6701, DXi6702	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6700, DXi6701, DXi6702	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication



# Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi6700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6700, DXi6701, DXi6702	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6700, DXi6701, DXi6702	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6800 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6802	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6800 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6802	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6800 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6802	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6900 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi6902	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[3]</a>	DXi8500, DXi8500 2TB, DXi8500 3TB	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi8500, DXi8500 2TB, DXi8500 3TB	2.5.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi8500, DXi8500 2TB, DXi8500 3TB	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi8500, DXi8500 2TB, DXi8500 3TB	2.7.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family <a href="#">[1]</a> <a href="#">[2]</a>	DXi8500, DXi8500 2TB, DXi8500 3TB	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi V Family [1] [2] [3] [4]	DXi V1000, DXi V4000	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi V Family [1] [2] [4]	DXi V1000, DXi V4000	2.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi V Family [1] [2] [4]	DXi V1000, DXi V4000	2.7.2	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. For more information, see <http://www.quantum.com/ServiceandSupport/SoftwareandDocumentationDownloads/OSTClientPlugIn/Index.aspx>
2. The Quantum hostname and storage server name needs to be different to avoid connection issues.
3. Please note: this device is nearing the end of support. Please see the 'Retiring Soon' section .
4. This device is a virtual appliance. Representative VMware-supported ESX4, ESXi4, or ESXi5 servers/storage were tested. Refer to [http://downloads.quantum.com/dxiv1000/6-67611-01\\_DXi\\_V1000\\_QuickStartGuide\\_RevA.pdf](http://downloads.quantum.com/dxiv1000/6-67611-01_DXi_V1000_QuickStartGuide_RevA.pdf)

## Symantec

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
NetBackup 5000 [1] [2] [3] [4]	NetBackup 5000	6.6.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
NetBackup 5020 [1] [2] [3] [4]	NetBackup 5020	6.6.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
NetBackup 5020 [1] [2] [3] [4]	NetBackup 5020	6.6.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
NetBackup 5020 [1] [2] [3] [4]	NetBackup 5020	6.6.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
NetBackup 5030 [1] [2] [4]	NetBackup 5030	6.6.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. BE 2012 introduced optimized duplication (opt-dupe) operations for GRT backup sets. If a NetBackup 50x0 is specified as the source of a GRT opt-dupe, the operation will fall back to the previous BE 2010 behavior of rehydrating all of the data from the NetBackup 50x0 to the media server before transmitting only the unique data to the target server.
2. If a NetBackup 50x0 is specified as the source of an optimized duplication (opt-dupe) operation, only 1 opt-dupe on that media server will execute at a time. Other opt-dupe, backup, verify, and restore operations will be blocked from running until that opt-dupe job finishes.
3. NBU 5000/5020 software versions v1.4.3.1, or newer, are strongly recommended.

4. The required plug-in for this appliance is included with Backup Exec. When adding the NBU 50x0 OpenStorage device, select the "PureDisk" option. Note: the PureDisk installation log-on screen references plug-ins. These are not needed since Backup Exec includes the plug-in natively.

## PureDisk Deduplication Option

PureDisk 6.6.1 includes Veritas Storage Foundation 5.0 MP4. By default, PureDisk installs the Storage Foundation file system, VxFS, and installs the Storage Foundation volume manager, VxVM. Symantec recommends that you use a storage array that is compatible with this version of Veritas Storage Foundation. The list of compatible (tested) storage arrays are listed in this section.

Similar to the hardware vendor solutions listed in the Partnered OST section, PureDisk is another option for a deduplication appliance, using the OpenStorage specification. PureDisk allows for flexibility in the disk subsystem. Tested arrays are listed in the following section.

## Symantec PureDisk

Storage Server	Software Version	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
PureDisk	6.6.1	6.6.1 [1]	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

1. See "Downloads | Windows Clients" links on the PureDisk installation's Log On screen for the appropriate 32- or 64-bit plug-in.

**For more information on supported array interfaces, advanced features, and a detailed list of arrays that VxVM/VxFS supports [including the necessary Array Support Libraries (ASL)] in the Storage Foundation 5.0 MP4 release, see the hardware compatibility list, SUSE section, at the following web site: <<http://www.symantec.com/docs/TECH47620>>**

**Additional helpful details about PureDisk 6.6.1 can seen in the PureDisk 6.6.1 Compatibility List: <<http://www.symantec.com/docs/TECH139108>>**

## 3PAR

Family	Devices in Family	Mode
E-Class, S-Class	E200 Storage System, S200 Storage System, S400 Storage System, S800 Storage System	A/A

## DataDirect Networks

Family	Devices in Family	Mode
S2A6620	S2A6620	A/A-A
SFA10K-X	SFA10K-X	A/A-A

## Dell

Family	Devices in Family	Mode
Compellent Storage Center 5	Compellent Storage Center 5.2, Compellent Storage Center 5.3, Compellent Storage Center 5.4	A/A
EqualLogic PS3000 series	EqualLogic PS3000E, EqualLogic PS3000X, EqualLogic PS3000XV	A/A
EqualLogic PS4000 series	EqualLogic PS4000E, EqualLogic PS4000X, EqualLogic PS4000XV, EqualLogic PS4100E, EqualLogic PS4100X, EqualLogic PS4100XV, EqualLogic PS4100XV3.5"	A/A
EqualLogic PS5000 series	EqualLogic PS5000E, EqualLogic PS5000X, EqualLogic PS5000XV, EqualLogic PS5500E	A/A
EqualLogic PS6000 series	EqualLogic PS6000E, EqualLogic PS6000S, EqualLogic PS6000X, EqualLogic PS6000XV, EqualLogic PS6000XVS, EqualLogic PS6010E, EqualLogic PS6010S, EqualLogic PS6010X, EqualLogic PS6010XV, EqualLogic PS6010XVS, EqualLogic PS6100E, EqualLogic PS6100X, EqualLogic PS6100XV, EqualLogic PS6100XV3.5", EqualLogic PS6500E, EqualLogic PS6500X, EqualLogic PS6500XV, EqualLogic PS6510E, EqualLogic PS6510X, EqualLogic PX6100S, EqualLogic PX6100XS	A/A
PowerVault MD3200i	PowerVault MD3200i	A/P-F

## Dot Hill

Family	Devices in Family	Mode
5730	5730	A/A

## EMC

Family	Devices in Family	Mode
CLARiiON AX series	Celerra NX4, CLARiiON AX4, CLARiiON AX100	A/P-F
CLARiiON CX3 series	CLARiiON CX3 Model 10, CLARiiON CX3 Model 20, CLARiiON CX3 Model 40, CLARiiON CX3 Model 80	A/A-A, A/P-F
CLARiiON CX4 series	CLARiiON CX4 Model 120, CLARiiON CX4 Model 240, CLARiiON CX4 Model 480, CLARiiON CX4 Model 960	A/A-A, A/P-F
CLARiiON CX series	CLARiiON CX300, CLARiiON CX400, CLARiiON CX500, CLARiiON CX600, CLARiiON CX700	A/A-A, A/P-F
Symmetrix 8000 series	Symmetrix 8230, Symmetrix 8430, Symmetrix 8530, Symmetrix 8830	A/A
Symmetrix DMX series	Symmetrix DMX-3, Symmetrix DMX-4, Symmetrix DMX 800, Symmetrix DMX 1000, Symmetrix DMX 2000, Symmetrix DMX 3000	A/A
Symmetrix VMAX series	Symmetrix VMAX, Symmetrix VMAXe	A/A
VNX series	VNX 5100, VNX 5300, VNX 5500, VNX 5700, VNX 7500	A/A-A, A/P-F

## Fujitsu

Family	Devices in Family	Mode
ETERNUS2000 series	ETERNUS2000 Model 50, ETERNUS2000 Model 100, ETERNUS2000 Model 200	A/A
ETERNUS4000 series	ETERNUS4000 Model 80, ETERNUS4000 Model 100, ETERNUS4000 Model 300, ETERNUS4000 Model 400, ETERNUS4000 Model 500, ETERNUS4000 Model 600	A/A
ETERNUS8000 series	ETERNUS8000 Model 700, ETERNUS8000 Model 800, ETERNUS8000 Model 900, ETERNUS8000 Model 1100, ETERNUS8000 Model 1200, ETERNUS8000 Model 2100, ETERNUS8000 Model 2200	A/A
ETERNUS DX60/DX80/DX90 series	ETERNUS DX60, ETERNUS DX60 S2, ETERNUS DX80, ETERNUS DX80 S2, ETERNUS DX90, ETERNUS DX90 S2	A/A
ETERNUS DX400 series	ETERNUS DX410, ETERNUS DX410 S2, ETERNUS DX440, ETERNUS DX440 S2	A/A

## Fujitsu

Family	Devices in Family	Mode
ETERNUS DX8000 series	ETERNUS DX8100, ETERNUS DX8100 S2, ETERNUS DX8400, ETERNUS DX8700, ETERNUS DX8700 S2	A/A
ETERNUS VS850	ETERNUS VS850	A/A-A
FibreCAT SX80/100 series	FibreCAT SX80, FibreCAT SX100	A/A

## Generic

Family	Devices in Family	Mode
FC JBOD	FC JBOD	A/A
SCSI JBOD	SCSI JBOD	A/A

## Hitachi

Family	Devices in Family	Mode
AMS/WMS series	AMS200, AMS500, AMS1000, WMS100	A/A-A
Lightning 9900V series	9970V, 9980	A/A
SMS/AMS2000 series	AMS2100, AMS2300, AMS2500, SMS100	A/A
Thunder 9500V series	9500 (DF600), 9500V, 9570V, 9580V, AMS200, AMS500, AMS1000, WMS100	A/A-A
TMS1000	TMS1000	A/A-A
USP/NSC series	NSC55, USP100, USP600, USP1100	A/A
USPV/USPVM	USP V, USP VM	A/A
VSP	VSP	A/A

# HP

Family	Devices in Family	Mode
3PAR F/T-Class, StoreServ 7000/10000 Storage	3PAR F200 Storage, 3PAR F400 Storage, 3PAR StoreServ 7200 Storage, 3PAR StoreServ 7400 Storage, 3PAR StoreServ 10400 Storage, 3PAR StoreServ 10800 Storage, 3PAR T400 Storage, 3PAR T800 Storage	A/A
2000 G2 series	MSA2312fc, MSA2312i, MSA2312sa, MSA2324fc, MSA2324i, MSA2324sa	A/A-A
EVA4000/6000/8000	EVA4000, EVA6000, EVA8000	A/A-A
EVA4100/6100/8100	EVA4100, EVA6100, EVA8100	A/A-A
EVA4400/6400/8400	EVA4400, EVA6400, EVA8400	A/A-A
EVA GL 3000/5000	EVA3000, EVA3000GL, EVA5000, EVA5000GL	A/A-A
MSA1500	MSA1500	A/A-A
MSA2000fc series	MSA2012fc, MSA2212fc	A/A
MSA2012sa	MSA2012sa	A/A-A
P2000 G3 MSA series	P2000 G3 FC, P2000 G3 FC/iSCSI, P2000 G3 iSCSI, P2000 G3 SAS	A/A-A
P6000 EVA series	P6300, P6350, P6500, P6550	A/A-A
P9500	P9500	A/A
XP128/1024	XP128, XP1024	A/A
XP10000/12000	XP10000, XP12000	A/A
XP20000/24000	XP20000, XP24000	A/A

# Huawei

Family	Devices in Family	Mode
S5000 series	S2100, S2300, S2300E, S2600, S5100, S5300, S5500, S5600, S6800E, V1500, V1800	A/P-F
S5000T series	Dorado2100, Dorado2100G2, Dorado5100, S2200T, S2600T, S2600T V2, S3900-M100, S3900-M200, S3900-M300, S5500T, S5500T V2, S5600T, S5600T V2, S5800T, S5800T V2, S5900-M100, S5900-M200, S6800T, S6800T V2, S6900-M100	A/P-F
VIS series	S8000, VIS6000, VIS6000T	A/P-F

## IBM

Family	Devices in Family	Mode
Storwize series	SANVC(2145), Storwize V3500, Storwize V3700, Storwize V5000, Storwize V7000, Storwize V7000 Unified	A/A-A
System Storage DS3000 series	DS3200, DS3300, DS3400	A/P-F
System Storage DS5000 series	DS5100, DS5300	A/P-F
System Storage DS6000 series	DS6000 (1750-511), DS6800	A/P-C
System Storage DS8000 series	DS8000, DS8100, DS8300, DS8700, DS8800, DS8870	A/A
System Storage N series	N3150, N3220, N3240, N3300, N3400, N3600, N3700, N5200, N5300, N5500, N5600, N6040, N6060, N6070, N6210, N6220, N6240, N6250, N6270, N7550T, N7600, N7700, N7750T, N7800, N7900, N7950T	A/A, A/P-C
System Storage XIV series	XIV Storage System, XIV Storage System Gen3	A/A
TotalStorage DS4000 series	DS4100 (FAStT100), DS4200, DS4300 (FAStT600), DS4400 (FAStT700), DS4500 (FAStT900), DS4700, DS4800	A/P, A/P-C, A/P-F

## NEC

Family	Devices in Family	Mode
iStorage D1/D3 series	iStorage D1-10, iStorage D1-30, iStorage D1-30i, iStorage D3-10, iStorage D3-10i, iStorage D3-30, iStorage D3-30i, iStorage D4-30, iStorage D4-30i	A/A



## NetApp

Family	Devices in Family	Mode
FAS2000/FAS900/FAS200 series	FAS250, FAS270, FAS920, FAS940, FAS960, FAS980, FAS2020, FAS2040, FAS2050, FAS2220, FAS2240-2, FAS2240-4	A/A, A/P-C
FAS3000/V3000 series	FAS3020, FAS3040, FAS3050, FAS3070, FAS3140, FAS3160, FAS3170, FAS3210, FAS3220, FAS3240, FAS3250, FAS3270, V3020, V3040, V3050, V3070, V3140, V3160, V3170, V3210, V3220, V3240, V3250, V3270	A/A, A/P-C
FAS6000/V6000 series	FAS6030, FAS6040, FAS6070, FAS6080, FAS6210, FAS6220, FAS6240, FAS6250, FAS6280, FAS6290, V6030, V6040, V6070, V6080, V6210, V6220, V6240, V6250, V6280, V6290	A/A, A/P-C

## Oracle

Family	Devices in Family	Mode
Storage 6580/6780 series	Sun Storage 6580 array, Sun Storage 6780 array	A/P-F
StorageTek 2500 series	StorageTek 2510 array, StorageTek 2530 array, StorageTek 2540 array, Sun Storage 2530-M2 array, Sun Storage 2540-M2 array	A/P-F
StorageTek 6140 array	StorageTek 6140 array	A/P-C
StorageTek 9900 series	StorageTek 9970 array, StorageTek 9980 array	A/A
StorageTek 9985/9990 series	StorageTek 9985 system, StorageTek 9990 system	A/A
StorageTek 9985V system	StorageTek 9985V system	A/A
StorageTek 9990V system	StorageTek 9990V system	A/A
Sun Storage 6180 array	Sun Storage 6180 array	A/P-F

## StorageTek

Family	Devices in Family	Mode
FlexLine 200/300 series	FlexLine FLX280, FlexLine FLX380	A/P-C

## Sun

Family	Devices in Family	Mode
StorageTek 6540	StorageTek 6540	A/P-C, A/P-F

## Winchester Systems

Family	Devices in Family	Mode
FlashDisk SX-2318R	FlashDisk SX-2318R	A/A-A

## Xiotech

Family	Devices in Family	Mode
Emprise 5000	Emprise 5000	A/A

# VSS Providers for Offhost backup

This list of tested Volume Shadow Copy Service (VSS) components represents what has been tested in Symantec labs, or in Symantec-supervised partner labs. To ensure compatibility, Symantec, the device manufacturers, and the operating system vendor must support the combination of VSS components. Note: The Backup Exec Advanced Disk Based Backup Option, now part of the Enterprise Server Option, is required for VSS. See the Administrator's Guide for more details on usage of the VSS provider.

## Please Note:

1. The provider version and array firmware listed in this section are the **minimum** levels that are supported. Where more than one entry level is listed in these "Minimum" columns, this implies a newer version has been tested. The earlier versions are the minimum versions required. The hardware vendor may specify rules for pairing of the provider and firmware versions.
2. The Array Firmware listed in this section are the **minimum** levels that are supported.
3. The Advanced Open File job options are not supported for use with Dynamic Disk Snapshots.

## Dell

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
Compellent Storage Center 5 <a href="#">[1]</a>	Compellent Storage Center 5.2, Compellent Storage Center 5.3, Compellent Storage Center 5.4	Fibre Channel, iSCSI	5.4.3	Replay Manager VSS Provider	06.00.02.002, 06.01.00.010
EqualLogic PS3000 series	EqualLogic PS3000E, EqualLogic PS3000X, EqualLogic PS3000XV	iSCSI	V4.3.0 (R104535)	VSS Provider	3.3.0.4883
EqualLogic PS4000 series	EqualLogic PS4000E, EqualLogic PS4000X, EqualLogic PS4000XV, EqualLogic PS4100E, EqualLogic PS4100X, EqualLogic PS4100XV, EqualLogic PS4100XV3.5"	iSCSI	V4.3.0 (R104535)	VSS Provider	3.3.0.4883
EqualLogic PS5000 series	EqualLogic PS5000E, EqualLogic PS5000X, EqualLogic PS5000XV, EqualLogic PS5500E	iSCSI	V4.3.0 (R104535)	VSS Provider	3.3.0.4883
EqualLogic PS6000 series	EqualLogic PS6000E, EqualLogic PS6000S, EqualLogic PS6000X, EqualLogic PS6000XV, EqualLogic PS6000XVS, EqualLogic PS6010E, EqualLogic PS6010S, EqualLogic PS6010X, EqualLogic PS6010XV, EqualLogic PS6010XVS, EqualLogic PS6100E, EqualLogic PS6100X, EqualLogic PS6100XV, EqualLogic PS6100XV3.5", EqualLogic PS6500E, EqualLogic PS6500X, EqualLogic PS6500XV, EqualLogic PS6510E, EqualLogic PS6510X, EqualLogic PX6100S, EqualLogic PX6100XS	iSCSI	V4.3.0 (R104535)	VSS Provider	3.3.0.4883
PowerVault MD3000 <a href="#">[2]</a> <a href="#">[3]</a>	PowerVault MD3000	SAS	06.17.77.60, 7.35.00.00	VSS Provider SmVssProvider	09.17.05

## Dell

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
PowerVault MD3000i <a href="#">[2]</a> <a href="#">[3]</a>	PowerVault MD3000i	iSCSI	06.70.10.60, 7.35.00.00	VSS Provider SmVssProvider	09.70.02, 10.70.08
PowerVault MD3200 <a href="#">[2]</a>	PowerVault MD3200	SAS	7.70.00.00	VSS Provider SmVssProvider	10.70.08
PowerVault MD3200i <a href="#">[2]</a>	PowerVault MD3200i	iSCSI	7.70.00.00	VSS Provider SmVssProvider	10.70.08
PowerVault MD3220 <a href="#">[2]</a>	PowerVault MD3220	SAS	7.70.00.00	VSS Provider SmVssProvider	10.70.08
PowerVault MD3220i <a href="#">[2]</a>	PowerVault MD3220i	iSCSI	7.70.00.00	VSS Provider SmVssProvider	10.70.08

1. Only Windows 2008 operating system versions are supported at this time.
2. Only basic disks are supported at this time.
3. The MD3000/MD3000i does not support concurrent multi-volume snapshot (includes Mount Points).

## EMC

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
CLARiiON CX3 series	CLARiiON CX3 Model 10, CLARiiON CX3 Model 20, CLARiiON CX3 Model 40, CLARiiON CX3 Model 80	Fibre Channel	FLARE 26	Solutions Enabler with VSS Provider	4.0.1
CLARiiON CX4 series <a href="#">[1]</a>	CLARiiON CX4 Model 120, CLARiiON CX4 Model 240, CLARiiON CX4 Model 480, CLARiiON CX4 Model 960	Fibre Channel	FLARE 28	Solutions Enabler with VSS Provider	4.1.2
CLARiiON CX series <a href="#">[2]</a>	CLARiiON CX300, CLARiiON CX400, CLARiiON CX500, CLARiiON CX600, CLARiiON CX700	Fibre Channel	02.19.500.5.016	CLARiiON VSS Provider	1.5.0.3.8
CLARiiON CX series <a href="#">[2]</a>	CLARiiON CX300, CLARiiON CX400, CLARiiON CX500, CLARiiON CX600, CLARiiON CX700	Fibre Channel	FLARE 26	Solutions Enabler with VSS Provider	4.0.1

1. Only basic disks are supported at this time.

2. For the older provider (CLARiiON VSS Provider), only Snapshots are supported. Clones are not supported. The newer provider (Solutions Enabler with VSS Provider) does not have this limitation.

## EqualLogic

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
PS series <a href="#">[1]</a>	PS100E	iSCSI	V2.2.3 (R75), V4.0.2 (R83937)	VSS Provider	2.0.0.0, 2.2.1, 3.0, 3.1.2.0

1. Only basic disks are supported at this time.

## Fujitsu

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
ETERNUS2000 series <a href="#">[1]</a> <a href="#">[2]</a>	ETERNUS2000 Model 50, ETERNUS2000 Model 100, ETERNUS2000 Model 200	Fibre Channel	V10L35-0000	Eternus VSS Hardware Provider	1.1.0
ETERNUS4000 series <a href="#">[1]</a>	ETERNUS4000 Model 80, ETERNUS4000 Model 100, ETERNUS4000 Model 300, ETERNUS4000 Model 400, ETERNUS4000 Model 500, ETERNUS4000 Model 600	Fibre Channel	V20L21-0000	Eternus VSS Hardware Provider	1.3.0
ETERNUS8000 series <a href="#">[1]</a>	ETERNUS8000 Model 700, ETERNUS8000 Model 800, ETERNUS8000 Model 900, ETERNUS8000 Model 1100, ETERNUS8000 Model 1200, ETERNUS8000 Model 2100, ETERNUS8000 Model 2200	Fibre Channel	N/A	Eternus VSS Hardware Provider	1.3.0
ETERNUS DX60/DX80/DX90 series <a href="#">[1]</a> <a href="#">[3]</a> <a href="#">[4]</a>	ETERNUS DX60, ETERNUS DX60 S2, ETERNUS DX80, ETERNUS DX80 S2, ETERNUS DX90, ETERNUS DX90 S2	Fibre Channel, iSCSI	N/A, V10L22-3000	Eternus VSS Hardware Provider	1.3.0, 2.1.0
ETERNUS DX400 series <a href="#">[1]</a> <a href="#">[3]</a>	ETERNUS DX410, ETERNUS DX410 S2, ETERNUS DX440, ETERNUS DX440 S2	iSCSI	N/A	Eternus VSS Hardware Provider	2.1.0
ETERNUS DX8000 series <a href="#">[1]</a> <a href="#">[3]</a>	ETERNUS DX8100, ETERNUS DX8100 S2, ETERNUS DX8400, ETERNUS DX8700, ETERNUS DX8700 S2	iSCSI	N/A	Eternus VSS Hardware Provider	2.1.0

1. Only basic disks are supported at this time.

2. The Fujitsu VSS Hardware Provider does not support the ETERNUS2000 Model 50.
3. Series S2 platforms require a v2.x provider.
4. The ETERNUS DX60 S2 requires a v1.x provider.

## Hitachi

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
AMS/WMS series	AMS200, AMS500, AMS1000, WMS100	Fibre Channel, iSCSI	0772/D-S	Shadow Copy Provider Software	v3.0.0.0
AMS/WMS series	AMS200, AMS500, AMS1000, WMS100	Fibre Channel	0893/E-X	VSS Hardware Provider	4.3.5
BR1200 [1]	BR1200	Fibre Channel, iSCSI, SAS	7.77.19.00	VSS Provider SmVssProvider	10.77.30
Lightning 9900V series	9970V, 9980	Fibre Channel	21-09-15-00/00	RM ShadowCopy Provider	01-02-03/01
SMS/AMS2000 series [1]	AMS2100, AMS2300, AMS2500, SMS100	Fibre Channel, iSCSI	0843/B-S	RM ShadowCopy Provider	01.01.0003.0000
SMS/AMS2000 series [1]	AMS2100, AMS2300, AMS2500, SMS100	Fibre Channel, iSCSI	1811/A-A, 0843/B-S	Shadow Copy Provider Software	v3.0.0.0, v3.2.0
SMS/AMS2000 series [1]	AMS2100, AMS2300, AMS2500, SMS100		0893/E-X	VSS Hardware Provider	4.3.5

1. Only basic disks are supported at this time.

## HP

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
2000 G2 series	MSA2312fc, MSA2312i, MSA2312sa, MSA2324fc, MSA2324i, MSA2324sa	Fibre Channel, iSCSI, SAS	M110R21	P2000/MSA2000 VSS Provider	2.7.0.0
EVA4000/6000/8000	EVA4000, EVA6000, EVA8000	Fibre Channel	XCS 5.031	EVA VSS Provider	3.0.6
EVA4100/6100/8100	EVA4100, EVA6100, EVA8100	Fibre Channel, iSCSI	XCS 5.031	EVA VSS Provider	3.0.6

# HP

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
EVA4400/6400/8400 [1] [2]	EVA4400, EVA6400, EVA8400	Fibre Channel, iSCSI	XCS 9.5011, XCS 9.5012	EVA VSS Provider	4.03.00.02, 5.01.00.02
LeftHand P4000 Virtual San Appliance	LeftHand P4300, LeftHand P4500	iSCSI	8.1.00.0047.0	SAN/iQ Solutions Pack	8.1.00.0047.0
P2000 G3 MSA series	P2000 G3 FC, P2000 G3 FC/iSCSI, P2000 G3 iSCSI, P2000 G3 SAS	Fibre Channel, iSCSI, SAS	TS200R021	P2000/MSA2000 VSS Provider	2.7.0.0

1. Only basic disks are supported at this time.
2. The minimum VSS provider for Windows 2008 is 5.01.00.02, For Windows 2003, 4.03.00.02.

# IBM

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
DS3950 [1]	DS3950	Fibre Channel, iSCSI	7.70.00.00	VSS Provider SmVssProvider	10.70.08
DS5020 [1]	DS5020	Fibre Channel	7.70.00.00	VSS Provider SmVssProvider	10.70.08
System Storage DS3000 series [1]	DS3200, DS3300, DS3400	Fibre Channel, iSCSI, SAS	07.35.42, 7.35.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
System Storage DS3500 series [1]	DCS3700, DS3512, DS3524	Fibre Channel, iSCSI, SAS	7.70.00.00	VSS Provider SmVssProvider	10.70.08
System Storage DS5000 series [1]	DS5100, DS5300	Fibre Channel, iSCSI	7.70.00.00	VSS Provider SmVssProvider	10.70.08
System Storage DS6000 series [2]	DS6000 (1750-511), DS6800	Fibre Channel	5.0.6.0041	TotalStorage Hardware Provider for VSS	2.4.2.0116
System Storage DS8000 series [2]	DS8000, DS8100, DS8300, DS8700, DS8800, DS8870	Fibre Channel	5.1	TotalStorage Hardware Provider for VSS	3.2.1.0319

## IBM

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
TotalStorage DS4000 series <a href="#">[1]</a> <a href="#">[3]</a>	DS4100 (FASiT100), DS4200, DS4300 (FASiT600), DS4400 (FASiT700), DS4500 (FASiT900), DS4700, DS4800	Fibre Channel	04.10.22.00, 7.60.40.00, 6.60.00.00, 7.60.00.00, 6.12.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08

1. Only basic disks are supported at this time.
2. Only Snapshots are supported. Clones are not currently supported.
3. In order to use the ADBO VSS feature, the IBM "Flash Copy" Premium Feature must be purchased.

## Imation

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
Nexsan E-Series V Systems	Nexsan E18V System, Nexsan E32V System, Nexsan E48V System, Nexsan E60V System	Fibre Channel, iSCSI	R011.1201.3	VSS Hardware Provider	1.6.33

## LeftHand Networks

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
NSM 150	NSM 150	iSCSI	6.6.00.0099.0	SAN/iQ Solutions Pack	1.3.0.44



## LSI Logic

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
Engenio 1932 [1]	Engenio 1932	Fibre Channel	07.35.42.00	VSS Provider SmVssProvider	09.70.06, 10.70.08

1. Only basic disks are supported at this time.

## NEC

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
iStorage S2000 series [1]	iStorage S2100, iStorage S2300, iStorage S2400, iStorage S2500, iStorage S2800, iStorage S2900	Fibre Channel	010A	Storage VSS Provider - iStorage S/A Series	1.1.1.3

1. Only Replication Control (full copy method) is supported.

## Oracle

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
Storage 6580/6780 series [1]	Sun Storage 6580 array, Sun Storage 6780 array	Fibre Channel	7.70.00.00	VSS Provider SmVssProvider	10.70.08
StorageTek 2500 series [1]	StorageTek 2510 array, StorageTek 2530 array, StorageTek 2540 array, Sun Storage 2530-M2 array, Sun Storage 2540-M2 array	Fibre Channel, iSCSI, SAS	6.70.54.11, 7.35.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
StorageTek 6140 array [1] [2]	StorageTek 6140 array	Fibre Channel	07.10.22.00, 7.60.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
Sun Storage 6180 array [1]	Sun Storage 6180 array	Fibre Channel	7.70.00.00	VSS Provider SmVssProvider	10.70.08

1. Only basic disks are supported at this time.

2. Requires Sun 'Data Snapshot' Software

## SGI

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
InfiniteStorage 350 <a href="#">[1]</a> <a href="#">[2]</a>	InfiniteStorage 350	Fibre Channel	04.10.22.00, 7.60.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
InfiniteStorage 4000 <a href="#">[1]</a> <a href="#">[2]</a>	InfiniteStorage 4000	Fibre Channel	04.10.22.00, 7.60.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
InfiniteStorage 4500 <a href="#">[2]</a>	InfiniteStorage 4500	Fibre Channel	04.10.22.00	VSS Provider SmVssProvider	09.70.06
TP9500 <a href="#">[1]</a>	TP9500	Fibre Channel	6.60.00.00	VSS Provider SmVssProvider	10.70.08

1. Only basic disks are supported at this time.
2. Requires SGI 'SnapCopy' Software

## StorageTek

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
FlexLine 200/300 series <a href="#">[1]</a>	FlexLine FLX280, FlexLine FLX380	Fibre Channel	6.60.00.00	VSS Provider SmVssProvider	10.70.08
OPENstorage 9176/9170 <a href="#">[1]</a>	OPENstorage 9176/9170	Fibre Channel	6.12.00.00	VSS Provider SmVssProvider	10.70.08

1. Only basic disks are supported at this time.

## Sun

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
StorageTek 6130 <a href="#">[1]</a> <a href="#">[2]</a>	StorageTek 6130	Fibre Channel	07.10.22.00, 6.60.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
StorageTek 6540 <a href="#">[1]</a> <a href="#">[2]</a>	StorageTek 6540	Fibre Channel	07.10.22.00, 7.60.00.00	VSS Provider SmVssProvider	09.70.06, 10.70.08
StorageTek 9176 <a href="#">[2]</a>	StorageTek 9176	Fibre Channel	07.10.22.00	VSS Provider SmVssProvider	09.70.06

1. Only basic disks are supported at this time.
2. Requires Sun 'Data Snapshot' Software

## Xiotech

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
Magnitude 3D	Magnitude 3D	Fibre Channel	0503	DataScale SP VSS HW Provider	4.1.0.44

## Xyratex

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
RS-1220	RS-1220	Fibre Channel	N/A	VSS Hardware Provider	0.0.1.01

# VDS Providers for Storage Provisioning Option

This list of tested Virtual Disk Service (VDS) components represents what has been tested in Symantec labs, or in Symantec-supervised partner labs. To ensure compatibility, Symantec, the device manufacturers, and the operating system vendor must support the combination of VDS components. Note: The Backup Exec Storage Provisioning Option is required for VDS. See the Administrator's Guide for more details on usage of the VDS provider.

## Please Note:

1. The provider version software listed in this section are the **minimum** software levels that are supported.
2. The Array Firmware listed in this section are the **minimum** levels that are supported.
3. For Windows 2008, SP2 is required. (or apply <http://support.microsoft.com/kb/958387> ).
4. For Windows 2008 R2, KB979940 is recommended. (<http://support.microsoft.com/kb/979940> ).

## Dell

Device Family	Device Family Members	Interface	Solution Stack Version	Provider Name	Minimum Provider Version	HBA	Minimum HBA Firmware
EqualLogic PS3000 series <a href="#">[1]</a>	EqualLogic PS3000E, EqualLogic PS3000X, EqualLogic PS3000XV	iSCSI	V4.3.5(R115269)	EqualLogic VDS Provider	3.4.2	Intel PRO 100 S	N/A
EqualLogic PS4000 series <a href="#">[1]</a>	EqualLogic PS4000E, EqualLogic PS4000X, EqualLogic PS4000XV, EqualLogic PS4100E, EqualLogic PS4100X, EqualLogic PS4100XV, EqualLogic PS4100XV3.5"	iSCSI	V4.3.5(R115269)	EqualLogic VDS Provider	3.4.2	Intel PRO 100 S	N/A
EqualLogic PS5000 series <a href="#">[1]</a>	EqualLogic PS5000E, EqualLogic PS5000X, EqualLogic PS5000XV, EqualLogic PS5500E	iSCSI	V4.3.5(R115269)	EqualLogic VDS Provider	3.4.2	Intel PRO/1000 MT Dual Port	N/A
EqualLogic PS5000 series <a href="#">[1]</a>	EqualLogic PS5000E, EqualLogic PS5000X, EqualLogic PS5000XV, EqualLogic PS5500E	iSCSI	V4.3.5(R115269)	EqualLogic VDS Provider	3.4.2	Intel PRO 100 S	N/A

## Dell

Device Family	Device Family Members	Interface	Solution Stack Version	Provider Name	Minimum Provider Version	HBA	Minimum HBA Firmware
EqualLogic PS6000 series <a href="#">[1]</a>	EqualLogic PS6000E, EqualLogic PS6000S, EqualLogic PS6000X, EqualLogic PS6000XV, EqualLogic PS6000XVS, EqualLogic PS6010E, EqualLogic PS6010S, EqualLogic PS6010X, EqualLogic PS6010XV, EqualLogic PS6010XVS, EqualLogic PS6100E, EqualLogic PS6100X, EqualLogic PS6100XV, EqualLogic PS6100XVS, EqualLogic PS6500E, EqualLogic PS6500X, EqualLogic PS6500XV, EqualLogic PS6510E, EqualLogic PS6510X, EqualLogic PX6100S, EqualLogic PX6100XS	iSCSI	V4.3.5(R115269)	EqualLogic VDS Provider	3.4.2	Intel PRO 100 S	N/A
PowerVault DL2000	PowerVault DL2000	SAS	1.0	Dell PERC VDS provider	91.00.36.36	Dell PERC 6/E	6.1.1-0047
PowerVault DL2100	PowerVault DL2100	SAS	1.2.6	Dell PERC VDS provider	91.01.36.05	Dell PERC 6/E	6.2.0-0013
PowerVault DL2100	PowerVault DL2100	SAS	2.1	Dell PERC VDS provider	91.02.36.07	Dell PERC 6/i	6.2.0-0013
PowerVault DL2200	PowerVault DL2200	SAS	3.0	Dell PERC VDS provider	91.02.36.12	Dell PERC H700	12.3.0-0032
PowerVault DL2200	PowerVault DL2200	SAS	3.0	Dell PERC VDS provider	91.02.36.12	Dell PERC H800	12.3.0-0032

1. The HBA details listed for this row indicate the NIC tested with the storage device. This specific HBA is not required for support.

## Fujitsu

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
ETERNUS2000 series <a href="#">[1]</a> <a href="#">[2]</a>	ETERNUS2000 Model 50, ETERNUS2000 Model 100, ETERNUS2000 Model 200	iSCSI	V10L78	Fujitsu VDS provider	1.4.0
ETERNUS DX400 series <a href="#">[1]</a> <a href="#">[2]</a>	ETERNUS DX410, ETERNUS DX410 S2, ETERNUS DX440, ETERNUS DX440 S2	Fibre Channel	V20L43-0000	Fujitsu VDS provider	1.4.0

1. Please log off any active sessions from the ETERNUS WEB GUI before using Backup Exec.

2. This VDS provider only supports one Backup Exec server running the Storage Provisioning Option per array. Sharing in a Shared Storage Option or Central Admin Server Option is not allowed.

## Hitachi

Device Family	Device Family Members	Interface	Minimum Array Firmware	Provider Name	Minimum Provider Version
AMS/WMS series	AMS200, AMS500, AMS1000, WMS100	Fibre Channel	0786/C-S	Hitachi Virtual Disk Service	4.x
SMS/AMS2000 series	AMS2100, AMS2300, AMS2500, SMS100	Fibre Channel	08B5/A-X	Hitachi Virtual Disk Service	4.x

# Virtual Tape Libraries with Drives

The virtual tape device support information is listed below. This information is organized by vendor and provides information on the level of software tested, inquiry string (vendor ID + product ID), and any other important notes about the hardware and its compatibility.

## **Please Note:**

1. The virtual tape device software listed in this section are the **minimum** software levels that are supported. Where more than one software level is listed, this implies a newer version has been tested. The earlier software version is the minimum version required.
2. Configure the virtual device with the unique inquiry string as listed in this document. Emulating other devices is not supported.
3. For each virtual library only the virtual tape drives that are listed are supported. This information can be found with each virtual section. Other virtual tape drive types are not supported even if the real device is supported with Backup Exec.
4. Do not fill up the disk space on a virtual device. Doing so may cause unpredictable behavior of the device. The device vendor will then have to recover from any errors that result from a full disk.
5. When moving virtual volumes to physical media it works best if the virtual device has a volume size that is dynamic. Make sure that the virtual volume is slightly smaller than the physical volume. When you migrate the data to physical media you will need to ensure that there is enough space on the physical device in order to accommodate the virtual volume size.
6. It is highly recommended that Backup Exec move virtual volumes to physical media so that the data can be restored directly from physical media rather than needing to utilize the virtual device as an intermediary restoration point. If the virtual tape library moves virtual volumes to physical media Backup Exec is not aware of the physical media and may not be able to recover that data directly from that physical media.
7. When a virtual volume becomes overwriteable, the virtual device is not aware that the data is no longer needed. When Backup Exec overwrites that virtual volume the virtual library is aware that the rest of the data is not needed and it can free up the disk space. Because of this, the virtual device may appear to be much closer to capacity than it really is.
8. Tested iSCSI versions of virtual tape libraries are listed in the "iSCSI Solutions" section, under the "SAN Infrastructure components" bookmark. Please reference the limitations listed in that section.
9. The software versions documented here are obtained from the library interface (web or physical) and may not match the firmware version logged in the adamm.log.
10. All VTLs shared with the Linux server(s) must be approved for both RMAL and ESO. Zoning or LUN masking are possible methods of preventing Linux servers from seeing a VTL not approved for RMAL.

## Virtual Tape Library/Drive Legend

Value	Meaning
^	Character used to denote a space in the INQUIRY STRING.
✓	Character used to denote support for the item listed in the column.
WinBES	The listed device is supported in a Windows Backup Exec Server platform. Shareability is determined by the ESO column. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Backup Exec Server Operating System platforms.
RMAL	The listed device is supported in a Remote Media Agent for Linux platform. Shareability is determined by the ESO column. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Remote Media Agent for Linux platforms.
NDMP	The listed device is supported for use with NDMP. See the "NDMP Option" section for platform specific details. Shareability is determined by the ESO column.
ESO	The listed device is supported by the Enterprise Server Option using Fibre Channel. ESO refers to WinBES, and optionally RMAL or NDMP.

### Contents

<u>Data Domain</u>	<u>EMC</u>	<u>FalconStor</u>
<u>Fujitsu</u>	<u>HP</u>	<u>IBM</u>
<u>NEC</u>	<u>NetApp</u>	<u>Overland Storage</u>
<u>Quantum</u>	<u>SEPATON</u>	<u>Sun</u>
<u>Virtual Tape Library Families</u>		



## Data Domain

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Appliance Series (members)	5.3	Fibre Channel	HP	Ultrium 960 LTO3	D_DOMAINRESTORER_L180 HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
Appliance Series (members)	5.3	Fibre Channel	HP	Ultrium 1840 LTO4	D_DOMAINRESTORER_L180 HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
Appliance Series (members) [1]	5.5	Fibre Channel	HP	Ultrium 3280 LTO5	D_DOMAINRESTORER_L180 HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
Appliance Series (members)	4.5.1.2	Fibre Channel	IBM	Ultrium 1	D_DOMAINRESTORER_L180 IBM~~~~~ULTRIUM-TD1	✓	✓	✓	✓
Appliance Series (members)	5.3	Fibre Channel	IBM	Ultrium 4	D_DOMAINRESTORER_L180 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
DD400 Series (members) [2]	4.1.5.0	Fibre Channel	IBM	Ultrium 1	D_DOMAINRESTORER_L180 IBM~~~~~ULTRIUM-TD1	✓	✓		✓

1. Both the "D\_DOMAINRESTORER\_L180" and "EMC~~~~~DDVTL" library inquiry strings are supported when using DDOS 5.5 (or higher) and "HF 212772" (or higher). Use latest SP available by downloading: <http://www.symantec.com/docs/TECH212772> or via LiveUpdate.

2. VTLs are not shareable between servers. Each VTL must be configured with LUN masking so that it can only be seen by 1 server to prevent interference.

## EMC

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
CDL300 Series (members)		Fibre Channel	IBM	TotalStorage 3580 Ultrium 1	EMC~~~~~Disk^Library IBM~~~~~ULT3580-TD1	✓		✓	✓
Disk Library Series (members)	2.1.5 build 1175	Fibre Channel	IBM	TotalStorage 3580 Ultrium 1	EMC~~~~~Disk^Library IBM~~~~~ULT3580-TD1	✓	✓	✓	✓
Disk Library Series (members)	2.1.5 build 1175	Fibre Channel	IBM	Ultrium 2	EMC~~~~~Disk^Library IBM~~~~~ULTRIUM-TD2	✓	✓	✓	✓
NDMP2D	5.5	NDMP	EMC	EMC DLT	EMC~~~~~svtIrobot EMC~~~~~svtIDrive			✓	

## FalconStor

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
VirtualTape Library (RedHat 5.3 VTL Server Platform)	5.20	Fibre Channel	IBM	Ultrium 3	FALCON^VTL IBM^ULTRIUM-TD3	✓	✓	✓	✓
VirtualTape Library (RedHat 5.3 VTL Server Platform)	5.21	Fibre Channel	IBM	Ultrium 4	FALCON^VTL IBM^ULTRIUM-TD4	✓	✓	✓	✓
VirtualTape Library (RedHat AS Linux VTL Server Platform)	3.00.1047 EE	Fibre Channel	IBM	Ultrium 1	FALCON^VTL IBM^ULTRIUM-TD1	✓	✓	✓	✓

## Fujitsu

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
CentricStor <a href="#">[1]</a> <a href="#">[2]</a>	3.1.4070	SCSI	Exabyte	Mammoth-2 (M2)	FSC^CS-TL EXABYTE^Mammoth2	✓			✓
ETERNUS CS <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[3]</a>	4.1A4040-SP00-P130	Fibre Channel	IBM	Ultrium 2	FSC^CS-TL IBM^ULTRIUM-TD2	✓	✓	✓	✓
ETERNUS CS <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[3]</a>	5.0A	Fibre Channel	IBM	Ultrium 4	FSC^CS-TL IBM^ULTRIUM-TD4	✓	✓	✓	✓
ETERNUS CS800 S2 <a href="#">[4]</a> <a href="#">[5]</a> <a href="#">[6]</a>	1.4.1_800	Fibre Channel	HP	Ultrium 1840 LTO4	FSC^CS-TL HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS CS800 S3 <a href="#">[4]</a> <a href="#">[5]</a> <a href="#">[7]</a>	2.0.2_800	Fibre Channel	HP	Ultrium 3280 LTO5	FSC^CS-TL HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS CS800 S4 <a href="#">[4]</a> <a href="#">[5]</a> <a href="#">[7]</a>	2.2, 2.3.0.1_S4	Fibre Channel	IBM	Ultrium 5	FSC^CS-TL IBM^ULTRIUM-TD5	✓	✓	✓	✓
ETERNUS CS800 <a href="#">[4]</a> <a href="#">[5]</a> <a href="#">[6]</a>	1.4.1_800	Fibre Channel	HP	Ultrium 1840 LTO4	FSC^CS-TL HP^Ultrium^4-SCSI	✓	✓	✓	✓

1. Capacity and compression reporting is not currently supported for this device.

2. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#).
3. The ETERNUS line was previously known as the CentricStor.
4. Backup Exec supports Fujitsu's Path-to-Tape (PTT) feature available on this VTL. PTT manages duplication backups directly from a virtual tape to physical tape while off-loading the duplication backup operations from the Backup Exec server. This is referred to as "DirectCopy to tape" in the Administrator's Guide.
5. The default port for Backup Exec remote agents may conflict with the NDMP port used for the Path-to-Tape feature. Refer to the following technote to change the default port: <http://www.symantec.com/docs/TECH24256>
6. This VTL also supports the following emulated tape drives: HP Ultrium 1-SCSI, HP Ultrium 2-SCSI, HP Ultrium 3-SCSI, HP Ultrium 4-SCSI, IBM ULTRIUM-TD1, IBM ULTRIUM-TD2, IBM ULTRIUM-TD3, and the IBM ULTRIUM-TD4.
7. This VTL also supports the following emulated tape drives: HP Ultrium 1-SCSI, HP Ultrium 2-SCSI, HP Ultrium 3-SCSI, HP Ultrium 4-SCSI, HP Ultrium 5-SCSI, IBM ULTRIUM-TD1, IBM ULTRIUM-TD2, IBM ULTRIUM-TD3, IBM ULTRIUM-TD4, and the IBM ULTRIUM-TD5.

## HP

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
D2D4000 Series Backup System ( <a href="#">members</a> ) [1]	pf86	Fibre Channel	HP	Ultrium 1840 LTO4	HP^D2DBS HP^Ultrium^4-SCSI	✓	✓	✓	✓
D2D4100 G2 Series Backup System ( <a href="#">members</a> )	2.2.10	Fibre Channel	HP	Ultrium 3280 LTO5	HP^D2DBS HP^Ultrium^5-SCSI	✓	✓	✓	✓
D2D4100 Series Backup System ( <a href="#">members</a> ) [1]		Fibre Channel	HP	Ultrium 1840 LTO4	HP^D2DBS HP^Ultrium^4-SCSI	✓	✓	✓	✓
D2D4300 G2 Series Backup System ( <a href="#">members</a> ) [1]		Fibre Channel	HP	Ultrium 3280 LTO5	HP^D2DBS HP^Ultrium^5-SCSI	✓	✓	✓	✓
StoreOnce 4000 Backup System ( <a href="#">members</a> ) [2]		Fibre Channel	HP	Ultrium 3280 LTO5	HP^D2DBS HP^Ultrium^5-SCSI	✓	✓	✓	✓
StoreOnce 6000 Backup System ( <a href="#">members</a> )	3.0.0-1146.6	Fibre Channel	HP	Ultrium 3280 LTO5	HP^D2DBS^Generic HP^Ultrium^5-SCSI	✓	✓	✓	✓
VLS 300 EVA Gateway [3]		Fibre Channel	HP	Ultrium 230 LTO1	HP^VLS HP^Ultrium^1-SCSI	✓	✓	✓	✓
VLS 300 EVA Gateway [3]		Fibre Channel	HP	Ultrium 460 LTO2	HP^VLS HP^Ultrium^2-SCSI	✓	✓	✓	✓

# HP

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
VLS 300 EVA Gateway [3]	1.1.0	Fibre Channel	HP	Ultrium 960 LTO3	HP~~~~~VLS HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
VLS 6000 Series (members) [3]	1.1.0	Fibre Channel	HP	Ultrium 230 LTO1	HP~~~~~VLS HP~~~~~Ultrium^1-SCSI	✓	✓	✓	✓
VLS 6000 Series (members) [3]	1.1.0	Fibre Channel	HP	Ultrium 460 LTO2	HP~~~~~VLS HP~~~~~Ultrium^2-SCSI	✓	✓	✓	✓
VLS 6000 Series (members) [3]	1.0.4, 1.1.0, 2.0	Fibre Channel	HP	Ultrium 960 LTO3	HP~~~~~VLS HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
VLS 9000 Series [3]	2.1	Fibre Channel	HP	Ultrium 230 LTO1	HP~~~~~VLS HP~~~~~Ultrium^1-SCSI	✓	✓	✓	✓
VLS 9000 Series [3]	2.1	Fibre Channel	HP	Ultrium 460 LTO2	HP~~~~~VLS HP~~~~~Ultrium^2-SCSI	✓	✓	✓	✓
VLS 9000 Series [3]	2.1	Fibre Channel	HP	Ultrium 960 LTO3	HP~~~~~VLS HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
VLS 9200 Series [3]	6.0.0, 6.0.0.2	Fibre Channel	HP	Ultrium 1840 LTO4	HP~~~~~VLS HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
VLS 12000 EVA Gateway [3]	2.0	Fibre Channel	HP	Ultrium 230 LTO1	HP~~~~~VLS HP~~~~~Ultrium^1-SCSI	✓	✓	✓	✓
VLS 12000 EVA Gateway [3]	2.0	Fibre Channel	HP	Ultrium 460 LTO2	HP~~~~~VLS HP~~~~~Ultrium^2-SCSI	✓	✓	✓	✓
VLS 12000 EVA Gateway [3]	2.0	Fibre Channel	HP	Ultrium 960 LTO3	HP~~~~~VLS HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓

1. This VTL also supports HP LTO2, LTO3, LTO4, and LTO5 tape drive emulation. These combinations are also supported.
2. This VTL also supports HP LTO3 and HP LTO2 tape drive emulation. These combinations are also supported.
3. HP supports with maximum block size of 256k

## IBM

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
System Storage TS7600 series with ProtecTIER <a href="#">(members)</a> [1] [2]	2.2.3.16, 3.3.0.0	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	IBM^V3584L32 IBM^ULT3580-TD3	✓	✓	✓	✓
Virtualization Engine TS7530 <a href="#">[3]</a> <a href="#">[4]</a>	1.10	Fibre Channel	IBM	System Storage TS2340 Ultrium 4	IBM^TS7530 IBM^ULT3580-TD4	✓	✓	✓	✓

1. Capacity and compression reporting is not currently supported for this device.
2. Minimum firmware level of 2.2.3.16 is required.
3. Consult with IBM for their "Best Practices" configuration, which is required for ESO.
4. The maximum Buffer/Block size supported for this device is 128K.

## NEC

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
T5000VT Series <a href="#">(members)</a> [1]	02.25.14	Fibre Channel	Quantum	DLT 7000	QUANTUM^DX100 QUANTUM^DLT7000	✓			✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## NetApp

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
NearStore Virtual Tape Library <a href="#">(members)</a>	4.1.2, 5.2.3 (VTL OS)	Fibre Channel	IBM	Ultrium 2	NETAPP^VTL IBM^ULTRIUM-TD2	✓	✓	✓	✓
NearStore Virtual Tape Library <a href="#">(members)</a>	6.0.1P2	Fibre Channel	IBM	Ultrium 4	NETAPP^VTL IBM^ULTRIUM-TD4	✓	✓	✓	✓

## Overland Storage

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
REO 9500D <a href="#">[1]</a>	1.2.2.8.3	Fibre Channel	Quantum	DLT 7000	DTC^VTF QUANTUM^DLT7000	✓	✓	✓	✓
REO Series 5.X <a href="#">(members)</a> <a href="#">[2]</a>	3.1.0.28, 4.0.2.31	Fibre Channel	HP	Ultrium 460 LTO2	OVERLANDREO^Series HP^Ultrium^2-SCSI	✓	✓	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#).
2. All family members are capable of either iSCSI or FC connectivity, with the exception of the REO 1500; it is iSCSI only.

## Quantum

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
DX30 <a href="#">[1]</a>	2769	Fibre Channel	Quantum	DLT 7000	QUANTUM^DX30 QUANTUM^DLT7000	✓			✓
DX100 <a href="#">[1]</a>	02.25.14, 02.31.11	Fibre Channel	Quantum	DLT 7000	QUANTUM^DX100 QUANTUM^DLT7000	✓		✓	✓

# Quantum

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
DX3000/DX5000 Series <a href="#">(members)</a> [1]	02.65.00	Fibre Channel	Quantum	DLT 7000	QUANTUM^DX QUANTUM^DLT7000	✓			✓
DXi3500/DXi5500 Dxi Series <a href="#">(members)</a>	04.00.114, 04.00.123, 0400	Fibre Channel	Quantum	DLT 7000	QUANTUM^DXi QUANTUM^DLT7000	✓	✓	✓	✓
DXi4700 Series <a href="#">(members)</a> [2]	2.3.1	Fibre Channel	HP	Ultrium 3280 LTO5	QUANTUM^DXi HP^Ultrium^5-SCSI	✓	✓	✓	✓
DXi6700 Series <a href="#">(members)</a> [2] [3] [4] [5] [6]	1.4.1, 2.0.1	Fibre Channel	HP	Ultrium 1840 LTO4	QUANTUM^DXi HP^Ultrium^4-SCSI	✓	✓	✓	✓
DXi6800 Series <a href="#">(members)</a> [2] [3] [4] [6]	2.2_68	Fibre Channel	HP	Ultrium 1840 LTO4	QUANTUM^DXi HP^Ultrium^4-SCSI	✓	✓	✓	✓
DXi6900 Series <a href="#">(members)</a> [2] [3] [4] [6]	3.0.0	Fibre Channel	HP	Ultrium 3280 LTO5	QUANTUM^DXi HP^Ultrium^5-SCSI	✓	✓	✓	✓
DXi7500 Series <a href="#">(members)</a> [3] [4] [6] [7]	1.0, 5.1.312b	Fibre Channel	HP	Ultrium 1840 LTO4	QUANTUM^DXi HP^Ultrium^4-SCSI	✓	✓	✓	✓
DXi8500 Series <a href="#">(members)</a> [2] [3] [4] [6]	1.4.2_85, 1.4.5_85	Fibre Channel	HP	Ultrium 1840 LTO4	QUANTUM^DXi HP^Ultrium^4-SCSI	✓	✓	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

2. This VTL also supports the following emulated tape drives: HP Ultrium 2-SCSI, HP Ultrium 3-SCSI, HP Ultrium 4-SCSI, HP Ultrium 5-SCSI, IBM ULTRIUM-TD2, IBM ULTRIUM-TD3, IBM ULTRIUM-TD4, and the IBM ULTRIUM-TD5.

3. Backup Exec supports Quantum's Path-to-Tape (PTT) feature available on this VTL. PTT manages duplication backups directly from a virtual tape to physical tape while off-loading the duplication backup operations from the Backup Exec server. This is referred to as "DirectCopy to tape" in the Administrator's Guide.

4. Block sizes greater than 64KB (the default) are currently not supported with Quantum's Path-to-Tape(PTT) feature.

5. In order to support 2TB capacity expansions for the DXi6700, Quantum Galaxy OS 2.0.1 software is required. Please contact Quantum Service [OSR@Quantum.com](mailto:OSR@Quantum.com)

6. The default port for Backup Exec remote agents may conflict with the NDMP port used for the Path-to-Tape feature. Refer to the following technote to change the default port: <http://www.symantec.com/docs/TECH24256>

7. This VTL also supports the following emulated tape drives: HP Ultrium 1-SCSI, HP Ultrium 2-SCSI, HP Ultrium 3-SCSI, HP Ultrium 4-SCSI, IBM ULTRIUM-TD1, IBM ULTRIUM-TD2, IBM ULTRIUM-TD3, IBM ULTRIUM-TD4, Quantum LTO-2, Quantum LTO-3, Quantum SDLT 600, and the Quantum DLT-S4.

## SEPATON

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
S2100 ( <a href="#">members</a> )	2.1.2	Fibre Channel	IBM	Ultrium 1	SEPATON^S2100 IBM^ULTRIUM-TD1	✓	✓	✓	✓
S2100 ( <a href="#">members</a> )	2.1.2, 5.2.2	Fibre Channel	IBM	Ultrium 3	SEPATON^S2100 IBM^ULTRIUM-TD3	✓	✓	✓	✓

## Sun

Device	Minimum Software Version	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageTek VTL Plus 1.0 ( <a href="#">members</a> ) [1]	4.0	Fibre Channel	StorageTek	T10000A	SUN^VTL STK^T10000A	✓			✓
StorageTek VTL Plus 2.0 ( <a href="#">members</a> ) [1] [2]	5.10	Fibre Channel	HP	Ultrium 1840 LTO4	SUN^VTL HP^Ultrium^4-SCSI	✓	✓	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

2. Export from disk (virtual tape) to physical tape is not supported.

## Virtual Tape Library Families

When a hardware family of devices is listed, refer to this section for a definition of family members. Generally speaking, the family name and members are defined by the hardware manufacturer, and share common operational traits. In some cases, a specific member of the family may not be supported in the same fashion as the other members. When this occurs, a footnote in the hardware category section will identify this limitation.



## Data Domain

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	Appliance Series	Fibre Channel	DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200
<a href="#">Backtrack</a>	DD400 Series	Fibre Channel	DD410, DD430, DD460

## EMC

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	CDL300 Series	Fibre Channel	CDL310
<a href="#">Backtrack</a>	Disk Library Series	Fibre Channel	CDL210, CDL300 Series, CDL310, CDL700, CDL700 Series, CDL710, CDL720, CDL740, DL4000 Series, DL6000 Series

## Fujitsu

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	ETERNUS CS	Fibre Channel	ETERNUS CS50, ETERNUS CS500, ETERNUS CS1000, ETERNUS CS1500, ETERNUS CS2000, ETERNUS CS3000, ETERNUS CS4000, ETERNUS CS5000, ETERNUS CS8000

## HP

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	D2D4000 Series Backup System	Fibre Channel	D2D4004fc Backup System, D2D4009fc Backup System
<a href="#">Backtrack</a>	D2D4100 G2 Series Backup System	Fibre Channel	D2D4106fc G2 Backup System, D2D4112 G2 Backup System
<a href="#">Backtrack</a>	D2D4100 Series Backup System	Fibre Channel	D2D4112fc Backup System
<a href="#">Backtrack</a>	D2D4300 G2 Series Backup System	Fibre Channel	D2D4312 G2 Backup System, D2D4324 G2 Backup System
<a href="#">Backtrack</a>	StoreOnce 4000 Backup System	Fibre Channel	StoreOnce 4210fc Backup System, StoreOnce 4220 Backup System, StoreOnce 4420 Backup System, StoreOnce 4430 Backup System, StoreOnce 4500 Backup System, StoreOnce 4700 Backup System
<a href="#">Backtrack</a>	StoreOnce 6000 Backup System	Fibre Channel	StoreOnce 6500 Backup System, StoreOnce B6200 Backup System
<a href="#">Backtrack</a>	VLS 6000 Series	Fibre Channel	VLS6105, VLS6109, VLS6218, VLS6227, VLS6510, VLS6518, VLS6636, VLS6653, VLS6840, VLS6870

## IBM

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	System Storage TS7600 series with ProtecTIER	Fibre Channel	System Storage TS7610SM1 ProtecTIER (V-TS3500), System Storage TS7620SM2 ProtecTIER (V-TS3500), System Storage TS7650AP1 ProtecTIER (V-TS3500), System Storage TS7650G ProtecTIER (V-TS3500)

## NEC

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	T5000VT Series	Fibre Channel	T5100VT, T5150VT, T5200VT, T5250VT

## NetApp

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	NearStore Virtual Tape Library	Fibre Channel	VTL300, VTL600, VTL700, VTL1200, VTL1400

## Overland Storage

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	REO Series 5.X	Fibre Channel	REO 1500, REO 4500, REO 4500c, REO 4600, REO 9100, REO 9100c

## Quantum

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	DX3000/DX5000 Series	Fibre Channel	DX3000, DX5000
<a href="#">Backtrack</a>	DXi3500/DXi5500 Dxi Series	Fibre Channel	DXi3500, DXi5500
<a href="#">Backtrack</a>	DXi4700 Series	Fibre Channel	DXi4701
<a href="#">Backtrack</a>	DXi6700 Series	Fibre Channel	DXi6700, DXi6701, DXi6702
<a href="#">Backtrack</a>	DXi6800 Series	Fibre Channel	DXi6802
<a href="#">Backtrack</a>	DXi6900 Series	Fibre Channel	DXi6902
<a href="#">Backtrack</a>	DXi7500 Series	Fibre Channel	DXi7500, DXi7500 Enterprise, DXi7500 Express, DXi7500-N
<a href="#">Backtrack</a>	DXi8500 Series	Fibre Channel	DXi8500, DXi8500 2TB, DXi8500 3TB

## SEPATON

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	S2100	Fibre Channel	S2100-DS2, S2100-DS3, S2100-ES2

## Sun

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	StorageTek VTL Plus 1.0	Fibre Channel	VTL1140, VTL2540, VTL3540
<a href="#">Backtrack</a>	StorageTek VTL Plus 2.0	Fibre Channel	VTL1200, VTL1202, VTL2600, VTL3600

# Tape Drives

The tape drive support information is listed below. This information is organized by vendor and provides information on the tape drives tested, the supported Inquiry Strings, the type of interface, media type, and any special notes on a per device basis.

## Please Note:

1. To ensure support, a device must be supported by Symantec and the device manufacturer.
2. Unless otherwise noted, Symantec tape class drivers were used when testing Windows-supported devices.
3. At times the manufacturer may refer to their devices by product name, which differs from the model name.
4. WORM is supported only on tape drives with a footnote indicating WORM support and a possible minimum firmware or software level. These footnotes are documented in this stand-alone tape drive section. To determine if WORM is supported in an automation environment. (i.e. physical tape libraries), please refer to the tape drive manufacturers stand-alone drive section and check for a footnote. If WORM is supported in the manufacturers drive section, then it is supported in all automation, unless documented otherwise in the automation section.
5. Hardware encryption is supported only on tape drives with a footnote indicating hardware encryption support and a possible minimum firmware or software level. These footnotes are documented in this stand-alone tape drive section. To determine if hardware encryption is supported in an automation environment. (i.e. physical tape libraries), please refer to the tape drive manufacturers stand-alone drive section and check for a footnote. If hardware encryption is supported in the manufacturers drive section, then it is supported in all automation, unless documented otherwise in the automation section.
6. The "ULTRIUM-TD" and the "ULT3580-TD" inquiry strings are interchangeable (both are supported), unless otherwise indicated. The "ULTRIUM-HH" and the "ULT3580-HH" inquiry strings are interchangeable (both are supported), unless otherwise indicated.
7. Unless specifically stated in technote <<http://www.symantec.com/docs/TECH70907>> , tape libraries or tape drives attached to a RAID controller are not supported.
8. The HP One Button Disaster Recovery (OBDR) feature is no longer supported with Backup Exec.

## Tape Drive Legend

Value	Meaning
^	Character used to denote a space in the INQUIRY STRING.
✓	Character used to denote support for the item listed in the column.
WinBES	The listed device is supported in a Windows Backup Exec Server platform. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Backup Exec Server Operating System platforms.
RMAL	The listed device is supported in a Remote Media Agent for Linux platform. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Remote Media Agent for Linux platforms.

## Contents

actidata

IBM

Sony

Tandberg

Dell

Imation

StorageTek

UNITEX

HP

Quantum

Sun

## actidata

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
actiTape LTO3 - Half Height	IBM~~~~~ULT3580-HH3	SCSI	LTO	✓	✓
actiTape LTO4 - Full Height	IBM~~~~~ULT3580-TD4	Fibre Channel	LTO	✓	✓
actiTape LTO4 - Full Height	IBM~~~~~ULT3580-TD4	SCSI	LTO	✓	✓
actiTape LTO4 - Half Height	IBM~~~~~ULT3580-HH4	SAS	LTO	✓	✓
actiTape LTO5 - Full Height	IBM~~~~~ULT3580-TD5	Fibre Channel	LTO	✓	✓
actiTape LTO5 - Full Height	IBM~~~~~ULT3580-TD5	SAS	LTO	✓	✓

## Dell

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
PowerVault 100T DAT72	SEAGATE^DAT^DAT72	SCSI	4mm	✓	
PowerVault 110T LTO2 (Certance)	CERTANCEULTRIUM^2	SCSI	LTO	✓	✓
PowerVault 110T LTO2 (Gen2 IBM)	IBM~~~~~ULTRIUM-TD2	SCSI	LTO	✓	✓
PowerVault 110T LTO3 (IBM) [1]	IBM~~~~~ULTRIUM-TD3	SCSI	LTO	✓	✓
PowerVault 110T SDLT320	QUANTUM^SDLT320	SCSI	DLT	✓	
PowerVault 110T VS160	QUANTUM^DLT^VS160	SCSI	DLT	✓	
PowerVault 112T series [2]	varies	SCSI		✓	
PowerVault 114T series [2]	varies	SAS		✓	

# Dell

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
PowerVault 114T series [2]	varies	SCSI		✓	
PowerVault 114X series [2]	varies	USB 2.0		✓	
PowerVault 114X series [2]	various^LTO^drives	SAS		✓	
PowerVault LTO-6 [3] [4] [5]	IBM^ULTRIUM-HH6	SAS	LTO	✓	✓
PowerVault LTO3-060 (IBM) [3]	IBM^ULTRIUM-HH3	SAS	LTO	✓	✓
PowerVault LTO3-060 (IBM) [3]	IBM^ULTRIUM-HH3	SCSI	LTO	✓	✓
PowerVault LTO3-060 (Quantum) [3]	QUANTUM^ULTRIUM^3	SAS	LTO	✓	✓
PowerVault LTO3-060 (Quantum) [6]	QUANTUM^ULTRIUM^3	SCSI	LTO	✓	✓
PowerVault LTO3-080 (IBM) [3]	IBM^ULTRIUM-HH3	SAS	LTO	✓	✓
PowerVault LTO4-120 (Quantum) [3] [5]	QUANTUM^ULTRIUM^4	SAS	LTO	✓	✓
PowerVault LTO4-120 [3] [5]	IBM^ULTRIUM-TD4	SAS	LTO	✓	✓
PowerVault LTO4-120HH [3] [5]	IBM^ULTRIUM-HH4	SAS	LTO	✓	✓
PowerVault LTO5-140 [3] [5]	IBM^ULTRIUM-HH5	SAS	LTO	✓	✓

1. WORM tape is supported with initial firmware level 5480
2. This is a rack mounted enclosure for Dell certified tape drives and should not be confused with actual Dell tape drives.
3. WORM tape is supported with this drive.
4. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
5. T10 Hardware Encryption is supported.
6. WORM tape is supported with initial firmware level 1896

# HP

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
DAT 72	HP^C7438A	SCSI	4mm	✓	
DAT 72 [1]	HP^C7438A	USB 2.0	4mm	✓	
DAT 160 [2]	HP^DAT160	SAS	4mm	✓	✓
DAT 160 [2]	HP^DAT160	SCSI	4mm	✓	✓
DAT 160 [1] [2]	HP^DAT160	USB 2.0	4mm	✓	
DAT 320 [2] [3]	HP^DAT320	SAS	4mm	✓	✓
DAT 320 [1] [2] [3]	HP^DAT320	USB 2.0	4mm	✓	
Ultrium 448 LTO2 [4] [5]	HP^Ultrium^2-SCSI	SAS	LTO	✓	✓
Ultrium 448 LTO2 [4] [5]	HP^Ultrium^2-SCSI	SCSI	LTO	✓	✓
Ultrium 460 LTO2	HP^Ultrium^2-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 460 LTO2	HP^Ultrium^2-SCSI	SCSI	LTO	✓	✓
Ultrium 920 LTO3 [2] [4] [5]	HP^Ultrium^3-SCSI	SAS	LTO	✓	✓
Ultrium 920 LTO3 [2] [4] [5]	HP^Ultrium^3-SCSI	SCSI	LTO	✓	✓
Ultrium 960 LTO3 [2]	HP^Ultrium^3-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 960 LTO3 [2]	HP^Ultrium^3-SCSI	SCSI	LTO	✓	✓
Ultrium 1760 LTO4 [2] [3] [4] [5]	HP^Ultrium^4-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 1760 LTO4 [2] [3] [4] [5]	HP^Ultrium^4-SCSI	SAS	LTO	✓	✓
Ultrium 1760 LTO4 [2] [3] [4] [5]	HP^Ultrium^4-SCSI	SCSI	LTO	✓	✓
Ultrium 1840 LTO4 [2] [3]	HP^Ultrium^4-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 1840 LTO4 [2] [3]	HP^Ultrium^4-SCSI	SAS	LTO	✓	✓
Ultrium 1840 LTO4 [2] [3]	HP^Ultrium^4-SCSI	SCSI	LTO	✓	✓
Ultrium 3000 LTO5 [2] [3] [4]	HP^Ultrium^5-SCSI	SAS	LTO	✓	✓
Ultrium 3280 LTO5 [2] [3]	HP^Ultrium^5-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 3280 LTO5 [2] [3]	HP^Ultrium^5-SCSI	SAS	LTO	✓	✓
Ultrium 6250 LTO6 [2] [3] [4] [6]	HP^Ultrium^6-SCSI	Fibre Channel	LTO	✓	✓



# HP

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
Ultrium 6250 LTO6 [2] [3] [4] [6]	HP^Ultrium^6-SCSI	SAS	LTO	✓	✓
Ultrium 6650 LTO6 [2] [3] [6]	HP^Ultrium^6-SCSI	Fibre Channel	LTO	✓	✓
Ultrium 6650 LTO6 [2] [3] [6]	HP^Ultrium^6-SCSI	SAS	LTO	✓	✓

1. For all USB tape drives, the vendor's device driver must be loaded prior to starting Backup Exec.
2. WORM tape is supported with this drive.
3. T10 Hardware Encryption is supported.
4. Half-Height drive configuration.
5. Supported in the HP BladeSystem c-Class chassis.
6. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>

# IBM

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
LTO Gen 3 400/800GB (P/N 25R0012 / 39M5657)	IBM^ULTRIUM-TD3	SCSI	LTO	✓	✓
LTO Gen 3 HH (P/N 43W8478/3628L3X/3628N3X) [1]	IBM^HH^LTO^Gen^3	SAS	LTO	✓	✓
LTO Gen 4 HH (P/N 44E8895/3628L4X/3628N4X) [1] [2]	IBM^HH^LTO^Gen^4	SAS	LTO	✓	✓
LTO Gen 5 HH (P/N 49Y9898/3628L5X/3628N5X) [1] [2]	IBM^HH^LTO^Gen^5	SAS	LTO	✓	✓
LTO Gen 6 HH (P/N 00D8924) [1] [2] [3]	IBM^HH^LTO^Gen^6	SAS	LTO	✓	✓
System Storage TS2230 Ultrium 3 Half Height [1]	IBM^ULT3580-HH3	SAS	LTO	✓	✓
System Storage TS2230 Ultrium 3 Half Height [1]	IBM^ULT3580-HH3	SCSI	LTO	✓	✓
System Storage TS2240 Ultrium 4 Half Height [2]	IBM^ULT3580-HH4	Fibre Channel	LTO	✓	✓
System Storage TS2240 Ultrium 4 Half Height [1] [2]	IBM^ULT3580-HH4	SAS	LTO	✓	✓
System Storage TS2250 Ultrium 5 Half Height [1] [2]	IBM^ULT3580-HH5	Fibre Channel	LTO	✓	✓
System Storage TS2250 Ultrium 5 Half Height [1] [2]	IBM^ULT3580-HH5	SAS	LTO	✓	✓

# IBM

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
System Storage TS2260 Ultrium 6 Half Height <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[4]</a>	IBM~~~~~ULT3580-HH6	Fibre Channel	LTO	✓	✓
System Storage TS2260 Ultrium 6 Half Height <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[4]</a>	IBM~~~~~ULT3580-HH6	SAS	LTO	✓	✓
System Storage TS2340 Ultrium 4 <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULT3580-TD4	Fibre Channel	LTO	✓	✓
System Storage TS2340 Ultrium 4 <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULT3580-TD4	SAS	LTO	✓	✓
System Storage TS2340 Ultrium 4 <a href="#">[1]</a>	IBM~~~~~ULT3580-TD4	SCSI	LTO	✓	✓
System Storage TS2350 Ultrium 5 <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULT3580-TD5	Fibre Channel	LTO	✓	✓
System Storage TS2350 Ultrium 5 <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULT3580-TD5	SAS	LTO	✓	✓
System Storage TS2360 Ultrium 6 <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[4]</a>	IBM~~~~~ULT3580-TD6	Fibre Channel	LTO	✓	✓
System Storage TS2360 Ultrium 6 <a href="#">[1]</a> <a href="#">[2]</a> <a href="#">[4]</a>	IBM~~~~~ULT3580-TD6	SAS	LTO	✓	✓
TotalStorage 3580 Ultrium 1	IBM~~~~~ULT3580-TD1	SCSI	LTO	✓	✓
TotalStorage 3580 Ultrium 2	IBM~~~~~ULT3580-TD2	Fibre Channel	LTO	✓	✓
TotalStorage 3580 Ultrium 2 <a href="#">[5]</a>	IBM~~~~~ULT3580-TD2	SCSI	LTO	✓	✓
TotalStorage 3580 Ultrium 3 <a href="#">[6]</a>	IBM~~~~~ULT3580-TD3	Fibre Channel	LTO	✓	✓
TotalStorage 3580 Ultrium 3 <a href="#">[6]</a>	IBM~~~~~ULT3580-TD3	SCSI	LTO	✓	✓
Ultrium 1	IBM~~~~~ULTRIUM-TD1	SCSI	LTO	✓	✓
Ultrium 2	IBM~~~~~ULTRIUM-TD2	Fibre Channel	LTO	✓	✓
Ultrium 2	IBM~~~~~ULTRIUM-TD2	SCSI	LTO	✓	✓
Ultrium 3 Half Height <a href="#">[6]</a>	IBM~~~~~ULTRIUM-HH3	SAS	LTO	✓	✓
Ultrium 3 Half Height <a href="#">[6]</a>	IBM~~~~~ULTRIUM-HH3	SCSI	LTO	✓	✓
Ultrium 3 <a href="#">[6]</a>	IBM~~~~~ULTRIUM-TD3	Fibre Channel	LTO	✓	✓
Ultrium 3 <a href="#">[6]</a>	IBM~~~~~ULTRIUM-TD3	SCSI	LTO	✓	✓
Ultrium 4 (U160) <a href="#">[1]</a>	IBM~~~~~ULTRIUM-TD4	SCSI	LTO	✓	✓
Ultrium 4 (U320) <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULTRIUM-TD4	SCSI	LTO	✓	✓
Ultrium 4 Half Height (U320) <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULTRIUM-HH4	SCSI	LTO	✓	✓
Ultrium 4 Half Height <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULTRIUM-HH4	Fibre Channel	LTO	✓	✓
Ultrium 4 Half Height <a href="#">[1]</a> <a href="#">[2]</a>	IBM~~~~~ULTRIUM-HH4	SAS	LTO	✓	✓

# IBM

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
Ultrium 4 [1] [2]	IBM~~~~ULTRIUM-TD4	Fibre Channel	LTO	✓	✓
Ultrium 4 [1] [2]	IBM~~~~ULTRIUM-TD4	SAS	LTO	✓	✓
Ultrium 5 Half Height [1] [2]	IBM~~~~ULTRIUM-HH5	Fibre Channel	LTO	✓	✓
Ultrium 5 Half Height [1] [2]	IBM~~~~ULTRIUM-HH5	SAS	LTO	✓	✓
Ultrium 5 [1] [2]	IBM~~~~ULTRIUM-TD5	Fibre Channel	LTO	✓	✓
Ultrium 5 [1] [2]	IBM~~~~ULTRIUM-TD5	SAS	LTO	✓	✓
Ultrium 6 Half Height [1] [2] [4]	IBM~~~~ULTRIUM-HH6	Fibre Channel	LTO	✓	✓
Ultrium 6 Half Height [1] [2] [4]	IBM~~~~ULTRIUM-HH6	SAS	LTO	✓	✓
Ultrium 6 [1] [2] [4]	IBM~~~~ULTRIUM-TD6	Fibre Channel	LTO	✓	✓
Ultrium 6 [1] [2] [4]	IBM~~~~ULTRIUM-TD6	SAS	LTO	✓	✓

1. WORM tape is supported with this drive.
2. T10 Hardware Encryption is supported.
3. Required driver support can be found in "DDI 2012 20121215". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
4. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
5. IBM Part Number 59P6744
6. WORM tape is supported with initial firmware level 5480

# Imation

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
LR1100 LTO 1U Storage Enclosure	varies	SAS		✓	✓
Ultrium 4 Half Height [1] [2]	IBM~~~~ULTRIUM-HH4	SAS	LTO	✓	✓
Ultrium 5 Half Height [1] [2]	IBM~~~~ULTRIUM-HH5	SAS	LTO	✓	✓

1. WORM tape is supported with this drive.
2. T10 Hardware Encryption is supported.

# Quantum

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
DAT 72 USB <a href="#">[1]</a> <a href="#">[2]</a>	QUANTUM^DAT^^^DAT72	SATA	4mm	✓	
DAT 72	QUANTUM^DAT^^^DAT72	SATA	4mm	✓	
DAT 72	QUANTUM^DAT^^^DAT72	SCSI	4mm	✓	
DAT 160 <a href="#">[3]</a>	QUANTUM^DAT^^^DAT160	SAS	4mm	✓	
DAT 160 <a href="#">[3]</a>	QUANTUM^DAT^^^DAT160	SCSI	4mm	✓	✓
DAT 160 <a href="#">[1]</a> <a href="#">[3]</a>	QUANTUM^DAT^^^DAT160	USB 2.0	4mm	✓	
DAT 320 <a href="#">[1]</a> <a href="#">[4]</a>	QUANTUM^DAT^^^DAT320-000	USB 2.0	4mm	✓	
DLT-S4 <a href="#">[3]</a>	QUANTUM^DLT-S4	Fibre Channel	DLT	✓	✓
DLT-S4 <a href="#">[3]</a>	QUANTUM^DLT-S4	SCSI	DLT	✓	✓
DLT-V4 <a href="#">[1]</a> <a href="#">[3]</a> <a href="#">[5]</a>	QUANTUM^DLT-V4	SATA	DLT	✓	
DLT-V4 <a href="#">[3]</a>	QUANTUM^DLT-V4	SCSI	DLT	✓	✓
DLT VS160	QUANTUM^DLT^VS160	SCSI	DLT	✓	
LTO-2 HH	CERTANCEULTRIUM^2	SCSI	LTO	✓	✓
LTO-2 <a href="#">[6]</a>	CERTANCEULTRIUM^2	SCSI	LTO	✓	✓
LTO-3 HH <a href="#">[3]</a>	QUANTUM^ULTRIUM^3	Fibre Channel	LTO	✓	✓
LTO-3 HH <a href="#">[3]</a>	QUANTUM^ULTRIUM^3	SAS	LTO	✓	✓
LTO-3 HH <a href="#">[7]</a>	QUANTUM^ULTRIUM^3	SCSI	LTO	✓	✓
LTO-3 <a href="#">[6]</a> <a href="#">[8]</a>	CERTANCEULTRIUM^3	SCSI	LTO	✓	✓
LTO-4 HH <a href="#">[3]</a> <a href="#">[4]</a>	QUANTUM^ULTRIUM^4	SAS	LTO	✓	✓
LTO-4 HH <a href="#">[3]</a> <a href="#">[4]</a>	QUANTUM^ULTRIUM^4	SCSI	LTO	✓	✓
LTO-5 FH <a href="#">[3]</a> <a href="#">[4]</a>	QUANTUM^ULTRIUM^5	SAS	LTO	✓	✓
LTO-5 HH <a href="#">[3]</a> <a href="#">[4]</a>	QUANTUM^ULTRIUM^5	SAS	LTO	✓	✓
LTO-6 HH <a href="#">[3]</a> <a href="#">[4]</a> <a href="#">[9]</a>	QUANTUM^ULTRIUM^6	SAS	LTO	✓	✓
SDLT 320	QUANTUM^SDLT320	SCSI	DLT	✓	

## Quantum

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
SDLT 600 [3]	QUANTUM^SDLT600	SCSI	DLT	✓	
Ultrium 4 HH [10] [3] [4]	QUANTUM^ULTRIUM-HH4	SAS	LTO	✓	✓
Ultrium 5 HH [10] [3] [4]	QUANTUM^ULTRIUM-HH5	SAS	LTO	✓	✓
Ultrium 6 HH [10] [3] [4]	QUANTUM^ULTRIUM-HH6	SAS	LTO	✓	✓

1. For all USB tape drives, the vendor's device driver must be loaded prior to starting Backup Exec.
2. Requires a SATA-to-USB Adapter provided by Quantum.
3. WORM tape is supported with this drive.
4. T10 Hardware Encryption is supported.
5. This SATA device is sold with a USB interface option. This option is a Quantum-supplied SATA~USB converter internal to the server. If used, the device appears as a USB tape drive to the OS, thus requiring a QUANTUM-supplied USB tape driver. Any escalations related to the use of the Quantum-supplied driver and/or USB/SATA converter should be handled by Quantum Technical Support.
6. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
7. WORM tape is supported with initial firmware level 1896
8. WORM tape is supported with firmware level 1856, or newer.
9. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
10. Required driver support can be found in "HF 212772". Use latest SP available by downloading: <http://www.symantec.com/docs/TECH212772> or via LiveUpdate

## Sony

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
SDTi320UB (DAT 320) [1] [2] [3] [4]	SONY^^^SDT320	USB 2.0	4mm	✓	
SDX-250V AITi50/S (AIT-E Turbo) [3]	SONY^^^SDX-250V	SCSI	8mm	✓	
SDX-450V AITi100/S (AIT-1 Turbo) [3]	SONY^^^SDX-450V	SCSI	8mm	✓	
SDX-460V AITe100-UL (AIT-1 Turbo) [3] [5]	SONY^^^SDX-460V	USB 2.0	8mm	✓	
SDX-470V AITi100-ST (AIT-1 Turbo S-ATA) [3]	SONY^^^SDX-470V	SATA	8mm	✓	

# Sony

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
SDX-550V AITi200/S (AIT-2 Turbo) [3] [6]	SONY^^^SDX-550V	SCSI	8mm	✓	
SDX-560V AITe200-UL (AIT-2 Turbo) [3] [5] [6] [7]	SONY^^^SDX-560V	USB 2.0	8mm	✓	
SDX-570V AITi200-ST (AIT-2 Turbo S-ATA) [3] [6]	SONY^^^SDX-570V	SATA	8mm	✓	✓
SDX-800V AITi390/S (AIT-3Ex) [3] [8]	SONY^^^SDX-800V	SCSI	8mm	✓	
SDX-870V AITi390/ST (AIT-3Ex) [2] [3]	SONY^^^SDX-870V	SATA	8mm	✓	
SDX-870V AITi390/ST (AIT-3Ex) USB [2] [3] [7] [9]	SONY^^^SDX-870V	SATA	8mm	✓	
SDX-900V AITi520/S (AIT-4) [10] [3]	SONY^^^SDX-900V	SCSI	8mm	✓	
SDX-1100 AITe1040 (AIT-5) [2] [3]	SONY^^^SDX-1100	SCSI	8mm	✓	✓
SDX-1100 AITi1040 (AIT-5) [2] [3]	SONY^^^SDX-1100	SCSI	8mm	✓	✓
SDZ-100 SAITi1300SS (SAIT) [11] [3]	SONY^^^SDZ-100	SCSI	SAIT	✓	
SDZ-130 SAITi1300SS (SAIT) [11] [3]	SONY^^^SDZ-130	Fibre Channel	SAIT	✓	
SDZ-200 [3]	SONY^^^SDZ-200	SCSI	SAIT	✓	

1. Capacity and compression reporting is not currently supported for this device.
2. WORM tape is supported with this drive.
3. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
4. T10 Hardware Encryption is supported.
5. Backup Exec Simplified Disaster Recovery (SDR) is not supported. The Sony S32AIT.SYS v2.0.0.5 (or higher) is required for use with Backup Exec for Windows Servers. Please contact Sony to acquire this driver. The Sony SDX-460V and SDX-560V with USB interfaces are not compatible with "Write SCSI pass-through mode". This option must be disabled in Backup Exec. Please contact Technical Support for more assistance or refer to ( <http://www.symantec.com/docs/TECH45377> )
6. WORM tape is supported with this drive (initial firmware level 0100).
7. For all USB tape drives, the vendor's device driver must be loaded prior to starting Backup Exec.
8. WORM tape is supported with this drive (initial firmware level 0101).
9. This SATA device is sold with a USB interface option. This option is a Sony-supplied SATA~USB converter internal to the server. If used, the device appears as a USB tape drive to the OS, thus requiring a Sony-supplied USB tape driver. The Sony s32ait.sys "AIT 150 GB USB Tape Drive" driver, version 3.0.0.1 (or higher) is required for use with Backup Exec. Any escalations related to the use of the Sony-supplied driver and/or USB/SATA converter should be handled by Sony Technical Support.
10. WORM tape is supported with this drive (initial firmware level 0103).

11. WORM tape is supported with this drive (initial firmware level 0201).

## StorageTek

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
T9840C	STK^T9840C	Fibre Channel	half inch	✓	
T9940B [1]	STK^T9940B	Fibre Channel	half inch	✓	
T10000A 4GB	STK^T10000A	Fibre Channel	half inch	✓	
T10000B	STK^T10000B	Fibre Channel	half inch	✓	✓
T10000C	STK^T10000C	Fibre Channel	half inch	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## Sun

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
LTO3 HH	HP^Ultrium^3-SCSI	SAS	LTO	✓	✓
LTO3 HH	HP^Ultrium^3-SCSI	SCSI	LTO	✓	✓
LTO4 HH	HP^Ultrium^4-SCSI	SAS	LTO	✓	✓
LTO4 HH	HP^Ultrium^4-SCSI	SCSI	LTO	✓	✓

# Tandberg

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
240LTO	IBM^ULTRIUM-TD1	SCSI	LTO	✓	✓
440LTO	IBM^ULTRIUM-TD2	SCSI	LTO	✓	✓
840LTO	IBM^ULTRIUM-TD3	SCSI	LTO	✓	✓
1640LTO [1]	IBM^ULTRIUM-TD4	SAS	LTO	✓	✓
1640LTO [1]	IBM^ULTRIUM-TD4	SCSI	LTO	✓	✓
DAT 72	HP^C7438A	SCSI	4mm	✓	
DAT 72 [2]	HP^C7438A	USB 2.0	4mm	✓	
DAT 160 [1]	HP^DAT160	SCSI	4mm	✓	✓
DAT 160 [1] [2]	HP^DAT160	USB 2.0	4mm	✓	
DAT 320 [1] [3]	HP^DAT320	SAS	4mm	✓	✓
DAT 320 [1] [2] [3]	HP^DAT320	USB 2.0	4mm	✓	
HH LTO 2	TANDBERGLTO-2^HH	SAS	LTO	✓	✓
HH LTO 2	TANDBERGLTO-2^HH	SCSI	LTO	✓	✓
HH LTO 3 [1]	TANDBERGLTO-3^HH	SAS	LTO	✓	✓
HH LTO 3 [1]	TANDBERGLTO-3^HH	SCSI	LTO	✓	✓
HH LTO 4 [1] [3]	TANDBERGLTO-4^HH	SAS	LTO	✓	✓
HH LTO 4 [1] [3]	TANDBERGLTO-4^HH	SCSI	LTO	✓	✓
HH LTO 5 [1] [3]	TANDBERGLTO-5^HH	Fibre Channel	LTO	✓	✓
HH LTO 5 [1] [3]	TANDBERGLTO-5^HH	SAS	LTO	✓	✓
HH LTO 6 [1] [3] [4]	TANDBERGLTO-6^HH	Fibre Channel	LTO	✓	✓
HH LTO 6 [1] [3] [4]	TANDBERGLTO-6^HH	SAS	LTO	✓	✓

1. WORM tape is supported with this drive.
2. For all USB tape drives, the vendor's device driver must be loaded prior to starting Backup Exec for Windows Servers.
3. T10 Hardware Encryption is supported.
4. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>



## UNITEX

Device	Inquiry String	Drive Interface	Media	WinBES	RMAL
LT50 USB <a href="#">[1]</a> <a href="#">[2]</a>	IBM^~~~~HH^LTO^Gen^5	USB	LTO	✓	

1. Backup Exec Simplified Disaster Recovery (SDR) is not supported.

2. T10 Hardware Encryption is supported.

# Tape Libraries with Drives

The library support information is listed below. This information is organized by vendor manufacturer/model, inquiry string (vendor ID + product ID), the interface of the library, and any other important notes or information relevant to the hardware and its compatibility.

Partitioning a library using the library management for sharing between applications and/or servers is a hardware specific feature available in certain library storage systems. Customers using this hardware feature with Backup Exec are supported, but due the variations in design and implementation, technical support is provided in a "reasonable effort" basis only. This means that Symantec Technical Support will work with customers to resolve issues associated only with the Backup Exec portion of the shared configurations, and any issues that cannot be duplicated outside of the shared environment will be the responsibility of the OEM hardware vendor to support.

## Please Note:

1. This listing is for library support and the tape drive it was tested with. If a tape library is configured with a drive other than that listed, it has not been tested and will not be supported.
2. Tested iSCSI versions of tape libraries are listed in the "iSCSI Solutions" section, under the "SAN Infrastructure components" bookmark. Please reference the limitations listed in that section.
3. The "ULTRIUM-TD" and the "ULT3580-TD" inquiry strings are interchangeable (both are supported), unless otherwise indicated. The "ULTRIUM-HH" and the "ULT3580-HH" inquiry strings are interchangeable (both are supported), unless otherwise indicated.
4. Unless specifically stated in technote <<http://www.symantec.com/docs/TECH70907>> , tape libraries or tape drives attached to a RAID controller are not supported.
5. Libraries or drives with an interface column of "SCSI" require an interface card or bridge to establish a connection to an FC switch. Please see the "SAN Infrastructure components/Fibre Channel Infrastructure/Bridges and Routers" section for supported devices.
6. Please refer to the stand-alone tape drive section (above) and look under the **drive manufacturer** to determine WORM or hardware encryption support status.

## Tape Library Legend

Value	Meaning
^	Character used to denote a space in the INQUIRY STRING.
✓	Character used to denote support for the item listed in the column.
WinBES	The listed device is supported in a Windows Backup Exec Server platform. Shareability is determined by the ESO column. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Backup Exec Server Operating System platforms.

# Tape Library Legend

Value	Meaning
RMAL	The listed device is supported in a Remote Media Agent for Linux platform. Shareability is determined by the ESO column. See the SCL ( <a href="http://entsupport.symantec.com/umi/V-269-1">http://entsupport.symantec.com/umi/V-269-1</a> ) for supported Remote Media Agent for Linux platforms.
NDMP	The listed device is supported for use with NDMP. See the "NDMP Option" section for platform specific details. Shareability is determined by the ESO column.
ESO	The listed device is supported by the Enterprise Server Option using Fibre Channel. ESO refers to WinBES, and optionally RMAL or NDMP.

## Contents

<a href="#"><u>actidata</u></a>	<a href="#"><u>ADIC</u></a>	<a href="#"><u>BDT</u></a>
<a href="#"><u>Dell</u></a>	<a href="#"><u>Fujitsu</u></a>	<a href="#"><u>HP</u></a>
<a href="#"><u>IBM</u></a>	<a href="#"><u>Imation</u></a>	<a href="#"><u>NEC</u></a>
<a href="#"><u>Oracle</u></a>	<a href="#"><u>Overland Storage</u></a>	<a href="#"><u>PivotStor</u></a>
<a href="#"><u>Qualstar</u></a>	<a href="#"><u>Quantum</u></a>	<a href="#"><u>Sony</u></a>
<a href="#"><u>Spectra Logic</u></a>	<a href="#"><u>StorageTek</u></a>	<a href="#"><u>Sun</u></a>
<a href="#"><u>Tandberg</u></a>	<a href="#"><u>Tape Library Families</u></a>	

## actidata

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
actiLib series	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^3-SCSI	✓	✓	✓	✓
actiLib series	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	✓
actiLib series	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	✓

# actidata

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
actiLib series	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	BDT~~~~~FlexStor^II HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
actiLib series	SAS	HP	Ultrium 920 LTO3	SAS	BDT~~~~~FlexStor^II HP~~~~~Ultrium^3-SCSI	✓	✓		
actiLib series	SAS	HP	Ultrium 1760 LTO4	SAS	BDT~~~~~FlexStor^II HP~~~~~Ultrium^4-SCSI	✓	✓		
actiLib series	SAS	HP	Ultrium 1840 LTO4	SAS	BDT~~~~~FlexStor^II HP~~~~~Ultrium^4-SCSI	✓	✓		
actiLib series	SAS	HP	Ultrium 3000 LTO5	SAS	BDT~~~~~FlexStor^II HP~~~~~Ultrium^5-SCSI	✓	✓		
actiLib series	SAS	HP	Ultrium 3280 LTO5	SAS	BDT~~~~~FlexStor^II HP~~~~~Ultrium^5-SCSI	✓	✓		
actiLib series	SCSI	HP	Ultrium 448 LTO2	SCSI	BDT~~~~~FlexStor^II HP~~~~~Ultrium^2-SCSI	✓	✓	✓	
actiLib series	SCSI	HP	Ultrium 920 LTO3	SCSI	BDT~~~~~FlexStor^II HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
actiLib series	SCSI	HP	Ultrium 960 LTO3	SCSI	BDT~~~~~FlexStor^II HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
actiLib series	SCSI	HP	Ultrium 1760 LTO4	SCSI	BDT~~~~~FlexStor^II HP~~~~~Ultrium^4-SCSI	✓	✓	✓	
actiLib series	SCSI	HP	Ultrium 1840 LTO4	SCSI	BDT~~~~~FlexStor^II HP~~~~~Ultrium^4-SCSI	✓	✓	✓	

# ADIC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Scalar 24 LUN	Fibre Channel	IBM	Ultrium 3	Fibre Channel	ADIC^Scalar^24 IBM^ULTRIUM-TD3	✓	✓	✓	✓
Scalar 24 LUN	Fibre Channel	IBM	Ultrium 4	Fibre Channel	ADIC^Scalar^24 IBM^ULTRIUM-TD4	✓	✓	✓	
Scalar 24 LUN	SCSI	IBM	Ultrium 3	SCSI	ADIC^Scalar^24 IBM^ULTRIUM-TD3	✓	✓	✓	
Scalar 24	Fibre Channel	IBM	Ultrium 3	Fibre Channel	ADIC^Scalar^24 IBM^ULTRIUM-TD3	✓	✓	✓	✓
Scalar 24	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^Scalar^24 IBM^ULT3580-TD2	✓	✓	✓	
Scalar 24	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	ADIC^Scalar^24 IBM^ULT3580-TD3	✓	✓	✓	
Scalar 24	SCSI	IBM	Ultrium 2	SCSI	ADIC^Scalar^24 IBM^ULTRIUM-TD2	✓	✓	✓	✓
Scalar 24	SCSI	IBM	Ultrium 4 (U160)	SCSI	ADIC^Scalar^24 IBM^ULTRIUM-TD4	✓	✓	✓	
Scalar 24 [1]	SCSI	Quantum	SDLT 600	SCSI	ADIC^Scalar^24 QUANTUM^SDLT600	✓			
Scalar i500 [1]	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	ADIC^Scalar^i500 IBM^ULT3580-TD2	✓	✓	✓	✓
Scalar i500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	ADIC^Scalar^i500 IBM^ULT3580-TD3	✓	✓	✓	✓
Scalar i500	Fibre Channel	IBM	Ultrium 3	Fibre Channel	ADIC^Scalar^i500 IBM^ULTRIUM-TD3	✓	✓	✓	✓
Scalar i500 [2]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	ADIC^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓	✓	✓
Scalar i500 [2]	SAS	IBM	Ultrium 4	SAS	ADIC^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓		
Scalar i500 [1]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^Scalar^i500 IBM^ULT3580-TD2	✓	✓	✓	✓

# ADIC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Scalar i500	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	ADIC^Scalar^i500 IBM^ULT3580-TD3	✓	✓	✓	✓
Scalar i500	SCSI	IBM	Ultrium 3	SCSI	ADIC^Scalar^i500 IBM^ULTRIUM-TD3	✓	✓	✓	✓
Scalar i500 [2]	SCSI	IBM	Ultrium 4 (U160)	SCSI	ADIC^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓	✓	
Scalar i2000	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	ADIC^Scalar^i2000 HP^Ultrium^3-SCSI	✓	✓	✓	✓
Scalar i2000	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	ADIC^Scalar^i2000 HP^Ultrium^4-SCSI	✓	✓	✓	✓
Scalar i2000 [1]	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	ADIC^Scalar^i2000 IBM^ULT3580-TD2	✓	✓	✓	✓
Scalar i2000	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	ADIC^Scalar^i2000 IBM^ULT3580-TD3	✓	✓	✓	✓
Scalar i2000 [1]	Fibre Channel	IBM	Ultrium 2	Fibre Channel	ADIC^Scalar^i2000 IBM^ULTRIUM-TD2	✓	✓	✓	✓
Scalar i2000	Fibre Channel	IBM	Ultrium 3	Fibre Channel	ADIC^Scalar^i2000 IBM^ULTRIUM-TD3	✓	✓		✓
Scalar i2000 [2]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	ADIC^Scalar^i2000 IBM^ULTRIUM-TD4	✓	✓	✓	✓
Scalar i2000	Fibre Channel	Quantum	DLT-S4	Fibre Channel	ADIC^Scalar^i2000 QUANTUM^DLT-S4	✓	✓	✓	
Scalar i2000 [1]	Fibre Channel	Quantum	SDLT 600	Fibre Channel	ADIC^Scalar^i2000 QUANTUM^SDLT600	✓			✓
Scalar i2000 [1]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^Scalar^i2000 IBM^ULT3580-TD2	✓	✓	✓	

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

2. L1 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L2 (or above) barcode labels for cleaning media.

# BDT

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
FlexStor II	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^3-SCSI	✓	✓	✓	✓
FlexStor II	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	✓
FlexStor II	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	✓
FlexStor II	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^5-SCSI	✓	✓	✓	✓
FlexStor II	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^5-SCSI	✓	✓	✓	✓
FlexStor II [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	BDT~~~~FlexStor^II HP~~~~Ultrium^6-SCSI	✓	✓	✓	✓
FlexStor II	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-HH5	✓	✓	✓	✓
FlexStor II	Fibre Channel	IBM	Ultrium 5	Fibre Channel	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-TD5	✓	✓	✓	✓
FlexStor II	Fibre Channel	IBM	Ultrium 6 Half Height	Fibre Channel	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-HH6	✓	✓	✓	✓
FlexStor II	SAS	HP	Ultrium 920 LTO3	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^3-SCSI	✓	✓		
FlexStor II	SAS	HP	Ultrium 1760 LTO4	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓		
FlexStor II	SAS	HP	Ultrium 1840 LTO4	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓		
FlexStor II	SAS	HP	Ultrium 3000 LTO5	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^5-SCSI	✓	✓		
FlexStor II	SAS	HP	Ultrium 3280 LTO5	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^5-SCSI	✓	✓		

# BDT

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
FlexStor II [2]	SAS	HP	Ultrium 6250 LTO6	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^6-SCSI	✓	✓		
FlexStor II	SAS	IBM	Ultrium 5 Half Height	SAS	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-HH5	✓	✓		
FlexStor II	SAS	IBM	Ultrium 5	SAS	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-TD5	✓	✓		
FlexStor II [1]	SAS	IBM	Ultrium 6 Half Height	SAS	BDT~~~~FlexStor^II IBM~~~~ULTRIUM-HH6	✓	✓		
FlexStor II	SCSI	HP	Ultrium 448 LTO2	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^2-SCSI	✓	✓	✓	
FlexStor II	SCSI	HP	Ultrium 920 LTO3	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^3-SCSI	✓	✓	✓	
FlexStor II	SCSI	HP	Ultrium 960 LTO3	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^3-SCSI	✓	✓	✓	
FlexStor II	SCSI	HP	Ultrium 1760 LTO4	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	
FlexStor II	SCSI	HP	Ultrium 1840 LTO4	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	
ThinStorPlus	SCSI	HP	Ultrium 960 LTO3	SCSI	BDT~~~~ThinStorPlus^AL HP~~~~Ultrium^3-SCSI	✓	✓	✓	
ThinStorPlus	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	BDT~~~~ThinStorPlus^AL IBM~~~~ULT3580-TD2	✓	✓	✓	
ThinStorPlus	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	BDT~~~~ThinStorPlus^AL IBM~~~~ULT3580-TD3	✓	✓	✓	
ThinStorPlus SM2	SCSI	HP	Ultrium 448 LTO2	SCSI	BDT~~~~ThinStorPlus^SM2 HP~~~~Ultrium^2-SCSI	✓	✓	✓	
ThinStorPlus SM2	SCSI	HP	Ultrium 960 LTO3	SCSI	BDT~~~~ThinStorPlus^SM2 HP~~~~Ultrium^3-SCSI	✓	✓	✓	
ThinStorPlus SM2	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	BDT~~~~ThinStorPlus^SM2 IBM~~~~ULT3580-TD3	✓	✓	✓	



1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
2. Required driver support can be found in "DDI 2012 20121215". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>

## Dell

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
PowerVault 124T	SAS	IBM	Ultrium 3 Half Height	SAS	DELL^PV-124T IBM^ULTRIUM-HH3	✓	✓		
PowerVault 124T	SAS	IBM	Ultrium 4 Half Height	SAS	DELL^PV-124T IBM^ULTRIUM-HH4	✓	✓		
PowerVault 124T	SAS	IBM	Ultrium 4	SAS	DELL^PV-124T IBM^ULTRIUM-TD4	✓	✓		
PowerVault 124T [1]	SAS	IBM	Ultrium 6 Half Height	SAS	DELL^PV-124T IBM^ULTRIUM-HH6	✓	✓		
PowerVault 124T	SAS	Quantum	LTO-3 HH	SAS	DELL^PV-124T QUANTUM^ULTRIUM^3	✓	✓		
PowerVault 124T	SAS	Quantum	LTO-4 HH	SAS	DELL^PV-124T QUANTUM^ULTRIUM^4	✓	✓		
PowerVault 124T	SAS	Quantum	LTO-5 FH	SAS	DELL^PV-124T QUANTUM^ULTRIUM^5	✓	✓		
PowerVault 124T	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	DELL^PV-124T CERTANCEULTRIUM^2	✓	✓	✓	✓
PowerVault 124T [2]	SCSI	Dell	PowerVault 124T VS160	SCSI	DELL^PV-124T QUANTUM^DLT^VS160	✓			
PowerVault 124T	SCSI	Dell	PowerVault LTO3-060 (Quantum)	SCSI	DELL^PV-124T QUANTUM^ULTRIUM^3	✓	✓		
PowerVault 124T	SCSI	IBM	Ultrium 3	SCSI	DELL^PV-124T IBM^ULTRIUM-TD3	✓	✓	✓	✓
PowerVault 124T	SCSI	Quantum	LTO-3 HH	SCSI	DELL^PV-124T QUANTUM^ULTRIUM^3	✓	✓	✓	

# Dell

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
PowerVault 132T	SCSI	Dell	PowerVault 132T LTO	SCSI	DELL~~~~PV-132T IBM~~~~ULTRIUM-TD1	✓	✓	✓	✓
PowerVault 132T	SCSI	Dell	PowerVault 132T LTO2	SCSI	DELL~~~~PV-132T IBM~~~~ULTRIUM-TD2	✓	✓	✓	✓
PowerVault 132T	SCSI	IBM	Ultrium 3	SCSI	DELL~~~~PV-132T IBM~~~~ULTRIUM-TD3	✓	✓	✓	✓
PowerVault 132T LUN	Fibre Channel	IBM	Ultrium 2	Fibre Channel	DELL~~~~PV-132T IBM~~~~ULTRIUM-TD2	✓	✓	✓	✓
PowerVault 132T LUN	Fibre Channel	IBM	Ultrium 3	Fibre Channel	DELL~~~~PV-132T IBM~~~~ULTRIUM-TD3	✓	✓	✓	✓
PowerVault 160T	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	ADIC~~~~Scalar^i2000 IBM~~~~ULT3580-TD2	✓	✓	✓	✓
PowerVault ML6000 Series (members) [3]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	ADIC~~~~Scalar^i500 IBM~~~~ULT3580-TD5	✓	✓	✓	✓
PowerVault ML6000 Series (members) [1]	Fibre Channel	IBM	System Storage TS2360 Ultrium 6	Fibre Channel	ADIC~~~~Scalar^i500 IBM~~~~ULT3580-TD6	✓	✓	✓	✓
PowerVault ML6000 Series (members)	Fibre Channel	IBM	Ultrium 3	Fibre Channel	ADIC~~~~Scalar^i500 IBM~~~~ULTRIUM-TD3	✓	✓	✓	✓
PowerVault ML6000 Series (members) [4]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	ADIC~~~~Scalar^i500 IBM~~~~ULTRIUM-TD4	✓	✓	✓	✓
PowerVault ML6000 Series (members)	SAS	IBM	System Storage TS2350 Ultrium 5	SAS	ADIC~~~~Scalar^i500 IBM~~~~ULT3580-TD5	✓	✓		
PowerVault ML6000 Series (members) [1]	SAS	IBM	System Storage TS2360 Ultrium 6	SAS	ADIC~~~~Scalar^i500 IBM~~~~ULT3580-TD6	✓	✓		
PowerVault ML6000 Series (members) [4]	SAS	IBM	Ultrium 4	SAS	ADIC~~~~Scalar^i500 IBM~~~~ULTRIUM-TD4	✓	✓		
PowerVault ML6000 Series (members)	SCSI	IBM	Ultrium 3	SCSI	ADIC~~~~Scalar^i500 IBM~~~~ULTRIUM-TD3	✓	✓	✓	✓
PowerVault TL2000/TL4000 series (members)	Fibre Channel	IBM	System Storage TS2240 Ultrium 4 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-HH4	✓	✓	✓	✓

# Dell

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
PowerVault TL2000/TL4000 series (members)	Fibre Channel	IBM	System Storage TS2250 Ultrium 5 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH5	✓	✓	✓	✓
PowerVault TL2000/TL4000 series (members) [1]	Fibre Channel	IBM	System Storage TS2260 Ultrium 6 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH6	✓	✓	✓	✓
PowerVault TL2000/TL4000 series (members)	Fibre Channel	IBM	System Storage TS2340 Ultrium 4	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULT3580-TD4	✓	✓	✓	✓
PowerVault TL2000/TL4000 series (members)	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULT3580-TD3	✓	✓	✓	✓
PowerVault TL2000/TL4000 series (members) [5]	SAS	IBM	System Storage TS2230 Ultrium 3 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH3	✓	✓		
PowerVault TL2000/TL4000 series (members)	SAS	IBM	System Storage TS2240 Ultrium 4 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH4	✓	✓		
PowerVault TL2000/TL4000 series (members) [5]	SAS	IBM	System Storage TS2250 Ultrium 5 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH5	✓	✓		✓
PowerVault TL2000/TL4000 series (members) [1]	SAS	IBM	System Storage TS2260 Ultrium 6 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULT3580-HH6	✓	✓		
PowerVault TL2000/TL4000 series (members) [5]	SAS	IBM	System Storage TS2340 Ultrium 4	SAS	IBM~~~~~3573-TL IBM~~~~~ULT3580-TD4	✓	✓		
PowerVault TL2000/TL4000 series (members) [5]	SAS	IBM	Ultrium 4 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓		
PowerVault TL2000/TL4000 series (members)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~~3573-TL IBM~~~~~ULT3580-TD3	✓	✓	✓	

1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
2. Please note: this device is nearing the end of support. Please see the 'Retiring Soon' section .
3. L1 & L2 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L3 (or above) barcode labels for cleaning media.
4. L1 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L2 (or above) barcode labels for cleaning media.
5. ESO is only supported with the TL24iSCSIxSAS blade.

# Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ETERNUS LT20	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT^TX08 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT20	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	FSC^FibreCAT^TX08 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT20	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT^TX08 HP^Ultrium^3-SCSI	✓	✓		
ETERNUS LT20	SAS	HP	Ultrium 1760 LTO4	SAS	FSC^FibreCAT^TX08 HP^Ultrium^4-SCSI	✓	✓		
ETERNUS LT20	SAS	HP	Ultrium 3000 LTO5	SAS	FSC^FibreCAT^TX08 HP^Ultrium^5-SCSI	✓	✓		
ETERNUS LT20/40/60 S2 (members)	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT20/40/60 S2 (members) [1]	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT20/40/60 S2 (members)	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT20/40/60 S2 (members) [1]	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT20/40/60 S2 (members) [2]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^6-SCSI	✓	✓	✓	✓
ETERNUS LT20/40/60 S2 (members)	SAS	HP	Ultrium 920 LTO3	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^3-SCSI	✓	✓		
ETERNUS LT20/40/60 S2 (members)	SAS	HP	Ultrium 1760 LTO4	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^4-SCSI	✓	✓		
ETERNUS LT20/40/60 S2 (members) [1]	SAS	HP	Ultrium 1840 LTO4	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^4-SCSI	✓	✓		
ETERNUS LT20/40/60 S2 (members)	SAS	HP	Ultrium 3000 LTO5	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^5-SCSI	✓	✓		
ETERNUS LT20/40/60 S2 (members) [1]	SAS	HP	Ultrium 3280 LTO5	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^5-SCSI	✓	✓		

# Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ETERNUS LT20/40/60 S2 (members) [2]	SAS	HP	Ultrium 6250 LTO6	SAS	FUJITSU^ETERNUS^LT^S2 HP^Ultrium^6-SCSI	✓	✓		
ETERNUS LT40	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT40	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT40	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	FSC^FibreCAT-TX24^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT40	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	FSC^FibreCAT-TX24^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT40	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^3-SCSI	✓	✓		
ETERNUS LT40	SAS	HP	Ultrium 1760 LTO4	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓		
ETERNUS LT40	SAS	HP	Ultrium 1840 LTO4	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓		
ETERNUS LT40	SAS	HP	Ultrium 3000 LTO5	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^5-SCSI	✓	✓		
ETERNUS LT40	SAS	HP	Ultrium 3280 LTO5	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^5-SCSI	✓	✓		
ETERNUS LT60	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT-TX48^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT60	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	FSC^FibreCAT-TX48^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
ETERNUS LT60	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	FSC^FibreCAT-TX48^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT60	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	FSC^FibreCAT-TX48^S2 HP^Ultrium^5-SCSI	✓	✓	✓	✓
ETERNUS LT60	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT-TX48^S2 HP^Ultrium^3-SCSI	✓	✓		

# Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ETERNUS LT60	SAS	HP	Ultrium 1760 LTO4	SAS	FSC~~~~~FibreCAT-TX48^S2 HP~~~~~Ultrium^4-SCSI	✓	✓		
ETERNUS LT60	SAS	HP	Ultrium 1840 LTO4	SAS	FSC~~~~~FibreCAT-TX48^S2 HP~~~~~Ultrium^4-SCSI	✓	✓		
ETERNUS LT60	SAS	HP	Ultrium 3000 LTO5	SAS	FSC~~~~~FibreCAT-TX48^S2 HP~~~~~Ultrium^5-SCSI	✓	✓		
ETERNUS LT60	SAS	HP	Ultrium 3280 LTO5	SAS	FSC~~~~~FibreCAT-TX48^S2 HP~~~~~Ultrium^5-SCSI	✓	✓		
ETERNUS LT210 (T16A2)	SAS	IBM	System Storage TS2230 Ultrium 3 Half Height	SAS	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH3	✓	✓		
ETERNUS LT210 (T16A2)	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH3	✓	✓		
ETERNUS LT210 (T16A2)	SCSI	IBM	Ultrium 4 (U160)	SCSI	NEC~~~~~T16A2 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
ETERNUS LT220 (T16A)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC~~~~~T16A IBM~~~~~ULT3580-TD3	✓	✓	✓	
ETERNUS LT220 (T16A2)	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH3	✓	✓		
ETERNUS LT220 (T16A2)	SCSI	IBM	Ultrium 4 (U160)	SCSI	NEC~~~~~T16A2 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
ETERNUS LT230 (T40A)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC~~~~~T40A IBM~~~~~ULT3580-TD3	✓	✓	✓	
ETERNUS LT230 (T40A2)	Fibre Channel	IBM	Ultrium 3	Fibre Channel	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
ETERNUS LT230 (T40A2)	Fibre Channel	IBM	Ultrium 4	Fibre Channel	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
ETERNUS LT230 (T40A2)	SCSI	IBM	Ultrium 3	SCSI	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	
ETERNUS LT250	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	FUJITSU^NML7A HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓

# Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ETERNUS LT250	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	FUJITSU^NML7A IBM^ULTR3580-TD5	✓	✓	✓	✓
ETERNUS LT250	Fibre Channel	IBM	Ultrium 3	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD3	✓	✓	✓	✓
ETERNUS LT250	Fibre Channel	IBM	Ultrium 4	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD4	✓	✓	✓	✓
ETERNUS LT250 [2]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD6	✓	✓	✓	✓
ETERNUS LT250	SCSI	HP	Ultrium 960 LTO3	SCSI	FUJITSU^NML7A HP^Ultrium^3-SCSI	✓	✓	✓	
ETERNUS LT250	SCSI	IBM	Ultrium 3	SCSI	FUJITSU^NML7A IBM^ULTRIUM-TD3	✓	✓	✓	
ETERNUS LT270 S2 [3]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	ETERNUS^LT270S2 HP^Ultrium^6-SCSI	✓	✓	✓	✓
ETERNUS LT270 S2 [3]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	ETERNUS^LT270S2 IBM^ULTRIUM-TD4	✓	✓	✓	✓
ETERNUS LT270 S2 [3]	Fibre Channel	IBM	Ultrium 5	Fibre Channel	ETERNUS^LT270S2 IBM^ULTRIUM-TD5	✓	✓	✓	✓
ETERNUS LT270 S2 [3]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	ETERNUS^LT270S2 IBM^ULTRIUM-TD6	✓	✓	✓	✓
ETERNUS LT270	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	FUJITSU^NML10A HP^Ultrium^3-SCSI	✓	✓	✓	✓
ETERNUS LT270	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	FUJITSU^NML10A IBM^ULTR3580-TD5	✓	✓	✓	✓
ETERNUS LT270	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	FUJITSU^NML10A IBM^ULTR3580-TD3	✓	✓	✓	✓
ETERNUS LT270	Fibre Channel	IBM	Ultrium 4	Fibre Channel	FUJITSU^NML10A IBM^ULTRIUM-TD4	✓	✓	✓	✓
FibreCAT TX08	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT^TX08 HP^Ultrium^4-SCSI	✓	✓	✓	✓

# Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
FibreCAT TX08	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT^TX08 HP^Ultrium^3-SCSI	✓	✓		
FibreCAT TX08	SAS	HP	Ultrium 1760 LTO4	SAS	FSC^FibreCAT^TX08 HP^Ultrium^4-SCSI	✓	✓		
FibreCAT TX08	SCSI	HP	Ultrium 448 LTO2	SCSI	FSC^FibreCAT^TX08 HP^Ultrium^2-SCSI	✓	✓	✓	
FibreCAT TX08	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT^TX08 HP^Ultrium^3-SCSI	✓	✓	✓	
FibreCAT TX24 S2	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
FibreCAT TX24 S2	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^3-SCSI	✓	✓		
FibreCAT TX24 S2	SAS	HP	Ultrium 1760 LTO4	SAS	FSC^FibreCAT-TX24^S2 HP^Ultrium^4-SCSI	✓	✓		
FibreCAT TX24	SCSI	HP	Ultrium 448 LTO2	SCSI	FSC^FibreCAT^TX24 HP^Ultrium^2-SCSI	✓	✓	✓	
FibreCAT TX24	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT^TX24 HP^Ultrium^3-SCSI	✓	✓	✓	
FibreCAT TX24	SCSI	IBM	Ultrium 3	SCSI	FSC^FibreCAT^TX24 IBM^ULTRIUM-TD3	✓	✓	✓	
FibreCAT TX48 S2	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	FSC^FibreCAT-TX48^S2 HP^Ultrium^4-SCSI	✓	✓	✓	✓
FibreCAT TX48 S2	SAS	HP	Ultrium 920 LTO3	SAS	FSC^FibreCAT-TX48^S2 HP^Ultrium^3-SCSI	✓	✓		
FibreCAT TX48 S2	SAS	HP	Ultrium 1760 LTO4	SAS	FSC^FibreCAT-TX48^S2 HP^Ultrium^4-SCSI	✓	✓		
FibreCAT TX48	Fibre Channel	IBM	Ultrium 3	Fibre Channel	FSC^FibreCAT^TX48 IBM^ULTRIUM-TD3	✓	✓	✓	✓
FibreCAT TX48	Fibre Channel	IBM	Ultrium 4	Fibre Channel	FSC^FibreCAT^TX48 IBM^ULTRIUM-TD4	✓	✓	✓	✓



## Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
FibreCAT TX48	SCSI	HP	Ultrium 448 LTO2	SCSI	FSC^FibreCAT^TX48 HP^Ultrium^2-SCSI	✓	✓	✓	
FibreCAT TX48	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT^TX48 HP^Ultrium^3-SCSI	✓	✓	✓	
FibreCAT TX48	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	FSC^FibreCAT^TX48 IBM^ULT3580-TD3	✓	✓	✓	

1. The ETERNUS LT20 only supports half height drives. The drive referenced in this row is a full height drive.
2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
3. Required driver support can be found in "HF 208600". Use latest SP available by downloading: <<http://www.symantec.com/docs/TECH208600>> or via LiveUpdate

## HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
1/8 G2 Tape Autoloader	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	HP^1x8^G2^AUTOLDR HP^Ultrium^5-SCSI	✓	✓	✓	✓
1/8 G2 Tape Autoloader [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	HP^1x8^G2^AUTOLDR HP^Ultrium^6-SCSI	✓	✓	✓	✓
1/8 G2 Tape Autoloader [2]	SAS	HP	Ultrium 920 LTO3	SAS	HP^1x8^G2^AUTOLDR HP^Ultrium^3-SCSI	✓	✓		
1/8 G2 Tape Autoloader [2]	SAS	HP	Ultrium 1760 LTO4	SAS	HP^1x8^G2^AUTOLDR HP^Ultrium^4-SCSI	✓	✓		
1/8 G2 Tape Autoloader [2]	SAS	HP	Ultrium 3000 LTO5	SAS	HP^1x8^G2^AUTOLDR HP^Ultrium^5-SCSI	✓	✓		
1/8 G2 Tape Autoloader [1] [2]	SAS	HP	Ultrium 6250 LTO6	SAS	HP^1x8^G2^AUTOLDR HP^Ultrium^6-SCSI	✓	✓		

# HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
1/8 G2 Tape Autoloader <a href="#">[2]</a>	SCSI	HP	Ultrium 448 LTO2	SCSI	HP^1x8^G2^AUTOLDR HP^Ultrium^2-SCSI	✓	✓	✓	
1/8 G2 Tape Autoloader <a href="#">[2]</a>	SCSI	HP	Ultrium 920 LTO3	SCSI	HP^1x8^G2^AUTOLDR HP^Ultrium^3-SCSI	✓	✓	✓	✓
1/8 G2 Tape Autoloader <a href="#">[2]</a>	SCSI	HP	Ultrium 1760 LTO4	SCSI	HP^1x8^G2^AUTOLDR HP^Ultrium^4-SCSI	✓	✓		
DAT 72x10	SCSI	HP	DAT 72	SCSI	HP^DAT^Autoloader HP^C7438A	✓			
EML E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	HP^EML^E-Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
EML E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^EML^E-Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
EML E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^EML^E-Series HP^Ultrium^5-SCSI	✓	✓		✓
EML E-Series <a href="#">(members)</a> <a href="#">[1]</a>	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	HP^EML^E-Series HP^Ultrium^6-SCSI	✓	✓	✓	✓
ESL E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	HP^ESL^E-Series HP^Ultrium^2-SCSI	✓	✓		✓
ESL E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 460 LTO2	SCSI	HP^ESL^E-Series HP^Ultrium^2-SCSI	✓	✓		✓
ESL E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	HP^ESL^E-Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
ESL E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^ESL^E-Series HP^Ultrium^4-SCSI	✓	✓	✓	
ESL E-Series <a href="#">(members)</a>	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^ESL^E-Series HP^Ultrium^5-SCSI	✓	✓		✓
ESL E-Series <a href="#">(members)</a>	SCSI	HP	Ultrium 960 LTO3	Fibre Channel	HP^ESL^E-Series HP^Ultrium^3-SCSI	✓	✓	✓	
ESL G3	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^ESL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓

# HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ESL G3	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓
ESL G3 [1]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^6-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members)	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members)	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members)	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members)	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members) [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^6-SCSI	✓	✓	✓	✓
MSL2024/4048/8048/8096 (G3 series) (members)	SAS	HP	Ultrium 920 LTO3	SAS	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
MSL2024/4048/8048/8096 (G3 series) (members)	SAS	HP	Ultrium 1760 LTO4	SAS	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		✓
MSL2024/4048/8048/8096 (G3 series) (members)	SAS	HP	Ultrium 3000 LTO5	SAS	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓		
MSL2024/4048/8048/8096 (G3 series) (members) [1]	SAS	HP	Ultrium 6250 LTO6	SAS	HP^MSL^G3^Series HP^Ultrium^6-SCSI	✓	✓		
MSL2024/4048/8048/8096 (G3 series) (members)	SCSI	HP	Ultrium 448 LTO2	SCSI	HP^MSL^G3^Series HP^Ultrium^2-SCSI	✓	✓	✓	
MSL2024/4048/8048/8096 (G3 series) (members)	SCSI	HP	Ultrium 460 LTO2	SCSI	HP^MSL^G3^Series HP^Ultrium^2-SCSI	✓	✓	✓	
MSL2024/4048/8048/8096 (G3 series) (members)	SCSI	HP	Ultrium 920 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
MSL2024/4048/8048/8096 (G3 series) (members)	SCSI	HP	Ultrium 960 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	

# HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
MSL2024/4048/8048/8096 (G3 series) ( <a href="#">members</a> )	SCSI	HP	Ultrium 1760 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	
MSL2024/4048/8048/8096 (G3 series) ( <a href="#">members</a> )	SCSI	HP	Ultrium 1840 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	
MSL6000 Series ( <a href="#">members</a> ) [3]	SCSI	HP	Ultrium 460 LTO2	SCSI	HP^MSL6000^Series HP^Ultrium^2-SCSI	✓	✓	✓	✓
MSL6000 Series ( <a href="#">members</a> ) [3]	SCSI	HP	Ultrium 960 LTO3	SCSI	HP^MSL6000^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
MSL6000 Series ( <a href="#">members</a> ) [3]	SCSI	HP	Ultrium 1840 LTO4	SCSI	HP^MSL6000^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
MSL6480 [4]	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	HP^MSL6480 HP^Ultrium^5-SCSI	✓	✓	✓	✓
MSL6480 [4]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	HP^MSL6480 HP^Ultrium^6-SCSI	✓	✓	✓	✓
MSL6480 [4]	SAS	HP	Ultrium 3000 LTO5	SAS	HP^MSL6480 HP^Ultrium^5-SCSI	✓	✓		
MSL6480 [4]	SAS	HP	Ultrium 6250 LTO6	SAS	HP^MSL6480 HP^Ultrium^6-SCSI	✓	✓		

1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
2. Minimum firmware level of 1.20 is required.
3. This library is often used with an HP bridge in an FC environment.
4. Required driver support can be found in "HF 208600". Use latest SP available by downloading: <http://www.symantec.com/docs/TECH208600> or via LiveUpdate

# IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
33614LX	Fibre Channel	IBM	Ultrium 3	Fibre Channel	IBM~~~~33614LX IBM~~~~ULTRIUM-TD3	✓	✓	✓	✓
33614LX	SCSI	IBM	Ultrium 3	SCSI	IBM~~~~33614LX IBM~~~~ULTRIUM-TD3	✓	✓	✓	
33622LX	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~33622LX IBM~~~~ULT3580-TD3	✓	✓	✓	
System Storage TS2900 (Machine Type 3572)	SAS	IBM	System Storage TS2230 Ultrium 3 Half Height	SAS	IBM~~~~3572-TL IBM~~~~ULT3580-HH3	✓	✓		
System Storage TS2900 (Machine Type 3572)	SAS	IBM	System Storage TS2240 Ultrium 4 Half Height	SAS	IBM~~~~3572-TL IBM~~~~ULT3580-HH4	✓	✓		
System Storage TS2900 (Machine Type 3572) [1]	SAS	IBM	System Storage TS2250 Ultrium 5 Half Height	SAS	IBM~~~~3572-TL IBM~~~~ULT3580-HH5	✓	✓		
System Storage TS2900 (Machine Type 3572) [2]	SAS	IBM	System Storage TS2260 Ultrium 6 Half Height	SAS	IBM~~~~3572-TL IBM~~~~ULT3580-HH6	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	Fibre Channel	IBM	System Storage TS2240 Ultrium 4 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-HH4	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	Fibre Channel	IBM	System Storage TS2250 Ultrium 5 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-HH5	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [2] [3]	Fibre Channel	IBM	System Storage TS2260 Ultrium 6 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-HH6	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	Fibre Channel	IBM	System Storage TS2340 Ultrium 4	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-TD4	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-TD5	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [2] [3]	Fibre Channel	IBM	System Storage TS2360 Ultrium 6	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-TD6	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULT3580-TD3	✓	✓	✓	✓
System Storage TS3100/TS3200 (Machine Type 3573) (members) [3]	SAS	IBM	System Storage TS2230 Ultrium 3 Half Height	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-HH3	✓	✓		

# IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SAS	IBM	System Storage TS2240 Ultrium 4 Half Height	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-HH4	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SAS	IBM	System Storage TS2250 Ultrium 5 Half Height	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-HH5	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [2] [3]	SAS	IBM	System Storage TS2260 Ultrium 6 Half Height	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-HH6	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SAS	IBM	System Storage TS2340 Ultrium 4	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-TD4	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SAS	IBM	System Storage TS2350 Ultrium 5	SAS	IBM~~~~3573-TL IBM~~~~ULT3580-TD5	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	IBM~~~~3573-TL IBM~~~~ULT3580-HH3	✓	✓		
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SCSI	IBM	System Storage TS2340 Ultrium 4	SCSI	IBM~~~~3573-TL IBM~~~~ULT3580-TD4	✓	✓	✓	
System Storage TS3100/TS3200 (Machine Type 3573) ( <a href="#">members</a> ) [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~3573-TL IBM~~~~ULT3580-TD3	✓	✓	✓	
System Storage TS3310 (Machine Type 3576) [4]	Fibre Channel	IBM	System Storage TS2340 Ultrium 4	Fibre Channel	IBM~~~~3576-MTL IBM~~~~ULT3580-TD4	✓	✓	✓	✓
System Storage TS3310 (Machine Type 3576) [5]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	IBM~~~~3576-MTL IBM~~~~ULT3580-TD5	✓	✓	✓	✓
System Storage TS3310 (Machine Type 3576) [2]	Fibre Channel	IBM	System Storage TS2360 Ultrium 6	Fibre Channel	IBM~~~~3576-MTL IBM~~~~ULT3580-TD6	✓	✓	✓	✓
System Storage TS3310 (Machine Type 3576)	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~3576-MTL IBM~~~~ULT3580-TD3	✓	✓	✓	✓
System Storage TS3310 (Machine Type 3576) [4]	SAS	IBM	System Storage TS2340 Ultrium 4	SAS	IBM~~~~3576-MTL IBM~~~~ULT3580-TD4	✓	✓		
System Storage TS3310 (Machine Type 3576)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~3576-MTL IBM~~~~ULT3580-TD3	✓	✓	✓	✓
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	System Storage TS1030 (3588 Model F3B) Ultrium 3	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD3	✓	✓	✓	✓

## IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	System Storage TS2340 Ultrium 4	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD4	✓	✓	✓	✓
System Storage TS3500 (Machine Type 3584) [2] [6]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD5	✓	✓	✓	✓
System Storage TS3500 (Machine Type 3584) [2] [6]	Fibre Channel	IBM	System Storage TS2360 Ultrium 6	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD6	✓	✓	✓	✓
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD2	✓	✓	✓	✓
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~03584 IBM~~~~ULT3580-TD3	✓	✓	✓	✓

1. Minimum firmware levels of 0018 are required for the library and B171 for the drive.
2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
3. IBM markets this under two names, with and without the words "Express Model". They are identical and both are supported.
4. L1 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L2 (or above) barcode labels for cleaning media.
5. L1 & L2 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L3 (or above) barcode labels for cleaning media.
6. Due to IBM ALMS virtualizing the tape slots: the tapes are not in the slot order as they appear in the BE GUI & the cleaning tapes are not visible to BE. Therefore drive cleaning must be done via the library itself.

## Imation

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
L1200 LTO 2U Tape Library	Fibre Channel	IBM	Ultrium 4 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULTRIUM-HH4	✓	✓	✓	✓
L1200 LTO 2U Tape Library	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	IBM~~~~3573-TL IBM~~~~ULTRIUM-HH5	✓	✓	✓	✓

## Imation

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
L1200 LTO 2U Tape Library	SAS	IBM	Ultrium 4 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓		
L1200 LTO 2U Tape Library	SAS	IBM	Ultrium 5 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH5	✓	✓		
L1400 LTO 4U Tape Library	Fibre Channel	IBM	Ultrium 4 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓	✓	✓
L1400 LTO 4U Tape Library	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH5	✓	✓	✓	✓
L1400 LTO 4U Tape Library	SAS	IBM	Ultrium 4 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓		
L1400 LTO 4U Tape Library	SAS	IBM	Ultrium 5 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH5	✓	✓		

## NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
LL009F	SAS	IBM	System Storage TS2250 Ultrium 5 Half Height	SAS	NEC~~~~~LL009F IBM~~~~~ULT3580-HH5	✓	✓		
LL009F [1]	SAS	IBM	Ultrium 3 Half Height	SAS	NEC~~~~~LL009F IBM~~~~~ULTRIUM-HH3	✓	✓		
LL009F [1]	SAS	IBM	Ultrium 4 Half Height	SAS	NEC~~~~~LL009F IBM~~~~~ULTRIUM-HH4	✓	✓		
LL009F [2]	SAS	IBM	Ultrium 6 Half Height	SAS	NEC~~~~~LL009F IBM~~~~~ULTRIUM-HH6	✓	✓		
LL0101H [3]	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	NEC~~~~~LL0101H-0A IBM~~~~~ULT3580-HH3	✓	✓		



# NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
LL0101H [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC~~~~~LL0101H-0A IBM~~~~~ULT3580-TD3	✓	✓	✓	
LL0101H [3]	SCSI	IBM	Ultrium 3	SCSI	NEC~~~~~LL0101H-0A IBM~~~~~ULTRIUM-TD3	✓	✓	✓	
T16A [3]	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC~~~~~T16A HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
T16A [3]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC~~~~~T16A IBM~~~~~ULT3580-TD2	✓	✓	✓	
T16A [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC~~~~~T16A IBM~~~~~ULT3580-TD3	✓	✓	✓	
T16A2	SAS	IBM	System Storage TS2240 Ultrium 4 Half Height	SAS	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH4	✓	✓		
T16A2	SAS	IBM	System Storage TS2350 Ultrium 5	SAS	NEC~~~~~T16A2 IBM~~~~~ULT3580-TD5	✓	✓		
T16A2	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC~~~~~T16A2 HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
T16A2	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH3	✓	✓		
T16A2	SCSI	IBM	Ultrium 4 (U160)	SCSI	NEC~~~~~T16A2 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
T30A/T60A (members)	Fibre Channel	IBM	Ultrium 4 Half Height	Fibre Channel	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH4	✓	✓	✓	✓
T30A/T60A (members)	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH5	✓	✓	✓	✓
T30A/T60A (members) [2]	Fibre Channel	IBM	Ultrium 6 Half Height	Fibre Channel	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH6	✓	✓	✓	✓
T30A/T60A (members)	SAS	IBM	Ultrium 3 Half Height	SAS	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH3	✓	✓		
T30A/T60A (members)	SAS	IBM	Ultrium 4 Half Height	SAS	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH4	✓	✓		

# NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
T30A/T60A (members)	SAS	IBM	Ultrium 5 Half Height	SAS	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH5	✓	✓		
T30A/T60A (members) [2]	SAS	IBM	Ultrium 6 Half Height	SAS	NEC~~~~~LL-2B01 IBM~~~~~ULTRIUM-HH6	✓	✓		
T40A [3]	SCSI	HP	Ultrium 460 LTO2	SCSI	NEC~~~~~T40A HP~~~~~Ultrium^2-SCSI	✓	✓	✓	
T40A [3]	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC~~~~~T40A HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
T40A [3]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC~~~~~T40A IBM~~~~~ULT3580-TD2	✓	✓	✓	✓
T40A [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC~~~~~T40A IBM~~~~~ULT3580-TD3	✓	✓	✓	
T40A2	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	NEC~~~~~T40A2 HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
T40A2	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	NEC~~~~~T40A2 IBM~~~~~ULT3580-TD5	✓	✓	✓	✓
T40A2	Fibre Channel	IBM	Ultrium 3	Fibre Channel	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
T40A2	Fibre Channel	IBM	Ultrium 4	Fibre Channel	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
T40A2	SAS	IBM	System Storage TS2350 Ultrium 5	SAS	NEC~~~~~T40A2 IBM~~~~~ULT3580-TD5	✓	✓		
T40A2	SAS	IBM	Ultrium 4	SAS	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD4	✓	✓		
T40A2	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC~~~~~T40A2 HP~~~~~Ultrium^3-SCSI	✓	✓	✓	
T40A2	SCSI	IBM	Ultrium 3	SCSI	NEC~~~~~T40A2 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	
T100A	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	FUJITSU^NML7A HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓

# NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
T100A	Fibre Channel	IBM	Ultrium 4	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD4	✓	✓	✓	✓
T100A	SCSI	HP	Ultrium 960 LTO3	SCSI	FUJITSU^NML7A HP^Ultrium^3-SCSI	✓	✓	✓	
T100A2	Fibre Channel	IBM	Ultrium 5	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD5	✓	✓	✓	✓
T100A2 [2]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	FUJITSU^NML7A IBM^ULTRIUM-TD6	✓	✓	✓	✓
T700A	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	FUJITSU^NML10A HP^Ultrium^3-SCSI	✓	✓	✓	✓
T700A	Fibre Channel	IBM	Ultrium 4	Fibre Channel	FUJITSU^NML10A IBM^ULTRIUM-TD4	✓	✓	✓	✓
T700A2 [4]	Fibre Channel	IBM	Ultrium 5	Fibre Channel	ETERNUS^LT270S2 IBM^ULTRIUM-TD5	✓	✓	✓	✓
T700A2 [4]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	ETERNUS^LT270S2 IBM^ULTRIUM-TD6	✓	✓	✓	✓

1. T10 Hardware Encryption is supported with library firmware 0002 and above.
2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
3. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
4. Required driver support can be found in "HF 208600". Use latest SP available by downloading: <http://www.symantec.com/docs/TECH208600> or via LiveUpdate

# Oracle

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageTek SL150 [1]	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	STK^SL150 HP^Ultrium^5-SCSI	✓	✓	✓	✓
StorageTek SL150 [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	STK^SL150 HP^Ultrium^6-SCSI	✓	✓	✓	✓
StorageTek SL150 [1]	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	STK^SL150 IBM^ULTRIUM-HH5	✓	✓	✓	✓
StorageTek SL150 [1]	Fibre Channel	IBM	Ultrium 6 Half Height	Fibre Channel	STK^SL150 IBM^ULTRIUM-HH6	✓	✓	✓	✓
StorageTek SL150 [1]	SAS	HP	Ultrium 3000 LTO5	SAS	STK^SL150 HP^Ultrium^5-SCSI	✓	✓		
StorageTek SL150 [1]	SAS	HP	Ultrium 6250 LTO6	SAS	STK^SL150 HP^Ultrium^6-SCSI	✓	✓		
StorageTek SL150 [1]	SAS	IBM	Ultrium 5 Half Height	SAS	STK^SL150 IBM^ULTRIUM-HH5	✓	✓		
StorageTek SL150 [1]	SAS	IBM	Ultrium 6 Half Height	SAS	STK^SL150 IBM^ULTRIUM-HH6	✓	✓		
StorageTek SL500 [2]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	STK^SL500 HP^Ultrium^6-SCSI	✓	✓	✓	✓

1. Required driver support can be found in "HF 208600". Use latest SP available by downloading: <http://www.symantec.com/docs/TECH208600> or via LiveUpdate

2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>

## Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
ARCvault series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	OVERLANDARCvault HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
ARCvault series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	OVERLANDARCvault HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
ARCvault series ( <a href="#">members</a> )	SAS	HP	Ultrium 1760 LTO4	SAS	OVERLANDARCvault HP~~~~~Ultrium^4-SCSI	✓	✓		
ARCvault series ( <a href="#">members</a> )	SCSI	HP	Ultrium 448 LTO2	SCSI	OVERLANDARCvault HP~~~~~Ultrium^2-SCSI	✓	✓	✓	
ARCvault series ( <a href="#">members</a> )	SCSI	HP	Ultrium 960 LTO3	SCSI	OVERLANDARCvault HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
ARCvault series ( <a href="#">members</a> )	SCSI	HP	Ultrium 1840 LTO4	SCSI	OVERLANDARCvault HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
NEO 100s 2nd Generation	SAS	IBM	Ultrium 5 Half Height	SAS	IBM~~~~~3572-TL IBM~~~~~ULTRIUM-HH5	✓	✓		
NEO 100s 2nd Generation [1]	SAS	IBM	Ultrium 6 Half Height	SAS	IBM~~~~~3572-TL IBM~~~~~ULTRIUM-HH6	✓	✓		
NEO E-Series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	OVERLANDNEO^Series HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	OVERLANDNEO^Series HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 4	Fibre Channel	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 5	Fibre Channel	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD5	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 6	Fibre Channel	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD6	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	SAS	HP	Ultrium 1840 LTO4	SAS	OVERLANDNEO^Series HP~~~~~Ultrium^4-SCSI	✓	✓		
NEO E-Series ( <a href="#">members</a> )	SAS	HP	Ultrium 3000 LTO5	SAS	OVERLANDNEO^Series HP~~~~~Ultrium^5-SCSI	✓	✓		

# Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
NEO E-Series ( <a href="#">members</a> )	SAS	HP	Ultrium 3280 LTO5	SAS	OVERLANDNEO^Series HP~~~~~Ultrium^5-SCSI	✓	✓		
NEO E-Series ( <a href="#">members</a> )	SAS	IBM	Ultrium 4	SAS	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD4	✓	✓		
NEO E-Series ( <a href="#">members</a> )	SAS	IBM	Ultrium 5	SAS	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD5	✓	✓		
NEO E-Series ( <a href="#">members</a> ) [1]	SAS	IBM	Ultrium 6	SAS	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD6	✓	✓		
NEO E-Series ( <a href="#">members</a> )	SCSI	HP	Ultrium 960 LTO3	SCSI	OVERLANDNEO^Series HP~~~~~Ultrium^3-SCSI	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	SCSI	HP	Ultrium 1840 LTO4	SCSI	OVERLANDNEO^Series HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
NEO E-Series ( <a href="#">members</a> )	SCSI	IBM	Ultrium 4 (U320)	SCSI	OVERLANDNEO^Series IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
NEO S-series 2nd Generation ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 4 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓	✓	✓
NEO S-series 2nd Generation ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH5	✓	✓	✓	✓
NEO S-series 2nd Generation ( <a href="#">members</a> ) [1]	Fibre Channel	IBM	Ultrium 6 Half Height	Fibre Channel	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH6	✓	✓	✓	✓
NEO S-series 2nd Generation ( <a href="#">members</a> )	SAS	IBM	Ultrium 4 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH4	✓	✓		
NEO S-series 2nd Generation ( <a href="#">members</a> )	SAS	IBM	Ultrium 5 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH5	✓	✓		
NEO S-series 2nd Generation ( <a href="#">members</a> ) [1]	SAS	IBM	Ultrium 6 Half Height	SAS	IBM~~~~~3573-TL IBM~~~~~ULTRIUM-HH6	✓	✓		
NEO series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	OVERLANDNEO^Series HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
NEO series ( <a href="#">members</a> )	SCSI	HP	Ultrium 460 LTO2	SCSI	OVERLANDNEO^Series HP~~~~~Ultrium^2-SCSI	✓	✓	✓	✓

## Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
NEO series ( <a href="#">members</a> )	SCSI	HP	Ultrium 960 LTO3	Fibre Channel	OVERLANDNEO^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
NEO series ( <a href="#">members</a> )	SCSI	HP	Ultrium 960 LTO3	SCSI	OVERLANDNEO^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
NEO series ( <a href="#">members</a> )	SCSI	HP	Ultrium 1840 LTO4	Fibre Channel	OVERLANDNEO^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
NEO series ( <a href="#">members</a> )	SCSI	HP	Ultrium 1840 LTO4	SCSI	OVERLANDNEO^Series HP^Ultrium^4-SCSI	✓	✓		
NEO series ( <a href="#">members</a> )	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	OVERLANDNEO^Series IBM^ULT3580-TD2	✓	✓	✓	✓
NEO series ( <a href="#">members</a> ) [2]	SCSI	Quantum	SDLT 600	SCSI	OVERLANDNEO^Series QUANTUM^SDLT600	✓			
NEOs series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
NEOs series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓
NEOs series ( <a href="#">members</a> )	SAS	HP	Ultrium 920 LTO3	SAS	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓		
NEOs series ( <a href="#">members</a> )	SAS	HP	Ultrium 1760 LTO4	SAS	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		
NEOs series ( <a href="#">members</a> )	SAS	HP	Ultrium 3000 LTO5	SAS	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓		
NEOs series ( <a href="#">members</a> )	SCSI	HP	Ultrium 920 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
NEOs series ( <a href="#">members</a> )	SCSI	HP	Ultrium 1760 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	

1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>

2. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## PivotStor

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
AP TL2000 2U	SAS	HP	Ultrium 1760 LTO4	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓		
AP TL2000 2U	SCSI	HP	Ultrium 1760 LTO4	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	
AP TL4000 4U	SAS	HP	Ultrium 1760 LTO4	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓		
AP TL4000 4U	SCSI	HP	Ultrium 1760 LTO4	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	
AP TL8000 8U	SAS	HP	Ultrium 1760 LTO4	SAS	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓		
AP TL8000 8U	SCSI	HP	Ultrium 1760 LTO4	SCSI	BDT~~~~FlexStor^II HP~~~~Ultrium^4-SCSI	✓	✓	✓	

## Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
CLS-4216 [1]	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARCLS-4 SONY~~~~SDX-700C	✓			
RLS-4000 AIT series (members) [1]	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARRLS-4 SONY~~~~SDX-700C	✓			
RLS-4000 AIT series (members)	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	QUALSTARRLS-4 SONY~~~~SDX-900V	✓	✓	✓	✓
RLS-4000 AIT series (members)	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	QUALSTARRLS-4 SONY~~~~SDX-1100	✓	✓	✓	✓



# Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
RLS-5000 SAIT series (members) [1]	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	QUALSTARRLS-5 SONY^^^SDZ-100	✓			
RLS-6000 (S)DLT series (members) [1]	SCSI	Quantum	SDLT 320	SCSI	QUALSTARRLS-6 QUANTUM^SDLT320	✓			
RLS-6000 (S)DLT series (members) [1]	SCSI	Quantum	SDLT 600	SCSI	QUALSTARRLS-6 QUANTUM^SDLT600	✓			✓
RLS-8000 LTO series (members)	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	QUALSTARRLS-8 IBM^^^ULTRIUM-HH5	✓	✓	✓	✓
RLS-8000 LTO series (members)	SAS	IBM	Ultrium 5 Half Height	SAS	QUALSTARRLS-8 IBM^^^ULTRIUM-HH5	✓	✓		
RLS-8000 LTO series (members)	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	QUALSTARRLS-8 IBM^^^ULT3580-TD2	✓	✓	✓	✓
RLS-8000 LTO series (members)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	QUALSTARRLS-8 IBM^^^ULT3580-TD3	✓	✓	✓	✓
RLS-8000 LTO series (members)	SCSI	IBM	Ultrium 2	Fibre Channel	QUALSTARRLS-8 IBM^^^ULTRIUM-TD2	✓	✓	✓	✓
RLS-8000 LTO series (members)	SCSI	IBM	Ultrium 2	SCSI	QUALSTARRLS-8 IBM^^^ULTRIUM-TD2	✓	✓	✓	✓
RLS-8000D LTO series (members)	Fibre Channel	IBM	Ultrium 4	Fibre Channel	QUALSTARRLS-8 IBM^^^ULTRIUM-TD4	✓	✓	✓	✓
RLS-8000D LTO series (members)	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	QUALSTARRLS-8 IBM^^^ULTRIUM-HH5	✓	✓	✓	✓
RLS-8000D LTO series (members)	SAS	IBM	Ultrium 5 Half Height	SAS	QUALSTARRLS-8 IBM^^^ULTRIUM-HH5	✓	✓		
RLS-8500 LTO series (members)	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	QUALSTARRLS-85 IBM^^^ULTRIUM-HH5	✓	✓	✓	✓
RLS-8500 LTO series (members)	SAS	IBM	Ultrium 5 Half Height	SAS	QUALSTARRLS-85 IBM^^^ULTRIUM-HH5	✓	✓		
TLS-4000 AIT series (members) [1]	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARTLS-4 SONY^^^SDX-700C	✓			✓

# Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
TLS-4000 AIT series ( <a href="#">members</a> )	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	QUALSTARTLS-4 SONY^^^SDX-900V	✓	✓	✓	✓
TLS-4000 AIT series ( <a href="#">members</a> )	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	QUALSTARTLS-4 SONY^^^SDX-1100	✓	✓	✓	
TLS-5000 SAIT series ( <a href="#">members</a> )	Fibre Channel	Sony	SDZ-130 SAITi1300SS (SAIT)	Fibre Channel	QUALSTARTLS-5 SONY^^^SDZ-130	✓	✓	✓	✓
TLS-5000 SAIT series ( <a href="#">members</a> )	SCSI	IBM	Ultrium 4 (U320)	SCSI	QUALSTARTLS-5 IBM^^^ULTRIUM-TD4	✓	✓	✓	✓
TLS-5000 SAIT series ( <a href="#">members</a> )	SCSI	IBM	Ultrium 4	Fibre Channel	QUALSTARTLS-5 IBM^^^ULTRIUM-TD4	✓	✓	✓	✓
TLS-5000 SAIT series ( <a href="#">members</a> ) [1]	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	QUALSTARTLS-5 SONY^^^SDZ-100	✓			✓
TLS-6000 DLT series ( <a href="#">members</a> ) [1]	SCSI	Quantum	SDLT 320	SCSI	QUALSTARTLS-6 QUANTUM^SDLT320	✓			✓
TLS-6000 DLT series ( <a href="#">members</a> ) [1]	SCSI	Quantum	SDLT 600	SCSI	QUALSTARTLS-6 QUANTUM^SDLT600	✓			✓
TLS-8000 LTO series ( <a href="#">members</a> )	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	QUALSTARTLS-8 IBM^^^ULT3580-TD2	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	QUALSTARTLS-8 IBM^^^ULT3580-TD3	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 4	Fibre Channel	QUALSTARTLS-8 IBM^^^ULTRIUM-TD4	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 5 Half Height	Fibre Channel	QUALSTARTLS-8 IBM^^^ULTRIUM-HH5	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	SAS	IBM	Ultrium 5 Half Height	SAS	QUALSTARTLS-8 IBM^^^ULTRIUM-HH5	✓	✓		
TLS-8000 LTO series ( <a href="#">members</a> )	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	QUALSTARTLS-8 IBM^^^ULT3580-TD2	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	QUALSTARTLS-8 IBM^^^ULT3580-TD3	✓	✓	✓	✓

## Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
TLS-8000 LTO series ( <a href="#">members</a> )	SCSI	IBM	Ultrium 3	Fibre Channel	QUALSTARTLS-8 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
TLS-8000 LTO series ( <a href="#">members</a> )	SCSI	IBM	Ultrium 4 (U160)	SCSI	QUALSTARTLS-8 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
XLS-8000	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULT3580-TD3	✓	✓	✓	✓
XLS-8000	Fibre Channel	IBM	Ultrium 3	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD3	✓		✓	✓
XLS-8000	Fibre Channel	IBM	Ultrium 4	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
XLS-8000	Fibre Channel	IBM	Ultrium 5	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD5	✓	✓	✓	✓
XLS-8000 [1]	SAS	IBM	Ultrium 5	SAS	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD5	✓	✓		
XLS-8000	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	QUALSTARXLS-8000 IBM~~~~~ULT3580-TD3	✓	✓	✓	✓
XLS series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 3	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
XLS series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 4	Fibre Channel	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
PX500 Series <a href="#">(members)</a> <a href="#">[1]</a>	Fibre Channel	HP	Ultrium 460 LTO2	SCSI	QUANTUM^PX500 HP^~~~~Ultrium^2-SCSI	✓	✓	✓	✓
PX500 Series <a href="#">(members)</a> <a href="#">[2]</a>	Fibre Channel	Quantum	DLT-S4	Fibre Channel	QUANTUM^PX500 QUANTUM^DLT-S4	✓	✓		✓
PX500 Series <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[2]</a>	Fibre Channel	Quantum	SDLT 600	Fibre Channel	QUANTUM^PX500 QUANTUM^SDLT600	✓		✓	✓
PX500 Series <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[2]</a>	SCSI	HP	Ultrium 460 LTO2	SCSI	QUANTUM^PX500 HP^~~~~Ultrium^2-SCSI	✓	✓	✓	✓
PX500 Series <a href="#">(members)</a>	SCSI	HP	Ultrium 920 LTO3	SCSI	QUANTUM^PX500 HP^~~~~Ultrium^3-SCSI	✓	✓	✓	
PX500 Series <a href="#">(members)</a> <a href="#">[2]</a>	SCSI	HP	Ultrium 960 LTO3	Fibre Channel	QUANTUM^PX500 HP^~~~~Ultrium^3-SCSI	✓	✓	✓	✓
PX500 Series <a href="#">(members)</a> <a href="#">[2]</a>	SCSI	HP	Ultrium 960 LTO3	SCSI	QUANTUM^PX500 HP^~~~~Ultrium^3-SCSI	✓	✓	✓	
PX500 Series <a href="#">(members)</a> <a href="#">[2]</a>	SCSI	Quantum	DLT-S4	SCSI	QUANTUM^PX500 QUANTUM^DLT-S4	✓	✓		✓
PX500 Series <a href="#">(members)</a>	SCSI	Quantum	LTO-3 HH	SCSI	QUANTUM^PX500 QUANTUM^ULTRIUM^3	✓	✓	✓	
PX500 Series <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[2]</a>	SCSI	Quantum	SDLT 320	SCSI	QUANTUM^PX500 QUANTUM^SDLT320	✓			✓
PX500 Series <a href="#">(members)</a> <a href="#">[1]</a> <a href="#">[2]</a>	SCSI	Quantum	SDLT 600	SCSI	QUANTUM^PX500 QUANTUM^SDLT600	✓			
PX720	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	QUANTUM^PX720 HP^~~~~Ultrium^2-SCSI	✓	✓	✓	✓
PX720	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	QUANTUM^PX720 HP^~~~~Ultrium^4-SCSI	✓	✓	✓	✓
PX720	Fibre Channel	Quantum	DLT-S4	Fibre Channel	QUANTUM^PX720 QUANTUM^DLT-S4	✓			✓
PX720	Fibre Channel	Quantum	SDLT 600	Fibre Channel	QUANTUM^PX720 QUANTUM^SDLT600	✓			✓

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
PX720	SCSI	HP	Ultrium 460 LTO2	SCSI	QUANTUM^PX720 HP^Ultrium^2-SCSI	✓	✓	✓	✓
PX720	SCSI	HP	Ultrium 960 LTO3	Fibre Channel	QUANTUM^PX720 HP^Ultrium^3-SCSI	✓	✓	✓	✓
PX720	SCSI	HP	Ultrium 960 LTO3	SCSI	QUANTUM^PX720 HP^Ultrium^3-SCSI	✓	✓	✓	
PX720	SCSI	HP	Ultrium 1840 LTO4	Fibre Channel	QUANTUM^PX720 HP^Ultrium^4-SCSI	✓	✓	✓	✓
PX720	SCSI	HP	Ultrium 1840 LTO4	SCSI	QUANTUM^PX720 HP^Ultrium^4-SCSI	✓	✓	✓	
PX720	SCSI	Quantum	SDLT 320	SCSI	QUANTUM^PX720 QUANTUM^SDLT320	✓		✓	✓
PX720	SCSI	Quantum	SDLT 600	SCSI	QUANTUM^PX720 QUANTUM^SDLT600	✓			
Scalar 50 (PX500) [3]	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	QUANTUM^PX500 HP^Ultrium^3-SCSI	✓	✓	✓	✓
Scalar 50 (PX500) [3]	SCSI	HP	Ultrium 960 LTO3	SCSI	QUANTUM^PX500 HP^Ultrium^3-SCSI	✓	✓	✓	
Scalar 50 (PX500) [1] [3]	SCSI	Quantum	DLT-V4	SCSI	QUANTUM^PX500 QUANTUM^DLT-V4	✓			
Scalar 50 (PX500) [3]	SCSI	Quantum	LTO-3 HH	SCSI	QUANTUM^PX500 QUANTUM^ULTRIUM^3	✓	✓	✓	
Scalar 50 (SCALAR50) [3]	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	QUANTUM^SCALAR50 HP^Ultrium^4-SCSI	✓	✓	✓	✓
Scalar 50 (SCALAR50) [3]	Fibre Channel	Quantum	DLT-S4	Fibre Channel	QUANTUM^SCALAR50 QUANTUM^DLT-S4	✓	✓		✓
Scalar 50 (SCALAR50)	SAS	HP	Ultrium 1760 LTO4	SAS	QUANTUM^SCALAR50 HP^Ultrium^4-SCSI	✓	✓		
Scalar 50 (SCALAR50) [3]	SCSI	HP	Ultrium 1840 LTO4	SCSI	QUANTUM^SCALAR50 HP^Ultrium^4-SCSI	✓	✓	✓	

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Scalar 50 (SCALAR50) [3]	SCSI	Quantum	LTO-3 HH	SCSI	QUANTUM^SCALAR50 QUANTUM^ULTRIUM^3	✓	✓	✓	✓
Scalar i40/i80 series (members)	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
Scalar i40/i80 series (members)	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
Scalar i40/i80 series (members)	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
Scalar i40/i80 series (members) [4]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^6-SCSI	✓	✓	✓	✓
Scalar i40/i80 series (members)	SAS	HP	Ultrium 1760 LTO4	SAS	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^4-SCSI	✓	✓		
Scalar i40/i80 series (members)	SAS	HP	Ultrium 1840 LTO4	SAS	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^4-SCSI	✓	✓		
Scalar i40/i80 series (members)	SAS	HP	Ultrium 3000 LTO5	SAS	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^5-SCSI	✓	✓		
Scalar i40/i80 series (members) [4]	SAS	HP	Ultrium 6250 LTO6	SAS	QUANTUM^Scalar^i40-i80 HP^~~~~~Ultrium^6-SCSI	✓	✓		
Scalar i500	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	Quantum^Scalar^i500 HP^~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
Scalar i500 [5]	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	Quantum^Scalar^i500 HP^~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
Scalar i500 [4]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	Quantum^Scalar^i500 HP^~~~~~Ultrium^6-SCSI	✓	✓	✓	✓
Scalar i500 [5]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	Quantum^Scalar^i500 IBM^~~~~~ULT3580-TD5	✓	✓	✓	✓
Scalar i500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	Quantum^Scalar^i500 IBM^~~~~~ULT3580-TD2	✓	✓	✓	✓
Scalar i500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	Quantum^Scalar^i500 IBM^~~~~~ULT3580-TD3	✓	✓	✓	✓

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Scalar i500 [6]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	Quantum^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓	✓	✓
Scalar i500 [4]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	Quantum^Scalar^i500 IBM^ULTRIUM-TD6	✓	✓	✓	✓
Scalar i500 [6]	SAS	HP	Ultrium 1840 LTO4	SAS	Quantum^Scalar^i500 HP^Ultrium^4-SCSI	✓	✓		
Scalar i500 [5]	SAS	HP	Ultrium 3280 LTO5	SAS	Quantum^Scalar^i500 HP^Ultrium^5-SCSI	✓	✓		
Scalar i500 [4]	SAS	HP	Ultrium 6650 LTO6	SAS	Quantum^Scalar^i500 HP^Ultrium^6-SCSI	✓	✓		
Scalar i500 [5]	SAS	IBM	System Storage TS2350 Ultrium 5	SAS	Quantum^Scalar^i500 IBM^ULT3580-TD5	✓	✓		
Scalar i500 [6]	SAS	IBM	Ultrium 4	SAS	Quantum^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓		
Scalar i500 [1]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	Quantum^Scalar^i500 IBM^ULT3580-TD2	✓	✓	✓	✓
Scalar i500	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	Quantum^Scalar^i500 IBM^ULT3580-TD3	✓	✓	✓	✓
Scalar i500 [6]	SCSI	IBM	Ultrium 4 (U160)	SCSI	Quantum^Scalar^i500 IBM^ULTRIUM-TD4	✓	✓	✓	
Scalar i2000	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	Quantum^Scalar^i2000 HP^Ultrium^3-SCSI	✓	✓	✓	✓
Scalar i2000	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	Quantum^Scalar^i2000 HP^Ultrium^4-SCSI	✓	✓	✓	✓
Scalar i2000 [6]	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	Quantum^Scalar^i2000 HP^Ultrium^5-SCSI	✓	✓	✓	✓
Scalar i2000 [1]	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	Quantum^Scalar^i2000 IBM^ULT3580-TD2	✓	✓	✓	✓
Scalar i2000	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	Quantum^Scalar^i2000 IBM^ULT3580-TD3	✓	✓	✓	✓

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
Scalar i2000 [6]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	Quantum^Scalar^i2000 IBM^ULTRIUM-TD4	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	Quantum^Scalar^i6000 HP^ULTRIUM^3-SCSI	✓	✓	✓	✓
Scalar i6000 [6] [7]	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	Quantum^Scalar^i6000 HP^ULTRIUM^4-SCSI	✓	✓	✓	✓
Scalar i6000 [5] [7]	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	Quantum^Scalar^i6000 HP^ULTRIUM^5-SCSI	✓	✓	✓	✓
Scalar i6000 [4] [7]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	Quantum^Scalar^i6000 HP^ULTRIUM^6-SCSI	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	Quantum^Scalar^i6000 IBM^ULT3580-TD2	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	IBM	Ultrium 3	Fibre Channel	Quantum^Scalar^i6000 IBM^ULTRIUM-TD3	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	Quantum^Scalar^i6000 IBM^ULTRIUM-TD4	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	IBM	Ultrium 5	Fibre Channel	Quantum^Scalar^i6000 IBM^ULTRIUM-TD5	✓	✓	✓	✓
Scalar i6000 [4] [7]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	Quantum^Scalar^i6000 IBM^ULTRIUM-TD6	✓	✓	✓	✓
Scalar i6000 [7]	Fibre Channel	Quantum	DLT-S4	Fibre Channel	Quantum^Scalar^i6000 QUANTUM^DLT-S4	✓	✓	✓	✓
SuperLoader 3	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	QUANTUM^UHD HP^ULTRIUM^3-SCSI	✓	✓	✓	✓
SuperLoader 3	Fibre Channel	Quantum	DLT-S4	Fibre Channel	QUANTUM^UHD QUANTUM^DLT-S4	✓	✓		
SuperLoader 3 [4]	SAS	IBM	Ultrium 4 Half Height	SAS	QUANTUM^UHD IBM^ULTRIUM-HH4	✓	✓		
SuperLoader 3 [4]	SAS	IBM	Ultrium 5 Half Height	SAS	QUANTUM^UHD IBM^ULTRIUM-HH5	✓	✓		



# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
SuperLoader 3 [4]	SAS	IBM	Ultrium 6 Half Height	SAS	QUANTUM^UHDL IBM^ULTRIUM-HH6	✓	✓		
SuperLoader 3	SAS	Quantum	LTO-3 HH	SAS	QUANTUM^UHDL QUANTUM^ULTRIUM^3	✓	✓		
SuperLoader 3	SAS	Quantum	LTO-4 HH	SAS	QUANTUM^UHDL QUANTUM^ULTRIUM^4	✓	✓		
SuperLoader 3	SAS	Quantum	LTO-5 FH	SAS	QUANTUM^UHDL QUANTUM^ULTRIUM^5	✓	✓		
SuperLoader 3	SAS	Quantum	LTO-5 HH	SAS	QUANTUM^UHDL QUANTUM^ULTRIUM^5	✓	✓		
SuperLoader 3 [4]	SAS	Quantum	LTO-6 HH	SAS	QUANTUM^UHDL QUANTUM^ULTRIUM^6	✓	✓		
SuperLoader 3 [1]	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	QUANTUM^UHDL CERTANCEULTRIUM^2	✓	✓	✓	
SuperLoader 3	SCSI	Certance	CL 800 LTO Ultrium 3	SCSI	QUANTUM^UHDL CERTANCEULTRIUM^3	✓	✓	✓	
SuperLoader 3	SCSI	HP	Ultrium 1840 LTO4	SCSI	QUANTUM^UHDL HP^ULtrium^4-SCSI	✓	✓	✓	
SuperLoader 3	SCSI	Quantum	DLT-S4	SCSI	QUANTUM^UHDL QUANTUM^DLT-S4	✓	✓		
SuperLoader 3	SCSI	Quantum	DLT-V4	SCSI	QUANTUM^UHDL QUANTUM^DLT-V4	✓			
SuperLoader 3 [1]	SCSI	Quantum	DLT VS160	SCSI	QUANTUM^UHDL QUANTUM^DLT^VS160	✓			
SuperLoader 3	SCSI	Quantum	LTO-3 HH	SCSI	QUANTUM^UHDL QUANTUM^ULTRIUM^3	✓	✓	✓	✓
SuperLoader 3	SCSI	Quantum	SDLT 600	SCSI	QUANTUM^UHDL QUANTUM^SDLT600	✓		✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
2. Please see <http://www.symantec.com/docs/TECH45373> for additional support details.

3. Any tape drive supported with the "QUANTUM^PX500" inquiry string is also supported with the "QUANTUM^SCALAR50" inquiry string, and vice versa.
4. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
5. L1 & L2 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L3 (or above) barcode labels for cleaning media.
6. L1 barcode labels on a cleaning media will cause a cleaning utility job to hang indefinitely. Recommend using L2 (or above) barcode labels for cleaning media.
7. i6000 Dual Robot supported with firmware 630Q-GS0xxxx and above.

## Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
CSM20 [1]	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	SONY^^^CSM-20 SONY^^^SDZ-100	✓			
LIB-81 [1]	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-81 SONY^^^SDX-550V	✓			
LIB-81 [1]	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^^^LIB-81 SONY^^^SDX-800V	✓			
LIB-81 [1]	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^^^LIB-81 SONY^^^SDX-900V	✓			
LIB-81 [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-81 SONY^^^SDX-1100	✓	✓	✓	
LIB-152 (SONY) [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-152 SONY^^^SDX-1100	✓	✓		
LIB-152 [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^215 SONY^^^SDX-1100	✓			
LIB-162 [1]	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-162 SONY^^^SDX-550V	✓			
LIB-162 [1]	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^^^LIB-162 SONY^^^SDX-800V	✓			
LIB-162 [1]	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^^^LIB-162 SONY^^^SDX-900V	✓			
LIB-162 [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-162 SONY^^^SDX-1100	✓	✓	✓	

## Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
LIB-302 (SONY) [1]	SCSI	Sony	SDX-1100 AITe1040 (AIT-5)	SCSI	SONY^^^LIB-302 SONY^^^SDX-1100	✓	✓		
LIB-302 (SONY) [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-302 SONY^^^SDX-1100	✓	✓		
LIB-D81 [1]	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-550V	✓			
LIB-D81 [1]	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-800V	✓			
LIB-D81 [1]	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-900V	✓			
LIB-D81 [1]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-1100	✓	✓	✓	
PetaSite Series (members) [1]	Fibre Channel	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	SONY^^^CSM- SONY^^^SDZ-100	✓			
PetaSite Series (members) [1]	SCSI	IBM	Ultrium 4	Fibre Channel	SONY^^^CSM- IBM^^^ULTRIUM-TD4	✓	✓		

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
K-Series (members) [1] [2]	Fibre Channel	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^GATOR SONY^^^SDX-900V	✓			✓
K-Series (members) [1] [2]	Fibre Channel	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^GATOR SONY^^^SDX-1100	✓	✓	✓	✓
K-Series (members) [1] [2]	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^GATOR SONY^^^SDX-900V	✓			✓

# Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
K-Series <a href="#">(members)</a> [1] [2]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^GATOR SONY^SDX-1100	✓	✓	✓	
Spectra 2K [2]	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^215 SONY^SDX-900V	✓			
Spectra 2K [2]	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^215 SONY^SDX-1100	✓	✓		
Spectra T24	SCSI	HP	Ultrium 448 LTO2	SCSI	SPECTRA^GECKO HP^Ultrium^2-SCSI	✓	✓	✓	
Spectra T24	SCSI	HP	Ultrium 920 LTO3	SCSI	SPECTRA^GECKO HP^Ultrium^3-SCSI	✓	✓	✓	
T-series <a href="#">(members)</a> [3] [4]	Fibre Channel	IBM	System Storage TS2250 Ultrium 5 Half Height	Fibre Channel	SPECTRA^PYTHON IBM^ULT3580-HH5	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	SPECTRA^PYTHON IBM^ULT3580-TD5	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4]	Fibre Channel	IBM	Ultrium 2	Fibre Channel	SPECTRA^PYTHON IBM^ULTRIUM-TD2	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4]	Fibre Channel	IBM	Ultrium 3	Fibre Channel	SPECTRA^PYTHON IBM^ULTRIUM-TD3	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	SPECTRA^PYTHON IBM^ULTRIUM-TD4	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4] [5]	Fibre Channel	IBM	Ultrium 6 Half Height	Fibre Channel	SPECTRA^PYTHON IBM^ULTRIUM-HH6	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4] [5]	Fibre Channel	IBM	Ultrium 6	Fibre Channel	SPECTRA^PYTHON IBM^ULTRIUM-TD6	✓	✓	✓	✓
T-series <a href="#">(members)</a> [3] [4]	SAS	IBM	System Storage TS2250 Ultrium 5 Half Height	SAS	SPECTRA^PYTHON IBM^ULT3580-HH5	✓	✓		
T-series <a href="#">(members)</a> [3] [4] [5]	SAS	IBM	Ultrium 6 Half Height	SAS	SPECTRA^PYTHON IBM^ULTRIUM-HH6	✓	✓		
T-series <a href="#">(members)</a> [3] [4] [5]	SAS	IBM	Ultrium 6	SAS	SPECTRA^PYTHON IBM^ULTRIUM-TD6	✓	✓		

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
T-series ( <a href="#">members</a> ) [3]	SCSI	HP	Ultrium 448 LTO2	SCSI	SPECTRA^PYTHON HP^~~~~Ultrium^2-SCSI	✓	✓	✓	
T-series ( <a href="#">members</a> ) [3]	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	SPECTRA^PYTHON IBM^~~~~ULT3580-TD2	✓	✓	✓	✓
T-series ( <a href="#">members</a> ) [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	SPECTRA^PYTHON IBM^~~~~ULT3580-TD3	✓	✓	✓	
T-series ( <a href="#">members</a> ) [3]	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	SPECTRA^PYTHON IBM^~~~~ULT3580-TD3	✓	✓	✓	✓
T-series ( <a href="#">members</a> ) [3]	SCSI	IBM	Ultrium 4 (U320)	SCSI	SPECTRA^PYTHON IBM^~~~~ULTRIUM-TD4	✓	✓	✓	
T-series ( <a href="#">members</a> ) [2] [3]	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	SPECTRA^PYTHON SONY^~~~~SDZ-100	✓			

1. See the referenced document for more details. ( [<http://www.symantec.com/docs/TECH53008>](http://www.symantec.com/docs/TECH53008) )
2. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
3. Minimum library firmware of BlueScale10.4.0-20080908F is suggested for proper import/export operation. Library firmware version is determined in the library GUI, not in the inquiry string.
4. Refer to Spectra KB article 1286 for incompatible media library issues. (Spectra login required)
5. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: [<http://www.symantec.com/docs/TECH208600>](http://www.symantec.com/docs/TECH208600)

# StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
L180	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	STK^L180 HP^Ultrium^2-SCSI	✓	✓	✓	✓
L180	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	STK^L180 HP^Ultrium^4-SCSI	✓	✓		✓
L180	Fibre Channel	IBM	Ultrium 3	Fibre Channel	STK^L180 IBM^ULTRIUM-TD3	✓	✓	✓	✓
L180	Fibre Channel	IBM	Ultrium 4	Fibre Channel	STK^L180 IBM^ULTRIUM-TD4	✓	✓		✓
L180 [1]	Fibre Channel	StorageTek	T9840C	Fibre Channel	STK^L180 STK^T9840C	✓		✓	✓
L180	SCSI	HP	Ultrium 460 LTO2	SCSI	STK^L180 HP^Ultrium^2-SCSI	✓	✓	✓	✓
L180	SCSI	HP	Ultrium 960 LTO3	SCSI	STK^L180 HP^Ultrium^3-SCSI	✓	✓	✓	
L180	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	STK^L180 IBM^ULT3580-TD2	✓	✓	✓	✓
L180 [1]	SCSI	StorageTek	T9840C	Fibre Channel	STK^L180 STK^T9840C	✓			✓
L180 [1]	SCSI	StorageTek	T9940B	Fibre Channel	STK^L180 STK^T9940B	✓			✓
L700	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	STK^L700 HP^Ultrium^2-SCSI	✓	✓	✓	✓
L700	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	STK^L700 HP^Ultrium^3-SCSI	✓	✓	✓	✓
L700	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	STK^L700 HP^Ultrium^4-SCSI	✓	✓	✓	✓
L700	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	STK^L700 IBM^ULT3580-TD3	✓	✓	✓	✓
L700	Fibre Channel	IBM	Ultrium 4	Fibre Channel	STK^L700 IBM^ULTRIUM-TD4	✓	✓	✓	✓

# StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
L700 [1]	Fibre Channel	StorageTek	T10000A 4GB	Fibre Channel	STK^L700 STK^T10000A	✓			✓
L700	SCSI	HP	Ultrium 460 LTO2	SCSI	STK^L700 HP^Ultrium^2-SCSI	✓	✓	✓	✓
L700	SCSI	HP	Ultrium 960 LTO3	SCSI	STK^L700 HP^Ultrium^3-SCSI	✓	✓	✓	
L700	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	STK^L700 IBM^ULT3580-TD2	✓	✓	✓	✓
L700 [1]	SCSI	StorageTek	T9840C	Fibre Channel	STK^L700 STK^T9840C	✓			✓
L700 [1]	SCSI	StorageTek	T9940B	Fibre Channel	STK^L700 STK^T9940B	✓			✓
L1400	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	STK^L700e HP^Ultrium^2-SCSI	✓	✓	✓	✓
L1400	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	STK^L700e HP^Ultrium^3-SCSI	✓	✓	✓	✓
SL500	Fibre Channel	HP	Ultrium 460 LTO2	Fibre Channel	STK^SL500 HP^Ultrium^2-SCSI	✓	✓	✓	✓
SL500	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	STK^SL500 HP^Ultrium^3-SCSI	✓	✓	✓	✓
SL500	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	STK^SL500 HP^Ultrium^4-SCSI	✓	✓	✓	✓
SL500	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	STK^SL500 HP^Ultrium^5-SCSI	✓	✓	✓	✓
SL500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	STK^SL500 IBM^ULT3580-TD2	✓	✓	✓	✓
SL500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	STK^SL500 IBM^ULT3580-TD3	✓	✓	✓	✓
SL500	Fibre Channel	IBM	Ultrium 3	Fibre Channel	STK^SL500 IBM^ULTRIUM-TD3	✓	✓	✓	✓

# StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
SL500	Fibre Channel	IBM	Ultrium 4 (U160)	SCSI	STK^SL500 IBM^ULTRIUM-TD4	✓	✓		
SL500	Fibre Channel	IBM	Ultrium 4	Fibre Channel	STK^SL500 IBM^ULTRIUM-TD4	✓	✓	✓	✓
SL500	Fibre Channel	IBM	Ultrium 5	Fibre Channel	STK^SL500 IBM^ULTRIUM-TD5	✓	✓	✓	✓
SL500	SAS	HP	Ultrium 3280 LTO5	SAS	STK^SL500 HP^Ultrium^5-SCSI	✓	✓		
SL500	SCSI	HP	Ultrium 460 LTO2	Fibre Channel	STK^SL500 HP^Ultrium^2-SCSI	✓	✓	✓	✓
SL500	SCSI	HP	Ultrium 460 LTO2	SCSI	STK^SL500 HP^Ultrium^2-SCSI	✓	✓	✓	✓
SL500	SCSI	HP	Ultrium 960 LTO3	Fibre Channel	STK^SL500 HP^Ultrium^3-SCSI	✓	✓	✓	✓
SL500	SCSI	HP	Ultrium 960 LTO3	SCSI	STK^SL500 HP^Ultrium^3-SCSI	✓	✓	✓	
SL500	SCSI	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	STK^SL500 IBM^ULT3580-TD2	✓	✓	✓	✓
SL500	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	STK^SL500 IBM^ULT3580-TD2	✓	✓	✓	✓
SL500	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	STK^SL500 IBM^ULT3580-TD3	✓	✓	✓	✓
SL3000 [2]	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	STK^SL3000 HP^Ultrium^4-SCSI	✓	✓	✓	✓
SL3000 [2]	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	STK^SL3000 HP^Ultrium^5-SCSI	✓	✓	✓	✓
SL3000 [2] [3]	Fibre Channel	HP	Ultrium 6650 LTO6	Fibre Channel	STK^SL3000 HP^Ultrium^6-SCSI	✓	✓	✓	✓
SL3000 [2]	Fibre Channel	IBM	System Storage TS2350 Ultrium 5	Fibre Channel	STK^SL3000 IBM^ULT3580-TD5	✓	✓	✓	✓



## StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
SL3000 [2]	Fibre Channel	IBM	Ultrium 4	Fibre Channel	STK^SL3000 IBM^ULTRIUM-TD4	✓	✓	✓	✓
SL3000 [2]	Fibre Channel	StorageTek	T9840C	Fibre Channel	STK^SL3000 STK^T9840C	✓	✓	✓	✓
SL3000 [2]	Fibre Channel	StorageTek	T9840D	Fibre Channel	STK^SL3000 STK^T9840D	✓	✓	✓	✓
SL3000 [2] [3]	Fibre Channel	StorageTek	T10000A	Fibre Channel	STK^SL3000 STK^T10000A	✓	✓	✓	✓
SL3000 [2] [3]	Fibre Channel	StorageTek	T10000B	Fibre Channel	STK^SL3000 STK^T10000B	✓	✓	✓	✓
SL3000 [2] [4]	Fibre Channel	StorageTek	T10000C	Fibre Channel	STK^SL3000 STK^T10000C	✓	✓	✓	✓

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
2. Minimum library firmware level of 2.30 is required.
3. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
4. Required driver support can be found in "HF 208600". Use latest SP available by downloading: <http://www.symantec.com/docs/TECH208600> or via LiveUpdate

## Sun

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageTek C4	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	QUANTUM^PX500 CERTANCEULTRIUM^2	✓	✓	✓	
StorageTek C4	SCSI	HP	Ultrium 960 LTO3	SCSI	QUANTUM^PX500 HP^Ultrium^3-SCSI	✓	✓	✓	
StorageTek C4	SCSI	Quantum	LTO-3 HH	SCSI	QUANTUM^PX500 QUANTUM^ULTRIUM^3	✓	✓	✓	

# Sun

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageTek C4	SCSI	Quantum	LTO-3	SCSI	QUANTUM^PX500 CERTANCEULTRIUM^3	✓	✓	✓	
StorageTek SL24	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
StorageTek SL24	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
StorageTek SL24	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓
StorageTek SL24	SAS	HP	Ultrium 920 LTO3	SAS	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓		
StorageTek SL24	SAS	HP	Ultrium 1760 LTO4	SAS	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		
StorageTek SL24	SAS	HP	Ultrium 3000 LTO5	SAS	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓		
StorageTek SL24	SCSI	HP	Ultrium 448 LTO2	SCSI	HP^MSL^G3^Series HP^Ultrium^2-SCSI	✓	✓	✓	
StorageTek SL24	SCSI	HP	Ultrium 920 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
StorageTek SL24	SCSI	HP	Ultrium 960 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
StorageTek SL24	SCSI	HP	Ultrium 1760 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		
StorageTek SL24	SCSI	HP	Ultrium 1840 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	
StorageTek SL48	Fibre Channel	HP	Ultrium 960 LTO3	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	✓
StorageTek SL48	Fibre Channel	HP	Ultrium 1840 LTO4	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	✓
StorageTek SL48	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓	✓	✓

# Sun

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageTek SL48	SAS	HP	Ultrium 920 LTO3	SAS	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓		
StorageTek SL48	SAS	HP	Ultrium 1760 LTO4	SAS	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		
StorageTek SL48	SAS	HP	Ultrium 3000 LTO5	SAS	HP^MSL^G3^Series HP^Ultrium^5-SCSI	✓	✓		
StorageTek SL48	SCSI	HP	Ultrium 448 LTO2	SCSI	HP^MSL^G3^Series HP^Ultrium^2-SCSI	✓	✓	✓	
StorageTek SL48	SCSI	HP	Ultrium 920 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
StorageTek SL48	SCSI	HP	Ultrium 960 LTO3	SCSI	HP^MSL^G3^Series HP^Ultrium^3-SCSI	✓	✓	✓	
StorageTek SL48	SCSI	HP	Ultrium 1760 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓		
StorageTek SL48	SCSI	HP	Ultrium 1840 LTO4	SCSI	HP^MSL^G3^Series HP^Ultrium^4-SCSI	✓	✓	✓	
StorageTek SL500	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	STK^SL500 IBM^ULT3580-TD2	✓	✓	✓	
StorEdge C2	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	QUANTUM^UHD CERTANCEULTRIUM^2	✓	✓	✓	
StorEdge C2	SCSI	HP	Ultrium 960 LTO3	SCSI	QUANTUM^UHD HP^Ultrium^3-SCSI	✓	✓	✓	
StorEdge C2	SCSI	Quantum	LTO-3	SCSI	QUANTUM^UHD CERTANCEULTRIUM^3	✓	✓	✓	

# Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageLibrary T24	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	EXABYTE^MAGNUM^224 HP^Ultrium^4-SCSI	✓	✓	✓	✓
StorageLibrary T24	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	EXABYTE^MAGNUM^224 HP^Ultrium^5-SCSI	✓	✓	✓	✓
StorageLibrary T24 [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	EXABYTE^MAGNUM^224 HP^Ultrium^6-SCSI	✓	✓	✓	✓
StorageLibrary T24	Fibre Channel	IBM	Ultrium 3	Fibre Channel	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD3	✓	✓	✓	✓
StorageLibrary T24	Fibre Channel	IBM	Ultrium 4	Fibre Channel	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD4	✓	✓	✓	✓
StorageLibrary T24	SAS	HP	Ultrium 1760 LTO4	SAS	EXABYTE^MAGNUM^224 HP^Ultrium^4-SCSI	✓	✓		
StorageLibrary T24	SAS	HP	Ultrium 3000 LTO5	SAS	EXABYTE^MAGNUM^224 HP^Ultrium^5-SCSI	✓	✓		
StorageLibrary T24 [1]	SAS	HP	Ultrium 6250 LTO6	SAS	EXABYTE^MAGNUM^224 HP^Ultrium^6-SCSI	✓	✓		
StorageLibrary T24	SAS	IBM	Ultrium 4 Half Height	SAS	EXABYTE^MAGNUM^224 IBM^ULTRIUM-HH4	✓	✓		
StorageLibrary T24	SCSI	HP	Ultrium 448 LTO2	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^2-SCSI	✓	✓	✓	
StorageLibrary T24	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^3-SCSI	✓	✓	✓	
StorageLibrary T24	SCSI	IBM	Ultrium 3	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD3	✓	✓	✓	
StorageLibrary T24	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD4	✓	✓	✓	
StorageLibrary T24	SCSI	IBM	Ultrium 4 Half Height (U320)	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-HH4	✓	✓	✓	

# Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 1760 LTO4	Fibre Channel	TANDBERGStorageLoader HP~~~~~Ultrium^4-SCSI	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	TANDBERGStorageLoader HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	Fibre Channel	HP	Ultrium 3280 LTO5	Fibre Channel	TANDBERGStorageLoader HP~~~~~Ultrium^5-SCSI	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> ) [1]	Fibre Channel	HP	Ultrium 6250 LTO6	Fibre Channel	TANDBERGStorageLoader HP~~~~~Ultrium^6-SCSI	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 3	Fibre Channel	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	Fibre Channel	IBM	Ultrium 4	Fibre Channel	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	SAS	HP	Ultrium 1760 LTO4	SAS	TANDBERGStorageLoader HP~~~~~Ultrium^4-SCSI	✓	✓		
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	SAS	HP	Ultrium 3000 LTO5	SAS	TANDBERGStorageLoader HP~~~~~Ultrium^5-SCSI	✓	✓		
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> ) [1]	SAS	HP	Ultrium 6250 LTO6	SAS	TANDBERGStorageLoader HP~~~~~Ultrium^6-SCSI	✓	✓		
StorageLibrary T40+/T80+/T120+/T160+ series ( <a href="#">members</a> )	SAS	IBM	Ultrium 4 Half Height	SAS	TANDBERGStorageLoader IBM~~~~~ULTRIUM-HH4	✓	✓		

# Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageLibrary T40+/T80+/T120+/T160+ series (members)	SCSI	HP	Ultrium 1760 LTO4	SCSI	TANDBERGStorageLoader HP~~~~~Ultrium^4-SCSI	✓	✓	✓	
StorageLibrary T40+/T80+/T120+/T160+ series (members)	SCSI	IBM	Ultrium 3	SCSI	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD3	✓	✓	✓	
StorageLibrary T40+/T80+/T120+/T160+ series (members)	SCSI	IBM	Ultrium 4 (U320)	SCSI	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
StorageLibrary T40+/T80+/T120+/T160+ series (members)	SCSI	IBM	Ultrium 4 Half Height (U320)	SCSI	TANDBERGStorageLoader IBM~~~~~ULTRIUM-HH4	✓	✓	✓	
StorageLibrary T40	Fibre Channel	IBM	Ultrium 3	Fibre Channel	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
StorageLibrary T40	Fibre Channel	IBM	Ultrium 4	Fibre Channel	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
StorageLibrary T40	SCSI	IBM	Ultrium 3	SCSI	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD3	✓	✓	✓	
StorageLibrary T40	SCSI	IBM	Ultrium 4 (U160)	SCSI	TANDBERGStorageLoader IBM~~~~~ULTRIUM-TD4	✓	✓	✓	
StorageLibrary T48	Fibre Channel	IBM	Ultrium 3	Fibre Channel	EXABYTE^MAGNUM^448 IBM~~~~~ULTRIUM-TD3	✓	✓	✓	✓
StorageLibrary T48	Fibre Channel	IBM	Ultrium 4	Fibre Channel	EXABYTE^MAGNUM^448 IBM~~~~~ULTRIUM-TD4	✓	✓	✓	✓
StorageLibrary T48	SAS	IBM	Ultrium 4 Half Height	SAS	EXABYTE^MAGNUM^448 IBM~~~~~ULTRIUM-HH4	✓	✓		
StorageLibrary T48	SCSI	HP	Ultrium 448 LTO2	SCSI	EXABYTE^MAGNUM^448 HP~~~~~Ultrium^2-SCSI	✓	✓	✓	
StorageLibrary T48	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^MAGNUM^448 HP~~~~~Ultrium^3-SCSI	✓	✓	✓	

# Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry	WinBES	RMAL	NDMP	ESO
StorageLibrary T48	SCSI	IBM	Ultrium 3	SCSI	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD3	✓	✓	✓	
StorageLibrary T48	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD4	✓	✓	✓	
StorageLibrary T48	SCSI	IBM	Ultrium 4 Half Height (U320)	SCSI	EXABYTE^MAGNUM^448 IBM^ULTRIUM-HH4	✓	✓	✓	
StorageLoader 2U LTO	SCSI	HP	Ultrium 448 LTO2	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^2-SCSI	✓	✓	✓	
StorageLoader 2U LTO	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^3-SCSI	✓	✓	✓	
StorageLoader 2U LTO	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	EXABYTE^MAGNUM^224 IBM^ULT3580-TD3	✓	✓	✓	
StorageLoader 2U LTO	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD4	✓	✓	✓	
StorageLoader LTO	Fibre Channel	HP	Ultrium 3000 LTO5	Fibre Channel	TANDBERGStorageLoader HP^Ultrium^5-SCSI	✓	✓	✓	✓
StorageLoader LTO	SAS	HP	Ultrium 1760 LTO4	SAS	TANDBERGStorageLoader HP^Ultrium^4-SCSI	✓	✓		
StorageLoader LTO	SAS	HP	Ultrium 3000 LTO5	SAS	TANDBERGStorageLoader HP^Ultrium^5-SCSI	✓	✓		
StorageLoader LTO [1]	SAS	HP	Ultrium 6250 LTO6	SAS	TANDBERGStorageLoader HP^Ultrium^6-SCSI	✓	✓		
StorageLoader LTO	SAS	IBM	Ultrium 4 Half Height	SAS	TANDBERGStorageLoader IBM^ULTRIUM-HH4	✓	✓		
StorageLoader LTO	SCSI	HP	Ultrium 920 LTO3	SCSI	TANDBERGStorageLoader HP^Ultrium^3-SCSI	✓	✓	✓	✓
StorageLoader LTO	SCSI	HP	Ultrium 1760 LTO4	SCSI	TANDBERGStorageLoader HP^Ultrium^4-SCSI	✓	✓	✓	

1. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>

# Tape Library Families

When a hardware family of devices is listed, refer to this section for a definition of family members. Generally speaking, the family name and members are defined by the hardware manufacturer, and share common operational traits. In some cases, a specific member of the family may not be supported in the same fashion as the other members. When this occurs, a footnote in the hardware category section will identify this limitation.

## Dell

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	PowerVault ML6000 Series	Fibre Channel	PowerVault ML6010, PowerVault ML6020, PowerVault ML6030
<a href="#">Backtrack</a>	PowerVault ML6000 Series	SAS	PowerVault ML6010, PowerVault ML6020, PowerVault ML6030
<a href="#">Backtrack</a>	PowerVault ML6000 Series	SCSI	PowerVault ML6010, PowerVault ML6020, PowerVault ML6030
<a href="#">Backtrack</a>	PowerVault TL2000/TL4000 series	Fibre Channel	PowerVault TL2000, PowerVault TL4000
<a href="#">Backtrack</a>	PowerVault TL2000/TL4000 series	SAS	PowerVault TL2000, PowerVault TL4000
<a href="#">Backtrack</a>	PowerVault TL2000/TL4000 series	SCSI	PowerVault TL2000, PowerVault TL4000

## Fujitsu

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	ETERNUS LT20/40/60 S2	Fibre Channel	ETERNUS LT20 S2, ETERNUS LT40 S2, ETERNUS LT60 S2
<a href="#">Backtrack</a>	ETERNUS LT20/40/60 S2	SAS	ETERNUS LT20 S2, ETERNUS LT40 S2, ETERNUS LT60 S2



## HP

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	EML E-Series	Fibre Channel	EML E-Series 71e, EML E-Series 103e, EML E-Series 245e, EML E-Series 348e, EML E-Series 375e, EML E-Series 442e, EML E-Series 469e, EML E-Series 505e
<a href="#">Backtrack</a>	ESL E-Series	Fibre Channel	ESL E-Series 286e, ESL E-Series 322e, ESL E-Series 630e, ESL E-Series 712e
<a href="#">Backtrack</a>	ESL E-Series	SCSI	ESL E-Series 286e, ESL E-Series 322e, ESL E-Series 630e, ESL E-Series 712e
<a href="#">Backtrack</a>	MSL2024/4048/8048/8096 (G3 series)	Fibre Channel	MSL2024, MSL4048, MSL8048, MSL8096
<a href="#">Backtrack</a>	MSL2024/4048/8048/8096 (G3 series)	SAS	MSL2024, MSL4048, MSL8048, MSL8096
<a href="#">Backtrack</a>	MSL2024/4048/8048/8096 (G3 series)	SCSI	MSL2024, MSL4048, MSL8048, MSL8096
<a href="#">Backtrack</a>	MSL6000 Series	SCSI	MSL6030L2, MSL6060L2

## IBM

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	System Storage TS3100/TS3200 (Machine Type 3573)	Fibre Channel	System Storage TS3100 (Machine Type 3573), System Storage TS3200 (Machine Type 3573)
<a href="#">Backtrack</a>	System Storage TS3100/TS3200 (Machine Type 3573)	SAS	System Storage TS3100 (Machine Type 3573), System Storage TS3200 (Machine Type 3573)
<a href="#">Backtrack</a>	System Storage TS3100/TS3200 (Machine Type 3573)	SCSI	System Storage TS3100 (Machine Type 3573), System Storage TS3200 (Machine Type 3573)

## NEC

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	T30A/T60A	Fibre Channel	T30A, T60A
<a href="#">Backtrack</a>	T30A/T60A	SAS	T30A, T60A

## Overland Storage

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	ARCvault series	Fibre Channel	ARCvault 24, ARCvault 48
<a href="#">Backtrack</a>	ARCvault series	SAS	ARCvault 12, ARCvault 24, ARCvault 48
<a href="#">Backtrack</a>	ARCvault series	SCSI	ARCvault 12, ARCvault 24, ARCvault 48
<a href="#">Backtrack</a>	NEO E-Series	Fibre Channel	NEO 2000e, NEO 4000e, NEO 8000e
<a href="#">Backtrack</a>	NEO E-Series	SAS	NEO 2000e, NEO 4000e, NEO 8000e
<a href="#">Backtrack</a>	NEO E-Series	SCSI	NEO 2000e, NEO 4000e, NEO 8000e
<a href="#">Backtrack</a>	NEO S-series 2nd Generation	Fibre Channel	NEO 200s 2nd Generation, NEO 400s 2nd Generation
<a href="#">Backtrack</a>	NEO S-series 2nd Generation	SAS	NEO 200s 2nd Generation, NEO 400s 2nd Generation
<a href="#">Backtrack</a>	NEO series	Fibre Channel	NEO 2000, NEO 4000, NEO 8000
<a href="#">Backtrack</a>	NEO series	SCSI	NEO 2000, NEO 4000, NEO 8000
<a href="#">Backtrack</a>	NEOs series	Fibre Channel	NEO 200s, NEO 400s
<a href="#">Backtrack</a>	NEOs series	SAS	NEO 200s, NEO 400s
<a href="#">Backtrack</a>	NEOs series	SCSI	NEO 200s, NEO 400s

## Qualstar

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	RLS-4000 AIT series	SCSI	RLS-4221, RLS-4445, RLS-4470
<a href="#">Backtrack</a>	RLS-5000 SAIT series	SCSI	RLS-5244
<a href="#">Backtrack</a>	RLS-6000 (S)DLT series	SCSI	RLS-6227
<a href="#">Backtrack</a>	RLS-8000 LTO series	Fibre Channel	RLS-8204, RLS-8236, RLS-8244
<a href="#">Backtrack</a>	RLS-8000 LTO series	SAS	RLS-8204, RLS-8236, RLS-8244
<a href="#">Backtrack</a>	RLS-8000 LTO series	SCSI	RLS-8204, RLS-8236, RLS-8244
<a href="#">Backtrack</a>	RLS-8000D LTO series	Fibre Channel	RLS-8204D, RLS-8236D, RLS-8244D

## Qualstar

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	RLS-8000D LTO series	SAS	RLS-8204D, RLS-8236D, RLS-8244D
<a href="#">Backtrack</a>	RLS-8500 LTO series	Fibre Channel	RLS-8350, RLS-8560, RLS-85120
<a href="#">Backtrack</a>	RLS-8500 LTO series	SAS	RLS-8350, RLS-8560, RLS-85120
<a href="#">Backtrack</a>	TLS-4000 AIT series	SCSI	TLS-4210, TLS-4212, TLS-4222, TLS-4440, TLS-4480, TLS-46120, TLS-412180, TLS-412360
<a href="#">Backtrack</a>	TLS-5000 SAIT series	Fibre Channel	TLS-5433, TLS-5466, TLS-58132, TLS-58264
<a href="#">Backtrack</a>	TLS-5000 SAIT series	SCSI	TLS-5433, TLS-5466, TLS-58132, TLS-58264
<a href="#">Backtrack</a>	TLS-6000 DLT series	SCSI	TLS-6210, TLS-6220, TLS-6430, TLS-6460, TLS-68120, TLS-68240
<a href="#">Backtrack</a>	TLS-8000 LTO series	Fibre Channel	TLS-8211, TLS-8222, TLS-8433, TLS-8466, TLS-88132, TLS-88264
<a href="#">Backtrack</a>	TLS-8000 LTO series	SAS	TLS-8211, TLS-8222, TLS-8433, TLS-8466, TLS-88132, TLS-88264
<a href="#">Backtrack</a>	TLS-8000 LTO series	SCSI	TLS-8211, TLS-8222, TLS-8433, TLS-8466, TLS-88132, TLS-88264
<a href="#">Backtrack</a>	XLS series	Fibre Channel	XLS-802500, XLS-810160, XLS-810240, XLS-812300, XLS-832700, XLS-8161100

## Quantum

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	PX500 Series	Fibre Channel	PX502, PX506, PX510
<a href="#">Backtrack</a>	PX500 Series	SCSI	PX502, PX506, PX510
<a href="#">Backtrack</a>	Scalar i40/i80 series	Fibre Channel	Scalar i40, Scalar i80
<a href="#">Backtrack</a>	Scalar i40/i80 series	SAS	Scalar i40, Scalar i80

## Sony

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	PetaSite Series	Fibre Channel	CSM60 PetaSite, CSM100 PetaSite, CSM200 PetaSite
<a href="#">Backtrack</a>	PetaSite Series	SCSI	CSM60B PetaSite, CSM100B PetaSite, CSM200B PetaSite

## Spectra Logic

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	K-Series	Fibre Channel	Spectra 12K, Spectra 20K, Spectra 64K
<a href="#">Backtrack</a>	K-Series	SCSI	Spectra 12K, Spectra 20K, Spectra 64K
<a href="#">Backtrack</a>	T-series	Fibre Channel	Spectra T50, Spectra T50e, Spectra T120, Spectra T200, Spectra T380, Spectra T680, Spectra T950
<a href="#">Backtrack</a>	T-series	SAS	Spectra T50e, Spectra T120
<a href="#">Backtrack</a>	T-series	SCSI	Spectra T50, Spectra T50e, Spectra T120, Spectra T200, Spectra T380, Spectra T680, Spectra T950

## Tandberg

Backtrack	Family	Interface	Family Members
<a href="#">Backtrack</a>	StorageLibrary T40+/T80+/T120+/T160+ series	Fibre Channel	StorageLibrary T40+, StorageLibrary T80+, StorageLibrary T120+, StorageLibrary T160+
<a href="#">Backtrack</a>	StorageLibrary T40+/T80+/T120+/T160+ series	SAS	StorageLibrary T40+, StorageLibrary T80+, StorageLibrary T120+, StorageLibrary T160+
<a href="#">Backtrack</a>	StorageLibrary T40+/T80+/T120+/T160+ series	SCSI	StorageLibrary T40+, StorageLibrary T80+, StorageLibrary T120+, StorageLibrary T160+

# NDMP Platforms

The NDMP platform support information is listed below. This information is organized by vendor manufacturer/model(s), minimum software required, method of connection, and any other important notes or information relevant to the hardware and its compatibility.

The storage devices supported by the NDMP option are included with the Tape Library / Virtual Tape Library sections. In these sections, search by storage device vendor, then model, then look for a check [✓] in the NDMP column for support. Please note that the presence of a check means that **Symantec will support the storage device and NDMP combination IF and ONLY IF the NDMP vendor also supports the library / drive combination**. Please refer to the NDMP vendors' documentation for storage device support and possible limitations. If known, these compatibility lists are listed in the notes section by vendor.

Please Note:

1. The tape library drivers are supplied by Symantec with Backup Exec 2012.
2. The tape drive drivers are supplied by the NDMP platform vendor when using Direct-attach or Remote NDMP Connection methods.
3. NDMP only supports libraries (real or virtual). Stand-alone tape drives are not supported when using Direct-attach or Remote NDMP Connection methods.
4. Validate that firewalls allow NDMP traffic.
5. LTO6 support is very new. Please verify LTO6 support with your NDMP platform provider.

## NDMP Option minimum requirements:

1. NDMP v4 is required.
2. The NDMP server has the Network Data Management Protocol enabled.

The following table describes the supported NDMP connection methods. Symantec supports these connection methods, provided the NDMP platform vendor does as well.

## NDMP Connection Methods

Connection Method	Description
Direct-attach	Data travels from disk to a tape device on the same NDMP host, or from disk to tape device on a SAN. Backup data is NOT sent over local network. The tape device is connected directly to the NAS device via SCSI or Fibre Channel.
Remote	Data travels from the NDMP host, across the local network to a Backup Exec server, to a tape or disk device connected to the Backup Exec server. Any supported tape or disk device can be used with this method. A checkmark is NOT needed in the NDMP column since the tape or disk device is not directly connected to the NAS.
3-way	Data travels from disk on an NDMP host to a tape device on another NDMP host of the same vendor. Backup data is sent over the local network. The tape device must have a checkmark in the NDMP column.

## Dell

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
Compellent FS8600	FluidFS 2.0	Remote	✓	✓	
Compellent FS8600	FluidFS 3.0	Remote	✓	✓	
EqualLogic FS7500	Scalable File System 1.0	Remote	✓	✓	
EqualLogic FS7500	FluidFS 2.0	Remote	✓	✓	
EqualLogic FS7500	FluidFS 3.0	Remote	✓	✓	
EqualLogic FS7600	FluidFS 2.0	Remote	✓	✓	
EqualLogic FS7600	FluidFS 3.0	Remote	✓	✓	
EqualLogic FS7610	FluidFS 2.0	Remote	✓	✓	
EqualLogic FS7610	FluidFS 3.0	Remote	✓	✓	
PowerVault NX3500	Scalable File System 1.0	Remote	✓	✓	
PowerVault NX3500	FluidFS 2.0	Remote	✓	✓	
PowerVault NX3500	FluidFS 3.0	Remote	✓	✓	
PowerVault NX3600	FluidFS 2.0	Remote	✓	✓	
PowerVault NX3600	FluidFS 3.0	Remote	✓	✓	
PowerVault NX3610	FluidFS 2.0	Remote	✓	✓	
PowerVault NX3610	FluidFS 3.0	Remote	✓	✓	

## EMC

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
Celerra series ( <a href="#">members</a> ) [1] [2] [3]	DART 5.5.25.2	Direct Attach, Remote, 3-way	✓	✓	✓
Celerra series ( <a href="#">members</a> ) [2]	DART 5.6	Direct Attach, Remote, 3-way	✓	✓	✓
Celerra series ( <a href="#">members</a> ) [2]	DART 6.0	Direct Attach, Remote, 3-way	✓	✓	✓
VNX2 series ( <a href="#">members</a> ) [2] [4]	VNX File 8.1	Direct Attach, Remote, 3-way	✓	✓	✓

## EMC

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
VNXe series ( <a href="#">members</a> ) [2] [5]	VNXe Operating Environment v2.0	Remote, 3-way	✓	✓	✓
VNXe series ( <a href="#">members</a> ) [2] [4] [5]	VNXe Operating Environment v2.4	Remote, 3-way	✓	✓	✓
VNX series ( <a href="#">members</a> ) [2]	VNX File 7.0	Direct Attach, Remote, 3-way	✓	✓	✓
VNX series ( <a href="#">members</a> ) [2] [6]	VNX File 7.1	Direct Attach, Remote, 3-way	✓	✓	✓

1. EMC Celerra with DART 5.5 or later is required.
2. EMC's HCL can be found here: <https://elabnavigator.emc.com> Select "Customers and Partners" and then select PDFs and Guides and open Celerra .pdf
3. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
4. Required driver support can be found in "DDI 2012 20140320 MP3 212772". Use latest DDI available: <http://www.symantec.com/docs/TECH212772>
5. VNXe supports "3-way" with the restriction that VNXe can't support the NDMP Tape Server part of a 3-way operation. 3-way requires a VNX or Celerra data mover as the NDMP Tape Server.
6. Required driver support can be found in "DDI 2012 20121215". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>

## Fujitsu

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
ETERNUS NR series [1]	Data ONTAP v7.0.3	Direct Attach, Remote, 3-way	✓	✓	✓

1. Supported tape drives of this product can be found here: <http://www.netapp.com/us/solutions/a-z/data-protection-devices.html>

## Hitachi

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
NAS Platform, 4000 and 3000 Series ( <a href="#">members</a> ) [1]	NAS OS 11.3	Direct Attach, Remote, 3-way	✓	✓	✓
NAS Platform F1000 (HNAS F1000) ( <a href="#">members</a> ) [1] [2] [3]	FOS 4.1	Remote	✓	✓	
Virtual File Platform (VFP) ( <a href="#">members</a> ) [1] [2] [3]	FOS 4.1	Remote	✓	✓	

1. Required driver support can be found in "DDI 2012 20131118 MP2 211740". Use latest DDI available: <http://www.symantec.com/docs/TECH211740>
2. FOS 4.1.1-00 or later version is required.
3. The restore from the incremental backup set fails if the backup set has no backup data.

## IBM

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
Scale Out Network Attached Storage (SONAS) [1]	IBM OS 1.4	Remote	✓	✓	
Storwize series ( <a href="#">members</a> ) [1]	IBM OS 1.4	Remote	✓	✓	
System Storage N series ( <a href="#">members</a> ) [2] [3]	Data ONTAP 7.2.3	Direct Attach, Remote, 3-way	✓	✓	✓
System Storage N series ( <a href="#">members</a> ) [2]	Data ONTAP 7.3.6	Direct Attach, Remote, 3-way	✓	✓	✓
System Storage N series ( <a href="#">members</a> ) [2]	Data ONTAP v8.0 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
System Storage N series ( <a href="#">members</a> ) [2]	Data ONTAP v8.0 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
System Storage N series ( <a href="#">members</a> ) [2]	Data ONTAP v8.1 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
System Storage N series ( <a href="#">members</a> ) [2]	Data ONTAP v8.1 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓

1. Required driver support can be found in "DDI 2012 20130725 MP1 208600". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>



2. IBM System Storage N series tape support: <<http://www-03.ibm.com/systems/storage/network/interophome.html>>
3. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>

## Imation

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
Nexsan NST5000 series ( <a href="#">members</a> ) [1]	NestOS 2.2	Remote	✓	✓	

1. Required driver support can be found in "DDI 2012 20131118 MP2 211740". Use latest DDI available: <<http://www.symantec.com/docs/TECH211740>>

## Isilon

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
IQ Storage [1]	OneFS 5.5.7.9	Direct Attach, Remote, 3-way			✓
IQ Storage [2]	OneFS 6.5.1.8	Direct Attach, Remote, 3-way	✓	✓	✓
IQ Storage [3] [4]	OneFS 7.0	Direct Attach, Remote, 3-way	✓	✓	✓
IQ Storage [4] [5]	OneFS 7.1	Direct Attach, Remote, 3-way	✓	✓	✓

1. Direct Access Recovery (DAR) and Directory Direct Access Recovery (DDAR) are currently not supported with this device/software combination.
2. OneFS versions 6.5.x are supported.
3. OneFS versions 7.0.x are supported.
4. Required driver support can be found in "DDI 2012 20121215". Use latest DDI available: <<http://www.symantec.com/docs/TECH208600>>
5. OneFS versions 7.1.x are supported.

## LSI Logic

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
Cougar 3000/6000 Series NAS Gateway	EverON 4.0.4.6	Direct Attach, Remote, 3-way	✓	✓	✓

## NetApp

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
FAS Series (members) [1] [2]	Data ONTAP v7.0.3	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v7.2.3	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v7.3.1	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v7.3.6	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.0 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.0 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.1 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.1 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.2 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.2 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.3 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.3 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.4 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1]	Data ONTAP v8.1.4 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1] [3] [4]	Data ONTAP v8.2 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1] [3] [4] [5]	Data ONTAP v8.2 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
FAS Series (members) [1] [3] [4]	Data ONTAP v8.2.1 (7-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓

## NetApp

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
FAS Series ( <a href="#">members</a> ) [1] [3] [4] [5]	Data ONTAP v8.2.1 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓
GX series [1]	Data ONTAP v8.0 (Cluster-Mode)	Direct Attach, Remote, 3-way	✓	✓	✓

1. NetApp's HCL can be found here: <http://www.netapp.com/us/solutions/a-z/data-protection-devices.html>
2. Required driver support can be found in "DDI 2012 20120615". Use latest DDI available: <http://www.symantec.com/docs/TECH208600>
3. Browsing of volumes (Backup Selections) is not available. Please use the Include/Exclude feature to configure the backup selections.
4. See this technote for limits when using tape libraries attached to the NetApp filer. <http://www.symantec.com/docs/TECH212366>
5. NetApp clustered data ONTAP (CDOT) features such as service name virtualization and multi-tenancy (VSERVER) capabilities are not supported. Node-scoped NDMP mode is required to be enabled. More information is available at <https://library.netapp.com/ecmdocs/ECMP1368707/html/GUID-21B82CCB-97F1-4FA6-BB22-095E97979110.html>

## Oracle

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
ZFS Storage Appliance series ( <a href="#">members</a> ) [1]	Oracle OS 2010.08.17	Direct Attach, Remote, 3-way	✓	✓	✓

1. Support for clustering of the Oracle Sun NDMP devices was not specifically tested, though may work. Contact Oracle for usage of this environment.

## Symantec

Device	Software Tested	Connection Method	Direct Access Restore	Directory Direct Access Restore	ESO
FileStore	FileStore 5.6	Remote	✓	✓	
FileStore	FileStore 5.7	Remote	✓	✓	

# NDMP Families

## EMC

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	Celerra series	Celerra NS40, Celerra NS120, Celerra NS700
<a href="#">Backtrack</a>	VNX2 series	VNX5200, VNX5400, VNX5600, VNX5800, VNX7600, VNX8000
<a href="#">Backtrack</a>	VNXe series	VNXe3100, VNXe3150, VNXe3300
<a href="#">Backtrack</a>	VNX series	VNX 5100, VNX 5300, VNX 5500, VNX 5700, VNX 7500

## Hitachi

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	NAS Platform, 4000 and 3000 Series	HNAS 3080 (M1), HNAS 3090 (M2), HNAS 4040, HNAS 4060, HNAS 4080, HNAS 4100
<a href="#">Backtrack</a>	NAS Platform F1000 (HNAS F1000)	HNAS F1140
<a href="#">Backtrack</a>	Virtual File Platform (VFP)	VFP 50, VFP 70, VFP 80, VFP 100N, VFP 110, VFP 200N, VFP 300N, VFP 500N, VFP 600N, VFP 2010, VFP 2100, VFP 2300

## IBM

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	Storwize series	SANVC(2145), Storwize V3500, Storwize V3700, Storwize V5000, Storwize V7000, Storwize V7000 Unified
<a href="#">Backtrack</a>	System Storage N series	N3150, N3220, N3240, N3300, N3400, N3600, N3700, N5200, N5300, N5500, N5600, N6040, N6060, N6070, N6210, N6220, N6240, N6250, N6270, N7550T, N7600, N7700, N7750T, N7800, N7900, N7950T

## Imation

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	Nexsan NST5000 series	Nexsan NST5100, Nexsan NST5300, Nexsan NST5500

## NetApp

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	FAS Series	All 'FAS' Models.

## Oracle

Backtrack	Family	Family Members
<a href="#">Backtrack</a>	ZFS Storage Appliance series	Oracle ZFS Storage 7110, Oracle ZFS Storage 7120, Oracle ZFS Storage 7210, Oracle ZFS Storage 7310, Oracle ZFS Storage 7320, Oracle ZFS Storage 7410, Oracle ZFS Storage 7420, ZFS Storage ZS3-2, ZFS Storage ZS3-4

# NAS Sources

NAS Source support information is listed below. This information is organized by vendor manufacturer/model(s), minimum software required, and any other important notes or information relevant to the hardware and its compatibility.

NAS devices listed in this sections have been tested with Backup Exec as a result of formal joint business agreements and OEM relationships.

Hardware is selected and prioritized for certification based on market research and input from the field, including customer feedback. If a customer would like to have their hardware considered for inclusion on this HCL, simply submit the request via an email [<Backup\\_Exec\\_HCL@symantec.com>](mailto:Backup_Exec_HCL@symantec.com) . Requests will be reviewed by the appropriate Symantec Product Management team members for possible certification, with final decisions based on the overall fit with the product, target market, and frequency of request.

## Overland Storage

Family	Family Members	Software Tested	Tape Support	Notes
SnapServer DX	SnapServer DX1, SnapServer DX2	GOS 7.2.126	SAS	Client Side Dedup is not supported.  Snapshots are not supported on the file system.  Overland Storage support link for agent installation instructions. <a href="http://support.overlandstorage.com/jive/servlet/KbServlet/download/10414-102-3212/10400441-001.pdf">&lt;http://support.overlandstorage.com/jive/servlet/KbServlet/download/10414-102-3212/10400441-001.pdf&gt;</a>

# SAN Infrastructure components

The SAN infrastructure components section of the HCL is split into three sections - traditional fibre channel infrastructure components, FCoE infrastructure, and iSCSI "solutions". The fibre channel and FCoE sections list possible components to be used interchangeably, whereas the iSCSI section lists SAN components to be used as a solution; a complete set of hardware from hardware or software initiator, through interconnect (if any), to storage device.

**Fibre channel SANs:** To verify support for tape libraries, or virtual tape libraries (VTL), refer to the column labelled "ESO" in the respective "Tape Libraries with Drives" or "Virtual Tape Libraries with Drives" sections.

Libraries or drives with an interface column of "SCSI" require an interface card or bridge to establish a connection to an FC switch. Please see the content below for supported devices.

## Fibre Channel Infrastructure

This list of supported fibre-channel storage area network (SAN) components represents what has been tested in Symantec labs, or in Symantec-supervised partner labs. All the devices in your SAN must be on this supported device list. To ensure compatibility, Symantec, the device manufacturers, and the operating system vendor must support the combination of SAN devices.

To verify support for tape libraries, or virtual tape libraries (VTL), refer to the column labelled "ESO" in the respective "Tape Libraries with Drives" or "Virtual Tape Libraries with Drives" sections.

## HBAs

Note: The OS and Version information indicate the tested platform. Unless specifically noted all other OS Versions are supported.

Symantec recommends (where possible), the following to avoid complications in the SAN environment:

1. Avoid mixing HBAs from different vendors.
2. All HBAs should use the same firmware, BIOS and driver revision.
3. Consult the hardware vendor's web site for up-to-date firmware and driver updates.
4. Where support is shown for Windows Server 2003 or Windows Server 2008, please reference the Software Compatibility List ( <http://entsupport.symantec.com/umi/V-269-1> ) for supported operating system versions.

## ATTO

Device	Bus Type	Windows
FC-41XS	PCI-X	Windows Server 2003
FC-44ES	PCIe	Windows Server 2003

## Brocade

Device	Bus Type	Windows
415	PCIe	Windows Server 2003
425	PCIe	Windows Server 2003, Windows Server 2008
815	PCIe	Windows Server 2003, Windows Server 2008
825	PCIe	Windows Server 2003
1860 (FC)	PCIe	Windows Server 2003, Windows Server 2008

## Emulex

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
LP10xxx / 105x series (Thor ASIC) <a href="#">[1]</a>	PCI-X, PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
LP1100x / 1150 series (Helios ASIC)	PCI-X	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
LPe11xxx / 115x series (Zephyr ASIC)	PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10, 11	4.0 (ES), 5.0 (Advanced), 5.0 (base)



## Emulex

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
LPe12xxx / 125x series (Saturn ASIC)	PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
LPe16002-M6	PCIe	Windows Server 2008			
LPe16002B-M6	PCIe	Windows Server 2008			

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## Hitachi

Device	Bus Type	Windows
HFC040x series	PCI-X, PCIe, mezzanine	Windows Server 2003
HFCE080x series	PCIe, mezzanine	Windows Server 2003, Windows Server 2008

## HP

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
81B	PCIe	Windows Server 2008			
81E	PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
81Q	PCIe	Windows Server 2008			
82B	PCIe	Windows Server 2008			
82E	PCIe	Windows Server 2008			
82Q	PCIe	Windows Server 2008			

## HP

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
A7388A	PCI-X	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
AJ764A	PCIe	Windows Server 2003, Windows Server 2008		9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FC1142SR	PCIe	Windows Server 2003, Windows Server 2008		9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FC1143	PCI-X	Windows Server 2003, Windows Server 2008		9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FC2142SR	PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FC2143	PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
QMH2462-HP-BK	PCIe	Windows Server 2008			

## LSI Logic

Device	Bus Type	Windows
LSI7102XP-LC	PCI-X	Windows Server 2003
LSI7104XP-LC	PCI-X	Windows Server 2003
LSI7202XP-LC	PCI-X	Windows Server 2008
LSI7204XP-LC	PCI-X	Windows Server 2003
LSI44929	PCI	Windows Server 2003

## QLogic

Device	Bus Type	Windows	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
Fabric Cache 10000 Series	PCI-e	Windows Server 2008		
QLA2x0 series [1]	PCI-X	Windows Server 2003	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
QLE220 [1]	PCIe	Windows Server 2008		
QLE256x series	PCIe	Windows Server 2003, Windows Server 2008	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
QLE2600 series (FC)	PCIe	Windows Server 2008		
QME2572	PCIe	Windows Server 2003, Windows Server 2008		
SANblade 23xx series [2]	PCI, PCI-X, PCIe	Windows Server 2003, Windows Server 2008	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
SANblade 24xx series	PCI-X, PCIe	Windows Server 2003, Windows Server 2008	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .
2. For Windows 2003, the latest driver from QLogic is required.

## Sun

Device	Bus Type	Windows
SG-XPCIE2FC-QF4	PCIe	Windows Server 2008

## Bridges and Routers

Consult the hardware vendor's web site for up-to-date firmware updates.

### ADIC

Device
SNC 4000 (embedded)

### ATTO

Device
FibreBridge 3300

### Crossroads

Device
6000 <a href="#">[1]</a>
6240 Storage Router <a href="#">[1]</a>

1. If hardware encryption is used, then a minimum firmware of 5.8.24 is required.

### Dell

Device
PV-132T (FCR embedded)

### HP

Device
e1200-320 4Gb
e2400-160 FC Interface Controller
e2400-FC 2Gb Interface Controller
e2400-FC 4Gb Interface Controller

### Overland Storage

Device
Fibre Channel Option (FCO)
NEO VIA FCO

## Qualstar

Device
FS1310B embedded router
VFS113 embedded router
VFS212 embedded router

## Quantum

Device
FC1202
FC470

## Spectra Logic

Device
F-QIP

## StorageTek

Device
Direct FC Attach (L180/L700)
L1400 Interface Control Module

## Switches

1. Avoid mixing switches/hubs from different vendors, unless specifically supported by the switch/hub vendors.
2. Consult the hardware vendor's web site for up-to-date firmware updates.

## Brocade

Device
300
5100
SilkWorm 12000
SilkWorm 200E
SilkWorm 2010
SilkWorm 2050
SilkWorm 220E
SilkWorm 240E
SilkWorm 3200
SilkWorm 3250
SilkWorm 3800
SilkWorm 3850
SilkWorm 3900
SilkWorm 4100

## Brocade

Device
SilkWorm 5100
SilkWorm 6505

## IBM

Device
2109 F32

## Cisco Systems

Device
MDS9216

## McDATA

Device
ED-5000
ES-3016
Sphereon 4500

## HP

Device
4Gb Virtual Connect Fibre Channel Module for c- Class Bla
SAN Switch 4/16
SAN Switch 4/32
SAN Switch 4/64
SAN Switch 4/8
SAN Switch 8/24
SAN Switch 8/40
SAN Switch 8/8

## QLogic

Device
SANbox 1400 <a href="#">[1]</a>
SANbox 3602
SANbox 3810
SANbox 5200 <a href="#">[1]</a>
SANbox 5600
SANbox 5602
SANbox 5800
SANbox 5802
SANbox 9000
SANbox 9008V
SANbox-8 <a href="#">[1]</a>

## QLogic

Device
SANbox2 Series 2Gb <a href="#">[1]</a>
SANbox2-16 <a href="#">[1]</a>
SANbox2-8 <a href="#">[1]</a>

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .



# FCoE Infrastructure

This list of supported Fibre Channel over Ethernet (FCoE) storage area network (SAN) components represents what has been tested in Symantec labs, or in Symantec-supervised partner labs. All the devices in your SAN must be on this supported device list. To ensure compatibility, Symantec, the device manufacturers, and the operating system vendor must support the combination of SAN devices.

To verify support for tape libraries, or virtual tape libraries (VTL), refer to the column labelled "ESO" in the respective "Tape Libraries with Drives" or "Virtual Tape Libraries with Drives" sections.

## CNAs

### Please Note:

1. All like CNAs within a SAN should use the same firmware, BIOS and driver revision as recommended by CNA vendors.
2. Consult the hardware vendor's web site for current firmware and driver updates (where applicable).
3. Running a server's Ethernet and Fibre Channel over Ethernet (FCoE) traffic on the same CNA port is not supported.
4. Where support is shown for Windows Server 2003 or Windows Server 2008, please reference the Software Compatibility List ( [\\_http://entsupport.symantec.com/umi/V-269-1](http://entsupport.symantec.com/umi/V-269-1) ) for supported operating system versions.

## Brocade

Device	Bus Type	Windows
1860 (FCoE)	PCIe	Windows Server 2008 R2

## Emulex

Device	Bus Type	Windows
OCe11102-FM	PCIe	Windows Server 2008 R2
OneConnect OCe14000 series	PCIe	Windows Server 2008 R2

## HP

Device	Bus Type	Windows	(Red Hat) Enterprise Linux
CN1000Q	PCIe	Windows Server 2008 R2	5.0 (base)
CN1100E	PCIe	Windows Server 2003, Windows Server 2008 R2	5.0 (base)
NC553i	PCIe	Windows Server 2008 R2	5.0 (base)

## QLogic

Device	Bus Type	Windows
QLE8142 [1]	PCIe	Windows Server 2008
QLE8152 [1]	PCIe	Windows Server 2003
QLE8242	PCIe	Windows Server 2008 R2
QLE8300 series (FCoE)	PCIe	Windows Server 2008 R2

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

# Bridges and Routers

## Cisco Systems

Device
N5K-1008

## Switches

## Cisco Systems

Device
Nexus 5010

## HP

Device
2408 FCoE CN Switch

# iSCSI Solutions

This list of tested iSCSI components represents what has been tested in Symantec labs, or in Symantec-supervised partner labs. The listed components in each row should be used together to ensure compatibility.

## Please Note:

1. Each column within the configuration tables represents the key components that were tested in an iSCSI SAN with the Backup Exec Shared Storage Option.
2. To ensure compatibility, Symantec, the device manufacturers, and the operating system vendor must support the combination of iSCSI devices.
3. Configurations that use the Microsoft iSCSI initiator aren't supported with the Intelligent Disaster Recovery option.
4. The firmware and driver versions listed are minimum recommended levels. For device support and firmware/driver updates, please contact your hardware vendor.
5. Where possible, avoid mixing of vendor HBAs. All like HBAs within your SAN should use the same firmware, BIOS and driver revision.
6. In some cases, tape libraries with mixed media drive types were tested. Either drive type may be used.
7. The "ULTRIUM-TD" and the "ULT3580-TD" inquiry strings are interchangeable (both are supported), unless otherwise indicated. The "ULTRIUM-HH" and the "ULT3580-HH" inquiry strings are interchangeable (both are supported), unless otherwise indicated.

## actidata

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
actidata actiDisk vTanis RDX ~ N/A ~ BDT~~~~RDStor_T [1]	HP Ultrium 1840 LTO4 ~ N/A ~ HP~~~~Ultrium^4-SCSI	Microsoft iSCSI Software Initiator ~ msiscsi.sys 6.0.6001.18000 - N/A	actidata Direct iSCSI Device ~ N/A

1. To Import, insert the RDX media into the slot(s) and select Scan from Backup Exec. Due to the physical design of the vTanis, regular import jobs will result in error messages in the import job log.

## BDT

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
BDT RDStor ~ R1.03 ~ BDT~~~~RDStor_T [1]	HP Ultrium 1840 LTO4 ~ N/A ~ HP~~~~Ultrium^4-SCSI	Microsoft iSCSI Software Initiator ~ msiscsi.sys 6.0.6001.18000 - N/A	BDT Direct iSCSI Device ~ N/A

1. To Import, insert the RDX media into the slot(s) and select Scan from Backup Exec. Due to the physical differences between the RDstor and a tape library, regular import jobs will result in error messages in the import job log.

## Dell

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Dell PowerVault TL2000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2230 Ultrium 3 Half Height ~ 73P9 ~ IBM~~~~ULT3580-HH3	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL2000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2250 Ultrium 5 Half Height ~ N/A ~ IBM~~~~ULT3580-HH5	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL2000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2340 Ultrium 4 ~ 74H6 ~ IBM~~~~ULT3580-TD4	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL2000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM Ultrium 4 Half Height ~ 89B1 ~ IBM~~~~ULTRIUM-HH4	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL4000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2230 Ultrium 3 Half Height ~ 73P9 ~ IBM~~~~ULT3580-HH3	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL4000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2250 Ultrium 5 Half Height ~ N/A ~ IBM~~~~ULT3580-HH5	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL4000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2340 Ultrium 4 ~ 74H6 ~ IBM~~~~ULT3580-TD4	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL4000 ~ 6.60 ~ IBM~~~~3573-TL [1]	IBM Ultrium 4 Half Height ~ 89B1 ~ IBM~~~~ULTRIUM-HH4	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - 1.5	Dell TL24iSCSIxSAS ~ v1.00.02
Dell PowerVault TL4000 ~ A.50 ~ IBM~~~~3573-TL	IBM System Storage TS2240 Ultrium 4 Half Height ~ B171 ~ IBM~~~~ULT3580-HH4	Microsoft iSCSI Software Initiator ~ N/A 6.1.7600.16385 - N/A	Dell TL24iSCSIxSAS ~ v1.00.05
Dell PowerVault TL4000 ~ A.50 ~ IBM~~~~3573-TL [1]	IBM System Storage TS2250 Ultrium 5 Half Height ~ B171 ~ IBM~~~~ULT3580-HH5	Microsoft iSCSI Software Initiator ~ N/A 6.1.7600.16385 - N/A	Dell TL24iSCSIxSAS ~ v1.00.05

1. See the referenced document for more details. ( <http://www.symantec.com/docs/TECH65411> )

# HP

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
HP D2D100 Series Backup System ~ kn6C-001.231 ~ HP^D2DBS [1] [2]	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.1748 - 2.03	HP Direct iSCSI Device ~ N/A
HP D2D100 Series Backup System ~ kn77 ~ HP^D2DBS [1] [2]	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.1748 - 2.03	HP Direct iSCSI Device ~ N/A
HP D2D100 Series Backup System ~ kn7b ~ HP^D2DBS [1] [2]	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.1748 - 2.03	HP Direct iSCSI Device ~ N/A
HP D2D2500 Series Backup System ~ pf86 ~ HP^D2DBS [1] [3]	HP Ultrium 1840 LTO4 ~ N/A ~ HP^Ultrium^4-SCSI	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - N/A	HP Direct iSCSI Device ~ N/A
HP D2D4000 Series Backup System ~ pf86 ~ HP^D2DBS [1] [3]	HP Ultrium 1840 LTO4 ~ N/A ~ HP^Ultrium^4-SCSI	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3640 - N/A	HP Direct iSCSI Device ~ N/A
HP VLS 1000i ~ 2.6.0.226 ~ HP^VLS1000i [1] [4]	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	QLogic QLA4052C ~ N/A 2.1.2.0 - 2.0.0.7	HP Direct iSCSI Device ~ N/A
HP VLS 1000i ~ 2.6.0.228 ~ HP^VLS1000i [1] [4]	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	QLogic QLA4052C ~ ql40xx.sys 2.1.3.26 - 2.0.0.7	HP Direct iSCSI Device ~ N/A

1. Each VTL may only be assigned to a single server (no sharing), but the physical library may be connected to multiple servers.
2. Minimum VTL software version kn7b is required to support automated robotic import/export functionality.
3. This VTL also supports HP LTO2, LTO3, LTO4, and LTO5 tape drive emulation. These combinations are also supported.
4. Both the "VLS1000i" and "VLS1002i" models are supported. The difference is in the capacity.

## Imation

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Imation RDX A8 ~ R1.04 ~ IMATION^A8^T [1]	HP Ultrium 1840 LTO4 ~ N/A ~ HP^Ultrium^4-SCSI	Microsoft iSCSI Software Initiator ~ msiscsi.sys 6.0.6001.18000 - N/A	Imation Direct iSCSI Device ~ N/A

1. To Import, insert the RDX media into the slot(s) and select Scan from Backup Exec. Due to the physical differences between the A8 and a tape library, regular import jobs will result in error messages in the import job log.

## Overland Storage

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Overland Storage REO 1500 ~ 4.0.2.36 ~ OVERLANDREO^Series	HP Ultrium 460 LTO2 ~ N/A ~ HP^Ultrium^2-SCSI	Microsoft iSCSI Software Initiator ~ msiscsi.sys 5.2.3790.3497 - N/A	Overland Storage Direct iSCSI Device ~ N/A

## Quantum

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Quantum DXi3500/DXi5500 Dxi Series ~ 0400 ~ QUANTUM^DXi	Quantum DLT 7000 ~ N/A ~ QUANTUM^DLT7000	Microsoft iSCSI Software Initiator ~ iscsi.sys 5.2.3790.3099 - 2.03	Quantum Direct iSCSI Device ~ N/A
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	HP Ultrium 460 LTO2 ~ F63Z ~ HP^Ultrium^2-SCSI	QLogic QLA4050C ~ N/A 2.1.2.0 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	HP Ultrium 460 LTO2 ~ F63Z ~ HP^Ultrium^2-SCSI	QLogic QLA4052C ~ N/A 2.1.2.5 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	HP Ultrium 960 LTO3 ~ G36Z ~ HP^Ultrium^3-SCSI	QLogic QLA4050C ~ N/A 2.1.2.0 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	HP Ultrium 960 LTO3 ~ G36Z ~ HP^Ultrium^3-SCSI	QLogic QLA4052C ~ N/A 2.1.2.5 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum DLT-S4 ~ 1414 (V20) ~ QUANTUM^DLT-S4	QLogic QLA4050C ~ N/A 2.1.2.0 - N/A	Quantum TC2201 ~ 6.1.21

# Quantum

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum DLT-S4 ~ 1414 (V20) ~ QUANTUM^DLT-S4	QLogic QLA4052C ~ N/A 2.1.2.5 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	Microsoft iSCSI Software Initiator ~ iscsiprt.sys 5.2.3790.3273 - 2.03	QLogic SANbox 6142 ~ 2.2.1.1c
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	QLogic QLA4050C ~ ql40xx.sys 2.1.3.26 - 2.0.0.45	QLogic SANbox 6142 ~ 2.2.1.1c
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	QLogic QLA4050C ~ N/A 2.1.2.0 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX500 Series ~ 0008 (V08) ~ QUANTUM^PX500	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	QLogic QLA4052C ~ N/A 2.1.2.5 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX720 ~ 1.01 ~ QUANTUM^PX720	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	QLogic QLA4050C ~ N/A 2.1.2.0 - N/A	Quantum TC2201 ~ 6.1.21
Quantum PX720 ~ 1.01 ~ QUANTUM^PX720	Quantum SDLT 600 ~ 2525 (V37) ~ QUANTUM^SDLT600	QLogic QLA4052C ~ N/A 2.1.2.5 - N/A	Quantum TC2201 ~ 6.1.21
Quantum RDX8000 ~ R1.08 ~ QUANTUM^RDX8000_T [1]	Quantum LTO-4 ~ N/A ~ QUANTUM^ULTRIUM^4	Microsoft iSCSI Software Initiator ~ msiscsi.sys 6.0.6001.18000 - N/A	Quantum Direct iSCSI Device ~ N/A
Quantum Scalar i40 ~ 120G ~ QUANTUM^Scalar^i40-i80	HP Ultrium 3000 LTO5 ~ Y23Z ~ HP^Ultrium^5-SCSI	Microsoft iSCSI Software Initiator ~ N/A 6.1.7600.16385 - N/A	Chelsio USR1100-ESAS-FB ~ USR_v2.0.1
Quantum Scalar i500 ~ 586G ~ Quantum^Scalar^i500	HP Ultrium 3280 LTO5 ~ X38Z ~ HP^Ultrium^5-SCSI	Microsoft iSCSI Software Initiator ~ N/A 6.1.7600.16385 - N/A	Chelsio USR1100-ESAS-FB ~ USR_v2.0.1
Quantum Scalar i80 ~ 120G ~ QUANTUM^Scalar^i40-i80	HP Ultrium 3000 LTO5 ~ Y23Z ~ HP^Ultrium^5-SCSI	Microsoft iSCSI Software Initiator ~ N/A 6.1.7600.16385 - N/A	Chelsio USR1100-ESAS-FB ~ USR_v2.0.1

1. To Import, insert the RDX media into the slot(s) and select "Scan" from Backup Exec. Due to the physical design of the RDX8000, regular Backup Exec import jobs will result in error messages in the import job log.



## StorageTek

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
StorageTek SL500 ~ 1048 ~ STK~~~~SL500	IBM TotalStorage 3580 Ultrium 3 ~ 5BG2 ~ IBM~~~~ULT3580-TD3	QLogic QLA4050C ~ ql40xx.sys 2.1.2.5 - 2.0.0.7	QLogic SANbox 6140 ~ 2.0.7.2d
StorageTek SL500 ~ 1048 ~ STK~~~~SL500	IBM TotalStorage 3580 Ultrium 3 ~ 5BG2 ~ IBM~~~~ULT3580-TD3	QLogic QLA4050C ~ ql40xx.sys 2.1.2.5 - 2.0.0.7	QLogic SANbox 6142 ~ 2.1.4.0a

## Tandberg

Library ~ Firmware ~ Inquiry	Drive ~ Firmware ~ Inquiry	HBA ~ Driver ~ Firmware	Interconnect ~ Firmware
Tandberg DPS1100 VTL ~ 0363 ~ TANDBERG DPS1000 [1]	HP Ultrium 960 LTO3 ~ G39W ~ HP~~~~Ultrium^3-SCSI	Microsoft iSCSI Software Initiator ~ e1g60i32.sys 6.0.6002 - N/A	Tandberg Direct iSCSI Device ~ N/A
Tandberg DPS1200 VTL ~ 0363 ~ TANDBERG DPS1000 [1]	HP Ultrium 960 LTO3 ~ G39W ~ HP~~~~Ultrium^3-SCSI	Microsoft iSCSI Software Initiator ~ e1g60i32.sys 6.0.6002 - N/A	Tandberg Direct iSCSI Device ~ N/A
Tandberg RDX QuikStation ~ 0111 ~ TANDBERG QuikStation [2] [3] [4]	HP Ultrium 960 LTO3 ~ D237 ~ HP~~~~Ultrium^3-SCSI	Microsoft iSCSI Software Initiator ~ e1g6030e.sys 6.0.6002 - N/A	Tandberg Direct iSCSI Device ~ N/A
Tandberg RDX QuikStation ~ 0210 ~ TANDBERG QuikStation [2] [3] [4]	HP Ultrium 960 LTO3 ~ D237 ~ HP~~~~Ultrium^3-SCSI	Microsoft iSCSI Software Initiator ~ N/A 6.1.7601.17514 - N/A	Tandberg Direct iSCSI Device ~ N/A

1. Each VTL may only be assigned to a single server (no sharing), but the physical library may be connected to multiple servers.
2. See the referenced document for more details. ( <http://www.symantec.com/docs/TECH155052> )
3. The VTL may only be assigned to a single server (no sharing).
4. This VTL has been validated as a backup device for use with VMware.

# Support End-of-Life

EOL Notice: These devices are no longer officially supported for use with this version of Backup Exec. This is a periodic process to bring Backup Exec support in line with what is still supported by the hardware vendors and/or the device's age, capacity or performance. Please be aware that different vendors may have different EOL policies for their particular model of a common device. See the HCL introduction for further clarification of our policies and goals. No changes were made to Backup Exec to drop support or recognition for these devices, so it is fully expected that they will continue to work with this version of Backup Exec. But if a problem is discovered with the device, it is likely that vendor support, repair parts, and/or firmware fixes are no longer available which limits the ability of our Symantec technical support team to help resolve your issue. Please be aware that Windows 2008 treats some devices (especially ATAPI/IDE/SATA) different than Windows 2003 did, so if you are moving old hardware to a new server, the operating system change may have more of an impact than changing versions of Backup Exec.

OST Note: The OST section contains rows that frequently indicate that support for a plug-in has expired, per the OST vendors request. Please do not assume that support for the entire device is withdrawn. Your OST device and OST plugin version probably just need to be updated.

## End-of-Life Tape Drives

### ACER

Device	Inquiry String	Drive Interface
DAT 72 USB	QUANTUM^DAT^~^DAT72	SATA
DAT 72	QUANTUM^DAT^~^DAT72	SATA
DAT 72	QUANTUM^DAT^~^DAT72	SCSI
LTO-2 HH	CERTANCEULTRIUM^2	SCSI
LTO-3 HH	QUANTUM^ULTRIUM^3	SAS
LTO-3 HH	QUANTUM^ULTRIUM^3	SCSI
LTO-4 HH	QUANTUM^ULTRIUM^4	SAS

## Dell

Device	Inquiry String	Drive Interface
PowerVault 100T DDS4 (Archive)	ARCHIVE^Python	SCSI
PowerVault 100T DDS4 (Seagate)	SEAGATE^DAT	SCSI
PowerVault 100T DDS4 (Sony)	SONY^^^SDT-10000	SCSI
PowerVault 110T DLT1	BNCHMARKDLT1	SCSI
PowerVault 110T LTO (Gen1 HP)	HP^^^^^Ultrium^1-SCSI	SCSI
PowerVault 110T LTO1 (Gen1 SEG)	SEAGATE^ULTRIUM06242	SCSI
PowerVault 110T LTO2-L	TANDBERGTS400	SCSI
PowerVault 110T SDLT220	QUANTUM^SuperDLT1	SCSI
PowerVault 110T VS80	BNCHMARKDLT1	SCSI
PowerVault LTO3-060 (TB)	TANDBERGTS800	SCSI

## Exabyte

Device	Inquiry String	Drive Interface
Magnum Tape Drive (LTO-2)	IBM^^^^ULTRIUM-TD2	SCSI
Magnum Tape Drive (LTO-2)	TANDBERGTS400	SCSI
Magnum Tape Drive (LTO-3)	IBM^^^^ULTRIUM-TD3	SCSI
VXA-2	EXABYTE^VXA-2	SCSI
VXA-3a	EXABYTE^VXA-3a	Firewire
VXA-3a	EXABYTE^VXA-3a	USB 2.0
VXA-172	EXABYTE^VXA-172	SCSI
VXA-320	EXABYTE^VXA-3	SCSI

## Fujitsu

Device	Inquiry String	Drive Interface
Full-High Ultrium 230 LTO1 (PGSLT101)	HP~~~~~Ultrium^1-SCSI	SCSI
PG-DT401 DDS4 DAT	HP~~~~~C5683A	SCSI
PG-DT402 (DDS4) DAT	SEAGATE^DAT~~~DAT72	SCSI
PG-DT402D 9SP40 DDS4 DAT	SEAGATE^DAT~~~9SP40-XXX	SCSI
PG-DT501 (DAT72)	HP~~~~~C7438A	SCSI
PG-DT502/502D	SEAGATE^DAT~~~DAT72-000	SCSI
PG-VX201 (VXA-2)	EXABYTE^VXA-2	SCSI

## HP

Device	Inquiry String	Drive Interface
DAT 40 SCSI	HP~~~~~C5683A	SCSI
DAT 40	HP~~~~~C5683A	USB 2.0
Ultrium 230 LTO1	HP~~~~~Ultrium^1-SCSI	SCSI
Ultrium 232 LTO1	HP~~~~~Ultrium^1-SCSI	SCSI

## IBM

Device	Inquiry String	Drive Interface
100-200 GB LTO Half-High	HP^Ultrium^1-SCSI	SCSI
DDS Gen5 (P/N 43W8480)	IBM^DDS^Gen5	SATA
DDS Gen5 (P/N 71P9145)	IBM^DDS^Gen5	SCSI
DDS Gen6 USB (P/N 39M5636)	IBM^DDS^Gen6	USB 2.0
DLTV4 (P/N 39M5659)	IBM^DLT-V4	SATA
LTO Gen 2 HH 200/400GB (P/N 25R0005 / 39M5658)	IBM^HH^LTO^Gen^2	SCSI
System Storage TS1120 (3592 Model E05)	IBM^03592E05	Fibre Channel
TotalStorage 3592 Model J1A	IBM^03592J1A	Fibre Channel
VS160 DLT1 Half-High	IBM^VS160	SCSI

## Quantum

Device	Inquiry String	Drive Interface
DLT VS80	BNCHMARKDLT1	SCSI
SDLT 220	QUANTUM^SuperDLT1	SCSI

## Seagate

Device	Inquiry String	Drive Interface
9SP40 DDS4 DAT	SEAGATE^DAT^9SP40-XXX	SCSI

## Sony

Device	Inquiry String	Drive Interface
SDT-10000 DDS-4	SONY^SDT-10000	SCSI
SDT-11000 DDS-4 (DRTape)	SONY^SDT-11000	SCSI
SDX-260V AITi50A/S (AIT-E Turbo)	SONY^SDX-260V	IDE/ATAPI
SDX-300C (AIT-1)	SONY^SDX-300C	SCSI
SDX-400C AITi90/S (AIT-1)	SONY^SDX-400C	SCSI
SDX-400V AITi90/S (AIT-1)	SONY^SDX-400V	SCSI
SDX-420C AITi90-A/S (AIT-1)	SONY^SDX-420C	IDE/ATAPI
SDX-420V AITi90-A/S (AIT-1)	SONY^SDX-420V	IDE/ATAPI
SDX-460V AITi100-A/S (AIT-1 Turbo)	SONY^SDX-460V	IDE/ATAPI
SDX-500C AITi130/S (AIT-2)	SONY^SDX-500C	SCSI
SDX-500V AITi130/S (AIT-2)	SONY^SDX-500V	SCSI
SDX-520C AITi130-A/S (AIT-2)	SONY^SDX-520C	IDE/ATAPI
SDX-520V AITi130-A/S (AIT-2)	SONY^SDX-520V	IDE/ATAPI
SDX-560V AITi200-A/S (AIT-2 Turbo)	SONY^SDX-560V	IDE/ATAPI
SDX-700C AITi260/S (AIT-3)	SONY^SDX-700C	SCSI
SDX-700V AITi260/S (AIT-3)	SONY^SDX-700V	SCSI

## StorageTek

Device	Inquiry String	Drive Interface
9840	STK~~~~9840	SCSI
T9840A	STK~~~~T9840	Fibre Channel
T9840A	STK~~~~T9840	SCSI
T9840B	STK~~~~T9840B	Fibre Channel
T9840B	STK~~~~T9840B	SCSI
T9940A	STK~~~~T9940A	Fibre Channel
T9940A	STK~~~~T9940A	SCSI

## Tandberg

Device	Inquiry String	Drive Interface
220LTO	TANDBERGTS200	SCSI
420LTO	TANDBERGTS400	SCSI
820LTO (LTO-3 HH)	TANDBERGTS800	SAS
820LTO (LTO-3 HH)	TANDBERGTS800	SCSI
1620LTO	TANDBERGTS1600	SCSI
SLR7	TANDBERGSLR7	SCSI
SLR60	TANDBERGSLR60	SCSI
SLR75	TANDBERGSLR60	SCSI
SLR100	TANDBERGSLR100	SCSI
SLR140	TANDBERGSLR140	SCSI

# End-of-Life Tape Libraries with Drives

## ADIC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
FastStor 2 LTO3	SCSI	HP	Ultrium 960 LTO3	SCSI	ADIC^^^FastStor^2.1 HP^^^Ultrium^3-SCSI
FastStor 2 SDLT600	SCSI	Quantum	SDLT 600	SCSI	ADIC^^^FastStor^2.1 QUANTUM^SDLT600
FastStor 2	SCSI	HP	Ultrium 230 LTO1	SCSI	ADIC^^^FastStor^2 HP^^^Ultrium^1-SCSI
FastStor 2	SCSI	HP	Ultrium 460 LTO2	SCSI	ADIC^^^FastStor^2 HP^^^Ultrium^2-SCSI
FastStor 2	SCSI	Quantum	SDLT 320	SCSI	ADIC^^^FastStor^2 QUANTUM^SDLT320
Scalar 24	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ADIC^^^Scalar^24 IBM^^^ULT3580-TD1
Scalar 24	SCSI	Quantum	SDLT 320	SCSI	ADIC^^^Scalar^24 QUANTUM^SDLT320
Scalar 100 LUN	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	ADIC^^^Scalar^100 IBM^^^ULT3580-TD3
Scalar 100 LUN	SCSI	IBM	Ultrium 2	SCSI	ADIC^^^Scalar^100 IBM^^^ULTRIUM-TD2
Scalar 100	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ADIC^^^Scalar^100 IBM^^^ULT3580-TD1
Scalar 100	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^^^Scalar^100 IBM^^^ULT3580-TD2
Scalar 100	SCSI	IBM	Ultrium 2	SCSI	ADIC^^^Scalar^100 IBM^^^ULTRIUM-TD2
Scalar 100	SCSI	Quantum	SDLT 320	SCSI	ADIC^^^Scalar^100 QUANTUM^SDLT320



## BDT

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
ThinStor	SCSI	HP	Ultrium 230 LTO1	SCSI	BDT^ThinStor^AutoLdr HP^Ultrium^1-SCSI
ThinStor	SCSI	HP	Ultrium 460 LTO2	SCSI	BDT^ThinStor^AutoLdr HP^Ultrium^2-SCSI

## Dell

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
PowerVault 132T	SCSI	Dell	PowerVault 132T SDLT320	SCSI	DELL^PV-132T QUANTUM^SDLT320
PowerVault 136T	SCSI	Dell	PowerVault 136T LTO	SCSI	DELL^PV-136T HP^ULTRIUM-1
PowerVault 136T	SCSI	Dell	PowerVault 136T LTO2	SCSI	DELL^PV-136T IBM^ULTRIUM-TD2
PowerVault 136T	SCSI	Dell	PowerVault 136T SDLT	SCSI	DELL^PV-136T QUANTUM^SuperDLT1
PowerVault 136T	SCSI	Dell	PowerVault 136T SDLT320	SCSI	DELL^PV-136T QUANTUM^SDLT320
PowerVault 136T	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	DELL^PV-136T IBM^ULT3580-TD3

# Exabyte

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
110L LTO	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	EXABYTE^Exabyte^110L IBM^ULTR3580-TD1
110L LTO	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	EXABYTE^Exabyte^110L IBM^ULTR3580-TD2
110L LTO	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	EXABYTE^Exabyte^110L IBM^ULTR3580-TD3
221L LTO	Fibre Channel	IBM	TotalStorage 3580 Ultrium 1	Fibre Channel	EXABYTE^Exabyte^221L IBM^ULTR3580-TD1
221L LTO	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	EXABYTE^Exabyte^221L IBM^ULTR3580-TD2
221L LTO	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	EXABYTE^Exabyte^221L IBM^ULTR3580-TD3
221L LTO	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	EXABYTE^Exabyte^221L IBM^ULTR3580-TD2
221L LTO	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	EXABYTE^Exabyte^221L IBM^ULTR3580-TD3
430V	SCSI	Exabyte	VXA-2	SCSI	EXABYTE^Exabyte^430 EXABYTE^VXA-2
AutoPak 1x7	SCSI	Exabyte	VXA-2	SCSI	EXABYTE^Exabyte^EZ17 EXABYTE^VXA-2
EZ17	SCSI	Exabyte	VXA-2	SCSI	EXABYTE^Exabyte^EZ17 EXABYTE^VXA-2
Magnum 1x7	SCSI	Exabyte	Magnum Tape Drive (LTO-3)	SCSI	EXABYTE^LTO^1x7^2U IBM^ULTRIUM-TD3
Magnum 1x7	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^LTO^1x7^2U HP^Ultrium^3-SCSI
Magnum 1x7	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	EXABYTE^LTO^1x7^2U IBM^ULTR3580-TD2
Magnum 1x7	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	EXABYTE^LTO^1x7^2U IBM^ULTR3580-TD3

# Exabyte

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
Magnum 1x7	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^LTO^1x7^2U IBM^ULTRIUM-TD4
Magnum 6x60	SCSI	Exabyte	Magnum Tape Drive (LTO-3)	SCSI	EXABYTE^Magnum20 IBM^ULTRIUM-TD3
Magnum 8x143 (Magnum20)	SCSI	Exabyte	Magnum Tape Drive (LTO-3)	SCSI	EXABYTE^Magnum20 IBM^ULTRIUM-TD3
Magnum 8x143 (Magnum20)	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	EXABYTE^Magnum20 IBM^ULT3580-TD1
Magnum 8x143 (Magnum20)	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	EXABYTE^Magnum20 IBM^ULT3580-TD2
Magnum 224	SCSI	HP	Ultrium 448 LTO2	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^2-SCSI
Magnum 224	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^MAGNUM^224 HP^Ultrium^3-SCSI
Magnum 224	SCSI	IBM	Ultrium 3	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD3
Magnum 224	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^MAGNUM^224 IBM^ULTRIUM-TD4
Magnum 448	Fibre Channel	IBM	Ultrium 3	Fibre Channel	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD3
Magnum 448	Fibre Channel	IBM	Ultrium 4	Fibre Channel	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD4
Magnum 448	SCSI	HP	Ultrium 448 LTO2	SCSI	EXABYTE^MAGNUM^448 HP^Ultrium^2-SCSI
Magnum 448	SCSI	HP	Ultrium 920 LTO3	SCSI	EXABYTE^MAGNUM^448 HP^Ultrium^3-SCSI
Magnum 448	SCSI	IBM	Ultrium 3	SCSI	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD3
Magnum 448	SCSI	IBM	Ultrium 4 (U160)	SCSI	EXABYTE^MAGNUM^448 IBM^ULTRIUM-TD4

## Exabyte

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
PacketLoader 1x10 1U	SCSI	Exabyte	VXA-2	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-2
PacketLoader 1x10 1U	SCSI	Exabyte	VXA-172	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-172
PacketLoader 1x10 1U	SCSI	Exabyte	VXA-320	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-3
StorageLoader	SCSI	Exabyte	Magnum Tape Drive (LTO-2)	SCSI	TANDBERGStorageLoader IBM^ULTRIUM-TD2
StorageLoader	SCSI	Exabyte	Magnum Tape Drive (LTO-2)	SCSI	TANDBERGStorageLoader TANDBERGTS400
StorageLoader	SCSI	Tandberg	420LTO	SCSI	TANDBERGStorageLoader TANDBERGTS400

## Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
ETERNUS LT20	SCSI	HP	Ultrium 448 LTO2	SCSI	FSC^FibreCAT^TX08 HP^Ultrium^2-SCSI
ETERNUS LT20	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT^TX08 HP^Ultrium^3-SCSI
ETERNUS LT40	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT-TX24^S2 HP^Ultrium^3-SCSI
ETERNUS LT60	SCSI	HP	Ultrium 920 LTO3	SCSI	FSC^FibreCAT-TX48^S2 HP^Ultrium^3-SCSI
ETERNUS LT130	SCSI	HP	Ultrium 230 LTO1	SCSI	OVERLANDNEO^Series HP^Ultrium^1-SCSI

## Fujitsu

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
ETERNUS LT130	SCSI	HP	Ultrium 460 LTO2	SCSI	OVERLANDNEO^Series HP^~~~~Ultrium^2-SCSI
ETERNUS LT210 (T16A)	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC^~~~~T16A IBM^~~~~ULT3580-TD2
ETERNUS LT270	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	FUJITSU^NML10A IBM^~~~~ULT3580-TD2
LTO1 Autoloader (PG-LTL102)	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ADIC^~~~~FastStor IBM^~~~~ULT3580-TD1
LTO1 Autoloader 1/9 (PG-LTL101)	SCSI	HP	Ultrium 230 LTO1	SCSI	HP^~~~~C7145 HP^~~~~Ultrium^1-SCSI
Scalar 100	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^~~~~Scalar^100 IBM^~~~~ULT3580-TD2

## Gateway

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
E-824R SuperLoader3	SCSI	Quantum	DLT-V4	SCSI	QUANTUM^UHDL QUANTUM^DLT-V4
E-826R SuperLoader3	SCSI	Certance	CL 800 LTO Ultrium 3	SCSI	QUANTUM^UHDL CERTANCEULTRIUM^3

# Hitachi

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
L20, L40, L80 Library series	SCSI	HP	Ultrium 230 LTO1	SCSI	FAMILY HP~~~~~Ultrium^1-SCSI
L20, L40, L80 Library series	SCSI	HP	Ultrium 460 LTO2	SCSI	FAMILY HP~~~~~Ultrium^2-SCSI

# HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
1/8 Autoloader (SCSI ID based)	SCSI	HP	Ultrium 230 LTO1	SCSI	HP~~~~~ThinStor^AutoLdr HP~~~~~Ultrium^1-SCSI
1/8 Autoloader (SCSI ID based)	SCSI	HP	Ultrium 460 LTO2	SCSI	HP~~~~~ThinStor^AutoLdr HP~~~~~Ultrium^2-SCSI
1/8 G2 Tape Autoloader	SCSI	HP	Ultrium 232 LTO1	SCSI	HP~~~~~1x8^G2^AUTOLDR HP~~~~~Ultrium^1-SCSI
1/8 Tape Autoloader	SCSI	HP	Ultrium 232 LTO1	SCSI	HP~~~~~1x8^autoloader HP~~~~~Ultrium^1-SCSI
1/8 Tape Autoloader	SCSI	HP	Ultrium 448 LTO2	SCSI	HP~~~~~1x8^autoloader HP~~~~~Ultrium^2-SCSI
1/8 Tape Autoloader	SCSI	HP	Ultrium 960 LTO3	SCSI	HP~~~~~1x8^autoloader HP~~~~~Ultrium^3-SCSI
1/8 ThinStor LTO1 (C9572CB)	SCSI	HP	Ultrium 230 LTO1	SCSI	HP~~~~~ThinStor^AutoLdr HP~~~~~Ultrium^1-SCSI
1/8 ThinStor LTO2 (AA927A)	SCSI	HP	Ultrium 460 LTO2	SCSI	HP~~~~~ThinStor^AutoLdr HP~~~~~Ultrium^2-SCSI
ESL 9000 Series	SCSI	HP	Ultrium 230 LTO1	SCSI	HP~~~~~ESL9000^Series HP~~~~~Ultrium^1-SCSI

## HP

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
ESL 9000 Series	SCSI	HP	Ultrium 460 LTO2	SCSI	HP^ESL9000^Series HP^Ultrium^2-SCSI

## IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
3586 (SL7)	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	IBM^ULT3581-TA IBM^ULT3580-TD1
3600 Model R20	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	HP^C7200 IBM^ULT3580-TD1
3623 Model 2LX	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM^36232LX IBM^ULT3580-TD2
3623 Model 2SX	SCSI	Quantum	SDLT 320	SCSI	IBM^36232SX QUANTUM^SDLT320
4560 SLX	SCSI	HP	Ultrium 230 LTO1	SCSI	IBM^4560SLX HP^Ultrium^1-SCSI
4560 SLX	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM^4560SLX IBM^ULT3580-TD2
4560 SLX	SCSI	Quantum	SDLT 320	SCSI	IBM^4560SLX QUANTUM^SDLT320
4560 SLX	SCSI	Quantum	SDLT 600	SCSI	IBM^4560SLX QUANTUM^SDLT600
3600109	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	HP^C7145 IBM^ULT3580-TD1
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	System Storage TS1120 (3592 Model E05)	Fibre Channel	IBM^03584 IBM^03592E05

# IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	TotalStorage 3580 Ultrium 1	SCSI	IBM~~~~~03584 IBM~~~~~ULT3580-TD1
System Storage TS3500 (Machine Type 3584)	Fibre Channel	IBM	TotalStorage 3592 Model J1A	Fibre Channel	IBM~~~~~03584 IBM~~~~~03592J1A
System Storage TS3500 (Machine Type 3584)	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	IBM~~~~~03584 IBM~~~~~ULT3580-TD1
System Storage TS3500 (Machine Type 3584)	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM~~~~~03584 IBM~~~~~ULT3580-TD2
System Storage TS3500 (Machine Type 3584)	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~~03584 IBM~~~~~ULT3580-TD3
TotalStorage 3581 2U	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM~~~~~ULT3581-TA2 IBM~~~~~ULT3580-TD2
TotalStorage 3581 2U	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~~ULT3581-TA2 IBM~~~~~ULT3580-TD3
TotalStorage 3581 2U Model F38	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~~ULT3581-TA2 IBM~~~~~ULT3580-TD3
TotalStorage 3581 2U Model L38	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~~ULT3581-TA2 IBM~~~~~ULT3580-TD3
TotalStorage 3581	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	IBM~~~~~ULT3581-TA IBM~~~~~ULT3580-TD1
TotalStorage 3581	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM~~~~~ULT3581-TA IBM~~~~~ULT3580-TD2
TotalStorage 3582	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~~ULT3582-TL IBM~~~~~ULT3580-TD3
TotalStorage 3582	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM~~~~~ULT3582-TL IBM~~~~~ULT3580-TD2
TotalStorage 3582	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM~~~~~ULT3582-TL IBM~~~~~ULT3580-TD3
TotalStorage 3583	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	IBM~~~~~ULT3583-TL IBM~~~~~ULT3580-TD3



## IBM

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
TotalStorage 3583	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	IBM^ULT3583-TL IBM^ULT3580-TD1
TotalStorage 3583	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	IBM^ULT3583-TL IBM^ULT3580-TD2
TotalStorage 3583	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	IBM^ULT3583-TL IBM^ULT3580-TD3

## Iomega

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
REV Autoloader 1000	SCSI	Iomega	REV (SCSI Removable Disk)	SCSI	Iomega^AUTLDR1000^350GB Iomega^RRD
USB LOADER 280 GB	USB	Iomega	REV (USB Removable Disk)	USB	IOMEGA^REV^LOADER Iomega^REV!^USB
USB LOADER 560 GB	USB	Iomega	REV 70GB	USB	IOMEGA^REV^LOADER Iomega^RRD2

# NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LL0101H	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC~~~~~LL0101H-0A HP~~~~~Ultrium^3-SCSI
LL0101H	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	NEC~~~~~LL0101H-0A IBM~~~~~ULT3580-TD1
LL0101H	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC~~~~~LL0101H-0A IBM~~~~~ULT3580-TD2
N8551-xxx/ N8552-12/ N8560-17	SCSI	NEC	N8551-xxx/ N8552-12/ N8560-17	SCSI	SONY~~~~~TSL-A300C SONY~~~~~TSL-A300C
SL0101H	SCSI	Quantum	SDLT 220	SCSI	NEC~~~~~SL0101H-0S QUANTUM^SuperDLT1
SL0101H	SCSI	Quantum	SDLT 320	SCSI	NEC~~~~~SL0101H-0S QUANTUM^SDLT320
T16A2	SAS	IBM	System Storage TS2230 Ultrium 3 Half Height	SAS	NEC~~~~~T16A2 IBM~~~~~ULT3580-HH3
T100A	Fibre Channel	IBM	Ultrium 3	Fibre Channel	FUJITSU^NML7A IBM~~~~~ULTRIUM-TD3
T100A	SCSI	IBM	Ultrium 3	SCSI	FUJITSU^NML7A IBM~~~~~ULTRIUM-TD3
T700A	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	FUJITSU^NML10A IBM~~~~~ULT3580-TD2
T700A	Fibre Channel	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	FUJITSU^NML10A IBM~~~~~ULT3580-TD3

## Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
NEO series	SCSI	HP	Ultrium 230 LTO1	SCSI	OVERLANDNEO^Series HP^~~~~^Ultrium^1-SCSI
NEO series	SCSI	Quantum	SDLT 220	SCSI	OVERLANDNEO^Series QUANTUM^SuperDLT1
NEO series	SCSI	Quantum	SDLT 320	SCSI	OVERLANDNEO^Series QUANTUM^SDLT320
NEO series	SCSI	Seagate	Viper 200 LTO	SCSI	OVERLANDNEO^Series SEAGATE^ULTRIUM06242-XXX

## Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
TLS-8000 LTO series	Fibre Channel	HP	Ultrium 230 LTO1	SCSI	QUALSTARTLS-8 HP^~~~~^Ultrium^1-SCSI
TLS-8000 LTO series	SCSI	HP	Ultrium 230 LTO1	SCSI	QUALSTARTLS-8 HP^~~~~^Ultrium^1-SCSI

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
M1500 (MagFile)	SCSI	HP	Ultrium 230 LTO1	SCSI	M4^DATA^MagFile HP^Ultrium^1-SCSI
M1500 (MagFile)	SCSI	Quantum	SDLT 600	SCSI	M4^DATA^MagFile QUANTUM^SDLT600
M1500	SCSI	HP	Ultrium 460 LTO2	SCSI	ATL^M1500 HP^Ultrium^2-SCSI
M1500	SCSI	HP	Ultrium 960 LTO3	SCSI	ATL^M1500 HP^Ultrium^3-SCSI
M1500	SCSI	Quantum	SDLT 220	SCSI	ATL^M1500 QUANTUM^SuperDLT1
M1500	SCSI	Quantum	SDLT 320	SCSI	ATL^M1500 QUANTUM^SDLT320
M1800	SCSI	HP	Ultrium 230 LTO1	SCSI	ATL^M1500 HP^Ultrium^1-SCSI
M1800	SCSI	HP	Ultrium 460 LTO2	SCSI	ATL^M1500 HP^Ultrium^2-SCSI
M1800	SCSI	Quantum	SDLT 220	SCSI	ATL^M1500 QUANTUM^SuperDLT1
M1800	SCSI	Quantum	SDLT 320	SCSI	ATL^M1500 QUANTUM^SDLT320
M1800	SCSI	Quantum	SDLT 600	SCSI	ATL^M1500 QUANTUM^SDLT600
M2500	SCSI	HP	Ultrium 230 LTO1	SCSI	ATL^M2500 HP^Ultrium^1-SCSI
M2500	SCSI	HP	Ultrium 460 LTO2	SCSI	ATL^M2500 HP^Ultrium^2-SCSI
M2500	SCSI	Quantum	SDLT 220	SCSI	ATL^M2500 QUANTUM^SuperDLT1
M2500	SCSI	Quantum	SDLT 320	SCSI	ATL^M2500 QUANTUM^SDLT320

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
M2500	SCSI	Quantum	SDLT 600	SCSI	ATL^M2500 QUANTUM^SDLT600
P3000	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ATL^P3000 IBM^ULT3580-TD1
P3000	SCSI	Quantum	SDLT 220	SCSI	ATL^P3000 QUANTUM^SuperDLT1
P3000	SCSI	Quantum	SDLT 320	SCSI	ATL^P3000 QUANTUM^SDLT320
P4000	SCSI	HP	Ultrium 460 LTO2	SCSI	ATL^P4000 HP^Ultrium^2-SCSI
P4000	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ATL^P4000 IBM^ULT3580-TD1
P4000	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ATL^P4000 IBM^ULT3580-TD2
P4000	SCSI	Quantum	SDLT 220	SCSI	ATL^P4000 QUANTUM^SuperDLT1
P4000	SCSI	Quantum	SDLT 320	SCSI	ATL^P4000 QUANTUM^SDLT320
P4000	SCSI	Quantum	SDLT 600	SCSI	ATL^P4000 QUANTUM^SDLT600
P7000	SCSI	HP	Ultrium 460 LTO2	SCSI	ATL^P7000 HP^Ultrium^2-SCSI
P7000	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	ATL^P7000 IBM^ULT3580-TD1
P7000	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ATL^P7000 IBM^ULT3580-TD2
P7000	SCSI	Quantum	SDLT 220	SCSI	ATL^P7000 QUANTUM^SuperDLT1
P7000	SCSI	Quantum	SDLT 320	SCSI	ATL^P7000 QUANTUM^SDLT320

# Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
P7000	SCSI	Quantum	SDLT 600	SCSI	ATL^P7000 QUANTUM^SDLT600
SuperLoader DLT1	SCSI	Benchmark	DLT1 (VS80)	SCSI	QUANTUM^UHDL BNCHMARKDLT1
SuperLoader LTO	SCSI	HP	Ultrium 230 LTO1	SCSI	QUANTUM^UHDL HP^Ultrium^1-SCSI
SuperLoader LTO2	SCSI	HP	Ultrium 460 LTO2	SCSI	QUANTUM^UHDL HP^Ultrium^2-SCSI
SuperLoader SDLT220	SCSI	Quantum	SDLT 220	SCSI	QUANTUM^UHDL QUANTUM^SuperDLT1
SuperLoader SDLT320	SCSI	Quantum	SDLT 320	SCSI	QUANTUM^UHDL QUANTUM^SDLT320
SuperLoader SDLT600	SCSI	Quantum	SDLT 600	SCSI	QUANTUM^UHDL QUANTUM^SDLT600
ValueLoader LTO	SCSI	HP	Ultrium 230 LTO1	SCSI	QUANTUM^ValueLoader HP^Ultrium^1-SCSI
ValueLoader LTO Gen2	SCSI	HP	Ultrium 460 LTO2	SCSI	Quantum^ValueLdr HP^Ultrium^2-SCSI
ValueLoader SDLT320	SCSI	Quantum	SDLT 320	SCSI	QUANTUM^ValueLoader QUANTUM^SDLT320
ValueLoader VS80 DLT1	SCSI	Quantum	SDLT 220	SCSI	QUANTUM^ValueLoader QUANTUM^SuperDLT1
ValueLoader VS160	SCSI	Quantum	DLT VS160	SCSI	QUANTUM^ValueLoader QUANTUM^DLT^VS160

# Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LIB-81	SCSI	Sony	SDX-300C (AIT-1)	SCSI	SONY^^^LIB-81 SONY^^^SDX-300C
LIB-81	SCSI	Sony	SDX-400C AITi90/S (AIT-1)	SCSI	SONY^^^LIB-81 SONY^^^SDX-400C
LIB-81	SCSI	Sony	SDX-400V AITi90/S (AIT-1)	SCSI	SONY^^^LIB-81 SONY^^^SDX-400V
LIB-81	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SONY^^^LIB-81 SONY^^^SDX-500C
LIB-81	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SONY^^^LIB-81 SONY^^^SDX-500V
LIB-81	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SONY^^^LIB-81 SONY^^^SDX-700C
LIB-81	SCSI	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SONY^^^LIB-81 SONY^^^SDX-700V
LIB-152	SCSI	Sony	SDX-300C (AIT-1)	SCSI	SPECTRA^215 SONY^^^SDX-300C
LIB-152	SCSI	Sony	SDX-400C AITi90/S (AIT-1)	SCSI	SPECTRA^215 SONY^^^SDX-400C
LIB-152	SCSI	Sony	SDX-400V AITi90/S (AIT-1)	SCSI	SPECTRA^215 SONY^^^SDX-400V
LIB-152	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SPECTRA^215 SONY^^^SDX-500C
LIB-152	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SPECTRA^215 SONY^^^SDX-500V
LIB-152	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SPECTRA^215 SONY^^^SDX-700C
LIB-152	SCSI	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SPECTRA^215 SONY^^^SDX-700V
LIB-162	SCSI	Sony	SDX-300C (AIT-1)	SCSI	SONY^^^LIB-162 SONY^^^SDX-300C

# Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LIB-162	SCSI	Sony	SDX-400C AITi90/S (AIT-1)	SCSI	SONY^^^LIB-162 SONY^^^SDX-400C
LIB-162	SCSI	Sony	SDX-400V AITi90/S (AIT-1)	SCSI	SONY^^^LIB-162 SONY^^^SDX-400V
LIB-162	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SONY^^^LIB-162 SONY^^^SDX-500C
LIB-162	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SONY^^^LIB-162 SONY^^^SDX-500V
LIB-162	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SONY^^^LIB-162 SONY^^^SDX-700C
LIB-162	SCSI	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SONY^^^LIB-162 SONY^^^SDX-700V
LIB-302 (SPECTRA)	SCSI	Sony	SDX-400V AITi90/S (AIT-1)	SCSI	SPECTRA^215 SONY^^^SDX-400V
LIB-302 (SPECTRA)	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SPECTRA^215 SONY^^^SDX-500V
LIB-302 (SPECTRA)	SCSI	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SPECTRA^215 SONY^^^SDX-700V
LIB-304	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SONY^^^LIB-304 SONY^^^SDX-500C
LIB-D81	SCSI	Sony	SDX-400V AITi90/S (AIT-1)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-400V
LIB-D81	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-500V
LIB-D81	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-700C
LIB-D81	SCSI	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-700V
TSL-11000	SCSI	Sony	TSL-11000	SCSI	SONY^^^TSL-11000 SONY^^^TSL-11000



## Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
TSL-A300C	SCSI	Sony	TSL-A300C	SCSI	SONY^TSL-A300C SONY^TSL-A300C
TSL-A400C	SCSI	Sony	TSL-A400C	SCSI	SONY^TSL-A400C SONY^TSL-A400C
TSL-A500C	SCSI	Sony	TSL-A500C	SCSI	SONY^TSL-A500C SONY^TSL-A500C

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
K-Series	Fibre Channel	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SPECTRA^GATOR SONY^SDX-500C
K-Series	Fibre Channel	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SPECTRA^GATOR SONY^SDX-500V
K-Series	Fibre Channel	Sony	SDX-700V AITi260/S (AIT-3)	SCSI	SPECTRA^GATOR SONY^SDX-700V
K-Series	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SPECTRA^GATOR SONY^SDX-500C
K-Series	SCSI	Sony	SDX-500V AITi130/S (AIT-2)	SCSI	SPECTRA^GATOR SONY^SDX-500V
K-Series	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SPECTRA^GATOR SONY^SDX-700C
Spectra 2K	Fibre Channel	Sony	SDX-300C (AIT-1)	SCSI	SPECTRA^215 SONY^SDX-300C
Spectra 2K	SCSI	Sony	SDX-300C (AIT-1)	SCSI	SPECTRA^215 SONY^SDX-300C

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
Spectra 2K	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SPECTRA^215 SONY^^^SDX-500C
Spectra 2K	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SPECTRA^215 SONY^^^SDX-700C
Spectra 10K	Fibre Channel	Sony	SDX-300C (AIT-1)	SCSI	SPECTRA^10000 SONY^^^SDX-300C
Spectra 10K	SCSI	Sony	SDX-300C (AIT-1)	SCSI	SPECTRA^10000 SONY^^^SDX-300C
Spectra 10K	SCSI	Sony	SDX-500C AITi130/S (AIT-2)	SCSI	SPECTRA^10000 SONY^^^SDX-500C
Spectra 10K	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	SPECTRA^10000 SONY^^^SDX-700C

## StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
9738	SCSI	StorageTek	9840	SCSI	STK^^^9738 STK^^^9840
L20, L40, L80 Library series	SCSI	Certance	CL 200 LTO Ultrium 1	SCSI	FAMILY SEAGATE^ULTRIUM06242-XXX
L20, L40, L80 Library series	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	FAMILY CERTANCEULTRIUM^2
L20, L40, L80 Library series	SCSI	HP	Ultrium 230 LTO1	SCSI	FAMILY HP^^^Ultrium^1-SCSI
L20, L40, L80 Library series	SCSI	HP	Ultrium 460 LTO2	SCSI	FAMILY HP^^^Ultrium^2-SCSI

# StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
L20, L40, L80 Library series	SCSI	HP	Ultrium 960 LTO3	SCSI	FAMILY HP~~~~~Ultrium^3-SCSI
L20, L40, L80 Library series	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	FAMILY IBM~~~~~ULT3580-TD1
L20, L40, L80 Library series	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	FAMILY IBM~~~~~ULT3580-TD2
L20, L40, L80 Library series	SCSI	Seagate	Viper 200 LTO	SCSI	FAMILY SEAGATE^ULTRIUM06242-XXX
L180	Fibre Channel	IBM	Ultrium 1	Fibre Channel	STK~~~~~L180 IBM~~~~~ULTRIUM-TD1
L180	SCSI	HP	Ultrium 230 LTO1	SCSI	STK~~~~~L180 HP~~~~~Ultrium^1-SCSI
L180	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	STK~~~~~L180 IBM~~~~~ULT3580-TD1
L180	SCSI	Seagate	Viper 200 LTO	SCSI	STK~~~~~L180 SEAGATE^ULTRIUM06242-XXX
L180	SCSI	StorageTek	T9840A	Fibre Channel	STK~~~~~L180 STK~~~~~T9840
L180	SCSI	StorageTek	T9840A	SCSI	STK~~~~~L180 STK~~~~~T9840
L180	SCSI	StorageTek	T9840B	Fibre Channel	STK~~~~~L180 STK~~~~~T9840B
L180	SCSI	StorageTek	T9840B	SCSI	STK~~~~~L180 STK~~~~~T9840B
L180	SCSI	StorageTek	T9940A	Fibre Channel	STK~~~~~L180 STK~~~~~T9940A
L180	SCSI	StorageTek	T9940A	SCSI	STK~~~~~L180 STK~~~~~T9940A
L700	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	STK~~~~~L700 IBM~~~~~ULT3580-TD1

## StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
L700	SCSI	Seagate	Viper 200 LTO	SCSI	STK^L700 SEAGATE^ULTRIUM06242-XXX
L700	SCSI	StorageTek	T9840A	Fibre Channel	STK^L700 STK^T9840
L700	SCSI	StorageTek	T9840A	SCSI	STK^L700 STK^T9840
L700	SCSI	StorageTek	T9840B	Fibre Channel	STK^L700 STK^T9840B
L700	SCSI	StorageTek	T9840B	SCSI	STK^L700 STK^T9840B
L700	SCSI	StorageTek	T9940A	Fibre Channel	STK^L700 STK^T9940A
L700	SCSI	StorageTek	T9940A	SCSI	STK^L700 STK^T9940A
SL500	SCSI	IBM	TotalStorage 3580 Ultrium 3	Fibre Channel	STK^SL500 IBM^ULT3580-TD3

## Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LL0101H	SCSI	IBM	TotalStorage 3580 Ultrium 1	SCSI	NEC^LL0101H-0A IBM^ULT3580-TD1
LL0101H	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC^LL0101H-0A IBM^ULT3580-TD3
LL0101H	SCSI	IBM	Ultrium 3	SCSI	NEC^LL0101H-0A IBM^ULTRIUM-TD3

# Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
S24	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^Scalar^24 IBM^ULT3580-TD2
S24	SCSI	IBM	Ultrium 3	SCSI	ADIC^Scalar^24 IBM^ULTRIUM-TD3
SLR Autoloader	SCSI	Tandberg	SLR100	SCSI	TANDBERGSLR^AUTOLOADER TANDBERGSLR100
SLR Autoloader	SCSI	Tandberg	SLR140	SCSI	TANDBERGSLR^AUTOLOADER TANDBERGSLR140
StorageLoader DLT VS160	SCSI	Quantum	DLT VS160	SCSI	TANDBERGAT1280-1R^VS160 QUANTUM^DLT^VS160
StorageLoader LTO	SCSI	Tandberg	220LTO	SCSI	TANDBERGStorageLoader TANDBERGTS200
StorageLoader LTO	SCSI	Tandberg	820LTO (LTO-3 HH)	SCSI	TANDBERGStorageLoader TANDBERGTS800
StorageLoader LTO2	SCSI	Tandberg	420LTO	SCSI	TANDBERGStorageLoader TANDBERGTS400
StorageLoader VXA	SCSI	Exabyte	VXA-2	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-2
StorageLoader VXA	SCSI	Exabyte	VXA-172	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-172
StorageLoader VXA	SCSI	Exabyte	VXA-320	SCSI	EXABYTE^VXA^1x10^1U EXABYTE^VXA-3
Superloader DLT1 1280L	SCSI	Benchmark	DLT1 (VS80)	SCSI	Quantum^UHD BNCHMARKDLT1
Superloader LTO2	SCSI	HP	Ultrium 460 LTO2	SCSI	QUANTUM^UHD HP^Ultrium^2-SCSI
ThinStor AutoLoader	SCSI	HP	Ultrium 230 LTO1	SCSI	BDT^ThinStor^AutoLdr HP^Ultrium^1-SCSI
ThinStorPlus Autoloader	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	BDT^ThinStorPlus^AL IBM^ULT3580-TD2

## Tandberg

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
ThinStorPlus Autoloader	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	BDT^ThinStorPlus^AL IBM^ULT3580-TD3

## End-of-Life Virtual Tape Libraries with Drives

### ADIC

Device	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry
Pathlight VX	Fibre Channel	IBM	Ultrium 2	ADIC^Pathlight^VX IBM^ULTRIUM-TD2
Pathlight VX	Fibre Channel	IBM	Ultrium 3	ADIC^Pathlight^VX IBM^ULTRIUM-TD3

### Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Library Inquiry Drive Inquiry
REO Series 3.X	Fibre Channel	HP	Ultrium 460 LTO2	OVERLANDREO^Series HP^Ultrium^2-SCSI

# End-of-Life OST-Appliance

## Data Domain

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
Appliance series	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.2	Ethernet	✓	✓	Basic Deduplication
DDX Array series	DDX	2.2	Ethernet	✓	✓	Basic Deduplication
Gateway series	DD560g, DD580g, DD690g, DD880g	2.2	Ethernet	✓	✓	Basic Deduplication
Global Deduplication Array series	GDA	2.2	Ethernet	✓	✓	Basic Deduplication

## ExaGrid

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
EX series	EX1000, EX2000, EX3000, EX4000, EX5000, EX7000, EX10000E, EX13000E, EX21000E	V10.1.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
EX series	EX1000, EX2000, EX3000, EX4000, EX5000, EX7000, EX10000E, EX13000E, EX21000E	V10.2.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## FalconStor

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
FDS series	FDS 100, FDS 300, FDS 600	2.1	Ethernet	✓	✓	Basic Deduplication

## Fujitsu

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
ETERNUS CS800 S3	ETERNUS CS800 S3	2.4.0	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
ETERNUS CS800	ETERNUS CS800	2.1.11	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi2500-D	DXi2500-D	2.1.17	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D	DXi2500-D	2.3.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D	DXi2500-D	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi2500-D	DXi2500-D	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.1.11	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.1.17	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.3.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.1.17	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication



# Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi6000 Family	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.3.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family	DXi6700, DXi6701, DXi6702	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family	DXi6700, DXi6701, DXi6702	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.1.17	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.3.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.1.17	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.1.18	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.1.19	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.3.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.4	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.5	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## End-of-Life ESO Bridges and Routers

### ADIC

Device
Pathlight 5100 <a href="#">[1]</a>
SNC 5100
SNC 5101 Internal
SNC 6101
SNC 6404

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

### Dell

Device
PV-136T (FCR embedded)

### IBM

Device
2108 R03 SAN Gateway
Integrated Router (358x)
Integrated Router (359x)

### Overland Storage

Device
SANpiper 400

### Quantum

Device
FC230
FC310
FC420

## End-of-Life ESO Switches

## Brocade

Device
SilkWorm 2400
SilkWorm 2800

## IBM

Device
2109 S16

## Dell

Device
PowerVault 50F
PowerVault 50F/51F
PowerVault 51F/56F
PowerVault 56F

## QLogic

Device
SANbox Series 1Gb

## HP

Device
Core Switch 2/64
Edge Switch 2/24
SAN Switch 2/16
SAN Switch 2/32
SAN Switch 2/8

# End-of-Life ESO HBAs

## Emulex

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
LP90xx / 94xx / 95x series (Centaur ASIC) [1]	PCI	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
LP98xx / 98x series (Pegasus ASIC) [1]	PCI-X	Windows Server 2003	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
LP8000 series (Dragonfly ASIC)	PCI	Windows Server 2003			

1. Please note: this device is nearing the end of support. Please see [the 'Retiring Soon' section](#) .

## HP

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
FCA-2101 2GB	PCI		2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FCA2214DC	PCI-X	Windows Server 2003		9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
FCA2404	PCI-X	Windows Server 2003	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)

## QLogic

Device	Bus Type	Windows	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
SANblade 22xx series	PCI	Windows Server 2003		

# Retiring Soon

The devices in this section will not be listed as supported in the Hardware Compatibility List for the next major Backup Exec release after Backup Exec 2012. Many of these devices are end-of-life products that are no longer supported by the manufacturer. This is a prediction, subject to frequent change, until the next version is actually released. This section is primarily for your education only as **IT HAS NO DIRECT IMPACT ON YOUR CURRENT SUPPORTABILITY**.

If this list contains a device you are actively using and are concerned about lack of support, please email [<Backup\\_Exec\\_HCL@symantec.com>](mailto:Backup_Exec_HCL@symantec.com) with details of the specific device you are using.

## Retiring Tape Libraries with Drives

### ADIC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
Scalar 24	SCSI	Quantum	SDLT 600	SCSI	ADIC^^^Scalar^24 QUANTUM^SDLT600
Scalar i500	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	ADIC^^^Scalar^i500 IBM^^^ULT3580-TD2
Scalar i500	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^^^Scalar^i500 IBM^^^ULT3580-TD2
Scalar i2000	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	ADIC^^^Scalar^i2000 IBM^^^ULT3580-TD2
Scalar i2000	Fibre Channel	IBM	Ultrium 2	Fibre Channel	ADIC^^^Scalar^i2000 IBM^^^ULTRIUM-TD2
Scalar i2000	Fibre Channel	Quantum	SDLT 600	Fibre Channel	ADIC^^^Scalar^i2000 QUANTUM^SDLT600
Scalar i2000	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	ADIC^^^Scalar^i2000 IBM^^^ULT3580-TD2

## Dell

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
PowerVault 124T	SCSI	Dell	PowerVault 124T VS160	SCSI	DELL^PV-124T QUANTUM^DLT^VS160

## NEC

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LL0101H	SCSI	IBM	System Storage TS2230 Ultrium 3 Half Height	SCSI	NEC^LL0101H-0A IBM^ULT3580-HH3
LL0101H	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC^LL0101H-0A IBM^ULT3580-TD3
LL0101H	SCSI	IBM	Ultrium 3	SCSI	NEC^LL0101H-0A IBM^ULTRIUM-TD3
T16A	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC^T16A HP^Ultrium^3-SCSI
T16A	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC^T16A IBM^ULT3580-TD2
T16A	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC^T16A IBM^ULT3580-TD3
T40A	SCSI	HP	Ultrium 460 LTO2	SCSI	NEC^T40A HP^Ultrium^2-SCSI
T40A	SCSI	HP	Ultrium 960 LTO3	SCSI	NEC^T40A HP^Ultrium^3-SCSI
T40A	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	NEC^T40A IBM^ULT3580-TD2
T40A	SCSI	IBM	TotalStorage 3580 Ultrium 3	SCSI	NEC^T40A IBM^ULT3580-TD3

## Overland Storage

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
NEO series	SCSI	Quantum	SDLT 600	SCSI	OVERLANDNEO^Series QUANTUM^SDLT600

## Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
CLS-4216	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARCLS-4 SONY^^^SDX-700C
RLS-4000 AIT series	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARRLS-4 SONY^^^SDX-700C
RLS-5000 SAIT series	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	QUALSTARRLS-5 SONY^^^SDZ-100
RLS-6000 (S)DLT series	SCSI	Quantum	SDLT 320	SCSI	QUALSTARRLS-6 QUANTUM^SDLT320
RLS-6000 (S)DLT series	SCSI	Quantum	SDLT 600	SCSI	QUALSTARRLS-6 QUANTUM^SDLT600
TLS-4000 AIT series	SCSI	Sony	SDX-700C AITi260/S (AIT-3)	SCSI	QUALSTARTLS-4 SONY^^^SDX-700C
TLS-5000 SAIT series	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	QUALSTARTLS-5 SONY^^^SDZ-100
TLS-6000 DLT series	SCSI	Quantum	SDLT 320	SCSI	QUALSTARTLS-6 QUANTUM^SDLT320
TLS-6000 DLT series	SCSI	Quantum	SDLT 600	SCSI	QUALSTARTLS-6 QUANTUM^SDLT600



## Qualstar

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
XLS-8000	SAS	IBM	Ultrium 5	SAS	QUALSTARXLS-8000 IBM~~~~~ULTRIUM-TD5

## Quantum

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
PX500 Series	Fibre Channel	HP	Ultrium 460 LTO2	SCSI	QUANTUM^PX500 HP~~~~~Ultrium^2-SCSI
PX500 Series	Fibre Channel	Quantum	SDLT 600	Fibre Channel	QUANTUM^PX500 QUANTUM^SDLT600
PX500 Series	SCSI	HP	Ultrium 460 LTO2	SCSI	QUANTUM^PX500 HP~~~~~Ultrium^2-SCSI
PX500 Series	SCSI	Quantum	SDLT 320	SCSI	QUANTUM^PX500 QUANTUM^SDLT320
PX500 Series	SCSI	Quantum	SDLT 600	SCSI	QUANTUM^PX500 QUANTUM^SDLT600
Scalar 50 (PX500)	SCSI	Quantum	DLT-V4	SCSI	QUANTUM^PX500 QUANTUM^DLT-V4
Scalar i500	SCSI	IBM	TotalStorage 3580 Ultrium 2	SCSI	Quantum^Scalar^i500 IBM~~~~~ULT3580-TD2
Scalar i2000	Fibre Channel	IBM	TotalStorage 3580 Ultrium 2	Fibre Channel	Quantum^Scalar^i2000 IBM~~~~~ULT3580-TD2
SuperLoader 3	SCSI	Certance	CL 400 LTO Ultrium 2	SCSI	QUANTUM^UHDL CERTANCEULTRIUM^2
SuperLoader 3	SCSI	Quantum	DLT VS160	SCSI	QUANTUM^UHDL QUANTUM^DLT^VS160

# Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
CSM20	SCSI	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	SONY^^^CSM-20 SONY^^^SDZ-100
LIB-81	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-81 SONY^^^SDX-550V
LIB-81	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^^^LIB-81 SONY^^^SDX-800V
LIB-81	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^^^LIB-81 SONY^^^SDX-900V
LIB-81	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-81 SONY^^^SDX-1100
LIB-152 (SONY)	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-152 SONY^^^SDX-1100
LIB-152	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^215 SONY^^^SDX-1100
LIB-162	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-162 SONY^^^SDX-550V
LIB-162	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^^^LIB-162 SONY^^^SDX-800V
LIB-162	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^^^LIB-162 SONY^^^SDX-900V
LIB-162	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-162 SONY^^^SDX-1100
LIB-302 (SONY)	SCSI	Sony	SDX-1100 AITe1040 (AIT-5)	SCSI	SONY^^^LIB-302 SONY^^^SDX-1100
LIB-302 (SONY)	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^^^LIB-302 SONY^^^SDX-1100
LIB-D81	SCSI	Sony	SDX-550V AITi200/S (AIT-2 Turbo)	SCSI	SONY^^^LIB-D81 SONY^^^SDX-550V

## Sony

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
LIB-D81	SCSI	Sony	SDX-800V AITi390/S (AIT-3Ex)	SCSI	SONY^LIB-D81 SONY^SDX-800V
LIB-D81	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SONY^LIB-D81 SONY^SDX-900V
LIB-D81	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SONY^LIB-D81 SONY^SDX-1100
PetaSite Series	Fibre Channel	Sony	SDZ-100 SAITi1300SS (SAIT)	SCSI	SONY^CSM- SONY^SDZ-100
PetaSite Series	SCSI	IBM	Ultrium 4	Fibre Channel	SONY^CSM- IBM^ULTRIUM-TD4

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
K-Series	Fibre Channel	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^GATOR SONY^SDX-900V
K-Series	Fibre Channel	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^GATOR SONY^SDX-1100
K-Series	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^GATOR SONY^SDX-900V
K-Series	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^GATOR SONY^SDX-1100
Spectra 2K	SCSI	Sony	SDX-900V AITi520/S (AIT-4)	SCSI	SPECTRA^215 SONY^SDX-900V
Spectra 2K	SCSI	Sony	SDX-1100 AITi1040 (AIT-5)	SCSI	SPECTRA^215 SONY^SDX-1100

## Spectra Logic

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
T-series	SCSI	Sony	SDZ-100 SAIT11300SS (SAIT)	SCSI	SPECTRA^PYTHON SONY^SDZ-100

## StorageTek

Device	Library Interface	Drive Mfr.	Drive Model	Drive Interface	Library Inquiry Drive Inquiry
L180	Fibre Channel	StorageTek	T9840C	Fibre Channel	STK^L180 STK^T9840C
L180	SCSI	StorageTek	T9840C	Fibre Channel	STK^L180 STK^T9840C
L180	SCSI	StorageTek	T9940B	Fibre Channel	STK^L180 STK^T9940B
L700	Fibre Channel	StorageTek	T10000A 4GB	Fibre Channel	STK^L700 STK^T10000A
L700	SCSI	StorageTek	T9840C	Fibre Channel	STK^L700 STK^T9840C
L700	SCSI	StorageTek	T9940B	Fibre Channel	STK^L700 STK^T9940B

# Retiring Tape Drives

## Quantum

Device	Inquiry String	Drive Interface
LTO-2	CERTANCEULTRIUM^2	SCSI
LTO-3	CERTANCEULTRIUM^3	SCSI

## Sony

Device	Inquiry String	Drive Interface
SDTi320UB (DAT 320)	SONY^^^SDT320	USB 2.0
SDX-250V AITi50/S (AIT-E Turbo)	SONY^^^SDX-250V	SCSI
SDX-450V AITi100/S (AIT-1 Turbo)	SONY^^^SDX-450V	SCSI
SDX-460V AITe100-UL (AIT-1 Turbo)	SONY^^^SDX-460V	USB 2.0
SDX-470V AITi100-ST (AIT-1 Turbo S-ATA)	SONY^^^SDX-470V	SATA
SDX-550V AITi200/S (AIT-2 Turbo)	SONY^^^SDX-550V	SCSI
SDX-560V AITe200-UL (AIT-2 Turbo)	SONY^^^SDX-560V	USB 2.0
SDX-570V AITi200-ST (AIT-2 Turbo S-ATA)	SONY^^^SDX-570V	SATA
SDX-800V AITi390/S (AIT-3Ex)	SONY^^^SDX-800V	SCSI
SDX-870V AITi390/ST (AIT-3Ex)	SONY^^^SDX-870V	SATA
SDX-870V AITi390/ST (AIT-3Ex) USB	SONY^^^SDX-870V	SATA
SDX-900V AITi520/S (AIT-4)	SONY^^^SDX-900V	SCSI
SDX-1100 AITe1040 (AIT-5)	SONY^^^SDX-1100	SCSI
SDX-1100 AITi1040 (AIT-5)	SONY^^^SDX-1100	SCSI
SDZ-100 SAITi1300SS (SAIT)	SONY^^^SDZ-100	SCSI

## Sony

Device	Inquiry String	Drive Interface
SDZ-130 SAITi1300SS (SAIT)	SONY^^^SDZ-130	Fibre Channel
SDZ-200	SONY^^^SDZ-200	SCSI

## StorageTek

Device	Inquiry String	Drive Interface
T9940B	STK^^^T9940B	Fibre Channel

## Retiring OST-Appliance

## Data Domain

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
Appliance series	DD120, DD140, DD160, DD510, DD530, DD560, DD565, DD580, DD610, DD620, DD630, DD640, DD660, DD670, DD690, DD860, DD880, DD890, DD990, DD2200, DD2500, DD4200, DD4500, DD7200	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DDX Array series	DDX	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Gateway series	DD560g, DD580g, DD690g, DD880g	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
Global Deduplication Array series	GDA	2.3	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## Dell

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DR Series	DR4000, DR4100, DR6000	1.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## GreenBytes

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
GB-X series	GB-1000, GB-2000, GB-4000	1.3.42	Ethernet	✓	✓	Basic Deduplication

## Quantum

Storage Server Family	Storage Server Family Members	Plug-in	Data Interface	Windows Server 2003	Windows Server 2008	Supported OpenStorage Functionality
DXi2500-D	DXi2500-D	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi4000 Family	DXi4510, DXi4520, DXi4601	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6000 Family	DXi6510, DXi6520, DXi6530, DXi6540, DXi6550	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi6700 Family	DXi6700, DXi6701, DXi6702	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi7500 Family	DXi7500 Enterprise, DXi7500 Express, DXi7500-N	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi8500 Family	DXi8500, DXi8500 2TB, DXi8500 3TB	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication
DXi V Family	DXi V1000, DXi V4000	2.5.1	Ethernet	✓	✓	Basic Deduplication, Optimized Duplication

## Retiring FCoE CNAs

### QLogic

Device	Bus Type	Windows
QLE8142	PCIe	Windows Server 2008
QLE8152	PCIe	Windows Server 2003

## Retiring ESO HBAs

### Emulex

Device	Bus Type	Windows	(Asianux Consortium) Asianux	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
LP10xxx / 105x series (Thor ASIC)	PCI-X, PCIe	Windows Server 2003, Windows Server 2008	2.0	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)

### QLogic

Device	Bus Type	Windows	(Novell) SUSE Linux Enterprise Server	(Red Hat) Enterprise Linux
QLA2x0 series	PCI-X	Windows Server 2003	9, 10	4.0 (ES), 5.0 (Advanced), 5.0 (base)
QLE220	PCIe	Windows Server 2008		



# Retiring ESO Switches

## QLogic

Device
SANbox 1400
SANbox 5200
SANbox-8
SANbox2 Series 2Gb
SANbox2-16
SANbox2-8