

Veritas Storage Foundation™ Release Notes

Linux

5.0 Maintenance Pack 1



Veritas Storage Foundation Release Notes

Copyright © 2007 Symantec Corporation. All rights reserved.

Storage Foundation 5.0 Maintenance Pack 1

Symantec, the Symantec logo, Veritas, and Veritas Storage Foundation are trademarks or registered trademarks of Symantec Corporation or its affiliates in the U.S. and other countries. Other names may be trademarks of their respective owners.

The product described in this document is distributed under licenses restricting its use, copying, distribution, and decompilation/reverse engineering. No part of this document may be reproduced in any form by any means without prior written authorization of Symantec Corporation and its licensors, if any.

THIS DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID, SYMANTEC CORPORATION SHALL NOT BE LIABLE FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES IN CONNECTION WITH THE FURNISHING PERFORMANCE, OR USE OF THIS DOCUMENTATION. THE INFORMATION CONTAINED IN THIS DOCUMENTATION IS SUBJECT TO CHANGE WITHOUT NOTICE.

The Licensed Software and Documentation are deemed to be "commercial computer software" and "commercial computer software documentation" as defined in FAR Sections 12.212 and DFARS Section 227.7202.

Symantec Corporation
20330 Stevens Creek Blvd.
Cupertino, CA 95014
www.symantec.com

Third-party legal notices

Third-party software may be recommended, distributed, embedded, or bundled with this Veritas product. Such third-party software is licensed separately by its copyright holder. All third-party copyrights associated with this product are listed in the *Veritas Storage Foundation 5.0 Release Notes*.

The *Veritas Storage Foundation 5.0 Release Notes* can be viewed at the following URL:

<http://entsupport.symantec.com/docs/283859>

Linux is a registered trademark of Linus Torvalds.

Licensing and registration

Veritas Storage Foundation is a licensed product. See the *Veritas Storage Foundation Installation Guide* for license installation instructions.

Technical support

For technical assistance, visit

http://www.symantec.com/enterprise/support/assistance_care.jsp

and select phone or email support. Use the Knowledge Base search feature to access resources such as TechNotes, product alerts, software downloads, hardware compatibility lists, and our customer email notification service.

Contents

Introduction	7
New features	8
Veritas File System	8
System requirements	9
Supported Linux operating systems	9
Memory requirements	9
Supported DB2 versions	9
Supported Oracle versions	9
Software and hardware requirements	10
VxVM licenses	10
Cross-Platform Data Sharing licensing	11
Component product release notes	11
Installing for the first time	12
Upgrading to Storage Foundation 5.0 MP1	14
Upgrading Storage Foundation on a cluster	15
Upgrading Storage Foundation on a standalone system	19
Changing permissions for Storage Foundation for Databases	23
Verifying software versions	24
Removing the 5.0 MP1 packages	24
Upgrading a High Availability cluster	26
Fixed issues	27
Veritas Volume Manager fixed issues	27
Veritas File System fixed issues	30
Veritas Volume Replicator fixed issues	32
Veritas Storage Foundation for DB2 fixed issues	34
Veritas Storage Foundation for Oracle fixed issues	35
Known issues	36
Veritas Storage Foundation known issues	36
Veritas Volume Manager known issues	37
Veritas File System known issues	42
Veritas Volume Replicator known issues	42
Veritas Storage Foundation for Databases known issues	44
Software limitations	49
Veritas File System software limitations	49
Veritas Storage Foundation for Databases software limitations	49
No longer supported	53
Documentation errata	54

Web GUI help errata	54
Veritas Storage Foundation Installation Guide errata	54
Veritas Storage Foundation Release Notes errata	54
Manual page errata	54
Veritas Volume Manager Administrator's Guide errata	54
Veritas Storage Foundation for Oracle Administrator's Guide errata	55
Veritas Storage Foundation for Oracle Graphical User Interface Guide errata	57
Veritas Storage Foundation for DB2 Administrator's Guide errata	57
Veritas Storage Foundation for DB2 Graphical User Interface Guide errata	59

Veritas Storage Foundation Release Notes

Introduction

This document provides release information about the products in the Veritas Storage Foundation 5.0 Maintenance Pack 1 (MP1) product line for the Linux platform:

- Veritas Storage Foundation (Basic, Standard, Standard HA, Enterprise, and Enterprise HA)
- Veritas Storage Foundation for DB2 (Standard, Enterprise, and HA Editions)
- Veritas Storage Foundation for Oracle (Standard, Enterprise, and HA Editions)
- Veritas Volume Manager (VxVM)
- Veritas File System (VxFS)
- Veritas Volume Replicator (VVR)

Note: Veritas Storage Foundation QuickStart is not available in this release.

Each of these Symantec products is activated by a single license key. You must obtain a license key before installing the product. For information on obtaining a license key, see the *Veritas Storage Foundation Installation Guide*.

Note: For the latest information on updates, patches, and software issues regarding this release, see the following TechNote on the Symantec Technical Support website:

<http://entsupport.symantec.com/docs/281993>

Review this entire document before installing your Veritas Storage Foundation product.

This document does not contain release information for Veritas Cluster Server. See the *Veritas Cluster Server Release Notes*.

New features

The following new features have been incorporated into Veritas Storage Foundation.

Veritas File System

This release of Veritas File System includes the following new features and enhancements

Block device support in Veritas File System

VxFS 5.0 only supported the creation of a VxFS file system on a VxVM volume. Creating a VxFS file system on raw devices, such as SCSI or IDE disks, was not supported. VxFS 5.0 MP1 supports the creation of VxFS file systems directly on such devices, without requiring a VxVM volume.

Both partitioned and non-partitioned block devices may now be used directly with VxFS. For example:

```
# mkfs -t vxfs /dev/sdc1
# mount -t vxfs /dev/sdc1 /mnt
# fsck -t vxfs /dev/sdc1
```

Similarly, all local mount features of VxFS, such as clones and file system snapshots, do not require the creation of a VxVM volume.

System requirements

This section describes the system requirements for this release.

Supported Linux operating systems

Storage Foundation operates on the following Linux operating systems and kernels distributed by Red Hat and SUSE:

- Red Hat Enterprise Linux 4 (RHEL 4) with Update 3 (2.6.9-34 kernel) or higher on AMD Opteron or Intel Xeon EM64T (x86_64).
- SUSE Linux Enterprise Server 9 (SLES 9) with SP3 (2.6.5-7.244 kernels) or higher on AMD Opteron or Intel Xeon EM64T (x86_64).

Note: If your system is running an older version of either Red Hat Enterprise Linux or SUSE Linux Enterprise Server, you must upgrade it before attempting to install the Veritas Storage Foundation software. Consult the Red Hat or SUSE documentation for more information on upgrading your system.

Supported Linux operating system updates

Veritas products will operate on subsequent kernel and patch releases provided the operating systems maintain kernel application binary interface (ABI) compatibility.

Information about the latest supported Red Hat errata and updates and SUSE service packs is available in the following TechNote. Read this TechNote before installing any Veritas product.

<http://entsupport.symantec.com/docs/281993>

Memory requirements

A minimum of 1 GB of memory is strongly recommended.

Supported DB2 versions

DB2 8.2, also referred to as DB2 8.1 with FixPak 7, or later is supported on the Linux operating systems listed above.

Supported Oracle versions

Oracle versions 9.2.0.6, 10g, and 10gR2 are all supported on the Linux operating systems listed above.

Mandatory patch required for Oracle Bug 4130116

If you are running Oracle version 9.2.0.6, you must apply the Oracle patch for Oracle Bug 4130116. Contact Oracle to obtain this patch, and for details on how to apply it.

Software and hardware requirements

The hardware compatibility list (HCL) contains the latest information about supported hardware and software and is updated regularly.

Note: Before installing or upgrading Veritas Volume Manager, review the current compatibility list to confirm the compatibility of your hardware and software.

The hardware compatibility list (HCL) is available at:

<http://entsupport.symantec.com/docs/283161>

The hardware TechNote is available at:

<http://entsupport.symantec.com/docs/283282>

If you do not find your hardware or software listed or if you have questions about the information in the compatibility list, contact Veritas Technical Services.

VxVM licenses

The following table shows the levels of licensing in Veritas Volume Manager and the features supported at each level:

VxVM License	Description of Supported Features
Full	Concatenation, spanning, rootability, volume resizing, multiple disk groups, co-existence with native volume manager, striping, mirroring, DRL logging for mirrors, striping plus mirroring, mirroring plus striping, RAID-5, RAID-5 logging, Smartsync, hot sparing, hot-relocation, online data migration, online relayout, volume snapshots, volume sets, Intelligent Storage Provisioning, FastResync with Instant Snapshots, Storage Expert, Device Discovery Layer (DDL), Dynamic Multipathing (DMP), and Veritas Enterprise Administrator (VEA).
Add-on Licenses	Features that augment the Full VxVM license such as clustering functionality (cluster-shareable disk groups and shared volumes) and Veritas Volume Replicator.

Note: You need a Full VxVM license to make effective use of add-on licenses to VxVM.

To see the license features that are enabled in VxVM, enter the following command:

```
# vxddctl license
```

Cross-Platform Data Sharing licensing

Note: The Cross-Platform Data Sharing (CDS) feature is also referred to as Portable Data Containers.

The ability to import a CDS disk group on a platform that is different from the platform on which the disk group was last imported is controlled by a CDS license. CDS licenses are included as part of the Veritas Storage Foundation license.

Component product release notes

Release notes for component products in all versions of Veritas Storage Foundation are located under the `storage_foundation/release_notes` directory of the Veritas Storage Foundation disc. It is important that you read the relevant component product release notes before installing any version of Veritas Storage Foundation:

Veritas Storage Foundation Release Notes (`sf_notes.pdf`)

Veritas Cluster Server Release Notes (`vcs_notes.pdf`)

Because product release notes are not installed by any packages, Symantec recommends that you copy them to the `/opt/VRTSproduct_name/doc` directory after the product installation so that they are available for future reference.

Installing for the first time

If you are installing the Veritas Storage Foundation 5.0 MP1 software for the first time and not upgrading an existing system, read the *Veritas Storage Foundation Installation Guide* for pre-installation instructions. Also review the *Veritas Storage Foundation Release Notes* and all documents in the `release_notes` directory for important release information.

Caution: Existing data could be destroyed on any disks that are touched by upgrading the operating system. While upgrading, do not reconfigure any disks other than the root disk. To ensure the integrity of your data, it is recommended that you back it up before starting the upgrade.

To install the Storage Foundation software

- 1 Before installing Veritas Storage Foundation 5.0 MP1, you must install the Veritas Storage Foundation 5.0 software as described in the *Veritas Storage Foundation 5.0 Installation Guide*. However, run the product installation script instead of the generic `installer` script. For example, if you are installing the Storage Foundation software, enter the following command from the top-level directory of the mounted DVD-ROM:

```
# ./installsf -installonly [-rsh]
```

The `-installonly` option is required to perform the installation without configuring the software. The `-rsh` option is required if you are using the remote shell (RSH) rather than the secure shell (SSH) to install the software simultaneously on several systems.

Note: Provided that the remote shell (RSH) or secure shell (SSH) has been configured correctly, this command can be run on a single node of the cluster to install the software on all the cluster nodes.

For help on how to respond to the installation prompts, see the *Veritas Storage Foundation 5.0 Installation Guide*.

- 2 Insert the Veritas Storage Foundation 5.0 MP1 software disc, and mount it on a suitable mount point. For example:

```
# mount -o ro /dev/cdrom /mnt/cdrom
```

- 3 Move to the top-level directory on the DVD:

```
# cd /mnt/cdrom
```

- 4 To install the Storage Foundation 5.0 MP1 software, you must invoke the `installmp` command from one of your cluster nodes using the option that corresponds to your configuration:
 - To install on the local system, enter the following command:

```
# ./installmp
```
 - To install on more than one system using secure shell (SSH) utilities, enter the following command:

```
# ./installmp system_name1 system_name2 ...
```
 - To install on more than one system using remote shell (RSH) utilities, enter the following command:

```
# ./installmp system_name1 system_name2 ... -rsh
```
- 5 After the initial system checks have completed successfully, press **Enter** to start the requirements checks for the upgrade.
- 6 After the requirement checks have completed successfully, press **Enter** to begin upgrading the packages.
- 7 If you are upgrading multiple systems, you can choose to upgrade the systems simultaneously.
- 8 After the upgrade of the packages is complete, press **Enter**.
- 9 Run the same installation script that you used in [step 1](#), this time specifying the `-configure` option to configure the software, for example:

```
# ./installsf -configure [-rsh]
```

For help on how to respond to the installation prompts, see the *Veritas Storage Foundation 5.0 Installation Guide*.

Upgrading to Storage Foundation 5.0 MP1

The following table contains notes about the upgrade paths for Red Hat systems:

Red Hat release	Notes
Red Hat Advanced Server 2.1	System must be upgraded to Red Hat Enterprise Linux 4 Update 3 or 4 before installing Storage Foundation 5.0 and Storage Foundation 5.0 MP1.
Red Hat Enterprise Linux 3	System must be upgraded to Red Hat Enterprise Linux 4 Update 3 or 4 before installing Storage Foundation 5.0 and Storage Foundation 5.0 MP1.
Red Hat Enterprise Linux 4 with Update 1 or 2	System must be upgraded to Red Hat Enterprise Linux 4 Update 3 or 4 before installing Storage Foundation 5.0 and Storage Foundation 5.0 MP1.

The following table contains notes about the upgrade paths for SUSE systems:

SUSE release	Notes
SUSE Linux Enterprise Server 8	System must be upgraded to SUSE Linux Enterprise Server 9 SP3 before installing Storage Foundation 5.0 and Storage Foundation 5.0 MP1.
SUSE Linux Enterprise Server 9 SP1 or SP2	System must be upgraded to SUSE Linux Enterprise Server 9 SP3 before installing Storage Foundation 5.0 and Storage Foundation 5.0 MP1.

The following sections describe how to upgrade a cluster and a standalone system:

- [“Upgrading Storage Foundation on a cluster”](#) on page 15.
- [“Upgrading Storage Foundation on a standalone system”](#) on page 19.

Upgrading Storage Foundation on a cluster

Caution: Existing data could be destroyed on any disks that are touched by upgrading the operating system. While upgrading, do not reconfigure any disks other than the root disk. To ensure the integrity of your data, it is recommended that you back it up before starting the upgrade.

To upgrade to Storage Foundation 5.0 MP1 on a cluster

- 1 Log in as superuser.
- 2 Make a complete backup of all data on the system. In particular, you will need the information in files such as `/boot/grub/menu.lst`, `/etc/grub.conf` or `/etc/lilo.conf` (as appropriate), and `/etc/fstab`.
- 3 Run the `vxlicrep`, `vxdisklist`, and `vxprint -ht` commands and record the output. Use this information to reconfigure your system after the upgrade.
- 4 Use `hastop` command to stop the cluster:

```
# /opt/VRTSvcs/bin/hastop -all
```

Note: Do not use the `-force` option when executing `hastop`. This will leave all service groups online and shut down Veritas Cluster Server (VCS), causing undesired results while upgrading the packages.

All nodes in a cluster must currently be running the Veritas Storage Foundation 5.0 software, and the correct licenses must be present on these system.

- 5 If you are upgrading the HA version of the Veritas Storage Foundation 5.0 software, follow the guidelines given in the *Veritas Cluster Server 5.0 Installation Guide* and *Veritas Cluster Server 5.0 Release Notes* for information on preserving your VCS configuration across the upgrade procedure.
- 6 Perform any necessary preinstallation checks and configuration. See the *Veritas Storage Foundation 5.0 Installation Guide* for more information.
- 7 For each node in the cluster, check if its root disk is under VxVM control:

```
# df -v /
```

The root disk is under VxVM control if `/dev/vx/dsk/rootvol` is listed as being mounted as the root (`/`) file system. If so, `unmirror` and `unencapsulate` the root disk as described in the following steps:

- a Use the `vxplex` command to remove all the plexes of the volumes `rootvol`, `swapvol`, `usr`, `var`, `opt` and `home` that are on disks other than the root disk.

For example, the following command removes the plexes `mirrootvol-01`, and `mirswapvol-01` that are configured on a disk other than the root disk:

```
# vxplex -o rm dis mirrootvol-01 mirswapvol-01
```

Note: Do not remove the plexes on the root disk that correspond to the original disk partitions.

- b Enter the following command to convert all the encapsulated volumes in the root disk back to being accessible directly through disk partitions instead of through volume devices:

```
# /etc/vx/bin/vxunroot
```

Following the removal of encapsulation, the system is rebooted from the unencapsulated root disk.

- 8 If required, upgrade the nodes in your cluster, and patch them to a supported kernel version. For more information on supported operating systems and kernel versions, see “[System requirements](#)” on page 9.
- 9 Check if any Veritas File Systems or Storage Checkpoints are mounted:

```
# df -T | grep vxfs
```

- 10 Unmount all Storage Checkpoints and Veritas File Systems:

```
# umount /checkpoint_name
```

```
# umount /filesystem
```

- 11 Verify that all file systems have been cleanly unmounted:

```
# echo "8192B.p S" | fsdb -t vxfs filesystem | grep clean
flags 0 mod 0 clean clean_value
```

A `clean_value` value of `0x5a` indicates the file system is clean, `0x3c` indicates the file system is dirty, and `0x69` indicates the file system is dusty. A dusty file system has pending extended operations.

- a If a file system is not clean, enter the following commands for that file system:

```
# fsck -t vxfs filesystem
```

```
# mount -t vxfs filesystem mountpoint
```

```
# umount mountpoint
```

This should complete any extended operations that were outstanding on the file system and unmount the file system cleanly.

There may be a pending large fileset clone removal extended operation if the `umount` command fails with the following error:

```
file system device busy
```

You know for certain that an extended operation is pending if the following message is generated on the console:

```
Storage Checkpoint asynchronous operation on file_system  
file system still in progress.
```

- b If an extended operation is pending, you must leave the file system mounted for a longer time to allow the operation to complete. Removing a very large fileset clone can take several hours.
 - c Repeat [step 11](#) to verify that the unclean file system is now clean.
- 12 If you have created any Veritas Volume Replicator (VVR) replicated volume groups (RVGs) on your system, perform the following steps. Otherwise, proceed to [step 13](#) on page 17.
- a Stop all applications that are involved in replication. For example, if a data volume contains a file system, unmount it.
 - b Use the `vxrvvg stop` command to stop each RVG individually:

```
# vxrvvg -g diskgroup stop rvg_name
```
 - c On the Primary node, use the `vxrlink status` command to verify that all RLINKs are up-to-date:

```
# vxrlink -g diskgroup status rlink_name
```

Caution: To avoid data corruption, do not proceed until all RLINKs are up-to-date.

- d If you are going to use cross-version replication between release 5.0 and release 4.0, perform the following step on the host that is running version 5.0 to make the tunable value persistent. Otherwise, proceed to [step 13](#).

```
# vxvoltune vol_vvr_use_host_byte_order 1
```
- 13 Stop activity to all VxVM volumes. For example, stop any applications such as databases that access the volumes, and unmount any file systems that have been created on the volumes.
- 14 Stop all VxVM volumes by entering the following command for each disk group:

```
# vxvol -g diskgroup stopall
```


To verify that no volumes remain open, use the following command:

```
# vxprint -Aht -e v_open
```
- 15 Comment out any mount points in the `/etc/fstab` file for Veritas File Systems, or for any file systems that are configured on VxVM volumes.
- 16 Check if the VEA service is running:

```
# /opt/VRTS/bin/vxsvcctrl status
```

If the VEA service is running, stop it:

```
# /opt/VRTS/bin/vxsvcctl stop
```

- 17 Insert the disc containing the Veritas software into the DVD-ROM drive, and mount the disc on a suitable mount point, for example:

```
# mount -o ro /dev/cdrom /mnt/cdrom
```

- 18 Move to the top-level directory on the DVD:

```
# cd /mnt/cdrom
```

- 19 To upgrade the Storage Foundation software, you must invoke the `installmp` command from one of your cluster nodes using the option that corresponds to your configuration:

- To install on the local system, enter the following command:

```
# ./installmp
```

- To install on more than one system using secure shell (SSH) utilities, enter the following command:

```
# ./installmp system_name1 system_name2 ...
```

- To install on more than one system using remote shell (RSH) utilities, enter the following command:

```
# ./installmp system_name1 system_name2 ... -rsh
```

- 20 After the initial system checks have completed successfully, press **Enter** to start the requirements checks for the upgrade.
- 21 After the requirement checks have completed successfully, press **Enter** to begin upgrading the packages.

Note: As you are upgrading multiple systems in a cluster, select to upgrade the systems simultaneously.

- 22 After the upgrade of the packages is complete, use the following command to shut down the cluster nodes:

```
# shutdown -r now
```

- 23 Reboot the cluster nodes, and reinstate any missing mount points in the `/etc/fstab` file.

- 24 Restart all the volumes by entering the following command for each disk group:

```
# vxvol -g diskgroup startall
```

- 25 Restart each RVG (if any were stopped in [step 12](#)):

```
# vxrvg -g diskgroup start rvg_name
```

- 26 Remount all Veritas File Systems and Storage Checkpoints:

```
# mount /filesystem
```

```
# mount /checkpoint_name
```

27 Check if the VEA service was restarted:

```
# /opt/VRTS/bin/vxsvcctl status
```

If the VEA service is not running, restart it:

```
# /opt/VRTS/bin/vxsvcctl start
```

28 If you set the value of the `vol_vvr_use_host_byte_order` tunable to 1 in [step d](#) of [step 12](#), reboot the system.

There are several optional configuration steps that you may perform:

- If you want to use features of Veritas Storage Foundation 5.0 for which you do not currently have an appropriate license installed, obtain the license and run the `vxlicinst` command to add it to your system.
- To encapsulate and mirror the boot disk, follow the procedures in the “Administering Disks” chapter of the *Veritas Volume Manager 5.0 Administrator’s Guide*.
- Restore any VCS configuration files as described in the *Veritas Cluster Server 5.0 Installation Guide* and *Veritas Cluster Server 5.0 Release Notes*.

Upgrading Storage Foundation on a standalone system

Caution: Existing data could be destroyed on any disks that are touched by upgrading the operating system. While upgrading, do not reconfigure any disks other than the root disk. To ensure the integrity of your data, it is recommended that you back it up before starting the upgrade.

To upgrade to Storage Foundation 5.0 MP1 on a standalone system

- 1 Log in as superuser.
- 2 Make a complete backup of all data on the system. In particular, you will need the information in files such as `/boot/grub/menu.lst`, `/etc/grub.conf` or `/etc/lilo.conf` (as appropriate), and `/etc/Estab`.
- 1 Run the `vxlicrep`, `vxdisk list`, and `vxprint -ht` commands and record the output. Use this information to reconfigure your system after the upgrade.
- 2 Perform any necessary preinstallation checks and configuration. See the *Veritas Storage Foundation 5.0 Installation Guide* for more information.
- 3 Check if the system’s root disk is under VxVM control:

```
# df -v /
```

The root disk is under VxVM control if `/dev/vx/dsk/rootvol` is listed as being mounted as the root (`/`) file system. If so, `unmirror` and `unencapsulate` the root disk as described in the following steps:

- a Use the `vxplex` command to remove all the plexes of the volumes `rootvol`, `swapvol`, `usr`, `var`, `opt` and `home` that are on disks other than the root disk.

For example, the following command removes the plexes `mirrootvol-01`, and `mirswapvol-01` that are configured on a disk other than the root disk:

```
# vxplex -o rm dis mirrootvol-01 mirswapvol-01
```

Note: Do not remove the plexes on the root disk that correspond to the original disk partitions.

- b Enter the following command to convert all the encapsulated volumes in the root disk back to being accessible directly through disk partitions instead of through volume devices:

```
# /etc/vx/bin/vxunroot
```

Following the removal of encapsulation, the system is rebooted from the unencapsulated root disk.

- 4 If required, upgrade your system, and patch it to a supported kernel version. For more information on supported operating systems and kernel versions, see “[System requirements](#)” on page 9.

- 5 Check if any Veritas File Systems or Storage Checkpoints are mounted:

```
# df -T | grep vxfs
```

- 6 Unmount all Storage Checkpoints and Veritas File Systems:

```
# umount /checkpoint_name  
# umount /filesystem
```

- 7 Verify that all file systems have been cleanly unmounted:

```
# echo "8192B.p S" | fsdb -t vxfs filesystem | grep clean  
flags 0 mod 0 clean clean_value
```

A `clean_value` value of `0x5a` indicates the file system is clean, `0x3c` indicates the file system is dirty, and `0x69` indicates the file system is dusty. A dusty file system has pending extended operations.

- a If a file system is not clean, enter the following commands for that file system:

```
# fsck -t vxfs filesystem  
# mount -t vxfs filesystem mountpoint  
# umount mountpoint
```

This should complete any extended operations that were outstanding on the file system and unmount the file system cleanly.

- 12 Check if the VEA service is running:
`/opt/VRTS/bin/vxsvcctl status`
If the VEA service is running, stop it:
`/opt/VRTS/bin/vxsvcctl stop`
 - 13 Insert the disc containing the Veritas software into the DVD-ROM drive, and mount the disc on a suitable mount point, for example:
`mount -o ro /dev/cdrom /mnt/cdrom`
 - 14 Move to the top-level directory on the DVD:
`cd /mnt/cdrom`
 - 15 To upgrade the Storage Foundation software, you must invoke the `installmp` command from one of your cluster nodes using the option that corresponds to your configuration:
 - To install on the local system, enter the following command:
`./installmp`
 - To install on more than one system using secure shell (SSH) utilities, enter the following command:
`./installmp system_name1 system_name2 ...`
 - To install on more than one system using remote shell (RSH) utilities, enter the following command:
`./installmp system_name1 system_name2 ... -rsh`
 - 16 After the initial system checks have completed successfully, press **Enter** to start the requirements checks for the upgrade.
 - 17 After the requirement checks have completed successfully, press **Enter** to begin upgrading the packages.
-
- Note:** If you are upgrading multiple standalone systems, you can choose to upgrade the systems simultaneously.
-
- 18 After the upgrade of the packages is complete, use the following command to shut down the system:
`shutdown -r now`
 - 19 Reboot the system, and reinstate any missing mount points in the `/etc/fstab` file.
 - 20 Restart all the volumes by entering the following command for each disk group:
`vxvol -g diskgroup startall`
 - 21 Restart each RVG (if any were stopped in [step 8](#)):
`vxrvg -g diskgroup start rvg_name`
 - 22 Remount all Veritas File Systems and Storage Checkpoints:
`mount /filesystem`

```
# mount /checkpoint_name
```

- 23 Check if the VEA service was restarted:

```
# /opt/VRTS/bin/vxsvcctl status
```

If the VEA service is not running, restart it:

```
# /opt/VRTS/bin/vxsvcctl start
```

- 24 If you set the value of the `vol_vvr_use_host_byte_order` tunable to 1 in [step d of step 8](#), reboot the system.

There are several optional configuration steps that you may perform:

If you want to use features of Veritas Storage Foundation 5.0 for which you do not currently have an appropriate license installed, obtain the license and run the `vxlicinst` command to add it to your system.

To encapsulate and mirror the boot disk, follow the procedures in the “Administering Disks” chapter of the *Veritas Volume Manager 5.0 Administrator’s Guide*.

Changing permissions for Storage Foundation for Databases

After installing the Veritas Storage Foundation 5.0 MP1 patches, follow these post-installation steps to ensure Veritas Storage Foundation for Databases commands work correctly. [772592]

Note: Do not recursively change permissions, groups, or owners.

To change permissions

- 1 Change permissions for the following directory, depending on which product you have installed:

For Veritas Storage Foundation for Oracle:

```
# chmod 550 /opt/VRTSdbed
```

For Veritas Storage Foundation for DB2:

```
# chmod 550 /opt/VRTSdb2ed
```

- 2 Reset owner and group settings to the appropriate owner and group for the database administrators on your system.

For example, in Veritas Storage Foundation for Oracle, to change owner to the user `oracle` and the group `dba`, run the following command:

```
# chown oracle:dba /opt/VRTSdbed
```

In Veritas Storage Foundation for DB2, for example, to change owner to the user `db2` and the group `db2grp`, run the following command:

```
# chown db2:db2grp /opt/VRTSdb2ed
```

3 Upgrade the repository.

In a standalone instance, run `sfua_db_config` once:

```
# /opt/VRTSdbcom/bin/sfua_db_config
```

In a cluster environment, follow these steps:

a Unconfigure the SFUA repository from the VCS configuration:

```
# /opt/VRTSdbcom/bin/sfua_db_config -o unconfig_cluster
```

b Mount the repository file system manually.

c Run the repository upgrade command again with no options:

```
# /opt/VRTSdbcom/bin/sfua_db_config
```

Verifying software versions

To list the Veritas packages installed on your system, enter the following command:

```
# rpm -qa | grep VRTS
```

Removing the 5.0 MP1 packages

Roll back of the 5.0 MP1 packages to the release 5.0 version of the packages is not supported. To restore release 5.0 on your system, you must completely remove 5.0 MP1, then reinstall Veritas Storage Foundation 5.0.

To uninstall the Veritas software

- 1 Log in as superuser.
- 2 Verify that `/opt/VRTS/bin` is in your `PATH` so you can execute all product commands.
- 3 If the systems are running as an HA cluster, use the following command to take all service groups offline, and shut down VCS:

```
# /opt/VRTSvcS/bin/hastop -all
```

Note: Do not use the `-force` option when executing `hastop`. This will leave all service groups online and shut down VCS, causing undesired results during uninstallation of the packages.

- 4 Check if the root disk is under VxVM control by running this command:

```
# df -v /
```

The root disk is under VxVM control if `/dev/vx/dsk/rootvol` is listed as being mounted as the root (`/`) file system. If so, unmirror and unencapsulate the root disk as described in the following steps:

- a Use the `vxplex` command to remove all the plexes of the volumes `rootvol`, `swapvol`, `usr`, `var`, `opt` and `home` that are on disks other than the root disk.

For example, the following command removes the plexes `mirrootvol-01`, and `mirswapvol-01` that are configured on a disk other than the root disk:

```
# vxplex -o rm dis mirrootvol-01 mirswapvol-01
```

Note: Do not remove the plexes on the root disk that correspond to the original disk partitions.

- b Enter the following command to convert all the encapsulated volumes in the root disk back to being accessible directly through disk partitions instead of through volume devices. There must be at least one other disk in the `rootdg` disk group in addition to the root disk for `vxunroot` to succeed.

```
# /etc/vx/bin/vxunroot
```

Following the removal of encapsulation, the system is rebooted from the unencapsulated root disk.

- 5 Use the following command to check if any VxFS file systems or Storage Checkpoints are mounted:

```
# df -T | grep vxfs
```

- 6 Unmount all Storage Checkpoints and file systems:

```
# umount /checkpoint_name  
# umount /filesystem
```

- 7 If you have created any Veritas Volume Replicator (VVR) replicated volume groups (RVGs) on your system, perform the following steps:

- a Stop all applications that are involved in replication. For example, if a data volume contains a file system, unmount it.

- b Use the `vxrvrg stop` command to stop each RVG individually:

```
# vxrvrg -g diskgroup stop rvg_name
```

- c On the Primary node, use the `vxrlink status` command to verify that all RLINKs are up-to-date:

```
# vxrlink -g diskgroup status rlink_name
```

Caution: To avoid data corruption, do not proceed until all RLINKs are up-to-date.

- 8 Stop activity to all VxVM volumes. For example, stop any applications such as databases that access the volumes, and unmount any file systems that have been created on the volumes.

- 9 Stop all VxVM volumes by entering the following command for each disk group:

```
# vxvol -g diskgroup stopall
```

To verify that no volumes remain open, use the following command:

```
# vxprint -Aht -e v_open
```

- 10 Check if the VEA service is running:

```
# /opt/VRTS/bin/vxsvcctl status
```

If the VEA service is running, stop it:

```
# /opt/VRTS/bin/vxsvcctl stop
```

- 11 To shut down and remove the installed Veritas packages, use the appropriate command in the `/opt/VRTS/install` directory. For example, to uninstall the Storage Foundation or Veritas Storage Foundation *for DB2* packages, use the following commands:

```
# cd /opt/VRTS/install
```

```
# ./uninstallsf [-rsh]
```

You can use this command to remove the packages from one or more systems. The `-rsh` option is required if you are using the remote shell (RSH) rather than the secure shell (SSH) to uninstall the software simultaneously on several systems.

Note: Provided that the remote shell (RSH) or secure shell (SSH) has been configured correctly, this command can be run on a single node of the cluster to install the software on all the cluster nodes.

After uninstalling the Veritas software, reinstall the release 5.0 software as described in the *Veritas Storage Foundation Installation Guide*, *Veritas Storage Foundation Cluster File System Installation Guide*, or *Veritas Cluster Server (VCS) Installation Guide*.

Upgrading a High Availability cluster

If you are upgrading an HA cluster, see the *Veritas Cluster Server Installation Guide* for information on preserving your VCS configuration across the upgrade procedure. In particular, back up configuration files, such as `main.cf` and `types.cf`, in the `/etc/VRTSvcs/conf/config` directory. If you installed any VCS agents, back up any additional configuration files in this directory, such as `Oracletypes.cf`.

Fixed issues

For a list of additional issues fixed in this release, see the following TechNote:
<http://entsupport.symantec.com/docs/285869>

Veritas Volume Manager fixed issues

The following table contains information about fixed issues in the 5.0 MP1 release of VxVM.

Incident	Description
528677	Volume relayout is now supported for site-confined volumes and for site-consistent volumes.
540351	Reattaching a site when the disks were in the serial-split brain condition gave an error message.
540523	Under some circumstances, DMP nodes could be incorrectly enabled.
563524	Split, join and move operations failed on a source disk group that had any site-confined volumes.
584200	The <code>vxmake</code> command could not be used to recreate site records.
601274	In a CVM cluster, DMP did not fail over to a secondary path when the primary paths were disconnected.
605743	If a disk group were split from a source disk group, volumes in the split-off disk group did not retain their volume tags.
609199	When the <code>vxddmpadm disable</code> command was applied to a primary path on one node in a CVM cluster, the other nodes did not fail over to the secondary path.
611333	DMP could not obtain the correct serial number for a device if its LUN serial number contained a comma. This problem was seen on EMC Symmetrix arrays with more than 8096 LUNs.
614061, 614787	Adding cache volumes (used by space-optimized instant snapshots) to volume sets could cause data corruption and system panics.
617331	I/O was not restored on a path that was re-enabled after a failback or a non-disruptive upgrade (NDU) operation.
618068	A system panic could occur when EMC PowerPath was configured to coexist with DMP as a third-party driver.

Incident	Description
618317	A system crash could occur while bringing up cluster if I/O were performed on a unopened path.
619958	<p>After encapsulating a SAN-connected root disk on an EMC CLARiON CX700 array, a system panic occurred during booting when multiple paths were enabled.</p> <p>Systems with an encapsulated root disk on an Active/Passive array in explicit failover mode (A/PF array) failed to boot if more than one path was enabled.</p> <p>Systems with an encapsulated root disk on an Active/Passive array (A/P array) took a longer time than usual to boot.</p>
621832	Immediately after installation, the <code>vxesd</code> daemon had the DVD mount point as its current working directory, which prevented the DVD from being unmounted.
625877	The error <code>"/etc/vx/vxvm-startup: line 241: /usr/sbin/vxddladm: No such file or directory"</code> was seen at boot time.
643089	Relayout from <code>mirror-stripe</code> to <code>concat-mirror</code> did not work for site-consistent volumes.
645749	Growing a volume by a specified amount did not work for a site-consistent volume with more than 2 disks per site.
771691	The <code>vxrootmir</code> command would not copy the Master Boot Record (MBR) to a root mirror disk. This behavior was generic to all arrays.
778352	Mirroring the root disk to a SAN boot disk could cause data corruption. This behavior was generic to all arrays.
793159	Automatic reattachment of a remote site did not work correctly.
801445	The DMP feature to detect and respond to intermittently failing paths was turned off by default in the 5.0 release, and the values of the <code>dmp_health_time</code> and <code>dmp_path_age</code> tunables were both set to 0. This feature is now enabled by default in 5.0 MP1. The default values of <code>dmp_health_time</code> and <code>dmp_path_age</code> are 60 and 300 seconds respectively.

Veritas Enterprise Administrator fixed issues

The following issues have been fixed in the 5.0 MP1 release of VEA.

Incident	Description
578688	The maximum size of the Alert and Task logs has been documented as 2MB.
596284	An Action pull-down menu item did not exist for the Layout View, the Disk View or the Volume View.
599060	Controller states were reported as “Not Healthy” when they were actually healthy, and “Healthy” when they were actually not healthy.
614761	The volume set creation wizard showed cache volumes in the “Available Volumes” list.
616661	When connecting to the central host, an “OutOfBoundException” error could occur.
618146	A Java exception error occurred in the Statistics View.

Veritas Web GUI fixed issues

The following issues have been fixed in the 5.0 MP1 release of the Web GUI.

Incident	Description
564455	Removing a volume from a volume set returned a Java exception.
565072	Creating a file system on a disabled volume returned both success and failure messages.
566619	The Scan Disks By Controller View did not list the available controllers.
574410	Attempting to create a volume without an existing disk group produced a misleading error.
575262	Disabling a path to a SENA storage array produced an erroneous message.
576794	Ghost entries for disconnected disks in the All Disks View could not be removed by using the GUI.

Incident	Description
596648	Messages about failures to import disk groups were not displayed by the Web GUI.
601157	The wizard could report that an ISP volume was created successfully when the command log showed that it was not.
605468	Forcibly removing a volume from a volume set displayed an erroneous message.
607026	At least one object had to be selected in the GUI before a disk could be initialized.
608573	Deleting a volume that had just been deleted produced a Java exception.
611894	Removing a disk from a disk group displayed an erroneous message.
615395	Attempting to delete an active cache volume failed with an error message that was incomplete.
619039	Messages about exceeding the Storage Foundation Basic soft limitations were not displayed by the Web GUI.
639751	Help for the Scan Disks by Controller page was missing.

Veritas File System fixed issues

The following table contains information about fixed issues in the 5.0 MP1 release of VxFS:

Incident	Description
616323	For WebGUI online help, the following issues have been fixed: For the Remount Storage Checkpoint operation, the More info link on the second wizard page does not function properly for cluster file systems. For the Unmount Storage Checkpoint operation, the More info link on the second wizard page does not function properly for cluster file systems.
770917	Inode ownership issues detected in large directory related code paths have been fixed.

Incident	Description
770935	Prevented the system from panicking when setting access time (<i>atime</i>) or modification time (<i>mtime</i>) of named data streams by calling <code>vxfs_nattr_utimes()</code> API on 32-bit kernel.
770953	<code>fsck</code> used to create the <code>lost+found</code> directory with the <code>rwrxrwxrwx</code> permissions if it decided to create one. Now, it creates the directory with the <code>rxrxr-xr-x</code> permissions, which is consistent with the behavior of <code>mkfs</code> .
770964	<code>fsck</code> has been enhanced to replay file systems created with earlier log versions on volume sets.
771086	Fixed an <code>fsck</code> problem in which users could end up creating multiple <code>lost+found</code> directories when running the <code>fsck -o full</code> command and answering <code>fsck</code> questions interactively. Now, <code>fsck</code> creates only one. It also checks for multiple <code>lost+found</code> entries and removes duplicate directory entries.
771996	Enhanced VxFS to use less CPU when doing administrative tasks on the devices of multi-volume file systems.
772013	Enhanced the <code>fsck</code> command to enforce the <code>lost+found</code> file name in the root directory of the file system to be a directory file type.
777012	If the system crashed or there was a metadata I/O error, after the <code>fsadm</code> command reorganized the <code>lost+found</code> directory, running the <code>fsck -o full</code> command may not have been able to clean the file system with regard to names that needed to be added to the <code>lost+found</code> directory. The problem happened on single-volume and multi-volume file systems.
785649	A situation where <code>vxfsconvert</code> of a dusty file system loops forever in user-level code when an inode with pending truncation operation is encountered has been fixed.
793022	The <code>vxfs_nattr_open()</code> API interface has been fixed to shrink files, as appropriate, when invoked with <code>O_TRUNC</code> flag.
793030	<code>vxfsutil.h</code> uses <code>struct timeval</code> in one of the function declarations, but does not include <code>time.h</code> . This causes user applications to report warnings during compilation. This issue has been fixed by including <code>time.h</code> in <code>vxfsutil.h</code> .
795073	The increased CPU utilization when writing to a file system that is almost full due to more background processing threads than are actually required being enqueued has been fixed.

Veritas Volume Replicator fixed issues

Veritas Volume Replicator vradmin fixed issues

The following table contains information about fixed issues in the 5.0 MP1 release of VVR `vradmin`:

Incident	Description
641429	A security issue was discovered that could have resulted in a Low or Medium Severity attack against the VVR Administration service port, TCP/8199. The attacker would have needed to gain access to the network or gotten the user to visit a malicious site from which the attacker could initiate the attack. An attack could crash the vradmind service (which auto restarts in 60 seconds). Potentially, an attack could degrade system performance if the attack was sustained.
776831	Migration of the Primary could not be done after one node of Primary cluster panicked.
786185	Replicating from the Bunker to a Secondary generated <code>startrep</code> notification continuously, causing the GUI to hang.

Veritas Volume Replicator Web GUI fixed issues

The following table contains information about fixed issues in the 5.0 MP1 release of VVR Web GUI:

Incident	Description
516812	On HP-UX, uninstalling did not remove all VRW files and directories.
576729	When a user without sufficient privileges tried to use the Create Primary wizard, the operation resulted in an incorrect error message.
611792	When a user tried to create a Primary without specifying the RVG name, the operation resulted in an RVG with an invalid configuration being created.
612565	VRW sometimes displayed the sizes of the SRL and data volumes incorrectly for an RDS replicating between VVR 4.1 and VVR 5.0 on the HP-UX operating system.
615758	If a CVM master node contains a private disk group, a Primary RVG created in that disk group was not displayed in the VVR Web GUI.

Incident	Description
615769	When you created a Primary with the VVR Web GUI while connected to the master node of a CVM cluster, the Create Primary wizard did not display private disk group names in the disk group selection list.
615834	In a shared disk group environment, in some cases, clicking on the link for a Secondary disk group did not display the view of the disk group.
766453	If the list of disk groups is empty, clicking the Next button showed a blank screen.
768497	In the Create Primary wizard, sometimes non-free volumes were displayed in the volume list as free volumes.
770478	In some situations, the Current Logging field showed the value SRL when it should have been DCM.
776618	The Creating a Primary wizard failed when the list of data volumes was too long.
784039	In a VVR setup using a bunker Secondary with the STORAGE protocol, if the bunker disk group had been deported and imported several times, VRW displayed incorrect information about the RDS.
785051	The Deactivate Bunker operation was failing to find the activated bunker.
859597	A volume could be resized incorrectly and data could be lost if the requested size contained a decimal point.

Veritas Volume Replicator VEA fixed issues

The following table contains information about fixed issues in the 5.0 MP1 release of VVR VEA:

Incident	Description
602261	In some situations, the Current Logging field showed the value SRL when it should have been DCM.
612565	VVR VEA sometimes displayed the sizes of the SRL and data volumes incorrectly for an RDS replicating between VVR 4.1 and VVR 5.0 on the HP-UX operating system.
616709	In the Japanese locale, the Add Bunker wizard page showed truncated text.

Incident	Description
776622	The Creating a Primary wizard failed when the list of data volumes was too long.
784039	In a VVR setup using a bunker Secondary with the STORAGE protocol, if the bunker disk group had been deported and imported several times, VVR VEA displayed incorrect information about the RDS.

Veritas Storage Foundation for DB2 fixed issues

The following issues have been fixed in the 5.0 MP1 release of Veritas Storage Foundation for DB2:

Incident	Description
567342	An unmounted checkpoint clone database no longer reappears in the Java GUI tree after rescanning.
582069	SFDB commands executed with a different locale than the locale in use when the SFDB server was started no longer fail with the following message: ([Sybase][ODBC Driver][Adaptive Server Anywhere]Syntax error).
600490	The <code>db2ed_clonedb</code> and <code>db2ed_vmclonedb</code> commands now support automatic storage databases.
604852	If a DB2 database is not in the SFDB repository and a user tries to start the instance from the GUI, the database is now properly displayed in the GUI.
608697	You can now refresh the View Statistics wizard in the Firefox browser. The Web GUI statistic scheduler no longer skips the first statistic collection.
610283	Previously, if a checkpoint used a mount prefix that was already used for another checkpoint, <code>db2ed_ckptmount</code> quit silently with return code 1.

Veritas Storage Foundation for Oracle fixed issues

The following issues have been fixed in the 5.0 MP1 release of the Veritas Storage Foundation for Oracle:

Incident	Description
567342	An unmounted checkpoint clone database no longer reappears in the Java GUI tree after rescanning.
582069	SFDB commands executed with a different locale than the locale in use when the SFDB server was started no longer fail with the following message: <code>[[Sybase][ODBC Driver][Adaptive Server Anywhere]Syntax error).</code>
582416	Clicking the Help button on a GUI wizard no longer produces the following error message: <code>Error V-39-53246-8 Get EntryPoint failed. Please check the manifest related information</code>
600431	Storage Checkpoint operations are now supported for databases cloned with Database FlashSnap.
607001	Repository changes resulting from executing SFDB Storage Checkpoint CLIs are no longer delayed in the SFDB GUI.
608697	You can now refresh the View Statistics wizard in the Firefox browser. The Web GUI statistic scheduler no longer skips the first statistic collection.
609682	Specifying a snapplan that does not exist to <code>dbed_vmsnap</code> no longer produces the following error: <code>SFORA dbed_vmsnap ERROR V-81-6518 Could not find snapplan 'snap_plan' in repository.</code>
786989	The <code>qio_getdbfiles_ora</code> script now detects when an Oracle instance is in Standby mode.

Incident	Description
853363	<p>The I/O performance of EMC Symmetrix arrays has been improved in this release. To enable these changes, after upgrading to this release, set the discovery mode of the VAIL provider to discover only those Symmetrix devices that are visible to the host:</p> <ol style="list-style-type: none">1 Determine the agent name under which the Symmetrix provider is configured: <pre># /opt/VRTSvail/bin/vail_symm_discovery_cfg.sh -l</pre>The agent name will be "VAILAgent" for installations of Veritas Storage Foundation, Veritas Storage Foundation for Databases, or Veritas Storage Foundation for RAC. It will be "StorageAgent" if VxFAS is configured.2 Set the discovery mode to discover host-visible devices only: <pre># /opt/VRTSvail/bin/vail_symm_discovery_cfg.sh \ -a agent_name -s 0</pre>where <i>agent_name</i> is the agent name out put from the -l option in the previous step.

Known issues

Veritas Storage Foundation known issues

Known issues in the previous release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

Upgrade issues

LUNs are not displayed by the Storage Foundation Web GUI after upgrade

Because of a bug in the DDL provider package (*VRTSddlpr*) in the 5.0 release, the entries for the DDL provider are removed from the registry if the *rpm* command is used to upgrade to 5.0 MP1. This results in the Web GUI not being able to display any LUNs that are attached to the system.

The workaround is to specify the *--nopreun* option to the *rpm -U* command when upgrading the *VRTSddlpr* package.

The error does not occur if you use the *installmp* script to upgrade to 5.0 MP1. [833516]

Upgrading the DCLI package

The `--nopreun` option should be specified if you use the `rpm -U` command to upgrade the distributed command line interface (`VRTSdcli`) package.

This issue does not apply if you use the `installmp` script to upgrade to 5.0 MP1.

Veritas Volume Manager known issues

Known issues in the 5.0 release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

The following sections contain information about known problems and issues in this release of VxVM.

Rootability issues

Encapsulated root disk cannot be mirrored

If persistent device naming is configured, and a new array is added to a system, the names of DMP nodes may no longer correspond to the OS-based device names. If you then attempt to mirror the encapsulated root disk, this can result in errors such as the following.

```
VxVM vxrootmir ERROR V-5-2-1969
Mirror disk sdb is smaller than Root disk sda
Cannot mirror root disk to sdb
VxVM vxrootmir ERROR V-5-2-1970 Mirror disk and Root disk should
have same geometry
```

In this example, the DMP node, `sdb`, no longer corresponds to the OS-based device following the addition of a new disk array.

You can use the following workaround:

- 1 Unencapsulate the root disk:

```
# /etc/vx/bin/vxunroot
```

The system will reboot.
- 2 Remove the `/etc/vx/disk.info` file:

```
# rm /etc/vx/disk.info
```
- 3 Shut down and reboot the system.
- 4 Use the `vxdiskadm` or `vxencap` command to re-encapsulate the root disk.
- 5 Use the `vxdiskadm` or `vxrootmir` command to remirror the root disk to the correct device.

You can avoid potentially misleading mapping between DMP node names and OS-based device names by turning off persistent device naming:

```
# vxddladm set namingscheme={ebn|osn} persistence=no
```

where `namingscheme=ebn` would select enclosure-based naming, and `namingscheme=osn` would select OS-based naming. [797829]

Utility issues

NFS cannot handle minor numbers greater than 255

The NFS implementation in Linux does not support minor numbers greater than 255 unless a patch is applied (see the description of Red HAT Bugzilla Bug 143897 or SUSE Bugzilla Bug 64552 for details). Without the patch, volume devices with large minor numbers cannot be remotely mounted via NFS. The workaround is to use the `vxdbg` command to change the base minor number of the disk group that contains the volumes, as shown here:

```
# vxdbg -g diskgroup remminor 2
```

DMP issues

Identification of ATA and SATA disks

DMP is unable to identify ATA or SATA disks uniquely. This results in a single DMP virtual device being created for multiple ATA and SATA disks. The workaround is to disable DMP for ATA and SATA disks.

To disable multipathing for ATA and SATA disks

- 1 Configure the device discovery layer to detect ATA disks as JBOD disks:

```
# vxddladm addjbod vid=ATA pid=*
```
- 2 Run the `vxdiskadm` command and select option 17 (Prevent multipathing/Suppress devices from VxVM's view)
- 3 Select option 7 (Prevent multipathing of disks by specifying a VID:PID combination).
- 4 Enter `ATA: *` as the VID:PID combination.
- 5 Exit from `vxdiskadm`, and reboot the system.

[862137]

Fabric Monitoring

The new Fabric Monitoring feature controls whether the Event Source daemon (`vxesd`) uses the Storage Networking Industry Association (SNIA) HBA API. This API allows DMP to improve the performance of failover by collecting information about the SAN topology and by monitoring fabric events. Note that the vendor-provided ASL must also support the use of the SNIA HBA API.

Fabric monitoring may be turned on or off by using the following `vxddladm` commands:

```
# vxddladm settune monitor_fabric=on
# vxddladm settune monitor_fabric=off
```

The current setting of `monitor_fabric` can be displayed by using the following command:

```
# vxddladm gettune monitor_fabric
```

The default setting of `monitor_fabric` is on. [784343]

Handling intermittently failing paths

The `dmp_health_time` and `dmp_path_age` tunables control how DMP handles intermittently failing paths. The default values in VxVM 5.0 MP1 of `dmp_health_time` and `dmp_path_age` are 60 and 300 seconds respectively. The value of `dmp_health_time` represents the minimum time in seconds for which a path must stay healthy. If a path changes state between enabled and disabled on a shorter time scale than this, DMP marks the path as intermittently failing and disables I/O on the path. I/O is not re-enabled on an intermittently failing path until `dmp_path_age` seconds have elapsed without further outage.

The minimum configurable value of `dmp_path_age` is 0, which prevents DMP from detecting intermittently failing paths.

Cluster issues

Handling intermittently failing paths in a Campus Cluster

In remote mirror configurations, a site is reattached when its disks come back online. Recovery is then initiated for the plexes of a volume that are configured at that site. Depending on the configuration, recovery of the plexes can take a considerable time and consume considerable resources. To minimize the frequency of having to perform a site reattachment operation, it is recommended that you use the `vxdlmpadm settune` command to configure a value smaller than 60 seconds for `dmp_health_time`, and a value larger than 300 seconds for `dmp_path_age`.

Automatic site reattachment

A new automatic site reattachment daemon, `vxstited`, has been implemented to provide automatic reattachment of sites. `vxstited` uses the `vxnotify` mechanism to monitor storage coming back online on a site after a previous failure, and to restore redundancy of mirrors across sites.

If the hot-relocation daemon, `vxrelocd`, is running, `vxstited` attempts to reattach the site, and allows `vxrelocd` to try to use the available disks in the disk group to relocate the failed subdisks. If `vxrelocd` succeeds in relocating the failed subdisks, it starts the recovery of the plexes at the site. When all the

plexes have been recovered, the plexes are put into the ACTIVE state, and the state of the site is set to ACTIVE.

If `vxrelocd` is not running, `vxstied` reattaches a site only when all the disks at that site become accessible. After reattachment succeeds, `vxstied` sets the site state to ACTIVE, and initiates recovery of the plexes. When all the plexes have been recovered, the plexes are put into the ACTIVE state.

Note: `vxstied` does not try to reattach a site that you have explicitly detached by using the `vx dg detachsite` command.

The automatic site reattachment feature is enabled by default. The `vxstied` daemon uses email to notify `root` of any attempts to reattach sites and to initiate recovery of plexes at those sites. To send mail to other users, add the user name to the line that starts `vxstied` in the `/etc/init.d/vxvm-recover` startup script, and reboot the system.

If you do not want a site to be recovered automatically, kill the `vxstied` daemon, and prevent it from restarting. To kill the daemon, run the following command from the command line:

```
# ps -afe
```

Locate the process table entry for `vxstied`, and kill it by specifying its process ID:

```
# kill -9 PID
```

If there is no entry in the process table for `vxstied`, the automatic site reattachment feature is disabled.

To prevent the automatic site reattachment feature from being restarted, comment out the line that starts `vxstied` in the `/etc/init.d/vxvm-recover` startup script.

Replacing a disk in a site-consistent disk group

If the `vxdiskadm` command is used to replace a disk in site-consistent disk group, the new disk is expected to be tagged with the same site name as the disk that is being replaced. If the sites do not match, `vxdiskadm` cannot complete the replacement without disabling site-consistency on the volume.

To avoid this, tag the replacement disk with same site name as the disk that is being replaced:

```
# vxdisk settag replacement_disk site=sitename
```

After tagging the replacement disk, you can use `vxdiskadm` to replace the failed disk. [536853]

Domain controller mode in CVM clusters

The slave nodes in a CVM cluster only have access to I/O objects. If non-I/O related information (for example, volume tags) are to be made available on a slave node, a command must be shipped to the Storage Agent on the master node for execution. The results are then communicated back to the slave node.

The domain controller mode of VEA allows all nodes of a CVM cluster to be placed in the same domain with a central authentication server. This allows commands to be executed on any node within the domain if the executing process has sufficient rights.

Provided domain controller mode is configured, non-I/O related information is accessible via VEA on any node in a CVM cluster.

However, even if domain controller mode is enabled in a CVM cluster, ISP commands must be run on the master node. ISP commands that are run on a slave node are not redirected to the Storage Agent on the master node. Such commands fail if they require access to non-I/O related information that is unavailable on a slave node. [603213]

Veritas Enterprise Administrator issues

Volume tags not displayed

In the VEA client for Microsoft Windows systems, existing volume tags are not displayed when adding a new volume tag. [602953]

Search does not return any objects for non-Administrator users

A search that is performed by a user in a non-Administrator group should return an access-denied error and not an empty list of objects. The workaround is to add the user to the Administrator group. [840452]

Veritas Web GUI issues

Incorrect error message when importing a disk group

An incorrect error message such as the following may be displayed when importing a disk group:

```
<!--td align="center" height="287" valign="midd
```

The workaround is to refresh the page. [607096]

Solaris x64 hosts cannot be managed

The Web GUI cannot be used to manage Solaris x64 for Opteron hosts that are running the Storage Foundation 4.1 software. [615554]

Error when creating a volume set

An error such as the following may be seen when attempting to create a volume set that includes a newly created volume:

```
Error: 0xcfff0021 Facility: 0xffff Severity: 0x3 Error number:  
0x21 Object Not Found.
```

The workaround is to refresh the page. [615960]

Veritas File System known issues

Known issues in the 5.0 release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

The following are new known issues in this MP1 release of Veritas File System:

File Change Log tunable setting for proper functioning of Dynamic Storage Tiering applications

If the active placement policy of a given file system uses I/O or access temperatures, after the policy becomes active by being assigned, you must tune the file system's *fcl_malloc* tunable with the following command:

```
# vxtunefs -o fcl_maxalloc=0 mount_point
```

However, if any applications other than DST use FCL, this setting may conflict with those applications.

Veritas Volume Replicator known issues

Known issues in the Veritas Volume Replicator 5.0 release are listed in the *Veritas Volume Replicator 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283839>

The following are new known issues in this MP1 release of Veritas Volume Replicator:

Upgrade issue

Replicated Volume Groups (RVGs) are not displayed by the Storage Foundation Web GUI as well as the VVR Java GUI after upgrade because of a bug in the Veritas Volume Replicator provider (VRTSVRPRO) and Veritas Volume Replicator Web Console (VRTSVRW) packages in the 5.0 release. If the `rpm` command is used to upgrade to 5.0 MP1, the entries for the VVR provider are removed from the registry. This results in the Web GUI and Java GUI not being able to display any Replicated Volume Groups that are present on the system.

The workaround is to upgrade to the 5.0 MP1 `VRTSvrpro` and `VRTSvrw` packages by using the following forms of the `rpm -U` command:

```
# rpm -U --nopreun VRTSvrpro
# rpm -U --nopreun --nopostun VRTSvrw
```

The error does not occur if you use the `installmp` script to upgrade to 5.0 MP1. [840927, 840955]

Synchronizing volumes and RVG with large volumes

The `vradmin syncrvg` and the `vradmin syncvol` commands do not work correctly for volumes larger than 1TB. When either of these two commands is used to synchronize large volumes, the command still runs, but it reports wrong total size of the volumes being synchronized and it actually synchronizes only a portion of the volume having size larger than 1TB.

Workaround: Instead of using the `vradmin syncrvg` command to synchronize the RVG, use the Automatic Synchronization feature when starting replication. To do this, use the `vradmin startrep -a` command. Or, reduce the size of the volume to below 1TB before running the `vradmin syncrvg` command.

For the `vradmin syncvol` command, the only workaround is to reduce the size of the volume to below 1TB. [840217]

Resynchronizing data between VVR 4.1MP2 (Solaris) and VVR 5.0MP1

You cannot use the `vradmin syncvol` command or the `vradmin syncrvg` command to resynchronize data if the Primary is using VVR 4.1MP2 on Solaris and the Secondary is using VVR 5.0MP1, or if the Primary is using VVR 5.0MP1 on Solaris and the Secondary is using VVR 4.1MP2. Using these commands causes a core dump due to differences in the resynchronization code in these versions of VVR.

Workaround: Instead of using the `vradmin syncrvg` command to synchronize the RVG, use the Automatic Synchronization feature when starting replication. To do this, use the `vradmin startrep -a` command.

For the `vradmin syncvol` command, there is no workaround. We recommend upgrading both hosts to VVR 5.0MP1, if possible. [846685]

Issue with VVR VEA in the Japanese locale

In the Japanese locale, the Add Bunker wizard page has truncated text. When you add a bunker using VVR VEA, the description text for the Bunker DG and Protocol fields is truncated. The incomplete text should read as follows:

Bunker DG: If protocol is Storage the Bunker DG is expected to have been imported on the Primary host.

Protocol: Protocol should be set to Storage when Bunker storage is directly accessible from the Primary host.

[616709]

Veritas Storage Foundation for Databases known issues

Veritas Storage Foundation for Oracle known issues

Known issues in the Veritas Storage Foundation for Oracle 5.0 release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

The following are new known issues in this MP1 release of Veritas Storage Foundation for Oracle:

Cannot unmount single-host clone in HA environment after failover

In an HA environment, after successfully taking a snapshot and cloning the database on the same host where primary is running, if a node failover happens then `dbed_vmclonedb -o umount` does not work. [818522]

Workaround: Fix the issue that caused the failover to the other node, and then fallback to the fixed node.

Problems uninstalling or upgrading Veritas Storage Foundation for Oracle when Veritas Storage Foundation Cluster File System is installed on the same system

If Veritas Storage Foundation for Oracle and Veritas Storage Foundation Cluster File System are installed on the same machine, do not use the installer to uninstall if you are planning to uninstall only one product.

You must uninstall the Veritas Storage Foundation for Oracle packages manually if you want to uninstall the product.

To uninstall the Veritas Storage Foundation for Oracle packages

- 1 Review the uninstallation requirements in the *Veritas Storage Foundation Installation Guide*.
- 2 Stop the repository database and unmount the repository volume.

In a stand-alone configuration:

Stop the database repository:

```
# /opt/VRTSdbcom/bin/sfua_db_config -o stopdb
```

Unmount the database repository:

```
# /opt/VRTSdbcom/config/sfua_rep_mount stop
```

In an HA configuration: Stop VCS processes on either the local system or all systems.

To stop VCS processes on the local system:

```
# hastop -local
```

To stop VCS processes on all systems:

```
# hastop -all
```

- 3 Remove the Veritas Storage Foundation for Oracle packages using the `rpm -e` command.

```
# rpm -e VRTSorgui-common VRTSdbed-common VRTSdbcom-common \
VRTSdbdoc
```

If Veritas Storage Foundation for Oracle and Veritas Storage Foundation Cluster File System are installed on the same machine and you are upgrading both products, use the installer to upgrade Veritas Storage Foundation Cluster File System first. Then, use the installer to upgrade Veritas Storage Foundation for Oracle.

If the second upgrade fails, remove the Veritas Storage Foundation for Oracle packages as described above, then run the installer to upgrade Veritas Storage Foundation for Oracle. [840486]

One-time scheduled tasks need Specific Date

When scheduling a one-time task from the GUI, the task may not be executed if a Specific Date (Include Date) is not set for it. [861274]

Cannot use Web GUI to view snapplan log

When trying to view a snapplan log with the Web GUI, the error message "Unable to load operation" is displayed.

Workaround: View snapplan logs with the VEA Java GUI or with the `dbed_vmchecksnap -o list` command. [861696]

Database FlashSnap archive log destinations

With Oracle Release 10g and above, Database FlashSnap clones do not support `DB_RECOVERY_FILE_DESTINATION` as the sole mandatory archive log destination. This issue will not be detected by FlashSnap validation with

`dbed_vmchecksnap`, or by the snapshot command `dbed_vmsnap`. However, recovery will fail when attempting to clone a database using the snapshot, and the message "ORA-01195: online backup of file 1 needs more recovery to be consistent" may appear in the log file.

Workaround: Define a mandatory log archive destination that is not `DB_RECOVERY_FILE_DESTINATION` and set the `ARCHIVELOG_DEST` parameter of the snapplan to this value. [862092, 862687]

Veritas Storage Foundation for DB2 known issues

Known issues in the Veritas Storage Foundation for DB2 5.0 release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

The following are new known issues in this MP1 release of Veritas Storage Foundation for DB2:

Problems uninstalling or upgrading Veritas Storage Foundation for DB2 when Veritas Storage Foundation Cluster File System is installed on the same system

If Veritas Storage Foundation for DB2 and Veritas Storage Foundation Cluster File System are installed on the same machine, do not use the installer to uninstall if you are planning to uninstall only one product.

You must uninstall the Veritas Storage Foundation for DB2 packages manually if you want to uninstall the product.

To uninstall the Veritas Storage Foundation for DB2 packages

- 1 Review the uninstallation requirements in the *Veritas Storage Foundation Installation Guide*.
- 2 Stop the repository database and unmount the repository volume.

In a stand-alone configuration:

Stop the database repository:

```
# /opt/VRTSdbcom/bin/sfua_db_config -o stopdb
```

Unmount the database repository:

```
# /opt/VRTSdbcom/config/sfua_rep_mount stop
```

In an HA configuration: Stop VCS processes on either the local system or all systems.

To stop VCS processes on the local system:

```
# hastop -local
```

To stop VCS processes on all systems:

```
# hastop -all
```

- 3 Remove the Veritas Storage Foundation for DB2 packages using the `rpm -e` command.

```
# rpm -e VRTSd2gui-common VRTSdb2ed-common VRTSdbcom-common \  
VRTSdbdoc
```

If Veritas Storage Foundation for DB2 and Veritas Storage Foundation Cluster File System are installed on the same machine and you are upgrading both products, use the installer to upgrade Veritas Storage Foundation Cluster File System first. Then, use the installer to upgrade Veritas Storage Foundation for DB2.

If the second upgrade fails, remove the Veritas Storage Foundation for DB2 packages as described above, then run the installer to upgrade Veritas Storage Foundation for DB2. [840486]

dbed_vmclonedb -p failed to create clonedb with modified pfile

If you are running the `dbed_vmclonedb -p` or the `dbed_clonedb -p` command, the pfile modification will fail if there is an unquoted or unescaped special character in the primary instance's pfile. The following error will be displayed:

```
SFORA pfile_mod ERROR V-81-5781 Parse error in file  
/oracle/dbs/<pfile_name>. line 6: .
```

```
SFORA dbed_vmclonedb WARNING V-81-5788 Pfile modification  
failed. Clone instance <CLONE SID> may not start.
```

Workaround: To avoid this issue, make sure all special characters in the primary instance's pfile are either placed within quotes or escaped.

You can check the Oracle Reference Manual for a list of special characters that must be either placed within quotes or escaped when used as pfile parameter values. In some cases, Oracle will process a pfile correctly at startup even if a parameter value contains unquoted special characters. However, the pfile parser used by Veritas Storage Foundation for Oracle strictly enforces the pfile specification contained in the Oracle Reference Manual.

Note: The primary instance's pfile is saved at the time of snapshot creation. If you attempt to clone the database using that snapshot you will be using the saved pfile, not the current pfile. Therefore you must create a new snapshot in order to ensure that the clone will use an updated pfile.[853792]

One-time scheduled tasks need Specific Date

When scheduling a one-time task from the GUI, the task may not be executed if a Specific Date (Include Date) is not set for it. [861274]

Cannot use Web GUI to view snapplan log

When trying to view a snapplan log with the Web GUI, the error message "Unable to load operation" is displayed.

Workaround: View snapplan logs with the VEA Java GUI or with the `db2ed_vmchecksnap -o list` command. [861696]

Software limitations

The following sections describe Veritas Storage Foundation software limitations that exist in this release.

Veritas File System software limitations

Software limitations in the Veritas Storage Foundation 5.0 release are listed in the *Veritas Storage Foundation 5.0 Release Notes*, which is available at the following URL:

<http://entsupport.symantec.com/docs/283859>

Veritas Storage Foundation for Databases software limitations

The following are the software limitations for Veritas Storage Foundation for Databases.

Some features stop working after a GCO failover

Some Storage Foundation for Databases features do not work correctly after a Global Cluster (GCO) Failover. In 5.0, the Storage Foundation for Database (SFDB) repository and tools do not manage virtual hostnames correctly in a Global Cluster environment. The SFDB repository does not correctly adjust to the secondary host after the failover.

Features like Storage Checkpoint, Database FlashSnap, the scheduler, and Database Dynamic Storage Tiering (DBDST) will not function as normal after a failover. However, features such as Oracle Disk Manager (ODM), Quick I/O, and Concurrent I/O (CIO) will continue to work after a failover. This issue will be fixed after the next release. [563603]

Differing locales produces unintelligible characters in GUI

The GUI does not support database users having a different locale than the superuser's locale. The GUI will display unintelligible characters if the SFDB repository server starts with a locale that is different from the database user locale (client). [605487]

DBDST limitations with non-English filenames and placement class names

DBDST does not work on non-English database filenames or non-English placement class names, due to limitations in VxFS Dynamic Storage Tiering and VxVM volume tags. VxFS Dynamic Storage Tiering does not support placement

of non-English filenames. The VxVM volume tag feature does not support non-English volume tag names. [599164]

Avoid using UNIX VEA via PC-based UNIX emulators

There can be problems displaying deep mapping topology in PC-based UNIX emulators like Exceed. Use the Windows VEA client instead of running the UNIX VEA client via emulators.

CLI database state changes are delayed in GUI

If you use the command line to start or stop the database, the state change is not immediately shown in the GUI. This delay can take up to 60 minutes.

Workaround: Start or stop the database from the GUI, or do a manual rescan from the GUI after starting or stopping with CLI. [604685]

Deep mapping unsupported

Deep mapping on EMC SYMCLI is currently not supported.

Command Line Interface limitations

The following commands do not support multipartition databases on SMP architectures:

- `db2ed_clonedb`
- `db2ed_vmchecksnap`
- `db2ed_vmclonedb`

Database cloning limitation

If you clone a database and mount it, ensure that the directory where the mount point resides is owned by the instance owner of the cloned database.

If the directory where the mount point resides is not owned by the instance owner, an error message is displayed when you attempt to remove and unmount the cloned database.

For example:

```
$ db2ed_clonedb -I inst01 -S prod -T clone -c \  
Checkpoint_1105997700 -m /mnt
```

where `/mnt` is created by root and the owner has been changed to `inst01`.

When you attempt to remove and unmount the clone database, you will get the following error message:

```
$ db2ed_clonedb -T clone -o umount -d  
rm: Unable to remove directory /mnt Permission denied
```

This error message does not affect the functionality of `db2ed_clonedb`. The clone database has been removed and unmounted even when you receive this error message.

To avoid this error, create a directory under `/` as root and change the owner of the directory to the instance owner. Then, specify a mount point under the newly created directory. For example, instead of using the mount point `/mnt` as in the above example, specify a mount point under `/mnt`, such as `/mnt/clone`:

```
$ db2ed_clonedb -I inst01 -S prod -T clone -c \  
Checkpoint_1105997700 -m /mnt/clone
```

Note: If your mount point is under the directory `/tmp`, you will not encounter this problem. [285139]

No support for Intelligent Storage Provisioning

The Standard, Standard HA, Enterprise, and Enterprise HA versions of Veritas Storage Foundation for DB2 do not support Intelligent Storage Provisioning (ISP).

Using VxVM volumes as DB2 DEVICE containers

For this release, it is recommended that the VxVM raw device interface be used when configuring a raw device as a DB2 container. Using VxVM raw interface ensures fast and reliable I/O support. Also, VxVM's 5.0 raw device interface supports full Linux native asynchronous I/O.

Make sure the DB2 instance owner has read/write access to the VxVM volume. Also, the DB2 instance owner should have permissions to change the directory to `/dev/vx`. By default, only the root user can access the `/dev/vx` directory.

The following example shows how a DMS tablespace is created on a VxVM volume:

```
CREATE REGULAR TABLESPACE USERRAW \  
PAGE SIZE 4K \  
MANAGED BY DATABASE \  
USING (DEVICE '/dev/vx/dsk/db2dg/db2vol11' 128000) \  
EXTENT SIZE 32 PREFETCH SIZE 32 \  
BUFFERPOOL IBMDEFAULTBP
```

An alternative method to use a VxVM volume is to go through the Linux raw binding interface. For further information, refer to the man page for raw commands on Linux. Using Linux raw binding is *not* a recommended method for VxVM.

Deep mapping on hard disk arrays

This release of Veritas Storage Foundation 5.0 for DB2 will not offer the deep mapping feature because partner disk array software on Linux platforms have been unavailable. The storage mapping display will show disk arrays only to the LUN level.

During installation, the `VRTSvail` package will not be installed. However, this package is included in this release, so that this issue can be corrected in a future maintenance pack release.

Use of buffered I/O

VxFS provides sequential consistency among the read and write accesses to a file – that is, the results of these reads and writes appear as if they occurred in a serial order consistent with program order, and each access appears to be atomic. This is consistent with traditional Unix file system semantics for reads and writes.

Other Linux file systems do not guarantee atomicity of reads and writes, which allows more efficient implementation, but also requires that applications use other mechanisms to achieve the same level of consistency if they require it.

VxFS file consistency can be relaxed in several ways. In case of a cluster mount, reads from and writes to a file are not considered conflicting unless they operate on an overlapping byte range. On a local mount, the user can request that the Concurrent I/O option be used on a specific file. This will mean that reads and writes are not guaranteed to be atomic, which can be desirable behavior for some applications.

Veritas recommends the use of Concurrent I/O with DB2. In DB2 UDB version 8.2.2 or above, Concurrent I/O is used with VxFS when DBAs choose “Direct I/O” for a given tablespace. When Direct I/O is specified this way, the DB2 server activates Concurrent I/O semantics in a way that is transparent to users.

See “Understanding Concurrent I/O” in the *Veritas Storage Foundation for DB2 Administrator’s Guide* to learn how to use Concurrent I/O with DB2 UDB on Linux, Unix, and Windows.

DBDST class names limited to 29 characters

The `dbdst_admin -o rmcclass` command fails when attempting to remove a class name of 30 characters or more. The maximum class name length is 29 characters. [601746]

Selected utilities require setuid

Some Veritas Storage Foundation for Databases programs are setuid binaries because they are meant to be run as a database administrator and the APIs used

are root access-only Symantec internal APIs. The affected binaries are used mainly for information query purposes. For these reasons, the following programs are setuid-enabled in Veritas Storage Foundation for Oracle:

- /opt/VRTSdbed/.dba/dbed_analyzer
- /opt/VRTSdbed/.dba/vxckptplan
- /opt/VRTSdbcom/bin/vxstorage_stats
- /opt/VRTSdbcom/.dba/vxdbd_start
- /opt/VRTSdbcom/.dba/vxckpt_ismounted

In Veritas Storage Foundation for DB2, the following programs are setuid-enabled:

- /opt/VRTSdb2ed/.dba/vxdb2adm
- /opt/VRTSdbcom/bin/vxstorage_stats
- /opt/VRTSdbcom/.dba/vxdbd_start
- /opt/VRTSdbcom/.dba/vxckpt_ismounted

[643964]

Multiple archive log destinations with RAC

Multiple archive log locations are not supported in RAC configurations.

[795617]

Repository hostnames are case insensitive

Because DNS host name lookup queries are by definition case insensitive, make sure the SFDB repository is running on a host with a name that is truly unique -- regardless of case -- within the local subnet. Errors may occur if the repository host name differs from another host name only by case. [859863]

No longer supported

This section describes Veritas Storage Foundation features that are no longer supported in this release and future end of support notices.

- The use of the `vxvoladm` command line utility will not be supported in the next major release of Veritas Storage Foundation.

Documentation errata

Web GUI help errata

The Web GUI help is updated in this Maintenance Pack to include corrections for several help screens.

Veritas Storage Foundation Installation Guide errata

In several places in the *Veritas Storage Foundation Installation Guide*, the wrong path is given for the DVD-ROM device special file. The correct path is `/dev/cdrom`. [625481]

Veritas Storage Foundation Release Notes errata

In the *Veritas Storage Foundation 5.0 Release Notes*, it is stated that EFI disks are not supported. In fact, EFI disks are supported except for use as CDS disks or as encapsulated root disks. [914736]

Manual page errata

The `vxassist(1M)`, `vxddladm(1M)`, `vxdisk(1M)`, `vxdlpadm(1M)`, `vxdlping(1M)`, `vxpool(1M)`, `vxresize(1M)`, `vxtemplate(1M)`, and `vxvoladm(1M)` manual pages are updated in this Maintenance Pack to include corrections for several errors or omissions.

Veritas Volume Manager Administrator's Guide errata

The following errata apply to the *Veritas Volume Manager Administrator's Guide*:

Specifying storage for version 20 DCO plexes

The section “Specifying storage for version 20 DCO plexes” in the “Administering volumes” chapter of the *Veritas Volume Manager Administrator's Guide* includes the following example:

```
# vxsnap -g mydg prepare myvol ndcomirs=2 disk05 disk06
```

This should read:

```
# vxsnap -g mydg prepare myvol ndcomirs=2 alloc=disk05,disk06
```

The `vxsnap prepare` command requires that you use the `alloc` attribute when specifying the storage for DCO plexes.

DMP configuration values

The minimum value of the `dmp_path_age` tunable is documented as 1 second. The correct minimum configurable value of `dmp_path_age` is 0, which prevents DMP from detecting intermittently failing paths.

The default recovery option settings are stated to be `queuedepth=20` for throttling and `retrycount=30` for I/O error retrying. The correct default settings are `iotimeout=10` for throttling and `retrycount=5` for I/O error retrying.

Veritas Storage Foundation for Oracle Administrator's Guide errata

The following sections are missing from the *Veritas Storage Foundation for Oracle Administrator's Guide*:

Setting up Oracle 9i RAC objects with `srvctl`

When configured within an Oracle RAC environment, you must set up the Oracle `srvctl` service and register the name of the RAC database with `srvctl`, so that Veritas Storage Foundation for Oracle can learn the status of remote database instances. Otherwise, commands such as `dbed_ckptcreate -o offline` may fail.

To set up Oracle 9i RAC objects

- 1 Look in `/var/opt/oracle/srvConfig.loc` to learn the pathname to the SRVM configuration file as defined by the variable `srvconfig_loc`. For example:

```
srvconfig_loc=/db/srvm.ora
```
- 2 List the details of the SRVM configuration file with `ls -l`:

```
# ls -l /db/srvm.ora
```
- 3 If the configuration file does not exist, create and initialize the file:

```
# touch /db/srvm.ora  
# srvconfig -init
```
- 4 If the configuration file exists, note the size of the file shown by the output of `ls -l`.

```
-rw-r--r-- 1 oracle dba 10569216 Jan 20 14:29 /db/srvm.ora
```
- 5 If the configuration file size is greater than zero (as shown in the example above), the file is initialized. If the file size is zero, initialize it:

```
# srvconfig -init
```
- 6 Start the Oracle RAC Manageability daemon on each system:

```
$ gsdctl start
```
- 7 Confirm the GSD daemon status:

```
$ gsdctl stat
GSD is running on the local node
```

- 8 Add the database to the srvctl configuration:

```
$ srvctl add database -d KPRDADV1 -o /apps/oracle/product/920rac
$ srvctl config database
KPRDADV1
```

- 9 Add each instance to the configuration. For example, in a two-instance configuration, add the first instance:

```
$ srvctl add instance -d KPRDADV1 -i KPADV1R1 -n node1
$ srvctl config database -d KPRDADV1
node1 KPADV1R1 /apps/oracle/product/920rac
```

Then add the second instance:

```
$ srvctl add instance -d KPRDADV1 -i KPADV1R2 -n node2
$ srvctl config database -d KPRDADV1
node1 KPADV1R1 /apps/oracle/product/920rac
node2 KPADV1R2 /apps/oracle/product/920rac
```

- 10 Check the status of the instances to confirm they are running:

```
$ srvctl status database -d KPRDADV1
Instance KPADV1R1 is running on node node1
Instance KPADV1R2 is running on node node2
```

Reconfigure virtual IP address for repository configuration

When configuring a two-node cluster, use the following to change the virtual IP address.

In a standalone instance, first change the IP address. Then run the `sfua_db_config` once to update IP information for SFUA repository access.

```
# /opt/VRTSdbcom/bin/sfua_db_config
```

In a cluster environment, do the following:

- 1 Change the IP address for the cluster.
- 2 Update the IP address for the repository configuration in HA environment by running the following set of commands:

- a Unconfigure the SFUA repository:


```
# /opt/VRTSdbcom/bin/sfua_db_config -o unconfig_cluster
```
- b Import the repository disk group.
- c Then, start then repository disk volume.
- d Mount the repository file system.
- e Then, run the command:


```
# /opt/VRTSdbcom/bin/sfua_db_config
```

When prompted, select the option to change the configuration parameters for the cluster configuration. Enter the new cluster IP address for the cluster configuration.

The following information is incorrect in the *Veritas Storage Foundation for Oracle Administrator's Guide*:

- (Page 223) In step 3 of the procedure "To remove a snapplan and snapshot volume", the correct command to remove a snapplan is:

```
# /opt/VRTS/bin/dbed_vmchecksnap -S db -f snapplan -o remove
```
- (Pages 127 and 266) In the table describing `dbed_clonedb` command options, the description of the `-d` option is potentially misleading. The description should read as follows:
Used with the `-o umount` option. If the `-d` option is specified, the read-write Storage Checkpoint mounted by `dbed_clonedb` is deleted along with the clone database.
Note that this does not delete the read-only Storage Checkpoint first created by `dbed_ckptcreate`, which is subsequently used by `dbed_clonedb` to create a read-write checkpoint.

Veritas Storage Foundation for Oracle Graphical User Interface Guide errata

The following information is incorrect in the *Veritas Storage Foundation for Oracle Graphical User Interface Guide*:

- (Page 23) In the procedure "To start the DBED agent," the command in step 2 should read as follows:

```
/etc/rc2.d/S75vxpal.DBEDAgent start
```
- (Page 23) In the procedure "To stop the DBED agent," the command in the single step should read as follows:

```
/etc/rc2.d/S75vxpal.DBEDAgent stop
```

Veritas Storage Foundation for DB2 Administrator's Guide errata

The following section is missing from the *Veritas Storage Foundation for DB2 Administrator's Guide*:

Reconfigure virtual IP address for repository configuration

When configuring a two-node cluster, use the following to change the virtual IP address.

In a standalone instance, first change the IP address. Then run the `sfua_db_config` once to update IP information for SFUA repository access.

```
# /opt/VRTSdbcom/bin/sfua_db_config
```

In a cluster environment, do the following:

- 1 Change the IP address for the cluster.
- 2 Update the IP address for the repository configuration in HA environment by running the following set of commands:

- a Unconfigure the SFUA repository:
`# /opt/VRTSdbcom/bin/sfua_db_config -o unconfig_cluster`
- b Import the repository disk group.
- c Then, start then repository disk volume.
- d Mount the repository file system.
- e Then, run the command:
`# /opt/VRTSdbcom/bin/sfua_db_config`

When prompted, select the option to change the configuration parameters for the cluster configuration. Enter the new cluster IP address for the cluster configuration.

The following information is incorrect in the *Veritas Storage Foundation for DB2 Administrator's Guide*:

- (Page 195) In the procedure "To abort reverse resynchronization," the single step should read as follows:
Use the `-o reverse_resync_abort` option of the `db2ed_vmsnap` command:
Note that the command is correct.
- (Pages 102 and 243) In the table describing `db2ed_clonedb` command options, the description of the `-d` option is potentially misleading. The description should read as follows:
Used with the `-o umount` option. If the `-d` option is specified, the read-write Storage Checkpoint mounted by `db2ed_clonedb` is deleted along with the clone database.
Note that this does not delete the read-only Storage Checkpoint first created by `db2ed_ckptcreate`, which is subsequently used by `db2ed_clonedb` to create a read-write checkpoint.

Veritas Storage Foundation for DB2 Graphical User Interface Guide errata

The following information is incorrect in the *Veritas Storage Foundation for DB2 Graphical User Interface Guide*:

- (Page 23) In the procedure "To start the DBED agent," the command in step 2 should read as follows:

```
/etc/rc2.d/S75vxpal.DBEDAgent start
```

- (Page 24) In the procedure "To stop the DBED agent," the command in the single step should read as follows:

```
/etc/rc2.d/S75vxpal.DBEDAgent stop
```

